



Cloud Monitor

Product Documentation





Contents

Cloud Monitor	4
• Quick Start	4
• Monitoring Overview	4
• Instance Grouping	6
• Cloud Services Monitoring	7
• Operation Guide	8
• Obtaining Monitoring Views	8
• Metric Data Use Limits	8
• Getting Monitoring Views and Reports	9
• Obtaining Monitoring Data for Specific Metrics	11
• Dashboard	12
• Dashboard Overview	12
• Creating Dashboards	13
• Creating Chart	14
• Viewing Dashboards	16
• Template Variables	18
• Link Management	19
• JSON	21
• Grouping Instances	27
• Alarm Service	30
• Alarm Overview	30
• Alarm Policies	32
• Creating Alarm Policies	32
• Trigger Condition Templates	34
• Associating and Dissociating Objects	38
• Alarm Notifications	39
• Creating and Managing Alarm Recipient Groups	39
• Alarm Callback	42
• Receiving Alarm Notifications Through a WeCom Group	44
• Notification Template	46
• Custom Callback Content Templates	48
• Viewing Alarm Records	51
• Event Center	53
• Event Center Overview	53
• Product Event List	56
• Cloud Product Monitoring	60
• Cloud Product Monitoring Metrics Overview	60
• CVM	62
• CVM Monitoring Metrics	62
• Installing the CVM Monitoring Component	64
• Common Causes and Solutions for Monitoring Components Going Offline	65
• Monitoring Metrics for TKE	66
• Monitoring Metrics for BMS	74
• Monitoring Metrics for CLB	77
• Monitoring Metrics for VPC	78
• Monitoring Metrics for DC	81
• Monitoring Metrics for CBS	82
• Monitoring Metrics for COS	83
• Monitoring Metrics for CSP	86
• Monitoring Metrics for CFS	88
• Monitoring Metrics for Redis®	90
• Monitoring Metrics for TDSQL for MySQL	95
• Monitoring Metrics for MongoDB	101
• Monitoring Metrics for CMQ	104
• Monitoring Metrics for Ckafka	105
• Monitoring Metrics for TSF	110
• Monitoring Metrics for TDMQ Pulsar	112
• Monitoring Metrics for TI-ONE Platform	114
• TI-ONE Task-Based Modeling	114
• TI-ONE Development Machine	132
• TI-ONE Online Services	141
• TI-ONE Resource Management	158
• Querying Monitoring Metrics: Guide for Calling the GetMonitorDat	166
• Shipping Monitoring Metrics to Kafka	173
• Best Practices	177
• Application of Instance Grouping in Alarms	177
• Best Practices for Monitoring Scenarios	179
• Configuring CVM Metric Alarms	182
• Product White Paper	184
• Product Overview	184
• Product Strengths	185
• Use Cases	186
• Product Architecture	187
• Features	188
• API Documentation	190
• Cloud Monitor(monitor)	190
• version(2018-07-24)	190
• API overview	190
• CallingMethod	193
• signaturev1	193
• signaturev3	201
• request	210
• result	211
• PublicParameter	214
• Alarm APIs	216
• CreateAlarmPolicy	216
• DescribeAlarmEvents	218
• DescribeAlarmMetrics	219
• DescribeAlarmPolicy	220



• DescribeMiniDashboardAlarmInfo	222
• ModifyAlarmPolicyInfo	224
• ModifyAlarmPolicyStatus	226
• Cloud Monitor API	228
• BindingPolicyObject	228
• CreateAlarmNotice	230
• CreateNoticeContentTpl	232
• CreatePolicyGroup	234
• DeleteAlarmNotices	235
• DeleteNoticeContentTpl	237
• DeletePolicyGroup	239
• DescribeAbnormalObjects	242
• DescribeAccidentEventList	244
• DescribeAgentStatusHistory	245
• DescribeAlarmHistories	247
• DescribeAlarmNotice	248
• DescribeAlarmNoticeCallbacks	250
• DescribeAlarmNotices	252
• DescribeAlarmPolicies	253
• DescribeAllNamespaces	255
• DescribeBaseMetrics	256
• DescribeBasicAlarmList	258
• DescribeBindingPolicyObjectList	260
• DescribeMonitorProducts	262
• DescribeNoticeContentTpl	264
• DescribePolicyConditionList	266
• DescribePolicyGroupInfo	269
• DescribePolicyGroupList	273
• DescribeProductEventList	276
• DescribeProductHealthStatusList	277
• DescribeProductList	279
• DescribeStatisticData	281
• DescribeUnifyDashboards	284
• GetMonitorData	287
• ModifyAlarmNotice	288
• ModifyAlarmPolicyCondition	290
• ModifyAlarmPolicyNotice	292
• ModifyAlarmPolicyTasks	294
• ModifyAlarmReceivers	295
• ModifyNoticeContentTpl	296
• PutMonitorData	298
• SetDefaultAlarmPolicy	300
• UnBindingAllPolicyObject	302
• UnBindingPolicyObject	305
• Other APIs	307
• DescribeLogTopics	307
• Data structure	308
• ErrorCode	339
• version(2017-03-12)	343
• API overview	343
• CallingMethod	344
• signaturev1	344
• signaturev3	352
• request	361
• result	362
• PublicParameter	365
• Cloud Monitor API	367
• DescribeBaseMetrics	367
• GetMonitorData	369
• Data structure	371
• ErrorCode	372

Quick Start

Monitoring Overview

The monitoring overview module provides an entry for viewing the overall monitoring status of cloud products. You can view the service health status from the past 24 hours, monitoring timeline from the past 7 days, exception monitoring status, and other information in this module.

Operation steps:


1. Log in to the cloud platform console and click Cloud Monitor to go to the Monitoring Overview page by default.
2. The Monitoring Overview page contains the following four modules.

i. Service Health Status in the Last 24 Hours

It displays the current three statuses of cloud resources, including Normal, Reminder, and In Alarm. The number of objects affected by abnormal cloud resources is also displayed.

- Normal: no resource exceptions.
- Reminder: Exceptions occurred in resources in the last 24 hours.
- In Alarm: There are currently resources in an abnormal status that have not been restored.

You can hover over the abnormal status icon to view the alarm exception records, and select the region where the cloud resource is located in the drop-down list.



ii. Exception Monitoring

It displays the number of policies for which no alarm receiving group is configured under the current account. You can click Configure Reception Group to go to the alarm policy list for configuration.



Cloud Monitor

Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition Template

Notification Template

Event Center

Cloud Product Monitoring

- Cloud Virtual Machine
- Bare Metal Server
- Cloud Load Balancer

Monitor Overview

Service Status in Last 24 Hours

All Items

Service Type	Current Status①	Affected Objects
Cloud Virtual Machine	Normal	-
docker(new)	Normal	-
docke(new)r	Normal	-
ckafka	Normal	-
consumergroup	Normal	-
partition	Normal	-
Cloud Load Balancer	Normal	-
NAT Gateway	Normal	-

Exception Monitoring

No exceptions found



Instance Grouping

You can group instances within the same cloud service across regions for unified management. When creating a large number of instances, you can create groups as needed, making it easier to manage instances, set alarm policies, and improve operational efficiency.

Cloud Monitor

Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition

Instance Group

Create

Please enter instance group name to search

Instance group name	Group Type	Instance Quantity	Bound Alarm Policies	Last Modified	Operation
No instance group					
0 item(s) in total					

Cloud Services Monitoring

Cloud Services Monitoring is a unified display platform within the Cloud Monitor console that aggregates the most detailed monitoring information. Users can view the list of cloud resources purchased under their account in Cloud Services Monitoring, as well as the corresponding monitoring and alarm details.

Compared to the monitoring data presented in the business console, Cloud Services Monitoring integrates the instance's health status with alarm data. It provides a feature for users to quickly locate exception instances and supports the troubleshooting of issues by combining specific data and error information.

Monitoring details are displayed based on the cloud products you have purchased. Unpurchased cloud products will not be displayed. Currently supported Cloud Product Monitoring includes Cloud Virtual Machine (CVM), Cloud Load Balancer (CLB) , etc.



Operation Guide

Obtaining Monitoring Views

Metric Data Use Limits

Metrics represent the performance data of user systems and are a core concept of Cloud Monitor. Metric data refers to the specific monitoring data of various cloud services, denoting a time-ordered collection of data points sent to Cloud Monitor. Statistical data about these data points can be retrieved as a time series. Currently, Cloud Monitor offers 1-minute and 5-minute data granularities, and the data storage durations for the two granularities are different.

Granularity	Storage Duration
1min	30 days
5min	30 days

Storage duration refers to the period from when Cloud Monitor collects the monitoring data until the data is terminated after reaching the corresponding period.

Note:

If a user's cloud resources are reclaimed or terminated, the monitoring data generated by the cloud resources will not be immediately cleared. Cloud Monitor continues to follow a unified storage duration to store and manage the monitoring data of terminated instances.

Users can view or retrieve the monitoring data generated by cloud resources under their accounts through the frontend console or API calls. If the resource object to be viewed has not been reclaimed or terminated, users can view the monitoring data in the frontend console. If the target instance no longer exists, users need to retrieve the corresponding monitoring data through API calls.



Getting Monitoring Views and Reports

1. Viewing Monitoring Chart

Cloud Monitor offers customers various channels to view monitoring data.

2. Viewing detailed monitoring data for a single instance

i. Viewing Through Cloud Services Monitoring

Cloud Service Monitoring is a unified display platform that gathers the most detailed monitoring information in the Cloud Monitor console. Users can view the list of cloud resources under their accounts and the corresponding monitoring and alert details.

Compared to the monitoring data displayed on the business console, Cloud Service Monitoring integrates the health status and alarm data of instances. It provides users with the functionality to quickly locate abnormal instances and supports users in troubleshooting issues by combining specific data and exceptions.

Cloud Product Monitoring currently supports displaying monitoring details for the following cloud services: CVM, CLB, etc.

2. View Through Console

Users can also log in to each cloud service's corresponding console to view the monitoring details of an instance.

Using CVM as an example:

- Users can quickly browse the performance data of each instance through the monitoring pop-up window in the list of cloud servers.
- Users can also click on the CVM ID in the list to further view the instance's monitoring details.

3. Batch View of Cloud Service Monitoring Data

i. View Through Dashboard

View cross-instance and cross-product monitoring data through the dashboard, providing users with the feature to view multiple instance data at once.

- Users can subscribe to the monitoring metrics they are most concerned about through the dashboard and keep track of the performance status of key instances through regular inspections or large screen displays of the dashboard.
- Users can subscribe to the overall performance status of a business/cluster through the dashboard. Intuitively understand the overall situation of resources, avoiding the efficiency problem of checking monitoring data one by one.

For specific instructions on using the dashboard, please refer to: [Create New Dashboard](#)

ii. Viewing Through Traffic Monitoring



Traffic Monitoring provides users with the feature of monitoring the public network traffic of CVM, showing the aggregated data of the public network outbound bandwidth of all cloud servers under the user's account. Log in to the Cloud Observability Platform console, click Traffic Monitoring, and enter the management page. You can view real-time traffic, or switch the display time span through the time selector to view the traffic status of the last 7 days, last 15 days, last 30 days, or any specific day.

4. Obtaining Data Report

i. Exporting from Dashboard

Log in to the TCOP console, and navigate to Cloud Monitor Console > Dashboard > Dashboard List.

Click the corresponding dashboard.

On the dashboard page, find the monitoring item you want to export data for and click ... above it to export the corresponding instance monitoring detail list.

Obtaining Monitoring Data for Specific Metrics

Cloud Monitor provides the following methods to support users in obtaining the specific metric data of a monitoring object at a specific time.

1. Obtain the specific metric data of a monitoring object at a specific time from the console.
 - i. Log in to the cloud platform console and navigate to the corresponding product console where you want to view monitoring data.
 - ii. Select the specific object you want to monitor and click the object ID to enter the monitoring details page. Alternatively, click the monitoring icon in the object list to view the data through the monitoring pop-up window.
 - iii. Locate the target metric on the monitoring details page or in the pop-up window.
 - iv. Use the time selector and granularity selector to adjust the view and display the specific content of the data. This allows you to see the specific metric data of the monitoring object at a specific time.
2. Obtain the specific metric data of a monitoring object at a specific time through an API.

See [Query Monitoring Metrics: GetMonitorData API Call Usage Guide](#).



Dashboard

Dashboard Overview

Dashboards are intelligent tools provided by Cloud Monitor for monitoring data of cloud product metrics, featuring visualization and analysis capabilities.

You can create a dashboard for cloud service metrics, and the dashboard will automatically present the monitoring data in a visually appealing chart format on the monitoring panel. This makes the data more intuitive and assists you in analyzing metrics through trends and exception values.

1. Use Cases

- When receiving a metric alarm, you can use the dashboard to analyze the cause of the alarm.
- After a new feature is released, you can use the dashboard to check for resource exceptions.
- Through real-time metric display, you can optimize performance during business peaks.
- View the loads through the dashboard to determine whether resource scaling is needed.

2. Limitations

Category	Upper Limitation
Custom dashboard	30
Number of charts per dashboard	20
Number of instances that can be associated with each chart	50

Creating Dashboards

Before creating monitoring charts, you need to create a dashboard first. You can refer to the following steps to create a dashboard.

1. Log in to the cloud platform console and choose Cloud Monitor > Dashboard to enter the dashboard list.
2. Click Create Dashboard in the upper-left corner of the dashboard list to go to the dashboard creation page.
3. Click Create New Chart in the empty chart to go to the chart editing page. For details, see [Creating a Chart](#).
4. Configure chart parameters. You can click <- in the upper-left corner to return to the dashboard creation page to add a chart.
5. After configuring the chart, click Save in the upper-right corner, and then fill in the dashboard name and choose the folder it belongs to in the pop-up box.

New Dashboard

Dashboard Name

New Dashboard

Folder

Public Dashboard Folder

OK

Cancel

6. Click OK to create the dashboard.

Creating Chart

You can follow the steps below to create a new chart.

1. Add New Metric

- i. Log in to the Cloud Platform console and click Cloud Monitor > Dashboard > Dashboard List.
- ii. Select the corresponding dashboard, and click Create New > Create New Chart.
- iii. Configure the metric information as follows:

- Metric: Select the product type and metric.
- Filtering: Choose the filtering conditions to filter and display the data on the chart that meets the criteria.

Instance: The chart will display the monitoring data of the selected instances.

Template Variables: The chart will display instances of template variable filters. See the template variable documentation for the configuration of template variables.

- Comparison: Supports sequential comparison (the same period yesterday), year-on-year comparison (same period last week), and custom time comparison. When both options are selected, the chart will display the monitoring curves for the selected instance during the same time period of yesterday and last week, providing convenience for you to compare the data.
- Left Y-axis, Right Y-axis: Supports adjusting the placement of the Y-axis on either side.
- More configurations:

Alias: Supports one-click renaming of all instance aliases. If you need different instances to have different aliases, you can create multiple metrics and enter an alias under each.

Enable Sorting Feature: The instances bound to the chart will be sorted according to the sorting rules and display quantity, used to implement the high and low load features of a large number of monitoring machines.

Sorting rules: Supports various methods of sorting metrics, which can be used to filter instances based on the sorting results.

Display quantity: Display the number of instances. For example, set the collation rule as "maximum; descending order", and display quantity as 10. This means the chart will display the top 10 instances with the maximum value in descending order.

- iv. Configure chart information as follows:

- Basic Information: Includes the chart name and chart annotation.
- Chart Type: Select from line chart, bar chart, gauge chart, pie chart, numerical statistic chart, heatmap, or table. Customize the chart display method based on each chart type.

- v. After configuration, click the top-left [<-] to return to the Dashboard page to add the new chart configuration.

2. Manage multiple metrics



- You can click [Add Metric] or the "Copy" icon button to display multiple metrics in the same chart for cross-instance metric data comparison.
- You can click the up and down arrows to adjust the metric order.
- You can click the "Delete" icon button to remove metrics.

3. Editing a chart

- i. Click the [...] in the upper right corner of the chart you need to edit.
- ii. Click [Edit] in the popup to enter the chart editing page.

Viewing Dashboards

You can refer to the following steps to view a dashboard.

1. Operation Steps

- i. Log in to the cloud platform console and choose Cloud Monitor > Dashboard to enter the dashboard list.
- ii. By clicking the corresponding dashboard, you can view the dashboard overview. The system allows you to view a dashboard in full-screen mode, customize the time span, and bookmark panels.

2. View a chart in full-screen mode.

Click the full screen icon in the upper-right corner of a chart to view it in full-screen mode.

To exit full-screen mode, press ESC or click the X icon in the upper-right corner.

3. Zoom and move a chart.

- Chart zooming: You can scale a chart by hovering your mouse pointer over the lower-right corner of the chart until a straight-angle icon appears, as shown below.
- Chart moving: You can move a chart by hovering your mouse pointer over the name of the chart until a movement icon appears, as shown below.

4. View monitoring data at a specific time.

You can hover your mouse pointer over the monitoring chart to view the monitoring data at a specific time.

5. Adjust the time span of charts to view monitoring data.

By default, dashboards display the data of the last 12 hours.

You can adjust the data interval and granularity for all charts in the dashboard by using the time selection control in the upper-right corner of the dashboard. This feature allows users to review historical monitoring data and troubleshoot issues.

Comparison table of time periods and granularities in charts

Time Range	Default Statistical Granularity
<=1 hour	1 minute
(1 hour, 12 hours]	1 minute
(12 hours, 3 days]	5 minutes
(3 days, 30 days]	1 hour
(30 days, 186 days]	1 day

6. Switch dashboard.




Click the inverted triangle button on the right of the current dashboard name to switch between panels and view by current folder, recently visited, favorites, or all.

- Current folder: It displays the dashboards in the folder where the current dashboard is located.
- Recently visited: It displays the dashboards you have recently visited.
- Favorites: It displays your favorite dashboards.
- All: It displays all the dashboards you have customized.


Template Variables

1. Configure template variables.

- Log in to the console and choose Cloud Monitor > Dashboard to go to the dashboard list.
- Choose the corresponding dashboard, click the settings icon, and select Template Variables on the Dashboard Management page.



- Template variables are used for customizing dashboard filter conditions. On the Dashboard Management page, you can use template variables to quickly filter instances.
- Click Create on the template management page, and then click OK to create a template variable.




2. Use template variables.

After template variables are created, they can be used as quick selectors for dashboards and monitoring charts.


- Use in dashboards: Template variables can be used on the Dashboard Management page to filter the dashboard data.
- Use in monitoring charts: On the Chart Editing page, quickly select tags to group and aggregate the instance data to be displayed.

Link Management

1. Log in to the cloud platform console and choose Cloud Monitor > Dashboard to enter the dashboard list.
2. Choose the corresponding dashboard, click the settings icon, and select Link Management on the dashboard management page.



3. Link management is used for customizing quick links to dashboards. To create a link, specify the link name, type, link target, and parameter,



as described below:

- Link Name: custom link name.
Type
- Custom Link: All links are supported.
- Other Panels: links to other panels.
- Link Target: link address or link panel.
Parameter
- Time: whether the destination page synchronizes the panel's time during link redirection.



Open Mode

- New Tab: opens the link in a new tab.
- Current Page: opens the link in the current tab.


4. Use links.

On the dashboard management page, you can quickly navigate to your custom links for troubleshooting or monitoring data comparison.


JSON

1. View and copy JSON data.

- Log in to the cloud platform console and choose Cloud Monitor > Dashboard to enter the dashboard list.
- Choose the corresponding dashboard, click the settings icon, and select JSON on the dashboard management page.



- You can copy the JSON content to deploy the dashboard to your self-built system.



The JSON template includes the dashboard's attributes, template variables, and panel query fields. For the specific field description, see the following text.

2. JSON field description.

```
{
  "Description": "",
  "Refresh": "close",
  "Title": "JSONTEST",
```



```
"UUID": "jdq4joy56is4w60q",
"Version": 1,
"Templating": [],
"Links": [],
"Panels": [],
"Time": {
  "From": "now-12h",
  "To": "now"
},
}
```

Name	Description
Description	Current dashboard remarks.
Refresh	Auto-refresh time interval.
Title	Current dashboard name.
UUID	Unique ID of the dashboard.
Version	Dashboard version, which increases with each save.
Templating	Dashboard template variables. For more information, see Templating.
Link	Dashboard link. For more information, see Links.
Panels	Chart configuration. See Panels.
Time	Time range of the dashboard.

1. Templating

```
"Templating": [ // Template variables.
{
  "Label": "CVM instance name", // Template variable alias.
  "Multi": true, // Whether multiple selection is allowed.
  "Name": "cvm", // Tag.
  "Selected": [], // Template variable value.
  "Type": "monitor", // Template variable type.
  "TemplatingType": "basics", // Tag type: basic monitoring or custom monitoring.
  "TemplatingType": '123', // Variable ID.
}
]
```

2. Link

```
"Links": [ // Dashboard link.
{
  "IncludeVars": true, // Whether to include template variables in the link parameters.
  "KeepTime": true, // Whether to include time variables in the link parameters.
}
```

```
"TargetBlank": true, // Whether to open the link in a new tab.
"Title": "xxx", // Link name.
"Type": "other", // Link type: custom links or links to other dashboards.
"Url": "/monitor/dashboard2/dashboards/d/130618223492100096hh64oj49rru3ctk/dashboard2-convergecloud_user_dir", // Link address.
"ID": 0 // ID
}
]
```

3. Panels

```
"Panels": [ // Panel configuration.
{
  "Collapsed": false, // Whether the chart group is collapsed.
  "Datasource": null, // Data source.
  "GridPos": { // Chart position.
    "H": 1,
    "W": 6,
    "X": 0,
    "Y": 0
  },
  "ID": 1595472129140, // Chart ID.
  "Panels": [], // Panel is a field for chart groups, containing sub-panels.
  "Title": "Default Chart Group", // Title.
  "Type": "row" // Chart type.
},
{
  "DataLinks": [], // Data links configured for the chart.
  "Description": "", // Remarks for the chart.
  "GridPos": {
    "H": 5,
    "W": 6,
    "X": 0,
    "Y": 1
  },
  "ID": 1595471392817,
  "Links": [], // Chart links.
  "Settings": { // Visualization configuration for the chart.
    "aliasColors": {},
    "bars": false,
    "dashLength": 10,
    "dashes": false,
    "datasource": null,
    "decimals": 2, // Legend precision.
    "fieldConfig": {
      "defaults": {
        "custom": {}
      },
      "overrides": []
    },
    "fill": "0.8", // Chart fill transparency.
```

```
"fillGradient": 0,
"gridPos": {
  "h": 8,
  "w": 12,
  "x": 0,
  "y": 0
},
"hiddenSeries": false,
"id": "1595471392817", // ID of the chart panel.
"legend": { // Legend settings.
  "alignAsTable": [ // Whether the legend is displayed in table form.
    "1"
  ],
  "avg": [ // Whether to display the average value. ['1'] for true; ['0'] for false.
    "1"
  ],
  "current": [ // Whether to display the current value. ['1'] for true; ['0'] for false.
    "1"
  ],
  "max": [ // Whether to display the maximum value. ['1'] for true; ['0'] for false.
    "1"
  ],
  "min": [ // Whether to display the minimum value. ['1'] for true; ['0'] for false.
    "1"
  ],
  "rightSide": [ // Whether to place the legend on the right. ['1'] for true; ['0'] for false.
    "1"
  ],
  "show": [ // Whether to display the legend. ['1'] for true; ['0'] for false.
    "1"
  ],
  "total": [ // Whether to display the cumulative value. ['1'] for true; ['0'] for false.
    "1"
  ],
  "values": false
},
"lines": [ // Whether to display the curve. ['1'] for true; ['0'] for false.
  "1"
],
"linesType": true, // Whether to display a smooth curve. ['1'] for true; ['0'] for false.
"linewidth": "2", // Curve width.
"markline": { // Mark settings.
  "marklineMax": {
    "max": [ // Whether to display the maximum value. ['1'] for true; ['0'] for false.
      "1"
    ]
  }
},
"nullPointMode": "1", // Display method for null values in the data. 0: connects null data; 1: does not fill i
n the gaps caused by null values; 2: automatically replaces null values with zeros.
"options": {
  "dataLinks": [] // Array of data links.
```

```
,
"percentage": false,
"pointradius": 2,
"points": false,
"renderer": "flot",
"seriesOverrides": [],
"spaceLength": 10,
"stack": [// Whether to display data in a stacked format. ['1'] for true; ['0'] for false.
  "1"
],
"steppedLine": false,
"targets": [
  {
    "refId": "A",
    "scenarioId": "random_walk"
  }
],
"thresholds": [],
"timeFrom": null,
"timeRegions": [],
"timeShift": null,
"title": "New Chart",
"tooltip": {
  "shared": true,
  "sort": 0,
  "value_type": "individual"
},
"type": "graph",
"xaxis": {
  "buckets": null,
  "mode": "time",
  "name": null,
  "show": true,
  "values": []
},
"yaxes": [
  {
    "decimals": 2, // Left y-axis precision.
    "format": "%", // Left y-axis label unit.
    "label": null,
    "logBase": 1,
    "max": 2, // Maximum value of the left y-axis coordinates.
    "min": 0, // Minimum value of the left y-axis coordinates.
    "show": [// Whether to display the left y-axis. ['1'] for true; ['0'] for false.
      "1"
    ]
  },
  {
    "decimals": 2,
    "format": "",
    "label": null,
    "logBase": 1,
```

```
        "max": null,
        "min": null,
        "show": [
            "1"
        ]
    }
],
"yaxis": {
    "align": false,
    "alignLevel": null
}
},
"Targets": [ // Metric configuration.
{
    "Aggregate": "", // Statistical method.
    "CompareLastWeek": false, // Week-on-week comparison.
    "CompareYesterday": false, // Day-on-day comparison.
    "Conditions": [ // Filter conditions.
        {
            "Dimension": [
                {"InstanceId": "ins-19827u5b"},
                {"InstanceId": "ins-xxooxxoo"},
                {"InstanceId": "ins-19719mfp"}
            ],
            "Region": "region-name",
            "Type": "normal"
        }
    ],
    "ConfigId": "cvm",
    "Datasource": "DS_QCEMetric", // Product type.
    "DimensionKey": [
        "InstanceId"
    ],
    "GroupBy": [ // groupby
        "InstanceId"
    ],
    "MetricNames": [ // Metric names.
        "BaseCpuUsage"
    ],
    "Namespace": "QCE/CVM", // Namespace.
    "Period": 60 // Granularity.
    },
],
"Title": "Single Metric - Default Configuration", // Chart name.
"Type": "graph" // Chart type.
},
]
```


Grouping Instances

1. Creating an instance group

- i. Log in to the cloud platform console and choose Cloud Monitor > Instance Group.
- ii. Click Create and configure the following options.
 - Group Name: Enter an instance group name.
 - Group Type: Select an option as needed.
 - Add to Group: Select the instances to be added to the group.

The screenshot shows the 'Create' dialog in the Cloud Monitor console. The 'Group Name' field is set to '1-20 characters'. The 'Group Type' is set to 'Cloud Virtual Machine'. The 'Add to group' section shows a table with columns for ID/CVM Name, Network Type, and IP Address. The 'Save' button is highlighted.

- iii. Click Save to create the instance group.

2. Viewing an instance group

- i. Log in to the cloud platform console and choose Cloud Monitor > Instance Group.
- ii. On the instance list page, you can view information such as the instance group name, number of instances, and number of associated alarm policies. You can also click the number of alarm policies to view the instances associated with the group.

3. Editing an instance group

Note:

- If an instance group is already bound to an alarm policy, instances added to this instance group will automatically be bound to this alarm policy.
- If an instance group is already bound to an alarm policy, instances removed from this instance group will no longer be bound to this alarm policy.

- i. Log in to the cloud platform console and choose Cloud Monitor > Instance Group.
- ii. Click the name of the instance group that needs to be edited to go to the Instance Management page. On

this page, you can edit (add or delete) the instances of this instance group.


- Adding an instance
 - Click Create.
 - In the pop-up configuration box, select the instance that needs to be added to this instance group.
 - Click OK to add the instance to this instance group.
- Deleting an instance
 - Select the instance you want to remove and click Remove.
 - In the pop-up confirmation dialog box, click Confirm to Remove Selected Instance to remove the instance from the instance group.

4. Deleting an instance group

Note:

If an instance group is already bound to an alarm policy, deleting the instance group will cause the bound alarm policy to become invalid.

- i. Log in to the cloud platform console and choose Cloud Monitor > Instance Group.
- ii. Find the instance group you want to delete, and click Delete in its right-side operation column.




- iii. In the pop-up confirmation dialog box, click Confirm Deletion to delete the instance group.

5. Copying an instance group

Note:

When an instance group is copied, only the instances contained within it will be copied, and the binding relationship between this instance group and the alarm policy will not be copied.

- i. Log in to the cloud platform console and choose Cloud Monitor > Instance Group.
- ii. Find the instance group you want to delete, and click Copy in its right-side operation column.



- iii. In the pop-up confirmation dialog box, click Confirm to Copy to successfully copy the instance group.





Alarm Service

Alarm Overview

When the status of certain products changes, you can create alarms to promptly notify you to take action. Alarms monitor specific metrics over a certain period and send alarms at configured intervals based on configured thresholds.

An alarm consists of the following components:

- Alarm trigger condition (under what conditions will the alarm be sent)
- Alarm object (which object will send an alarm)
- Alarm recipient group (who receives the alarm).
- Alarm receiving method (how the alarm is received)

This document describes how to create alarms for one or more objects, and select the objects to receive alarms.

1. Basic Concepts

Term	Definition
Alarm policy type	Policy type identifies policy category and corresponds to specific cloud products, with a distinct layer of granularity under cloud products. For example, when you choose Cloud Virtual Machine > Basic Monitoring policy, you can customize alarm metrics such as CPU utilization and disk utilization; when you choose Cloud Virtual Machine > Storage Monitoring policy, you can customize alarm metrics such as disk I/O wait time and disk read traffic.
Alarm rule	Alarm rules correspond to the trigger conditions that specific monitoring metrics should satisfy. For example, when disk utilization exceeds 80% per minute and lasts for 3 minutes, an alarm is triggered once every hour.
Relationship between policy types and alarm rules	An alarm type contains multiple alarm rules and is a collection of a series of alarm rules. For example, when you choose Cloud Virtual Machine > Basic Monitoring policy, the policy includes disk utilization alarms, ping unreachable alarms, CPU utilization alarms, and more.

2. Alarm statuses

Alarm Status	Description
Unresolved	Alarms that have not been handled or are being handled, but the resources are still in an abnormal status.



Alarm Status	Description
Resolved	Alarms have been resolved.
Insufficient Data	- The alarm policy that triggered an alarm has been deleted. - The CVM has been migrated from one project to another. - No data is reported because the Cloud Monitor control has not been installed or has been uninstalled.
Expired	- The alarm policy has changed. - The most recent alarm time has not been updated for more than 24 hours.



Alarm Policies

Creating Alarm Policies

When users need to set alarms for a specific product status, they need to first create an alarm policy. The alarm policy consists of six required components: policy name, monitoring type, policy type, alarm object, trigger condition, and notification template. You can create an alarm policy according to the following instructions:

1. Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration > Alarm Policy.
2. Click Create and configure the alarm according to the following instructions.

Configuration Type	Configuration Item	Description
Basic information	Policy name	Enter a custom policy name.
	Remarks	Enter custom policy remarks.
	Monitoring type	Only cloud service monitoring is supported.
	Policy type	Choose the cloud product policy type you need to monitor, for example, Cloud Virtual Machine > Basic Monitoring.
Alarm rule configuration	Alarm object	○ If you select an instance ID, the alarm policy will be associated with the selected instance. ○ If you select an instance group, the alarm policy will be associated with the selected instance group. ○ If you select all objects, the alarm policy will be associated with all instances under the current account.
	Manual configuration (metric alarm)	Alarm trigger condition: It is a semantically meaningful condition composed of metrics, comparison relation, thresholds, statistical granularity, and continuous N monitoring data points. You can set up alarm thresholds based on the trend of metric changes in the chart. For example, when the metric is CPU utilization, the comparison relation is >, the threshold is 80%, the statistical granularity is 5 minutes, and the number of continuous monitoring data points is 2, the condition means to collect CPU utilization data every 5 minutes, and

Configuration Type	Configuration Item	Description
		if the CPU utilization of a CVM is greater than 80% for two consecutive times, an alarm will be triggered. Alarm frequency: You can set a repeated notification policy for each alarm rule. This way, an alarm notification will be sent repeatedly at a specified frequency when an alarm is triggered. Options: No repetition, 5 minutes, 10 minutes, periodic exponential increasing interval, and other repetition frequencies. An exponentially increasing interval means that alarm information is sent to you when an alarm is triggered the first time, second time, fourth time, eighth time, ... and 2 raised to the power of N times. In other words, the alarm information will be sent less and less frequently as time goes on to reduce the disturbance caused by repeated alarms. Default logic for repeated alarms: An alarm notification will be sent to you at the configured frequency within 24 hours after an alarm is triggered. After 24 hours, the alarm notification will be sent once every day.
	Manual configuration (event alarm)	When an exception occurs in cloud product resources or underlying infrastructure services, you can create an event alarm to promptly notify you to take action. For details, see the Event Center document.
	Template selection	Click the template selection button, and select the configured template from the dropdown list. For specific configurations, see the Trigger Condition Template document. If the created template is not displayed, you can click Refresh on the right side of the dropdown list to refresh the template selection list.
Alarm notification configuration	Alarm notification	Supports choosing a system preset notification template or a user-defined notification template. Each alarm policy can be associated with up to three notification templates. For details, see the Notification Template document.

3. After configuring the above information, click Complete to create the alarm policy.

Trigger Condition Templates

When the same alarm trigger conditions are required for different alarm policies, users can configure an alarm trigger condition template, which can be reused with one click when an alarm policy is created, avoiding repeated configurations. For alarm policies using the alarm trigger condition template, users can modify the template trigger conditions, and the changes will automatically apply to the corresponding alarm policies, improving the Ops efficiency.

Note:

One trigger condition template is used to set up trigger condition rules for one cloud product.

1. Create a trigger condition template.

- i. Log in to the cloud platform console and choose Cloud Monitor > Trigger Condition Template.
- ii. Click Create, and configure the trigger conditions in the pop-up window as follows.
 - Template name: Enter a template name.
 - Note: Enter a note for the template.
 - Policy type: Choose the service to be monitored, such as Cloud Virtual Machine > Basic Monitoring.
 - Trigger condition: It is divided into metric alarm and event alarm. Below it, click Add to set up multiple alarm items.

The screenshot shows the 'Create' dialog for a Trigger Condition Template. The dialog has a sidebar on the left with a 'Create' button highlighted. The main area contains the following fields and options:

- Template Name:** A text input field with a placeholder '1-20 characters or underscores'.
- Remarks:** A text input field with a placeholder '1-100 Chinese and English characters or underscores'.
- Policy Type:** A dropdown menu currently set to 'Cloud Virtual Machine'.
- Trigger Condition:**
 - ☒ **Metric alarm**
 - Condition met:** A dropdown menu set to 'any'.
 - conditions are met.** A text input field.
 - If:** A dropdown menu set to 'CPUUtilization'.
 - Statistical Period:** A dropdown menu.
 - >** A dropdown menu.
 - 0** A text input field.
 - %** A dropdown menu.
 - Last for 1 per** A dropdown menu.
 - then** A dropdown menu.
 - Alarm once every 1 c** A dropdown menu.
 - Add** A button.
 - ☒ **Event Alarm**
 - DiskReadonly** A dropdown menu.
 - Add** A button.

At the bottom right of the dialog are 'Save' and 'Cancel' buttons.

- iii. After completing the configuration, click Save.

2. Edit a trigger condition template.

Note:

When a trigger condition template is already associated with alarm policies, if the trigger condition template is edited, the modification will be applied to all associated alarm policies.

- i. Log in to the cloud platform console and choose Cloud Monitor > Trigger Condition Template.
- ii. In the template list, click the name of the template that needs to be edited to go to the template details



page.

- iii. In the Template Information Tab, you can click different buttons to edit and modify different information items.

Cloud Monitor

Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition Template

Notification Template

Event Center

Cloud Product Monitoring

test

Template informationChange Log

Basic Info

Template Name

test

Policy Type

Cloud Virtual Machine

Last Modified by

Last Modified

2025/09/25 17:39:33

Remarks

Trigger Condition

Edit

Metric alarm any

CPUUtilization > 0%, last for 1 minute(s), repeat alarm every 1 day(s)

Event Alarm


DiskReadonly, alarm is not repeated

Associate Alarm Policy

Policy Name

3. View the change records of the trigger condition template.

1. Log in to the cloud platform console and choose Cloud Monitor > Trigger Condition Template.
2. In the template list, click the name of the template for which you need to view the change records to go to the template details page.
3. In the Change Log tab, you can view the change time, updater, and change result of historical change operations.




4. Delete a trigger condition template.

Note:

When the trigger condition template is already associated with alarm policies, deleting the trigger condition template will cause the alarm policies associated with the template to become invalid.

- Log in to the cloud platform console and choose Cloud Monitor > Trigger Condition Template.
- Locate the template you need to modify in the template list, and click Delete in the operation column on the right to delete the template.



5. Copy a trigger condition template.

Note:

Copying a trigger condition template means that only the trigger condition rules of the template will be copied, while the association between the template and alarm policies will not be copied.

- Log in to the cloud platform console and choose Cloud Monitor > Trigger Condition Template.
- On the trigger condition template list page, locate the template you need to copy, and click Copy in the operation column on the right.
- In the pop-up dialog box, click Confirm Copy to copy the trigger condition template.



Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition Template

Notification

Trigger conditions in trigger condition templates can be reused and modified in batches. [Learn more](#)

Create

Search by trigger condition template name

Template Name	Trigger Condition	Policy Type	Remarks	Bound Alarm Policies	Last Modified	Operation
test	CPUUtilization > 0%, last for 1... DiskReadonly, alarm is not rep...	Cloud Virtual Machine	-	0	2025/09/25 17:39:33	CopyDelete

1 item(s) in total

Lines per page 20

1/1

Associating and Dissociating Objects

After creating an alarm policy, you need to associate some alarm objects with it to indicate which instance objects will trigger an alarm when they meet the alarm trigger conditions.

1. Add an associated object.

- Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration > Alarm Policy.
- In the alarm policy list, click on the name of the alarm policy you want to associate objects with to enter the policy details page.
- In the Alarm Object module, click Edit.
- In the pop-up box for alarm object editing, users can select instance ID, instance group, or all object types, and then choose the instance objects or instance groups available for that type accordingly.
- Click OK to establish the association between the alarm policy and the alarm object.

2. Remove the association.

- Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration > Alarm Policy.
- In the alarm policy list, click on the name of the alarm policy you want to associate objects with to enter the policy details page.
- In the Alarm Object module:
 - If the alarm policy is already associated with an alarm object, click Remove after selecting the instances for which you want to remove the association, and then click Remove in the pop-up confirmation dialog box. If you need to remove the association between the alarm policy and all instances, click Remove All, and then click Remove All in the pop-up confirmation dialog box to remove the association between the selected instances and the alarm policy.


- If the alarm policy is already associated with an instance group, click Unbind on the right side of the instance group for which you want to remove the association. In the pop-up confirmation dialog box, click Confirm Unbind to remove its association with the alarm policy.

Alarm Notifications

Creating and Managing Alarm Recipient Groups

Alarm recipient groups determine who can receive alarm notifications. You can group people concerned with the same alarms into a group, so when an alarm is triggered, everyone in the group receives the corresponding alarm notification.

1. Create an alarm recipient group.
 - i. Log in to the cloud platform console, move the mouse pointer over your account avatar, and click Access Management.



- ii. Choose User Management > User Group.
- iii. Click Create New User Group, fill in the user group name and remarks, and then click Submit to create it successfully.
- iv. In the operation column on the right side of the created user group, click Add User. Alternatively, click the user group name to go to the user group details page, choose the Added Users tab, and click Add User.
- v. In the pop-up Add User window, select the users you want to add to the user group, and then click

OK.

2. You can also manage and create alarm recipient groups when configuring the alarm notification template.

- i. Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration > Alarm Policy.
- ii. In the alarm policy list, click the name of the alarm policy you want to associate objects with to enter the Details page.
- iii. In the Alarm Notification module, click Create New Template.
- iv. In the pop-up Create Notification Template box, when a user group is selected as the recipient, click Add User Group to redirect to the CAM console to configure user groups.

3. Manage an alarm recipient group.

- i. Log in to the cloud platform console, move the mouse pointer over your account avatar, and click Access Management.
- ii. Choose User Management > User Group.
- iii. If you want to delete a user group, locate it in the user group list, click Delete in the operation column on the right, and then click Confirm to Delete.
- iv. If you want to manage user members in a user group, click the name of the user group you want to manage to go to the user group details page, and choose the Added Users tab.
- v. If you want to add a user, click Add User. If you want to remove a user, select the user you want to remove, and click Remove User or Remove from Group.

Alarm Callback

By using API callbacks, you can directly receive alarm notifications from the Cloud Platform (TCOP) on your self-built system. API callbacks can push alarm information to URLs that are accessible over the public network through HTTP POST requests. You can take further actions based on the alarm information pushed by API callbacks.

1. Usages

- Callback API: Users need to provide a URL that is capable of receiving HTTP POST requests and is accessible over the public network as the callback address.
- Callback trigger: the trigger logic is similar to that of alarm SMS and emails. When an alarm policy created by the user is triggered or the alarm is resolved, the alarm messages will be pushed through the API callbacks. API callbacks also support repeated alarms.
- Binding API Callbacks: Users can configure API callbacks during the API Callback step of creating an alarm, or add API callbacks on the alarm policy details page. A single alarm policy group can only be bound to one alarm callback URL.
- Returned content: After sending an alarm notification to the user's bound URL, we need to receive the following returned content to confirm that the user has successfully received the information; otherwise, we will resend the alarm notification, up to three times.

Note:

sessionId, used to authenticate the callback request.

retCode, to determine whether the request was successfully sent.

```
{
  sessionId: "xxxxxxx",
  retCode: 0
}
```

2. Callback Parameters

The callback API will send data in JSON format through HTTP POST requests. The parameters are as follows:

```
{
  "sessionId": "xxxxxxx",
  "alarmStatus": 1,
  "alarmObjInfo": {
    "region": "CAX01", // This field will not be returned for products that are not region-specific.
```



```
"namespace": "qce/cvm",    // Product namespace
"dimensions": {           // Content in the dimensions field varies by service.
  "unInstanceId": "ins-o9p3rg3m",
  "objId": "xxxxxxxxxxxx",
}
}
"alarmPolicyInfo": {
  "policyId": "policy-n4exeh88", // ID of the alarm policy group.
  "policyType": "cvm_device",    // Alarm policy type.
  "policyName": "test",         // Name of the alarm policy group.
  "conditions": {
    "metricName": "cpu usage",    // Metric name.
    "metricShowName": "CPU usage", // Displayed metric name.
    "calcType": ">",             // This field will not be returned for metrics without a threshold.
    "calcValue": "90",           // This field will not be returned for metrics without a threshold.
    "currentValue": "100",       // This field will not be returned for metrics without a threshold.
    "unit": "%",                // This field will not be returned for metrics without a threshold.
    "period": "60",             // This field will not be returned for metrics without a threshold.
    "periodNum": "1",           // This field will not be returned for metrics without a threshold.
    "alarmNotifyType": "continuousAlarm", // Whether repeated alarms are supported, this field will not be returned for metrics without a threshold.
    "alarmNotifyPeriod": 300     // Frequency of repeated alarms. This field will not be returned for metrics without a threshold.
  }
  "firstOccurTime": "2017-03-09 07:00:00", // TTime when the alarm is triggered for the first time.
  "durationTime": 500,             // Alarm duration in seconds.
  "recoverTime": "0"              // Time when the alarm is resolved in seconds. If it is not resolved, the value is 0.
}
}
```

Receiving Alarm Notifications Through a WeCom Group

1. Limitations

Regarding sending WeCom group messages, the number of messages sent by each bot cannot exceed 20 per minute. If you have many alarm policies, it is recommended to create multiple bots and associate alarm policies with different bots. Otherwise, multiple alarm policies may trigger alarms simultaneously, and you may fail to receive some alarm notifications as a result.

2. Step 1: Add a bot on WeCom.

i. WebCom for PC

On WeCom for PC, find the target WeCom group for receiving alarm notifications.

Select and right-click the WeCom group. In the pop-up box, click Add Group Robot.

In the pop-up box, click Create a New Robot.

In the pop-up box, enter a custom bot name and click Add Robot.

Copy the webhook URL and configure the API callback by following Step 2.

ii. WebCom for Web

On WeCom for Web, open the target WeCom group for receiving alarm notifications.

Click the group settings icon in the upper-right corner.

On the Group Settings page, choose Group Bot > Add Robot.

On the Add Bot page, enter a custom name for the new bot.

Click Add, copy the webhook URL, and configure the API callback by following Step 2.

WeCom alarm messages are in markdown format.

3. Step 2: Configure the alarm API callback.

i. Log in to the cloud platform console and choose Cloud Monitor > Notification Template.

ii. Click Create to enter the Create Notification Template page.

iii. After configuring the basic information, paste the copied webhook URL in the API callback field.

Cloud Monitor

Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition Template

Notification Template

Event Center

Cloud Product Monitoring

Create Notification Template

Basic Info

Template Name

It can contain up to 64 characters, letters, digits, underscores, or symbol (-).

Notification Type

☒ Alarm Trigger

☒ Alarm Recovery

Notification Language

English

Notifications (Fill in at least one item)

User Notification

You can add a user only for receiving messages.

Recipient Object

User

Notification Period

00:00:00 ~ 23:59:59

Receiving Channel

☒ Email

☒ SMS

☐ WeCom

☐ Call

Add User Notification

API Callback

Enter a URL accessible over public networks as the API callback address (domain name or IP[:port]/[path])

Add API Callback

iv. On the Alarm Policy List page, click the name of the alarm policy to be associated with an alarm callback to enter the Manage Alarm Policy page. Associate a notification template on the Alarm Policy page. After successful configuration, when an alarm policy is triggered or recovered, you can receive alarm notifications sent by the group bot in the WeCom group.

Copyright: Converge Cloud

8/2/2026, 8:21:54 AM

45 Pages Total 374 Pages

Notification Template

1. Creating Notification Template

- i. Log in to the Cloud Platform console, and click Cloud Monitor > Notification Template.
- ii. Click Create and enter relevant information in Create Notification Template.
 - Template Name: Enter a custom template name.
 - Notification Type:
 - Alarm Trigger: A notification will be sent when an alarm is triggered.
 - Alarm Recovery: A notification will be sent when an alarm is resolved.
 - User Notification:
 - Recipient: Optional users or user groups. For creating an alert receiving group, please refer to Create and Manage Alert Receiving Groups.
 - Notification Period: Define the time period for receiving alarms.
 - Receiving Channel: Supports three alarm channels: Email, and SMS . You can modify the user's phone, and email information in CAM to decide how the user receives the alert information.
 - API Callback: You can enter up to three URLs accessible over the public network as the callback API addresses, and Cloud Monitor will push alarm messages to them promptly. If the HTTP response returns code 200, the verification is successful. For more information on alarm callback fields, see Alarm Callback Parameters.
 - After you save the callback URL, the system will automatically verify your URL once. The timeout threshold for this verification is 5 seconds. When an alarm policy created by the user is triggered or the alarm is resolved, the alarm messages will be pushed through the API callbacks. An alarm message can be pushed up to three times, and the timeout threshold for each request is 5 seconds.
 - When an alarm policy created by the user is triggered or the alarm is resolved, the alarm messages will be pushed through the API callbacks. API callbacks also support repeated alarms.
 - The outbound IP of the Cloud Monitor callback API is dynamically and randomly allocated, so



no specific IP information can be provided to you, but the IP port is fixed at 80. We recommend you configure a weighted opening policy in the security group based on port 80.

iii. Click Complete to create a notification template.

2. Default Notification Template

The system automatically creates a default notification template for you as detailed below:

Feature	Default Configuration
Template Name	Preset notification template
Notification Type	Alarm trigger, alarm recovery
Alarm Recipient	Root account administrator
Notification Period	00:00:00–23:59:59 (all day)
Receipt Channel	Email, SMS

3. You can also create a new notification template when configuring the alarm policy.

- Log in to the Cloud Platform console, click Cloud Monitor > Alarm Configuration > Alarm Policy.
- In the alarm policy list, click on the name of the alarm policy associated with the object to enter its details page.
- In the alarm notification module, click Create Template.
- In the pop-up Create Notification Template dialog, enter the template name, select the recipient and the receiving channel, and then click Confirm to complete creating the notification template.

Custom Callback Content Templates

Scenarios

Through a custom callback content template, you can customize the content and field mapping of the callback message body. This document describes how to create a custom callback content template.

Operation Steps

1. Log in to the cloud platform console, choose Cloud Monitor > Notification Template, and select the Callback Content Template tab.
2. Click Create Callback Content Template, and configure the content and field mapping of the callback message body on the page.

Note:

Write the callback content template in JSON format. For details, see the callback content example on the right side of the page. Format issues may cause the callback content to fail to parse.

1. Users can click Use the Preset Callback Content to automatically fill in the preset callback content and perform customization based on the preset callback content.
2. The list on the right of the callback content shows the currently supported variable placeholders. Users can directly click to copy and use them.



Cloud Monitor

Monitoring Overview

Dashboard

Instance Group

Alarm Records

Alarm Configuration

Trigger Condition Template

Notification Template

Event Center

Cloud Product Monitoring

Language

Callback content

AlarmTrigger Use preset callback content

Body

```
{
  "uin": "{{.uin}}",
  "appid": "{{.appid}}",
  "sessionId": "{{.sessionId}}",
  "alarmStatus": {{.alarmStatus}},
  "alarmObjInfo": {
    "region": "{{.region}}",
    "namespace": "{{.namespace}}",
    "dimensions": {{.alarmObject}}
  },
  "alarmPolicyInfo": {
    "policyType": "{{.policyType}}",
    "policyName": "{{.policyName}}",
    "conditions": {
      "metricName": "{{.metricName}}",
      "metricShowName": "{{.metricShowName}}",
      "calcType": "{{.calcType}}",
      "metricName": "CPU Utilization",
      "calcType": ">"
    }
  }
}
```

Write the callback content template in JSON format, refer to the callback content example on the right, format problems may cause the callback content to be unparseable

AlarmRecovery Use preset callback content

Body

Alarm content example

```
{
  "uin": "554212",
  "appid": "124567",
  "sessionId": "xxxxxxxx",
  "alarmStatus": 1,
  "alarmObjInfo": {
    "region": "qce/cvm",
    "namespace": "qce/cvm",
    "dimensions": "alarmObject"
  },
  "alarmPolicyInfo": {
    "policyType": "cvm_device",
    "policyName": "test",
    "conditions": {
      "metricName": "cpu usage",
      "metricShowName": "CPU Utilization",
      "calcType": ">"
    }
  }
}
```

Variable	Unfold	Fold	Explanation	Example
{{.uin}}			Account uin	233332
{{.appid}}			Account appid	1232312

3. Click OK to complete the creation of the callback content template.
4. When you choose Create Alarm Policy > Configure Alarm Notifications, if the notification template includes a callback method, you can select a custom callback content template. After the configuration is completed, the callback content will be sent based on the template.

Note:

Users can only select a callback content template with the same language as the notification template.

Variable Description

Currently, only the following variables can be used as placeholders for custom notification content. If an invalid variable is used, the field of the callback content may have no data in it.

Variable	Description	Example
{{.uin}}	Account UIN.	233332
{{.appId}}	Account AppID.	1232312
{{.sessionId}}	Alarm sessionId.	LxePI1H4oYQCeg9BN1WZ74JG
{{.alarmStatus}}	Alarm status.	0: alarm recovered; 1: alarm triggered; -: no status notification
{{.region}}	Region.	Cavite



{{.namespace}}	Namespace.	convergecloud/cvm
{{.alarmObject}}	Cloud product dimension information.	{"unInstanceId": "ins-o9p3rg3m", "objId": "xxxxxxxxxxxxx"}
{{.policyType}}	Alarm policy type.	cvm_device
{{.policyName}}	Alarm policy name.	CVM alarm
{{.metricName}}	Metric name.	cpu usage
{{.metricShowName}}	Metric display name.	CPU utilization
{{.calcType}}	Calculation type.	>
{{.calcValue}}	Threshold.	90
{{.currentValue}}	Current value.	92
{{.unit}}	Unit.	%
{{.period}}	Statistical granularity (unit: s).	5
{{.periodNum}}	Number of lasted data points.	5
{{.alarmNotifyType}}	Whether repeated alarms are supported. singleAlarm: single alarm; exponentialAlarm: exponential period alarm; continuousAlarm: continuous alarm. For metrics without thresholds, this field is not returned.	singleAlarm
{{.alarmNotifyPeriod}}	Alarm notification frequency (unit: s).	300
{{.firstOccurTime}}	First occurrence time.	2024-07-09 14:35:00 (UTC+08:00)
{{.durationTime}}	Alarm duration (unit: s).	500
{{.recoverTime}}	Recovery time (0 when not recovered).	0

Viewing Alarm Records

Cloud Monitor provides you with the alarm records feature, allowing you to trace and view alarm records from the last six months. You can also quickly subscribe to alarm policies on the Alarm Records page.

1. View alarm records.


- Log in to the cloud platform console, and choose Cloud Monitor > Alarm Records.
- (Optional) To view alarm records for a certain time period, click the time filter button in the upper-left corner. You can filter alarms generated today, yesterday, and in the last 7 days or 30 days, and you can also select a custom time period. You can view the alarm records in the last six months at most.
- (Optional) You can enter the information of an alarm object (such as instance name, public IP address, and private IP address) in the Alarm Object search box to search for corresponding records.
- (Optional) You can click Advanced Filter to search for matching alarm records based on policy name, alarm content, user information, monitoring type, policy type, and alarm object.
- (Optional) You can click the alarm policy name in the list of alarm records to redirect to the detailed alarm policy information.

2. Clear filter conditions.

After successfully filtering alarm records, click Clear Filter Conditions in the list.

3. Customize list fields.

- Log in to the cloud platform console, and choose Cloud Monitor > Alarm Records.
- Click the settings icon in the upper-right corner. You can select the fields to be displayed in the left section of the pop-up box and drag field names in the right section to reorder them, as shown below.



4. Download the list of alarm records.

- Log in to the cloud platform console, and choose Cloud Monitor > Alarm Records.
- Click the download icon in the upper-right corner to save the alarm records as a local .csv file.



Event Center

Event Center Overview

1. Event overview

An event is a medium that carries information, describing a non-persistent change of a specific object at a particular moment, associated with a unique moment and a unique object. For example, a computer changing from running to shutdown status, the start and end of a program run, or a power outage in an office building. An event is a record of the change at a moment between two different states of an object.

The purpose of monitoring services is to assist in the discovery, location, and resolution of issues, ensuring the overall stability and performance of systems and services. Information and data are the core drivers of Ops and monitoring.

Metrics, as the primary source of monitoring information, describe the numerical values and trends of specific variables of particular objects over time in a threshold-based, periodic, persistent form. They reflect the usage and health status of resources and environments. For example, the CPU utilization of a CVM and the number of slow queries in a database instance.

Metrics can cover the vast majority of scenarios where monitoring identifies issues. However, using metrics alone as the monitoring information source has the following drawbacks:

- Information transmission latency: Changes in metric thresholds may only become apparent (or not at all) some time after a specific event has occurred.
- Low accuracy and distinguishability of transmitted information: It becomes more challenging to determine and locate real events or the causes of issues based only on changes in thresholds.
- Limited dimensions of information: Metrics record information only in threshold form, lacking the capability to provide additional supplementary and ancillary information through textual means.

Events are introduced as a carrier of monitoring information to more accurately and directly describe the operational status of resources and underlying infrastructure services, facilitating the discovery, location, and resolution of issues in a more efficient manner.

The advantages of introducing events include improving information accuracy in a result-oriented manner, reducing latency, conveying more information, and enhancing the dimensionality of monitoring information.

2. Event Center introduction

As the event information center of the cloud platform, Cloud Monitor's Event Center manages the important event information during the lifecycle and running of all product resources on the cloud platform. It builds a complete event consumption channel and process to support users' monitoring and Ops on the cloud.

The event information provided by Event Center is obtained from various product modules and underlying infrastructure services on the cloud platform. It is then aggregated, determined, condensed, and finally displayed. The information sources originate from the underlying system logs and monitoring items of each module, ensuring the accuracy and value of the information for users.


3. Event Type

Based on the information source, cause, characteristics, and form of events, the events covered by Event Center are divided into two main categories: product events and platform events, each supported by two separate product pages and consumption processes.

- Product events: They originate from the products and resource instances (such as a CVM instance)

purchased and used by users on the cloud. They are directly or indirectly triggered by users' operational behaviors during use, and belong to the dimension specific to particular resource instances. Users have control over the events and the ability to handle them themselves. The impact and associated resource instances of the events can be identified.

- Platform events: They are generated in the underlying infrastructure and services that support the cloud platform (such as the virtualization layer VMM, underlying physical servers, networks, and storage modules that support CVM). They are generated or caused by the underlying infrastructure and services that support the cloud platform. Since the root causes of events are not user behaviors and events belong to the service dimension, users can not control these events, and only the cloud platform has the handling capability. Services and product modules affected by and associated with events can be identified, but the affected and associated resource instances may not be identified.



• Event comparison


Comparison Item	Product Event	Platform Event
Event source	Products and resource instances purchased and used by users on the cloud.	Underlying infrastructure services of the cloud platform.
Event cause	Directly or indirectly triggered by users' operational behaviors.	Generated or caused by the underlying cloud infrastructure and services.
Event dependency dimension	Resource instances.	Underlying services.
Event handling capability	Users have control over the events and can handle them themselves.	Users have no control over the events and need the cloud platform to handle them.
Event-related object granularity	The impacted and associated resource instances can be	The impacted and associated underlying services or product modules can be confirmed, while the

clearly confirmed.

impacted resource instances upstream may not be confirmed.

4. Event Center use cases

Based on event information, Event Center plans and provides comprehensive event consumption channels and capabilities.



- Presentation and tracing: Records all event information related to the account, with the console providing the ability to view, globally filter, search, and trace event information.
- Alarm notifications: Enables users to receive alarms or subscribe to notifications for monitored events and resources, ensuring timely communication with the owner.
- Retrieval with APIs: Provides APIs to retrieve event information for integration with self-built monitoring systems.
- Automation: Subsequent updates will support configuring linked invocation operations with events as triggers, enabling users to achieve automated Ops.

5. Benefits

- It enhances the monitoring information dimensions of cloud resources, providing more comprehensive data support for monitoring and Ops.
- It provides event information consumption channels, aiding in the transformation of monitoring information into value.
- It converges determination logic to more efficiently and directly pinpoint impacted resources and causes.
- It allows traceable review of event information, ensuring awareness of significant changes in resource and platform lifecycle events.
- It can trigger automatic responses to specific resource and environment changes.



Product Event List

The Event Center of Cloud Monitor currently provides the following monitoring information for product events:

1. CVM

Event Name	Event English Name	Event Type	Event Dimension	Recovery Concept Involved	Event Description	Handling Method and Suggestion
Kernel Failure	GuestCoreError	Exception	CVM instance	No	An operating system kernel bug or driver issue causes a critical error in the operating system kernel.	1.Check whether any kernel driver modules are loaded into the system other than those provided by the kernel. Try not to load these modules and observe the operating status of the system. 2. Monitor bug reports of the kernel and operating system distributions, and consider upgrading the kernel to resolve the bugs. 3. By default, kdump is enabled for CVM instances. When a panic occurs, system memory dump information will be generated in the /var/crash directory. Use the crash tool to analyze the information.
Out of Memory (OOM)	GuestOom	Exception	CVM instance	No	System memory usage is overloaded.	1.Check whether the memory capacity configured in the current



Event Name	Event English Name	Event Type	Event Dimension	Recovery Concept Involved	Event Description	Handling Method and Suggestion
						system meets business requirements. If additional capacity is required, it is recommended to upgrade the CVM memory configuration. 2. View processes that are terminated during OOM based on system logs (such as dmesg and /var/log/messages) to check whether the memory used by the processes meets the expectations. Use tools such as valgrind to analyze whether memory leakage occurs.
Disk read-only	DiskReadonly	Exception	CVM instance	Yes	Data cannot be written into the disk.	1.Check whether the disk storage is full. 2. For Linux operating systems, check whether inodes are exhausted (df -i). 3. Check whether the file system is corrupted.
Server Restart	GuestReboot	Status change	CVM instance	Yes	The CVM instance is restarted.	This event is triggered when the CVM instance is restarted. Check whether the status



Event Name	Event English Name	Event Type	Event Dimension	Recovery Concept Involved	Event Description	Handling Method and Suggestion
						change meets the expectations based on the actual situation.
Packet Loss Due to Outbound Bandwidth Limit of the Public Network Exceeded	PacketDroppedByQosWanOutBandwidth	Exception	CVM instance	Yes	The outbound public network bandwidth of the CVM instance exceeds the upper limit, causing packet loss.	Increase the upper limit of the public network bandwidth. If the maximum purchase limit has been reached, reduce the bandwidth usage of the instance through means such as load balancing.
Packet Loss Due to Connection Limit Exceeded	PacketDroppedByQosConnectionSession	Exception	CVM instance	Yes	An excessive number of connections to the CVM instance leads to packet loss. Taking the 8255C CPU model as an example, it is generally recognized that if the number of connections exceeds 500,000, packet loss may occur.	Contact after-sales service personnel.

2. VPN Gateway

Event Name	Event English Name	Event Type	Event Dimension	Recovery Concept Involved	Event Description	Handling Method and Suggestion
Packet Loss	PacketDroppedByQosWanOutBandwidth	Exception	VPN	Yes	The	Increase



Event Name	Event English Name	Event Type	Event Dimension	Recovery Concept Involved	Event Description	Handling Method and Suggestion
Due to Outbound Bandwidth Limit of the Public Network Exceeded			gateway instance		outbound public network bandwidth of the VPN gateway instance exceeds the upper limit, causing packet loss.	the upper limit of the public network bandwidth.
Packet Loss Due to Connection Limit Exceeded	PacketDroppedByQosConnectionSession	Exception	VPN gateway instance	Yes	The number of connections to the VPN gateway instance exceeds the limit, causing packet loss.	Contact after-sales service personnel.

Cloud Product Monitoring

Cloud Product Monitoring Metrics Overview

This section describes the monitoring metrics for various products in Cloud Monitor.

Computing

- For CVM, see [CVM](#).
- For Kubernetes Engine (TKE), see [Monitoring Metrics for TKE](#).
- For Bare Metal Server (BMS), see [Monitoring Metrics for BMS](#).

Network

- For Cloud Load Balancer (CLB), see [Monitoring Metrics for CLB](#).
- For Virtual Private Cloud (VPC), see [Monitoring Metrics for VPC](#).
- For Direct Connect (DC), see [Monitoring Metrics for DC](#).

Storage

- For Cloud Block Storage (CBS), see [Monitoring Metrics for CBS](#).
- For Cloud Object Storage (COS), see [Monitoring Metrics for COS](#).
- For Cloud Storage Private (CSP), see [Monitoring Metrics for CSP](#).
- For Cloud File Storage (CFS), see [Monitoring Metrics for CFS](#).

Database

- For CloudDB for Redis® (Redis®), see [Monitoring Metrics for Redis®](#).
- For TDSQL for MySQL, see [Monitoring Metrics for TDSQL for MySQL](#).
- For Cloud MongoDB (MongoDB), see [Monitoring Metrics for MongoDB](#).

Middleware

- For TDMQ for CMQ (CMQ), see [Monitoring Metrics for CMQ](#).
- For TDMQ for CKafka (Ckafka), see [Monitoring Metrics for Ckafka](#).
- For Service Framework (TSF), see [Monitoring Metrics for TSF](#).
- For TDMQ for Apache Pulsar (TDMQ Pulsar), see [Monitoring Metrics for TDMQ Pulsar](#).

TI-ONE

- For TI-ONE Platform, see [Monitoring Metrics for TI-ONE Platform](#).





CVM

CVM Monitoring Metrics

CVM monitoring metrics need to be collected through the CVM monitoring component. Users can automatically install the monitoring component by selecting Cloud Monitor when purchasing machines, or manually install it based on the [Monitoring Component Installation Guide](#).

Cloud Monitor provides the following monitoring metrics for CVM instances:

Metric/Event ID	Metric/Event Name	Unit	Metric Description
CPUUsage	CPU utilization	%	Real-time CPU utilization during machine operation.
BaseCpuUsage	Basic CPU utilization	%	Basic CPU utilization is collected and reported by the host, and data can be viewed without the need to install the monitoring component. Data can still be collected and reported even when the instance is under high load.
MemUsed	Memory usage	MB	Amount of memory actually used by the user, excluding the memory occupied by buffers and system cache.
MemUsage	Memory utilization	%	Amount of memory actually used by the user, excluding the memory occupied by buffers and system cache.
CvmDiskUsage	Disk utilization	%	Disk utilization monitoring.
DiskIOAwait	Disk I/O wait	ms	Average wait time per I/O operation for disk partitions.
DiskReadtraffic	Disk read traffic	KB/s	Average data read volume from disk to memory per second.
DiskWritetraffic	Disk write traffic	KB/s	Average data write volume from memory to disk per second.
LanIntraffic	Inbound private network bandwidth	MB/s	Average inbound traffic per second on private NIC.



Metric/Event ID	Metric/Event Name	Unit	Metric Description
LanOuttraffic	Outbound private network bandwidth	MB/s	Average outbound traffic per second on private NIC.
LanInpkg	Number of inbound packets on the private network	Counts/second	Average inbound packet volume per second for private NIC.
LanOutpkg	Number of outbound packets on the private network	Counts/second	Average outbound packet volume per second for private NIC.
WanIntraffic	Inbound public network bandwidth	MB/s	Average inbound traffic per second on public NIC.
WanOuttraffic	Outbound public network bandwidth	MB/s	Average outbound traffic per second on public NIC.
WanInpkg	Number of inbound packets on the public network	Counts/second	Average inbound packet volume per second for public network NIC.
WanOutpkg	Number of outbound packets on the public network	Counts/second	Average outbound packet volume per second for public network NIC.
TcpCurrEstab	Number of TCP connections	Count	Monitoring of TCP connections.

Installing the CVM Monitoring Component

If users need to use Cloud Monitor to view the CVM metric data and trigger alarms, they need to correctly install the monitoring component on the CVM, as CVM metric data collection depends on the monitoring component.

Note: To ensure the normal reporting of monitoring data, the user's CVM needs to allow tcp dport 80.

Linux Installation Guide

After [logging in to the Linux instance](#), users can execute the following commands for installation:

```
wget http://update2.agent.convergecloud.com/update/linux_stargate_installer
chmod +x linux_stargate_installer
./linux_stargate_installer
```

If the installation is successful, the following content will be displayed:

```
root@vm-10-218-shuntan:~# crontab -l | grep stargate
*/1 * * * * /usr/local/qcloud/stargate/admin/start.sh > /dev/null 2>&1 &
```

```
root@vm-10-218-shuntan:~# ps ax | grep sgagent
14751 ?        S1           0:00 /usr/local/qcloud/stargate/sgagent -d
```

```
root@vm-10-218-shuntan:~# ps ax | grep barad_agent
15286 pts/0    S+           0:00 grep --color=auto barad_agent
22515 ?        S             0:06 barad_agent
22530 ?        S             1:04 barad_agent
22531 ?        S1           10:16 barad_agent
```

Windows Installation Guide

1. After [logging in to the Windows instance](#), users can access <http://update2.agent.tencentyun.com/update/windows-stargate-installer.exe> via the private network to download the installation package windows-stargate-installer.exe .
2. Run this program to perform automated installation.

Common Causes and Solutions for Monitoring Components Going Offline

Offline criteria for monitoring components:

When the monitoring component of a CVM fails to report data for 5 consecutive minutes, the platform considers the monitoring component of this CVM to be offline.

The following are the top causes for monitoring components going offline and the corresponding troubleshooting methods.

1. User Operations on the CVM Through the Console or Command Line

When a CVM is shut down through operations, it enters a shutdown status, causing the monitoring component to go offline and no data available.

When users operate through the CVM console or log into the CVM to perform common CVM Ops such as restarting, upgrading the CVM, reinstalling, or creating images, it will result in a timeout in CVM monitoring data reporting, causing the monitoring component to go offline.

Troubleshooting method: You can check whether there are relevant Ops on the CVM based on the specific time point. You can also view operation logs by clicking Operation Log on the CVM Details page.

2. High Load on the CVM

High CPU load, full memory, and full bandwidth on CVM can all lead to abnormal data reporting by the monitoring component.

Troubleshooting method: You can log in to the CVM or view the monitoring views to check whether CPU, memory, and bandwidth utilization reach 100%. If so, you can scale out the CVM based on the actual situation.

3. Configuration Error of CVM's Private DNS

The configuration error of CVM's private DNS will prevent the monitoring component from reporting data.

Troubleshooting method: For private DNS configuration of the Cloud Platform, see [Private DNS Access and Configuration](#).



Monitoring Metrics for TKE

Cloud Monitor provides monitoring metrics for TKE in the following dimensions:

Monitoring Metrics for Clusters

Metric ID	Metric Name	Unit
K8sClusterNodeTotal	Number of nodes	Count
K8sClusterPodsUsedTotal	Number of Pods	Count
K8sClusterAllocatablePodsTotal	Number of allocatable Pods	Count
K8sClusterCpuCoreTotal	Total CPU configuration	Cores
K8sClusterRateCpuCoreRequest	CPU allocation percentage	%
K8sClusterCpuCoreUsed	CPU usage	Cores
K8sClusterEksCpuCoreUsed	CPU usage (elastic containers)	Cores
K8sClusterRateCpuCoreUsed	CPU utilization	%
K8sClusterMemoryTotal	Total memory	GB
K8sClusterRateMemRequestBytes	Memory allocation rate	%
K8sClusterMemUsageBytes	Memory usage	MB
K8sClusterRateMemUsageBytes	Memory utilization	%
K8sClusterMemNoCacheBytes	Memory usage (excluding cache)	MB
K8sClusterRateMemNoCacheBytes	Memory utilization (excluding cache)	%
K8sClusterEksMemUsageBytes	Memory usage (elastic containers)	MB
K8sClusterEksMemNoCacheBytes	Memory usage (elastic containers, excluding cache)	MB
K8sClusterNetworkReceiveBytes	Inbound network traffic	MB
K8sClusterNetworkTransmitBytes	Outbound network traffic	MB
K8sClusterNetworkReceiveBytesBw	Inbound network bandwidth	MB/s



Metric ID	Metric Name	Unit
K8sClusterNetworkTransmitBytesBw	Outbound network bandwidth	MB/s
K8sClusterNetworkReceivePackets	Number of inbound network packets	Counts/ second
K8sClusterNetworkTransmitPackets	Number of outbound network packets	Counts/ second
K8sClusterFsReadTimes	Number of reads from the block device	Times
K8sClusterFsWriteTimes	Number of writes on the block device	Times
K8sClusterFsReadBytes	Size of data read from the block device	MB
K8sClusterFsWriteBytes	Size of data written on the block device	MB
K8sClusterEtcdDbTotalSizeBytes	etcd storage capacity	MB
K8sClusterGpuTotal	Total GPU	Cards
K8sClusterRateGpuRequest	GPU allocation rate	%
K8sClusterGpuUsed	GPU usage	Cards
K8sClusterRateGpuUsed	GPU utilization	%
K8sClusterGpuMemoryTotalBytes	Total GPU memory	GB
K8sClusterRateGpuMemoryRequest	GPU memory allocation rate	%
K8sClusterGpuMemoryUsedBytes	GPU memory usage	MB
K8sClusterRateGpuMemoryUsed	GPU memory utilization	%

Monitoring Metrics for Nodes

Metric ID	Metric Name	Unit
K8sNodeStatus	Node status	-
K8sNodePodRestartTotal	Number of Pod restarts	Times
K8sNodeCpuCoreRequest	CPU allocation	Cores
K8sNodeCpuUsage	CPU utilization	%



Metric ID	Metric Name	Unit
K8sNodeMemRequestBytes	Memory allocation	MB
K8sNodeMemUsage	Memory utilization	%
K8sNodeLanIntraffice	Inbound private network bandwidth	MB/s
K8sNodeLanOuttraffice	Outbound private network bandwidth	MB/s
K8sNodeWanIntraffice	Inbound public network bandwidth	MB/s
K8sNodeWanOuttraffice	Outbound public network bandwidth	MB/s
K8sNodeTcpCurrEstab	Number of TCP connections	Count
K8sNodeGpuUsed	GPU usage	Cards
K8sNodeRateGpuUsed	GPU utilization	%
K8sNodeGpuMemoryUsedBytes	GPU memory usage	MB
K8sNodeRateGpuMemoryUsed	GPU memory utilization	%
K8sNodeEniipRequestNode	eniip allocation on the node	Count
K8sNodeDirecteniRequestNode	direct_eni allocation on the node	Count

Monitoring Metrics for Workloads

Metric ID	Metric Name	Unit
K8sWorkloadAnomaly	Workload exception	-
K8sWorkloadPodsUsedTotal	Number of Pods	Count
K8sWorkloadPodRestartTotal	Number of Pod restarts	Times
K8sWorkloadCpuCoreUsed	CPU usage	Cores
K8sWorkloadRateCpuCoreUsed	CPU utilization	%
K8sWorkloadRateEksCpuCoreUsedPod	CPU utilization (elastic containers, as % of Pod specification)	%
K8sWorkloadMemUsageBytes	Memory usage	MB
K8sWorkloadRateMemUsed	Memory utilization	%



Metric ID	Metric Name	Unit
K8sWorkloadMemNoCacheUsedBytes	Memory usage (excluding cache)	MB
K8sWorkloadRateMemNoCacheUsed	Memory utilization (excluding cache)	%
K8sWorkloadRateEksMemUsedPod	Memory utilization (elastic containers, as % of Pod specification)	%
K8sWorkloadRateEksMemNoCacheUsedPod	Memory utilization (elastic containers, as % of Pod specification, excluding cache)	%
K8sWorkloadNetworkReceiveBytesBw	Inbound network bandwidth	MB
K8sWorkloadNetworkTransmitBytesBw	Outbound network bandwidth	MB
K8sWorkloadNetworkReceiveBytes	Inbound network traffic	MB
K8sWorkloadNetworkTransmitBytes	Outbound network traffic	MB
K8sWorkloadNetworkReceivePackets	Number of inbound network packets	Counts/ second
K8sWorkloadNetworkTransmitPackets	Number of outbound network packets	Counts/ second
K8sWorkloadGpuUsed	GPU usage	Cards
K8sWorkloadRateGpuUsed	GPU utilization	%
K8sWorkloadRateEksGpuUsed	GPU utilization (elastic containers)	%
K8sWorkloadGpuMemoryUsedBytes	GPU memory usage	MB
K8sWorkloadRateGpuMemoryUsed	GPU memory utilization	%
K8sWorkloadEksGpuVideoMemoryUsedBytes	GPU memory usage (elastic containers)	MB
K8sWorkloadRateEksGpuVideoMemoryUsed	GPU memory utilization (elastic containers)	%
K8sWorkloadFsReadTimes	Number of reads from the block device	Times
K8sWorkloadFsWriteTimes	Number of writes on the block device	Times
K8sWorkloadFsReadBytes	Size of data read from the block device	MB
K8sWorkloadFsWriteBytes	Size of data written on the block device	MB



Monitoring Metrics for Pods

Metric ID	Metric Name	Unit
K8sPodRestartTotal	Number of Pod restarts	Times
K8sPodReadyStatus	PodReady status	-
K8sPodCpuCoreUsed	CPU usage	Cores
K8sPodRateCpuCoreUsedNode	CPU utilization (% of node)	%
K8sPodRateCpuCoreUsedRequest	CPU utilization (% of request)	%
K8sPodRateCpuCoreUsedLimit	CPU utilization (% of limit)	%
K8sPodEksCpuCoreUsedPod	CPU utilization (elastic containers, as % of Pod specification)	%
K8sPodMemUsageBytes	Memory usage	MB
K8sPodMemNoCacheBytes	Memory usage (excluding cache)	MB
K8sPodRateMemUsageNode	Memory utilization (% of node)	%
K8sPodRateMemUsageRequest	Memory utilization (% of request)	%
K8sPodRateMemUsageLimit	Memory utilization (% of limit)	%
K8sPodRateMemNoCacheNode	Memory utilization (% of node, excluding cache)	%
K8sPodRateMemNoCacheRequest	Memory utilization (% of request, excluding cache)	%
K8sPodRateMemNoCacheLimit	Memory utilization (% of limit, excluding cache)	%
K8sPodRateEksMemUsagePod	Memory utilization (elastic containers, as % of Pod specification)	%
K8sPodRateEksMemNoCachePod	Memory utilization (elastic containers, as % of Pod specification, excluding cache)	%
K8sPodNetworkReceiveBytesBw	Inbound network bandwidth	MB
K8sPodNetworkTransmitBytesBw	Outbound network bandwidth	MB/s
K8sPodNetworkReceiveBytes	Inbound network traffic	MB



Metric ID	Metric Name	Unit
K8sPodNetworkTransmitBytes	Outbound network traffic	MB
K8sPodNetworkReceivePackets	Number of inbound network packets	Counts/second
K8sPodNetworkTransmitPackets	Number of outbound network packets	Counts/second
K8sPodGpuRequest	GPU application volume	Cards
K8sPodGpuUsed	GPU usage	MB
K8sPodRateGpuUsedNode	GPU utilization (% of node)	%
K8sPodRateGpuUsedRequest	GPU utilization (% of request)	%
K8sPodRateEksGpuUsed	GPU utilization (elastic container)	%
K8sPodGpuMemoryRequest	GPU memory application volume	MB
K8sPodGpuMemoryUsed	GPU memory usage	MB
K8sPodRateGpuMemoryUsedNode	GPU memory utilization (% of node)	%
K8sPodRateGpuMemoryUsedRequest	GPU memory utilization (% of request)	%
K8sPodEksGpuVideoMemoryUsed	GPU memory usage (elastic containers)	MB
K8sPodRateEksGpuVideoMemoryUsed	GPU memory utilization (elastic containers)	%
K8sPodFsReadBytes	Block device read bandwidth	MB/s
K8sPodFsWriteBytes	Block device write bandwidth	MB/s
K8sPodFsReadTimes	Number of reads from the block device	Times
K8sPodFsWriteTimes	Number of writes on the block device	Times
K8sPodRootfsSize	rootfs space size	MiB
K8sPodRootfsUsed	rootfs space usage	GB

Monitoring Metrics for Containers

Metric ID	Metric Name	Unit
-----------	-------------	------



Metric ID	Metric Name	Unit
K8sContainerCpuCoreUsed	CPU usage	Cores
K8sContainerRateCpuCoreUsedNode	CPU utilization (% of node)	%
K8sContainerRateCpuCoreUsedRequest	CPU utilization (% of request)	%
K8sContainerRateCpuCoreUsedLimit	CPU utilization (% of limit)	%
K8sContainerMemUsageBytes	Memory usage	MB
K8sContainerRateMemUsageNode	Memory utilization (% of node)	%
K8sContainerRateMemUsageRequest	Memory utilization (% of request)	%
K8sContainerRateMemUsageLimit	Memory utilization (% of limit)	%
K8sContainerMemNoCacheBytes	Memory usage (excluding cache)	MB
K8sContainerRateMemNoCacheNode	Memory utilization (% of node, excluding cache)	%
K8sContainerRateMemNoCacheRequest	Memory utilization (% of request, excluding cache)	%
K8sContainerRateMemNoCacheLimit	Memory utilization (% of limit, excluding cache)	%
K8sContainerFsReadBytes	Block device read bandwidth	MB/s
K8sContainerFsWriteBytes	Block device write bandwidth	MB/s
K8sContainerFsReadTimes	Number of writes on the block device	Times
K8sContainerFsWriteTimes	Number of reads from the block device	Times
K8sContainerGpuUsed	GPU usage	MB
K8sContainerRateGpuUsedNode	GPU utilization (% of node)	%
K8sContainerRateGpuUsedRequest	GPU utilization (% of request)	%
K8sContainerGpuMemoryUsedBytes	GPU memory usage	MB
K8sContainerRateGpuMemoryUsedNode	GPU memory utilization (% of node)	%
K8sContainerRateGpuMemoryUsedRequest	GPU memory utilization (% of request)	%
K8sContainerNetworkReceiveBytes	Inbound network traffic	MB



Metric ID	Metric Name	Unit
K8sContainerNetworkTransmitBytes	Outbound network traffic	MB
K8sContainerNetworkReceiveBytesBw	Inbound network bandwidth	MB/s
K8sContainerNetworkTransmitBytesBw	Outbound network bandwidth	MB/s
K8sContainerNetworkReceivePackets	Number of inbound network packets	Counts/ second
K8sContainerNetworkTransmitPackets	Number of outbound network packets	Counts/ second
K8sContainerRootfsUsed	rootfs space usage	GB



Monitoring Metrics for BMS

Cloud Monitor provides monitoring metrics for BMS in the following dimensions:

Metrics for Basic Monitoring

Metric ID	Metric/Event Name	Unit	Metric Description
cpu_usage	CPU utilization	%	CPU utilization
cpu_loadavg	1-minute average load of CPU	-	Average CPU load within 1 minute, calculated using the data of the first column in /proc/loadavg (this metric is not available on Windows operating systems), dependent on the monitoring component installation for collection
MemUsed	Memory usage	MB	Memory usage
MemUsage	Memory utilization	%	Memory utilization
TcpCurrEstab	Number of TCP connections	Count	Number of TCP connections

Metrics for Network Monitoring

Metric ID	Metric/Event Name	Unit	Metric Description
WanIntraffic	Inbound public network bandwidth	Mb/s	Average inbound traffic per second on public NIC
WanOuttraffic	Outbound public network bandwidth	Mb/s	Average outbound traffic per second on public NIC
WanInpkg	Number of inbound packets on the public network	Counts/second	Average inbound packets per second on public NIC
WanOutpkg	Number of outbound packets on the public network	Counts/second	Average outbound packets per second on public NIC



Metrics for Disk Monitoring

Metric ID	Metric/Event Name	Unit	Metric Description
CvmDiskUsage	Disk utilization	%	Disk utilization monitoring.
DiskIOAwait	Disk I/O wait	-	Disk I/O wait time
DiskReadtraffic	Disk read traffic	Kb/s	Average disk read traffic per second
DiskWritetraffic	Disk write traffic	Kb/s	Average disk write traffic per second
DiskReadIops	Disk read IOPS	Count	Average disk write traffic per second
DiskWriteIops	Disk write IOPS	Count	Average disk read I/O operations per second

Metrics for Private Network Monitoring

Metric/Event Name	Unit
bond1 inbound packet loss on the private network	Count
bond1 inbound error packets on the private network	Count
bond1 inbound packets on the private network	Count/s
bond1 inbound bandwidth on the private network	Byte/s
bond1 outbound packet loss on the private network	Count
bond1 outbound error packets on the private network	Count
bond1 outbound packets on the private network	Count/s
bond1 outbound bandwidth on the private network	Byte/s
eth0 inbound packet loss on the private network	Count
eth0 inbound error packets on the private network	Count
eth0 inbound packets on the private network	Count/s
eth0 inbound bandwidth on the private network	Byte/s
eth0 outbound packet loss on the private network	Count
eth0 outbound error packets on the private network	Count



Metric/Event Name	Unit
eth0 outbound packets on the private network	Count/s
eth0 outbound bandwidth on the private network	Byte/s
eth1 inbound packet loss on the private network	Count
eth1 inbound error packets on the private network	Count
eth1 inbound packets on the private network	Count/s
eth1 inbound bandwidth on the private network	Byte/s
eth1 outbound packet loss on the private network	Count
eth1 outbound error packets on the private network	Count
eth1 outbound packets on the private network	Count/s
eth1 outbound bandwidth on the private network	Byte/s



Monitoring Metrics for CLB

Monitoring Metrics for Listeners on Private Network

Metric/Event ID	Metric Name	Unit
intratrafic	Inbound bandwidth	Mbps
outtraffice	Outbound bandwidth	Mbps
inpkg	Number of inbound packets	Counts/second
outpkg	Number of outbound packets	Counts/second

Cloud Monitor provides monitoring metrics for CLB in the following dimensions:

Monitoring Metrics for Listeners on Public Network

Metric/Event ID	Metric Name	Unit
intratrafic	Inbound bandwidth	Mbps
outtraffice	Outbound bandwidth	Mbps
inpkg	Number of inbound packets	Counts/second
outpkg	Number of outbound packets	Counts/second

Monitoring Metrics for Server Ports

Metric/Event ID	Metric Name	Unit
re_port_status	Abnormal server port status	-
health_status	Number of normal RS for health check	Count



Monitoring Metrics for VPC

Cloud Monitor provides monitoring metrics for VPC in the following dimensions:

Monitoring Metrics for the NAT Gateway

Metric/Event ID	Metric Name	Unit	Metric Description
WanOutBandwidth	Outbound public network bandwidth	MB/s	Average outbound traffic per second on the NAT gateway
WanInBandwidth	Inbound public network bandwidth	MB/s	Average inbound traffic per second on the NAT gateway
Outpkg	Number of outbound packets on the public network	Counts/second	Average outbound packets per second on the NAT gateway
Inpkg	Number of inbound packets on the public network	Counts/second	Average inbound packets per second on the NAT gateway
WanConnCount	Public network connections	Count	Real-time concurrent connections on the NAT gateway
Droppkg	Number of dropped packets	Count	Number of lost data packets

Monitoring Metrics for the DC Gateway

Metric/Event ID	Metric Name	Unit	Metric Description
OutBandwidth	Outbound network bandwidth	MB/s	Average outbound traffic per second on the DC gateway
InBandwidth	Inbound network bandwidth	MB/s	Average inbound traffic per second on the DC gateway
Outpkg	Number of outbound packets	Counts/second	Average outbound packets per second on the DC gateway
Inpkg	Number of inbound packets	Counts/second	Average inbound packets per second on the DC gateway



Monitoring Metrics for the Network Probe

Metric/Event ID	Metric Name	Unit	Metric Description
TimeOut	Latency	ms	Network latency
RateDroppkg	Packet loss rate	%	Ratio of lost network data packets to total data packets

Monitoring Metrics for PC

Metric/Event ID	Metric Name	Unit	Metric Description
OutBandwidth	Outbound network bandwidth	MB/s	Average outbound traffic per second on peering connection (PC)
InBandwidth	Inbound network bandwidth	MB/s	Average inbound traffic per second on PC
Outpkg	Number of outbound packets	Counts/second	Average outbound packets per second on PC
Inpkg	Number of inbound packets	Counts/second	Average inbound packets per second on PC
RateDroppkg	Packet loss rate	%	Ratio of packets dropped due to bandwidth limit to total packets on PC

Monitoring Metrics for the VPN Gateway

Metric/Event ID	Metric Name	Unit	Metric Description
OutBandwidth	Outbound network bandwidth	MB/s	Average outbound traffic per second on the VPN gateway
InBandwidth	Inbound network bandwidth	MB/s	Average inbound traffic per second on the VPN gateway
Outpkg	Number of outbound packets	Counts/second	Average outbound packets per second on the VPN gateway



Metric/Event ID	Metric Name	Unit	Metric Description
Inpkg	Number of inbound packets	Counts/second	Average inbound packets per second on the VPN gateway

Monitoring Metrics for EIP

Metric/Event ID	Metric Name	Unit	Metric Description
VipOutBandwidth	Outbound bandwidth	MB/s	Outbound bandwidth of EIP
VipInBandwidth	Inbound bandwidth	MB/s	Inbound bandwidth of EIP
VipOutpkg	Number of outbound packets	Counts/second	Outbound packets of EIP
VipInpkg	Number of inbound packets	Counts/second	Inbound packets of EIP



Monitoring Metrics for DC

Cloud Monitor provides the following monitoring metrics for DC:

Connection Monitoring Metrics

Metric/Event ID	Metric Name	Unit	Metric Description
InBandwidth	Inbound network bandwidth	MB/s	Inbound bandwidth data measured from the access point AR to the VPC, collected every 1 or 5 minutes
OutBandwidth	Outbound network bandwidth	MB/s	Outbound bandwidth data measured from the VPC to the access point AR, collected every 1 or 5 minutes

DC Tunnel Monitoring Metrics

Metric/Event ID	Metric Name	Unit	Metric Description
InBandwidth	Inbound network bandwidth	MB/s	Average inbound traffic per second on the physical dedicated line
OutBandwidth	Outbound network bandwidth	MB/s	Average outbound traffic per second on the physical dedicated line



Monitoring Metrics for CBS

Cloud Monitor provides the following monitoring metrics for CBS:

Monitoring Metrics for CBS

Metric/Event ID	Metric Name	Unit	Metric Description
disk_read_iops	Disk read IOPS	Times	Average disk read operations per second
disk_write_iops	Disk write IOPS	Times	Average disk write operations per second
disk_read_traffic	Disk read traffic	KB/s	Average amount of data read from disk to memory per second
disk_write_traffic	Disk write traffic	KB/s	Average amount of data written from memory to disk per second
disk_await	Disk I/O wait time	ms	Average wait time per disk I/O operation
disk_svctm	Disk I/O service time	ms	Average time taken per disk I/O operation
disk_util	Busy time ratio of disk I/O	%	The percentage of time taken by I/O operations on the disk out of the total time

Monitoring Metrics for CBS Snapshots

Metric/Event ID	Metric Name	Unit
snap_capacity_usage	Capacity used by CBS snapshots	GB
snap_count_usage	Number of used CBS snapshots	Count



Monitoring Metrics for COS

Cloud Monitor provides the following types of monitoring metrics for COS:

Monitoring Metrics for Status Codes

Metric/Event ID	Metric Name	Unit	Metric Description
2xxResponse	2xx status code	Count	Number of requests returned with 2xx status code
2xxResponseRate	Percentage of 2xx status code	%	Percentage of requests returned with 2xx status code out of total requests
3xxResponse	3xx status code	Count	Number of requests returned with 3xx status code
3xxResponseRate	Percentage of 3xx status code	%	Percentage of requests returned with 3xx status code out of total requests
4xxResponse	4xx status code	Count	Number of requests returned with 4xx status code
4xxResponseRate	Percentage of 4xx status code	%	Percentage of requests returned with 4xx status code out of total requests
400Response	400 status code	Count	Number of requests returned with 400 status code
400ResponseRate	Percentage of 400 status code	%	Percentage of requests returned with 400 status code out of total requests
403Response	403 status code	Count	Number of requests returned with 403 status code
403ResponseRate	Percentage of 403 status code	%	Percentage of requests returned with 403 status code out of total requests
404Response	404 status code	Count	Number of requests returned with 404 status code
404ResponseRate	Percentage of 404 status code	%	Percentage of requests returned with 404 status code out of total requests
5xxResponse	5xx status code	Count	Number of requests returned with 5xx status code



Metric/Event ID	Metric Name	Unit	Metric Description
5xxResponseRate	Percentage of 5xx status code	%	Percentage of requests returned with 5xx status code out of total requests
500Response	500 status code	Count	Number of requests returned with 500 status code
500ResponseRate	Percentage of 500 status code	%	Percentage of requests returned with 500 status code out of total requests
501Response	501 status code	Count	Number of requests returned with 501 status code
501ResponseRate	Percentage of 501 status code	%	Percentage of requests returned with 501 status code out of total requests
502Response	502 status code	Count	Number of requests returned with 502 status code
502ResponseRate	Percentage of 502 status code	%	Percentage of requests returned with 502 status code out of total requests
503Response	503 status code	Count	Number of requests returned with 503 status code
503ResponseRate	Percentage of 503 status code	%	Percentage of requests returned with 503 status code out of total requests
504Response	504 status code	Count	Number of requests returned with 504 status code

Monitoring Metrics for Requests

Metric/Event ID	Metric Name	Unit	Metric Description
StdReadRequests	Read requests for standard storage	Times	Number of read requests for the standard storage type, calculated based on the number of request commands sent
StdWriteRequests	Write requests for standard storage	Times	Number of write requests for the standard storage type, calculated based on the number of request commands sent



Metric/Event ID	Metric Name	Unit	Metric Description
LFRadRequests	Infrequent storage read requests	Times	Number of read requests for infrequent storage type, calculated based on the number of request commands sent
LFWriteRequests	Infrequent storage write requests	Times	Number of write requests for infrequent storage type, calculated based on the number of request commands sent

Monitoring Metrics for Traffic

Metric/Event ID	Metric Name	Unit	Metric Description
UploadFlow	Upload traffic	Byte	Traffic from local to remote
DownloadFlow	Download traffic	Byte	Traffic from remote to local

Monitoring Metrics for Capacity

Metric/Event ID	Metric Name	Unit	Metric Description
BucketCapacity	Bucket capacity	MB	Bucket capacity
BucketsUsedRate	Percentage of bucket quota used by the tenant	%	Percentage of used buckets out of total buckets
CapacityUsedRate	Percentage of capacity quota used by the tenant	%	Percentage of used capacity out of total capacity
ObjectsUsedRate	Percentage of object quota used by the tenant	%	Percentage of used objects out of total objects
ObjCapacityUsedRate	Percentage of used bucket capacity quota	%	Percentage of used bucket capacity out of total bucket capacity
ObjNumsUsedRate	Percentage of used bucket object quota	%	Percentage of used bucket objects out of total bucket objects



Monitoring Metrics for CSP

Cloud Monitor provides the following monitoring metrics for CSP:

Metric/Event ID	Metric Name	Unit	Metric Description
2xx_response	2xx status code	Count	Number of requests returned with 2xx status code
2xx_response_pct	Percentage of 2xx status code	%	-
3xx_response	3xx status code	Count	Number of requests returned with 3xx status code
3xx_response_pct	Percentage of 3xx status code	%	-
400_response	400 status code	Count	Number of requests returned with 400 status code
400_response_pct	Percentage of 400 status code	%	-
403_response	403 status code	Count	Number of requests returned with 403 status code
403_response_pct	Percentage of 403 status code	%	-
404_response	404 status code	Count	Number of requests returned with 404 status code
404_response_pct	Percentage of 404 status code	%	-
4xx_response	4xx status code	Count	Number of requests returned with 4xx status code
4xx_response_pct	Percentage of 4xx status code	%	-
500_response	500 status code	Count	Number of requests returned with 500 status code
500_response_pct	Percentage of 500 status code	%	-



Metric/Event ID	Metric Name	Unit	Metric Description
501_response	501 status code	Count	Number of requests returned with 501 status code
501_response_pct	Percentage of 501 status code	%	-
502_response	502 status code	Count	Number of requests returned with 502 status code
502_response_pct	Percentage of 502 status code	%	-
503_response	503 status code	Count	Number of requests returned with 503 status code
503_response_pct	Percentage of 503 status code	%	-
5xx_response	5xx status code	Count	Number of requests returned with 5xx status code
5xx_response_pct	Percentage of 5xx status code	%	-
bucket_storage	Bucket capacity	Bytes	Capacity of the bucket
bucket_obj	Number of bucket objects	Count	Number of objects in the bucket
inbound_traffic	Upload traffic	Bytes	-
outbound_traffic	Download traffic	Bytes	-
std_read_requests	Read requests for standard storage	Count	Number of read requests for the standard storage type, calculated based on the number of request commands sent
std_write_requests	Write requests for standard storage	Count	Number of write requests for the standard storage type, calculated based on the number of request commands sent

Monitoring Metrics for CFS

Cloud Monitor provides the following types of monitoring metrics for CFS:

Monitoring Metrics for Bandwidth

Metric/Event ID	Metric Name	Unit	Metric Description
DataReadIoBytes	Read bandwidth	KB/s	Average amount of data read from a file system per second
DataWriteIoBytes	Write bandwidth	KB/s	Average amount of data written to a file system per second

Monitoring Metrics for Read/Write Counts

Metric/Event ID	Metric Name	Unit	Metric Description
DataReadIoCount	Read IOPS	Times/second	Read operations per second on the file system
DataWriteIoCount	Write IOPS	Times/second	Write operations per second on the file system

Monitoring Metrics for Storage

Metric/Event ID	Metric Name	Unit	Metric Description
Storage	Storage capacity	GB	File system storage capacity at the current time

Monitoring Metrics for Latencies

Metric/Event ID	Metric Name	Unit	Metric Description
DataReadIoLatency	Read latency	ms	Average read latency on the file system
DataWriteIoLatency	Write latency	ms	Average write latency on the file system



Other Monitoring Metrics

Metric/Event ID	Metric Name	Unit	Metric Description
ConnClientsNums	Number of connected clients	Count	Number of connected clients
HealthCheckSuccessRate	Success rate of client health monitoring	%	Percentage of successful client health check attempts



Monitoring Metrics for Redis®

Cloud Monitor provides monitoring metrics in the following dimensions for Redis®:

Monitoring Metrics for Community Edition

Metric/Event ID	Metric Name	Unit	Metric Description
InFlow	Inbound traffic	MB	-
InFlowUtil	Inbound traffic utilization	%	Ratio of actual inbound traffic usage to maximum traffic
OutFlow	Outbound traffic	MB	-
OutFlowUtil	Outbound traffic utilization	%	Ratio of actual outbound traffic usage to maximum traffic
CPUUsedUtilMax	Maximum CPU utilization of cache shards	%	Peak CPU utilization of shards within the time window
MemUsedUtilMax	Maximum memory utilization of shards	%	Peak memory utilization of shards within the time window
MemUsed	Memory usage	MB	Memory capacity actually used, including data and cache
Connections	Number of connections	Count	Number of TCP connections to the instance
ConnectionsUtil	Connection utilization	%	Ratio of actual TCP connections to maximum connections
Commands	Total number of requests	Times	Total number of commands executed
CmdRead	Number of read requests	Times/second	Number of read command executions per second
CmdWrite	Number of write requests	Times/second	Number of write command executions per second
CmdValue	Number of large-value requests	Times/second	Number of large-value command executions per second



Metric/Event ID	Metric Name	Unit	Metric Description
CmdOther	Number of other requests	Times/second	Number of executions of commands other than read and write commands per second
CmdSlow	Number of slow queries	Count	Number of commands with the execution latency greater than the value of slowlog-log-slower-than
KeyNum	Total number of keys	Count	Total number of keys stored in an instance (first-level keys)
KeyExpired	Number of expired keys	Count	Number of keys evicted within the time window, corresponding to the evicted_keys metric generated by the info command
KeyEvicted	Number of evicted keys	Count	Number of keys evicted within the time window, corresponding to the expired_keys metric generated by the info command
CmdMiss	Read request misses	Count	Number of read requests where keys do not exist, corresponding to the keyspace_misses metric generated by the info command
CmdErr	Number of execution errors	Count	Number of command execution errors, such as nonexistent commands and parameter errors

Monitoring Metrics for Memory Edition (5-Second Granularity)

Metric/Event ID	Metric Name	Unit	Metric Description
InFlow	Inbound traffic	MB/s	-
InFlowUtil	Inbound traffic utilization	%	Ratio of actual inbound traffic usage to maximum traffic
InFlowLimit	Throttling-triggered inbound traffic	Count	Number of times when inbound traffic triggers throttling
OutFlow	Outbound traffic	MB/s	-



Metric/Event ID	Metric Name	Unit	Metric Description
OutFlowUtil	Outbound traffic utilization	%	Ratio of actual outbound traffic usage to maximum traffic
OutFlowLimit	Throttling-triggered outbound traffic	Count	Number of times when outbound traffic triggers throttling
MemUsed	Memory usage	MB	Memory capacity actually used, including data and cache
MemUsedUtil	Memory utilization	%	Ratio of actual memory usage to total memory requested
CpuUsedUtil	CPU utilization	%	Percentage of CPU in non-idle status, calculated from /proc/stat data
MemUsedUtilMax	Maximum memory utilization of nodes	%	Peak memory utilization within the time window
CpuUsedUtilMax	Maximum node CPU utilization	%	Peak CPU utilization within the time window
Commands	Total number of requests	Times	Total number of commands executed
CmdRead	Number of read requests	Times/second	Number of read command executions per second
CmdWrite	Number of write requests	Times/second	Number of write command executions per second
CmdKey	Number of key requests	Times/second	Number of key requests executed per second
CmdMget	Number of MGET requests	Times/second	Number of MGET requests executed per second
CmdValue	Number of large-value requests	Times/second	Number of large-value command executions per second
CmdOther	Number of other requests	Times/second	Number of executions of commands other than read and write commands per second
CmdHits	Read request hits	Times	Number of read requests where keys exist, corresponding to the keyspace_hits metric generated by the info command



Metric/Event ID	Metric Name	Unit	Metric Description
CmdMiss	Read request misses	Count	Number of read requests where keys do not exist, corresponding to the keyspace_misses metric generated by the info command
CmdHitsRatio	Read request hit rate	%	Key hits/(Key hits + Key misses), which can reflect the cache miss status
CmdSlow	Number of slow queries	Count	Number of commands with the execution latency greater than the value of slowlog-log-slower-than
CmdErr	Number of execution errors	Count	Number of command execution errors, such as nonexistent commands and parameter errors
Connections	Number of connections	Count	Number of TCP connections to the instance
ConnectionsUtil	Connection utilization	%	Ratio of the actual number of TCP connections to the maximum number of connections
KeyNum	Total number of keys	Count	Total number of keys stored in an instance (first-level keys)
KeyEvicted	Number of evicted keys	Count	Number of keys evicted within the time window, corresponding to the expired_keys metric generated by the info command
KeyExpired	Number of expired keys	Count	Number of keys evicted within the time window, corresponding to the evicted_keys metric generated by the info command
LatencyRead	Average read latency	ms	Average execution latency of read commands from Proxy to the Redis® server
latency_write	Average write latency	ms	Average execution latency of write commands from Proxy to the Redis® server
LatencyAvgProxy	Average execution latency	ms	Average execution latency of requests from Proxy to the Redis® server
LatencyMax	Maximum execution latency	ms	Maximum execution latency of requests from Proxy to the Redis® server
LatencyOther	Average latency of other commands	ms	Average execution latency of commands other than read and write commands from



Metric/Event ID	Metric Name	Unit	Metric Description
			Proxy to the Redis® server



Monitoring Metrics for TDSQL for MySQL

Cloud Monitor provides the following monitoring metrics for TDSQL for MySQL cloud database instances:

Monitoring Metrics for Nodes

Metric/Event ID	Metric Name	Unit	Metric Description
DBNosurviveNode	Number of inactive DB nodes	-	Number of inactive DB nodes
ProxyNosurviveNode	Number of inactive proxy nodes	-	Number of inactive proxy nodes

Monitoring Metrics for Instances

Metric/Event ID	Metric Name	Unit	Metric Description
ActiveThreadCount	Number of active threads	Count	A monitoring metric for instances, calculated by summing active threads on the primary and standby nodes of all shards
BinlogMinDiskAvailable	Minimum remaining Binlog disk space	GB	A monitoring metric for instances, calculated by summing the minimum values of the BinlogDiskAvailableShard metric across all shards
BinlogUsedDisk	Binlog disk space	GB	A monitoring metric for instances, calculated by summing the used Binlog disk space on the primary nodes of all shards
ConnUsageRate	Maximum DB connection utilization	%	A monitoring metric for instances, calculated as the maximum value of the DB connection utilization on the primary and standby nodes of all shards in the instance



Metric/Event ID	Metric Name	Unit	Metric Description
CpuUsageRate	Maximum CPU utilization	%	A monitoring metric for instances, calculated as the maximum value of the CPU utilization on the primary nodes of all shards in the instance
DataDiskAvailable	Available data disk space	GB	A monitoring metric for instances, calculated by summing the available data disk space on the primary nodes of all shards
DataDiskUsedRate	Maximum data disk space utilization	%	A monitoring metric for instances, calculated as the maximum data disk space utilization on the primary nodes of all shards in the instance
DeleteTotal	Number of DELETE requests	Times/second	A monitoring metric for instances, calculated by summing the number of DELETE requests on the primary nodes of all shards in the instance
IOUsageRate	Maximum I/O utilization	%	A monitoring metric for instances, calculated as the maximum I/O utilization on the primary nodes of all shards in the instance
InnodbBufferPoolReads	Number of InnoDB disk page reads	Times	A monitoring metric for instances, calculated by summing the read page counts in the InnoDB disk on all primary and standby nodes of all shards in the instance
InnodbBufferPoolReadAhead	Number of buffer pool page reads ahead in InnoDB	Times	A monitoring metric for instances, calculated by summing the number of page reads ahead in the InnoDB buffer pool on all primary and standby nodes of all shards in the instance



Metric/Event ID	Metric Name	Unit	Metric Description
InnodbBufferPoolReadRequests	Number of page reads in the InnoDB buffer pool	Times	A monitoring metric for instances, calculated by summing the number of page reads in the InnoDB buffer pool on all primary and standby nodes of all shards in the instance
InnodbRowsDeleted	Number of deleted rows in InnoDB	Rows	A monitoring metric for instances, calculated by summing the number of deleted rows in InnoDB on the primary nodes of all shards in the instance
InnodbRowsInserted	Number of rows inserted in InnoDB	Rows	A monitoring metric for instances, calculated by summing the number of inserted rows in InnoDB on the primary nodes of all shards in the instance
InnodbRowsRead	Number of rows read in InnoDB	Rows	A monitoring metric for instances, calculated by summing the number of rows read in InnoDB on all primary and standby nodes of all shards in the instance
InnodbRowsUpdated	Number of rows updated in InnoDB	Rows	A monitoring metric for instances, calculated by summing the number of updated rows in InnoDB on the primary nodes of all shards in the instance
InsertTotal	Number of INSERT requests	Times/second	A monitoring metric for instances, calculated by summing the number of INSERT requests on the primary nodes of all shards in the instance
LongQueryCount	Number of slow queries	Times	A monitoring metric for instances, calculated by summing the number of slow queries on the primary nodes of



Metric/Event ID	Metric Name	Unit	Metric Description
			all shards in the instance
MemAvailable	Available cache space	GB	A monitoring metric for instances, calculated by summing the available cache space on the primary nodes of all shards in the instance
MemHitRate	Cache hit rate	%	A monitoring metric for instances, calculated as the minimum value of the cache hit rate on the primary nodes of all shards in the instance.
ReplaceSelectTotal	Number of REPLACE_SELECT requests	Times/second	A monitoring metric for instances, calculated by summing the number of REPLACE_SELECT requests on the primary nodes of all shards in the instance.
ReplaceTotal	Number of REPLACE requests	Times/second	A monitoring metric for instances, calculated by summing the number of REPLACE requests on the primary nodes of all shards in the instance.
RequestTotal	Total number of requests	Times/second	A monitoring metric for instances, calculated by summing the number of requests on all primary and standby nodes in the instance.
SelectTotal	Number of SELECT requests	Times/second	A monitoring metric for instances, calculated by summing the number of SELECT requests on all primary and standby nodes of all shards in the instance.
SlaveDelay	Secondary latency	Seconds	A monitoring metric for instances. The standby delay of an instance is the maximum standby delay of all shards in the instance, with the standby delay



Metric/Event ID	Metric Name	Unit	Metric Description
			of each shard calculated first. The standby delay of a shard is the minimum standby delay of all the standby nodes of the shard.
UpdateTotal	Number of UPDATE requests	Times/second	A monitoring metric for instances, calculated by summing the number of UPDATE requests on the primary nodes of all shards in the instance.
ThreadsConnected	Number of open connections	Times	A monitoring metric for instances, calculated by summing the number of current open connections on all primary and standby nodes of all shards in the instance.
ConnMax	Maximum number of connections	Count	A monitoring metric for instances, calculated by summing the maximum connections on all primary and standby nodes of all shards in the instance.
ClientConnTotal	Total number of client connections	Count	A monitoring metric for instances, calculated by summing the number of connections on all proxies in the instance. This metric accurately indicates how many of your clients are connected to the database instance.
SQLTotal	Number of SQL errors	Count	A monitoring metric for instances, indicating the number of SQL statements sent to the database instance.
ErrorSQLTotal	Total number of SQL queries	Count	A monitoring metric for instances, indicating the number of SQL statements executed with errors.



Metric/Event ID	Metric Name	Unit	Metric Description
SuccessSQLTotal	Number of successful SQL queries	Count	A monitoring metric for instances, indicating the number of successfully executed SQL statements.
TimeRange0	Number of requests with execution time less than 5 ms	Times/second	A monitoring metric for instances, indicating the number of requests with execution time less than 5ms.
TimeRange1	Number of requests with execution time between 5 ms and 20 ms	Times/second	A monitoring metric for instances, indicating the number of requests with execution time between 5 ms and 20 ms
TimeRange2	Number of requests with execution time between 20 ms and 30 ms	Times/second	A monitoring metric for instances, indicating the number of requests with execution time between 20 ms and 30 ms
TimeRange3	Number of requests with execution time more than 30 ms	Times/second	A monitoring metric for instances, indicating the number of requests with execution time more than 30 ms
MasterSwitchedTotal	Number of primary-secondary switches	Times	A monitoring metric for instances, indicating the number of primary-secondary switchovers that occurred for the instance



Monitoring Metrics for MongoDB

Cloud Monitor provides the following dimensions of monitoring metrics for MongoDB:

Monitoring Metrics for the Replica Sets

Metric Name	Unit	Metric Description
Cache dirty data percentage	%	Percentage of dirty data volume to total data volume in the cache
Cache utilization	%	Percentage of used cache space to total cache space
Disk utilization	%	-
Cache hit rate	%	Percentage of cache hits to total access times
Oplog retention time	Hour	-
Average primary/secondary node latency per unit of time	s	Average latency of primary/secondary nodes per unit of time

Monitoring Metrics for Nodes

Metric Name	Unit	Metric Description
CPU utilization	%	-
Memory utilization	%	-
Number of read requests in the waiting queue	Count	-
Number of write requests in the waiting queue	Count	-
Inbound network traffic	MB/s	Average inbound traffic per second
Outbound network traffic	MB/s	Average outbound traffic per second
Number of connections	Count	-
Node disk usage	MB	Disk space size used by a single node



Metric Name	Unit	Metric Description
WT engine's ActiveRead	Count	Number of active read operations in the WT engine
WT engine's ActiveWrite	Count	Number of active write operations in the WT engine
Number of data entries deleted after TTL is triggered	Count	-
Number of TTL running rounds	Count	Number of rounds of data cleanup operations triggered based on the TTL index

Monitoring Metrics Instances

Metric Name	Unit	Metric Description
Number of write requests	Times	Number of write requests initiated
Number of read requests	Times	Number of read requests initiated
Number of update requests	Times	Number of update requests initiated
Number of deletion requests	Times	Number of deletion requests initiated
Number of count requests	Times	Number of count requests initiated
Number of aggregation requests	Times	Number of aggregation requests initiated
Number of command requests	Times	Number of command requests initiated
Number of successful requests	Times	Number of requests that succeeded and received the expected response
Disk utilization	%	-
Number of requests with unit time latency (10 ms to 50 ms)	Times	Number of requests with latency between 10 ms and 50 ms
Number of requests with unit time latency (50 ms to 100 ms)	Times	Number of requests with latency between 50 ms and 100 ms
Number of requests with unit time latency (over 100 ms)	Times	Number of requests with latency over 100 ms
Connection utilization	%	-
Number of connections	Count	-



Monitoring Metrics for Instances (Replica Set Instance for Versions Above MongoDB 4.0)

Metric Name	Unit	Metric Description
Number of write requests	Times	-
Number of read requests	Times	-
Number of update requests	Times	-
Number of deletion requests	Times	-
Number of successful requests	Times	-
Disk utilization	%	-
Number of requests with unit time latency (10 ms to 50 ms)	Times	Number of requests with latency between 10 ms and 50 ms
Number of requests with unit time latency (50 ms to 100 ms)	Times	Number of requests with latency between 50 ms and 100 ms
Number of requests with unit time latency (over 100 ms)	Times	Number of requests with latency over 100 ms
Number of connections	Count	-
Connection percentage	%	-



Monitoring Metrics for CMQ

Cloud Monitor provides the following monitoring metrics for CMQ:

Metric/Event ID	Metric Name	Unit
msg_heap_num	Number of heaped messages	Count
msg_product_rate	Message production rate	Count/s
msg_product_flow	Message production traffic	Byte/s
msg_consume_rate	Message consumption rate	Count/s
msg_consume_flow	Message consumption traffic	Byte/s
invisible_msg_Limit_count	Upper limit of invisible messages	Count
batch_delete_message_rate	Batch deletion request rate	Count/s
batch_product_message_rate	Batch production rate	Count/s
batch_consume_message_rate	Batch consumption request rate	Count/s
delete_message_rate	Deletion request rate	Count/s
product_message_rate	Production request rate	Count/s
consume_message_rate	Consumption request rate	Count/s



Monitoring Metrics for Ckafka

Cloud Monitor provides the following traffic monitoring metrics for Ckafka:

Monitoring Metrics for Topics

Metric/Event ID	Metric Name	Unit	Metric Description
CtopicProFlow	Topic produced traffic	MB	Topic production traffic (excluding traffic generated by replicas), summed statistically according to the selected time granularity
CtopicProFlowMax	Maximum traffic of topic production	MB	Peak traffic of topic production
CtopicProCount	Number of messages produced for the topic	Count	The actual number of messages produced for the topic, summed statistically according to the selected time granularity
CtopicConFlow	Topic consumption traffic	MB	Topic consumption traffic (excluding traffic generated by replicas), summed according to the selected time granularity
CtopicConFlowMax	Maximum traffic of topic consumption	MB	Peak traffic of topic consumption
CtopicConCount	Number of messages consumed for the topic	Count	The number of messages consumed for the topic, summed statistically according to the selected time granularity
CtopicMsg	Total disk usage of messages for the topic	MB	Total disk usage of messages for the topic
CtopicMsgCount	Total number of messages written to the disk for the topic	Count	Total number of messages written to the disk for the topic (excluding replicas), calculated as the latest value according to the selected time granularity



Metric/Event ID	Metric Name	Unit	Metric Description
CtopicMsgRequestProCount	Number of requests produced for the topic	Count	The actual number of requests produced for the topic
CtopicMsgRequestConCount	Number of requests consumed for the topic	Count	The actual number of requests consumed for the topic

Monitoring Metrics for Instances

Metric/Event ID	Metric Name	Unit	Metric Description
InstanceProCount	Number of produced messages	Count	The actual number of messages produced for the instance, summed statistically according to the selected time granularity
InstanceConCount	Number of consumed messages	Count	The number of messages consumed for the instance, summed statistically according to the selected time granularity
InstanceProTrafficMax	Peak bandwidth of message production	MB/s	
RequestProCount	Number of requests produced	Count	The actual number of requests produced for the instance
RequestConCount	Number of requests consumed	Count	The actual number of requests consumed for the instance
InstanceMsgCount	Number of messages written to the disk	Count	The number of messages written to the disk for the instance (excluding replicas), calculated as the latest value according to the selected time granularity
InstanceProFlow	Amount of production traffic	MB/min	Instance production traffic (excluding traffic generated by replicas), summed statistically according to the selected time granularity



Metric/Event ID	Metric Name	Unit	Metric Description
InstanceMaxProFlow	Maximum production traffic	MB/s	The peak traffic of messages produced for the instance (excluding bandwidth generated by replica production)
InstanceProTrafficRate	Production bandwidth percentage	%	
InstanceProLimitNums	Production throttling frequency	Count	
InstanceConFlow	Amount of consumed traffic	MB/min	Instance consumption traffic (excluding traffic generated by replicas), summed statistically according to the selected time granularity
InstanceMaxConFlow	Maximum consumption traffic	MB/s	The peak traffic of messages consumed for the instance (no concept of replicas during consumption)
InstanceConTrafficRate	Consumption bandwidth percentage	%	
InstanceConLimitNums	Consumption throttling frequency	Count	The throttling frequency of messages consumed for the instance
InstanceConGroupNums	Number of consumer groups	Count	Number of consumer groups
InstanceConGroupNumsRate	Consumer group percentage	%	
InstanceDiskUsage	Disk usage percentage	%	The percentage of current disk usage to the total disk capacity of the instance specification
InstanceMsgHeap	Disk usage	MB	Disk usage of the instance (including replicas), calculated as the latest value according to the selected time granularity



Metric/Event ID	Metric Name	Unit	Metric Description
InstanceConnectionCount	Number of instance connections	Count	The current total number of connections of the instance
InstanceConnectionRate	Instance connection percentage	%	The ratio of the current total number of connections to the total number of instances
PartitionNums	Number of partitions	Count	
PartitionNums	Partition percentage	%	
TopicNums	Number of topics	Count	
TopicNums	Topic percentage	%	

Monitoring Metrics for Consumer Groups

Metric/Event ID	Metric Name	Unit	Metric Description
CgroupTopicMaxOffset	Maximum offset of the current topic	Count	Maximum offset of the consumer group under the current topic
CgroupTopicMsgOffset	Current consumption offset	Count	Current offset of the consumer group
CgroupTopicUnconsumeMsgCount	Number of unconsumed messages	Count	Number of unconsumed messages under the consumer group
CgroupTopicMsgRate	Consumption speed	Count/min	Message consumption speed under the consumer group
CgroupTopicUnconsumeMsgSize	Size of unconsumed messages	MB	Size of unconsumed messages under the consumer group
CgroupPartMaxOffset	Maximum offset of the consumer group	Count	Maximum offset under the consumer group



Metric/Event ID	Metric Name	Unit	Metric Description
CgroupPartOffset	Partition offset	Count	Offset under the partition
CgroupPartUnconsumeMsgCount	Number of unconsumed messages in the partition	Count	Number of unconsumed messages under the partition
CgroupPartMsgRate	Partition consumption speed	Count/min	Message consumption speed under the partition
CgroupPartUnconsumeMsgSize	Backlog of unconsumed messages in the partition	MB	Backlog of unconsumed messages under the partition

Monitoring Metrics for Partitions

Metric/Event ID	Metric Name	Unit	Metric Description
CpartitionProFlow	Partition production traffic	MB	Partition production traffic (excluding traffic generated by replicas), summed statistically according to the selected time granularity
CpartitionConFlow	Partition consumption traffic	MB	Partition consumption traffic (excluding traffic generated by replicas), summed statistically according to the selected time granularity



Monitoring Metrics for TSF

Cloud Monitor provides the following monitoring metrics for TSF:

Monitoring Metrics for Services

Metric/Event ID	Metric Name	Unit	Metric Description
RequestAverageTime	Average time consumed for received requests	ms	The average processing time consumed by the requested service
RequestErrorPercentage	Failure rate of received requests	%	Percentage of abnormal results from the requested service
RequestCount	Number of received requests	Times	Number of times the service was requested
Response4xx	HTTP 4xx response code	Count	Number of requests with 4xx response code
Response5xx	HTTP 5xx response code	Count	Number of requests with 5xx response code

Monitoring Metrics for Deployment Groups

Metric/Event ID	Metric Name	Unit	Metric Description
HealthyInstancePercentage	Health rate of deployment group nodes	%	Percentage of healthy nodes in a TSF component

Monitoring Metrics for APIs

Metric/Event ID	Metric Name	Unit
ReqCount	Number of requests	Count
TimeSpentAvg	Average duration	ms
FailureRate	Failure rate	%



Monitoring Metrics for Logs

Metric/Event ID	Metric Name	Unit
KeyNums	Keyword occurrence count	Count

Monitoring Metrics for TCT

Metric/Event ID	Metric Name	Unit
FailureTimes	Number of execution failures	Count

Monitoring Metrics for Instances

Metric/Event ID	Metric Name	Unit
full_gcEventNums	FULL_GC event statistics metric	Count

Monitoring Metrics for TDMQ Pulsar

Cloud Monitor provides the following dimensions of monitoring metrics for TDMQ Pulsar:

Monitoring Metrics for the Subscription

Metric Name	Unit	Metric Description
Number of heaped messages	count	Number of heaped messages
Percentage of quota used by unacknowledged messages	%	Ratio of unacknowledged messages to the total quota
Message consumption rate	count/s	-
Amount of consumed traffic	Byte/s	-
Number of unacknowledged messages	Count	Number of unacknowledged messages
Number of delayed messages	Count	Number of delayed messages
Number of consumers	Count	-

Monitoring Metrics for Topics

Metric Name	Unit	Metric Description
Message production rate	count/s	-
Message production traffic	Byte/s	-
Message consumption rate	count/s	-
Message consumption traffic	Byte/s	-
Message storage size	Count	-
Number of consumers	Count	-
Number of producers	Count	-



Metric Name	Unit	Metric Description
Quota usage percentage of message production traffic	%	The ratio of message production traffic to the total quota
Quota usage percentage of message consumption traffic	%	The ratio of message consumption traffic to the total quota
Quota usage percentage of message production count	%	The ratio of produced message count to the total quota
Quota usage percentage of message consumption count	%	The ratio of consumed message count to the total quota
Number of heaped messages	Count	-
Heaped message size	Byte	-
Producer count throttling times	Count	-
Quota usage percentage of heaped messages	%	The ratio of heaped messages to the total quota

Monitoring Metrics for Clusters

Metric Name	Unit	Metric Description
Tenant-level message production rate	count/s	-
Tenant-level message consumption rate	count/s	-
Peak cluster production bandwidth	count/s	-
Peak cluster consumption bandwidth	Byte/s	-
Tenant-level heaped message size	Byte	-
Transactions per second (TPS) of the Pulsar cluster	Count/s	The number of messages processed per second by the cluster



Monitoring Metrics for TI-ONE Platform

TI-ONE Task-Based Modeling

Metric English Name	Metric Chinese Name	Metric Description	Unit	Dimension	Statistical Granularity
CfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	Instance-dimension TuroCFS single-node server read bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	Instance-dimension TuroCFS single-node server read bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsClientDataWriteBandwidth	TuroCFS single-node server write bandwidth	Instance-dimension TuroCFS single-node server write bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataReadIoBytes	CFS server read bandwidth	Instance-dimension CFS server read bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



CfsDataReadIoLatency	CFS read latency	Instance-dimension CFS read latency	ms	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataWriteIoBytes	CFS server write bandwidth	Instance-dimension CFS server write bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataWriteIoLatency	CFS write latency	Instance-dimension CFS write latency	ms	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsStrageUsageGb	CFS storage data capacity	Instance-dimension CFS storage data capacity	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Cpuutil	CPU utilization	Task-dimension CPU utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFiDevFbUsed	GPU memory usage	GPU memory usage in the task instance-GPU card dimension	MBytes	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



DcgmFiDevGpuUtil	GPU utilization	GPU utilization in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFiDevMemCopyUtil	GPU memory utilization	GPU memory utilization in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoUtil	Disk I/O utilization	Instance-dimension disk I/O utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoWait	Disk I/O wait time	Instance-dimension disk I/O wait time	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadByte	Disk read bandwidth	Instance-dimension disk read bandwidth	MBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadIops	Disk read IOPS	Instance-dimension disk read IOPS	Count	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



DiskUsageRadio	System disk partition utilization	Instance-dimension system disk partition utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskWriteByte	Disk write bandwidth	Instance-dimension disk write bandwidth	MBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskWriteIops	Disk write IOPS	Instance-dimension disk write IOPS	Count	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp16EngineActivity	FP16 active time ratio	Instance-dimension FP16 active time ratio	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp32EngineActivity	FP32 active time ratio	Instance-dimension FP32 active time ratio	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp64EngineActivity	FP64 active time ratio	Instance-dimension FP64 active time ratio	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GpuFp16EngineActivity	FP16 active time ratio	FP16 active time ratio in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuFp32EngineActivity	FP32 active time ratio	FP32 active time ratio in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuFp64EngineActivity	FP64 active time ratio	FP64 active time ratio in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Gpumemutil	GPU memory utilization	Task-dimension GPU memory utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Gpumemvalue	GPU memory usage	Task-dimension GPU memory usage	MBytes	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkBandwidth	NVLink transmission rate	NVLink transmission rate in the task instance-GPU card dimension	Bytes/s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GpuPcieBandwidth	PCIe bus transmission rate	PCIe bus transmission rate in the task instance-GPU card dimension	Bytes/s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuSmActivity	SM active time ratio	SM active time ratio in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuTensorActivity	Tensor active time ratio	Tensor active time ratio in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Gpuutil	GPU utilization	Task-dimension GPU utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancecpuutil	CPU utilization	Instance-dimension CPU utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancegpumemutil	GPU memory utilization	Instance-dimension GPU memory utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



Instancegpumemvalue	GPU memory usage	Instance-dimension GPU memory usage	MBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancegpuutil	GPU utilization	GPU utilization in the task instance dimension	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancememutil	Memory utilization	Instance-dimension memory utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancememvalue	Memory usage	Instance-dimension memory usage	MBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Memutil	Memory utilization	Task-dimension memory utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Memvalue	Memory usage	Task-dimension memory usage	MBytes	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



NvlinkBandwidth	NVLink transmission rate	Instance-dimension NVLink transmission rate	Bytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
PcieBandwidth	PCIe bus transmission rate	Instance-dimension PCIe bus transmission rate	Bytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaInpkt	RDMA NIC inbound packet count	Instance-dimension RDMA NIC inbound packet count	pps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaIntraffic	RDMA NIC receive bandwidth	Instance-dimension RDMA NIC receive bandwidth	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaOutpkt	RDMA NIC outbound packet count	Instance-dimension RDMA NIC outbound packet count	pps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaOuttraffic	RDMA NIC transmit bandwidth	Instance-dimension RDMA NIC transmit bandwidth	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



SmActivity	SM active time ratio	Instance-dimension SM active time ratio	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	Task-dimension TuroCFS single-node server read bandwidth	KBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsClientDataWriteBandwidth	TuroCFS single-node server write bandwidth	Task-dimension TuroCFS single-node server write bandwidth	KBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsDataReadIoBytes	CFS server read bandwidth	Task-dimension CFS server read bandwidth	KBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsDataReadIoLatency	CFS read latency	Task-dimension CFS read latency	ms	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsDataWriteIoBytes	CFS server write bandwidth	Task-dimension CFS server write bandwidth	KBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskCfsDataWriteIoLatency	CFS write latency	Task-dimension CFS write latency	ms	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskCfsStrageUsageGb	CFS storage data capacity	Task-dimension CFS storage data capacity	GBytes	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskIoUtil	Disk I/O utilization	Task-dimension disk I/O utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskIoWait	Disk I/O wait time	Task-dimension disk I/O wait time	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskReadByte	Disk read bandwidth	Task-dimension disk read bandwidth	MBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskReadIops	Disk read IOPS	Task-dimension disk read IOPS	Count	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskDiskUsageRadio	System disk partition utilization	Task-dimension system disk partition utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskWriteByte	Disk write bandwidth	Task-dimension disk write bandwidth	MBytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskDiskWriteIops	Disk write IOPS	Task-dimension disk write IOPS	Count	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskFp16EngineActivity	FP16 active time ratio	Task-dimension FP16 active time ratio	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskFp32EngineActivity	FP32 active time ratio	Task-dimension FP32 active time ratio	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskFp64EngineActivity	FP64 active time ratio	Task-dimension FP64 active time ratio	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskNvlinkBandwidth	NVLink transmission rate	Task-dimension NVLink transmission rate	Bytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskPcieBandwidth	PCIe bus transmission rate	Task-dimension PCIe bus transmission rate	Bytes/s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskRdmaInpkt	RDMA NIC inbound packet count	Task-dimension RDMA NIC inbound packet count	pps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskRdmaIntraffic	RDMA NIC receive bandwidth	Task-dimension RDMA NIC receive bandwidth	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskRdmaOutpkt	RDMA NIC outbound packet count	Task-dimension RDMA NIC outbound packet count	pps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskRdmaOuttraffic	RDMA NIC transmit bandwidth	Task-dimension RDMA NIC transmit bandwidth	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskSmActivity	SM active time ratio	Task-dimension SM active time ratio	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskTensorActivity	Tensor active time ratio	Task-dimension Tensor active time ratio	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TensorActivity	Tensor active time ratio	Instance-dimension Tensor active time ratio	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuDecUtil	GPU decoder utilization	Instance-dimension GPU decoder utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuEncUtil	GPU encoder utilization	Instance-dimension GPU encoder utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemoryClock	GPU memory frequency	Instance-dimension GPU memory frequency	s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GpuMemoryFree	Available GPU memory	Instance-dimension available GPU memory	MBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemoryUtil	GPU memory utilization	Instance-dimension GPU memory utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkRxMb	NVLink received data volume	Instance-dimension NVLink received data volume	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkTxMb	NVLink transmitted data volume	Instance-dimension NVLink transmitted data volume	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuPcieRxMb	PCIe received data volume	Instance-dimension PCIe received data volume	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuPcieTxMb	PCIe transmitted data volume	Instance-dimension PCIe transmitted data volume	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GpuSmClock	SM clock frequency	Instance-dimension SM clock frequency	s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuDecUtil	GPU decoder utilization	Task-dimension GPU decoder utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuEncUtil	GPU encoder utilization	Task-dimension GPU encoder utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryClock	GPU memory frequency	Task-dimension GPU memory frequency	s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryFree	Available GPU memory	Task-dimension available GPU memory	MBytes	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryUtil	GPU memory bandwidth utilization	Task-dimension GPU memory bandwidth utilization	%	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskGpuNvlinkRxMb	NVLink received data volume	Task-dimension NVLink received data volume	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuNvlinkTxMb	NVLink transmitted data volume	Task-dimension NVLink transmitted data volume	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuPcieRxMb	PCIe received data volume	Task-dimension PCIe received data volume	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuPcieTxMb	PCIe transmitted data volume	Task-dimension PCIe transmitted data volume	Mbps	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuSmClock	SM clock frequency	Task-dimension SM clock frequency	s	AppId TaskId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuDecUtilGpu	GPU decoder utilization	GPU decoder utilization in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskGpuEncUtilGpu	GPU encoder utilization	GPU encoder utilization in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryClockGpu	GPU memory frequency	GPU memory frequency in the task instance-GPU card dimension	s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryFreeGpu	Available GPU memory	Available GPU memory in the task instance-GPU card dimension	MBytes	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuMemoryUtilGpu	GPU memory bandwidth utilization	GPU memory bandwidth utilization in the task instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuNvlinkRxMbGpu	NVLink received data volume	NVLink received data volume in the task instance-GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuNvlinkTxMbGpu	NVLink transmitted data volume	NVLink transmitted data volume in the task instance-GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TaskGpuPcieRxMbGpu	PCIe received data volume	PCIe received data volume in the task instance-GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuPcieTxMbGpu	PCIe transmitted data volume	PCIe transmitted data volume in the task instance-GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TaskGpuSmClockGpu	SM clock frequency	SM clock frequency in the task instance-GPU card dimension	s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TI-ONE Development Machine

Metric English Name	Metric Chinese Name	Metric Description	Unit	Dimension	Statistical Granularity
CfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	Instance-dimension TuroCFS single-node server read bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsClientDataWriteBandwidth	TuroCFS single-node server write bandwidth	Instance-dimension TuroCFS single-node server write bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataReadIoBytes	CFS server read bandwidth	Instance-dimension CFS server read bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataReadIoLatency	CFS read latency	Instance-dimension CFS read latency	ms	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataWriteIoBytes	CFS server write bandwidth	Instance-dimension CFS server write bandwidth	KBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



CfsDataWriteIoLatency	CFS write latency	Instance-dimension CFS write latency	ms	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsStrageUsageGb	CFS storage data capacity	Instance-dimension CFS storage data capacity	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoUtil	Disk I/O utilization	Instance-dimension disk I/O utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoWait	Disk I/O wait time	Instance-dimension disk I/O wait time	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadByte	Disk read bandwidth	Instance-dimension disk read bandwidth	MBytes/ s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadIops	Disk read IOPS	Instance-dimension disk read IOPS	Count	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



					[86400s, avg]
DiskUsageRadio	System disk partition utilization	Instance-dimension system disk partition utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskWriteByte	Disk write bandwidth	Instance-dimension disk write bandwidth	MBytes/s	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskWriteIops	Disk write IOPS	Instance-dimension disk write IOPS	Count	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancecpuutil	CPU utilization	Instance-dimension CPU utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancegpumemutil	GPU memory utilization	Instance-dimension GPU memory utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancegpumemvalue	GPU memory usage	Instance-dimension GPU memory	MBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



		usage			[3600s, avg] [86400s, avg]
Instancegpuutil	GPU utilization	Instance-dimension GPU utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancememutil	Memory utilization	Instance-dimension memory utilization	%	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancememvalue	Memory usage	Instance-dimension memory usage	MBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuFp16EngineActivity	FP16 active time ratio	FP16 active time ratio in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuFp32EngineActivity	FP32 active time ratio	FP32 active time ratio in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GpuFp64EngineActivity	FP64 active time ratio	FP64 active time ratio in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
NvlinkBandwidth	NVLink transmission rate	NVLink transmission rate in the instance-GPU card dimension	Bytes/s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
PcieBandwidth	PCIe bus transmission rate	PCIe bus transmission rate in the instance-GPU card dimension	Bytes/s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuSmActivity	SM active time ratio	SM active time ratio in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TensorActivity	Tensor active time ratio	Tensor active time ratio in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFidevfbused	GPU memory usage	GPU memory usage in the instance-GPU card dimension	MBytes	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



					[86400s, avg]
DcgmFiDevGpuUtil	GPU utilization	GPU utilization in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFiDevMemCopyUtil	GPU memory utilization	GPU memory utilization in the instance-GPU card dimension	%	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemoryClockGpu	GPU memory frequency	GPU memory frequency in the instance-GPU card dimension	s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemoryFreeGpuv	Available GPU memory	Available GPU memory in the instance-GPU card dimension	MBytes	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkRxMb	NVLink received data volume	NVLink received data volume in the instance-GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkTxMb	NVLink transmitted data volume	NVLink transmitted data volume in the	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



		instance- GPU card dimension			[3600s, avg] [86400s, avg]
GpuPcieRxMb	PCIe received data volume	PCIe received data volume in the instance- GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuPcieTxMb	PCIe transmitted data volume	PCIe transmitted data volume in the instance- GPU card dimension	Mbps	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuSmClock	SM clock frequency	SM clock frequency in the instance- GPU card dimension	s	AppId InstanceGpuNum SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
PodDiskLimit	Total disk size of the instance	Instance- dimension total disk size	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
PodDiskValue	Disk usage of the instance	Instance- dimension disk usage	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



NodeDiskLimit	Total disk size of the node	Instance-dimension total node disk size	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
NodeDiskValue	Node disk usage	Instance-dimension node disk usage	GBytes	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaInpkt	RDMA NIC inbound packet count	Instance-dimension RDMA NIC inbound packet count	pps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaOutpkt	RDMA NIC outbound packet count	Instance-dimension RDMA NIC outbound packet count	pps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaIntraffic	RDMA NIC receive bandwidth	Instance-dimension RDMA NIC receive bandwidth	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
RdmaOuttraffic	RDMA NIC transmit bandwidth	Instance-dimension RDMA NIC transmit bandwidth	Mbps	AppId InstanceId SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



					[86400s, avg]
--	--	--	--	--	--------------------



TI-ONE Online Services

Metric English Name	Metric Chinese Name	Metric Description	Unit	Dimension	Statistical Granularity
Apicallerrortotal	Number of failed API calls	Number of failed API calls	Count	ServiceGroupId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Apicalllimittotal	Total number of throttled requests	Total number of API calls throttled	Count	ServiceGroupId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Apicallsuccesstotal	Total number of successful calls	Total number of successful API calls	Count	ServiceGroupId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Apicalltotal	Total number of API calls	Total number of API calls	Count	ServiceGroupId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Apiresponsetime	Average response time	Average response time	ms	ServiceGroupId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



CfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	TuroCFS single-node server read bandwidth in the task instance dimension	KBytes/ s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsClientDataWriteBandwidth	TuroCFS single-node server write bandwidth	TuroCFS single-node server write bandwidth in the task instance dimension	KBytes/ s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataReadIoBytes	CFS server read bandwidth	CFS server read bandwidth in the task instance dimension	KBytes/ s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataReadIoLatency	CFS read latency	CFS read latency in the task instance dimension	ms	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataWriteIoBytes	CFS server write bandwidth	CFS server write bandwidth in the task instance dimension	KBytes/ s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsDataWriteIoLatency	CFS write latency	CFS write latency in the task instance dimension	ms	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
CfsStrageUsageGb	CFS storage data	CFS storage data	GBytes	InstanceId Source	[10s, avg] [60s, avg]



	capacity	capacity in the task instance dimension		SubUin	[300s, avg] [3600s, avg] [86400s, avg]
Cpuutil	CPU utilization	Task-dimension CPU utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoUtil	Disk I/O utilization	Disk I/O utilization in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskIoWait	Disk I/O wait time	Disk I/O wait time in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadByte	Disk read bandwidth	Disk read bandwidth in the task instance dimension	MBytes/s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskReadIops	Disk read IOPS	Disk read IOPS in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskUsageRadio	System disk partition utilization	System disk partition utilization in the task	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg]



		instance dimension			[3600s, avg] [86400s, avg]
DiskWriteByte	Disk write bandwidth	Disk write bandwidth in the task instance dimension	MBytes/s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DiskWriteIops	Disk write IOPS	Disk write IOPS in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Gpumemutil	GPU memory utilization	Task-dimension GPU memory utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Gpuutil	GPU utilization	Task-dimension GPU utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancecpuutil	CPU utilization	CPU utilization in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancegpumemutil	GPU memory utilization	GPU memory utilization in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



					[86400s, avg]
Instancegpuutil	GPU utilization	GPU utilization in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancehttpqps	HTTP call QPS	HTTP requests per second in the task instance dimension	Count/s	InstanceId Source SubUin	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]
Instancehttpqpslimit	Rate-limited HTTP QPS	HTTP requests per second limited in the task instance dimension	Count/s	InstanceId Source SubUin	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]
Instancememutil	Memory utilization	Memory utilization in the task instance dimension	%	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancememvalue	Memory usage	Memory usage in the task instance dimension	MBytes	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Instancenetworkbytes	Inbound network traffic	Inbound network traffic in the task instance	MBytes	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg]



		dimension			[3600s, avg] [86400s, avg]
Instanceready	Number of running instances	Number of running instances in the task dimension	Count	AppId Source SubUin TaskId	[10s, last] [60s, last] [300s, last] [3600s, last] [86400s, last]
InstanceTiemsCurrentRequests	Number of concurrent requests	Number of concurrent requests in the task instance dimension	Count	InstanceId Source SubUin	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]
Instancetotal	Number of instances	Number of instances in the task dimension	Count	AppId Source SubUin TaskId	[10s, last] [60s, last] [300s, last] [3600s, last] [86400s, last]
Memutil	Memory utilization	Task-dimension memory utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Memvalue	Memory usage	Task-dimension memory usage	MBytes	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Networkreceivebytes	Inbound network traffic	Inbound network traffic in the task	MBytes	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg]



		dimension			[3600s, avg] [86400s, avg]
ServiceCfsClientDataReadBandwidth	TuroCFS single-node server read bandwidth	Task-dimension TuroCFS single-node server read bandwidth	KBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceCfsClientDataWriteBandwidth	TuroCFS single-node server write bandwidth	Task-dimension TuroCFS single-node server write bandwidth	KBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceCfsDataReadIoBytes	CFS server read bandwidth	Task-dimension CFS server read bandwidth	KBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceCfsDataReadIoLatency	CFS read latency	Task-dimension CFS read latency	ms	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceCfsDataWriteIoBytes	CFS server write bandwidth	Task-dimension CFS server write bandwidth	KBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceCfsDataWriteIoLatency	CFS write latency	Task-dimension CFS write latency	ms	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg]



					[86400s, avg]
ServiceCfsStrageUsageGb	CFS storage data capacity	Task-dimension CFS storage data capacity	GBytes	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskIoUtil	Disk I/O utilization	Task-dimension disk I/O utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskIoWait	Disk I/O wait time	Task-dimension disk I/O wait time	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskReadByte	Disk read bandwidth	Task-dimension disk read bandwidth	MBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskReadIops	Disk read IOPS	Task-dimension disk read IOPS	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskUsageRadio	System disk partition utilization	Task-dimension system disk partition utilization	%	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



ServiceDiskWriteByte	Disk write bandwidth	Task-dimension disk write bandwidth	MBytes/s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceDiskWriteIops	Disk write IOPS	Task-dimension disk write IOPS	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Servicehttpqps	HTTP call QPS	HTTP requests per second in the task dimension for the service	Count/s	AppId Source SubUin TaskId	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]
Servicehttpqpslimit	Rate-limited HTTP QPS	Rate-limited HTTP requests per second in the task dimension for the service	Count/s	AppId Source SubUin TaskId	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]
ServiceTiemsCurrentRequests	Number of concurrent requests	Number of concurrent requests in the task dimension	Count	AppId Source SubUin TaskId	[10s, max] [60s, max] [300s, max] [3600s, max] [86400s, max]



ServiceGpuMemValue	GPU memory usage	Task-dimension GPU memory usage	MBytes	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsTokenThroughput	Number of tokens processed per minute	Number of tokens processed per minute in the task dimension	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsTokenThroughputInput	Number of input tokens processed per minute	Number of input tokens processed per minute in the task dimension	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsTokenThroughputOutput	Number of output tokens processed per minute	Number of output tokens processed per minute in the task dimension	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsFirstTokenLatency	First token latency	Task-dimension first token latency	s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsNonFirstTokenLatency	Non-first token latency	Task-dimension non-first token latency	s	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
ServiceEmsProcessingRequestCount	Number of requests in	Number of requests in	Count	AppId Source	[10s, sum]



	processing	processing in the task dimension		SubUin TaskId	[60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
ServiceEmsQueuingRequestCount	Number of queued requests	Number of queued requests in the task dimension	Count	AppId Source SubUin TaskId	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
ServiceEmsTotalProcessedTokens	Total number of tokens processed	Total number of tokens processed in the task dimension	Count	AppId Source SubUin TaskId	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
ServiceEmsTotalProcessedTokensInput	Total number of input tokens processed	Total number of output tokens in the task dimension	Count	AppId Source SubUin TaskId	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
ServiceEmsTotalProcessedTokensOutput	Total number of output tokens processed	Total number of output tokens in the task dimension	Count	AppId Source SubUin TaskId	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
ServiceEmsAverageLengthInput	Average input length (tokens)	Average input length in tokens in	Count	AppId Source SubUin	[10s, avg] [60s, avg] [300s, avg]



		the task dimension		TaskId	[3600s, avg] [86400s, avg]
ServiceEmsAverageLengthOutput	Average output length (tokens)	Average output length in tokens in the task dimension	Count	AppId Source SubUin TaskId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemValue	GPU memory usage	GPU memory usage in the task instance dimension	MBytes	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsTokenThroughput	Number of tokens processed per minute	Number of tokens processed per minute in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsTokenThroughputInput	Number of input tokens processed per minute	Total number of input tokens processed per minute in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsTokenThroughputOutput	Number of output tokens processed per minute	Total number of output tokens processed per minute in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsFirstTokenLatency	First token latency	First token latency in the task instance	s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg]



		dimension			[3600s, avg] [86400s, avg]
EmsNonFirstTokenLatency	Non-first token latency	Non-first token latency in the task instance dimension	s	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsProcessingRequestCount	Number of requests in processing	Number of requests in processing in the task instance dimension	Count	InstanceId Source SubUin	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
EmsQueuingRequestCount	Number of queued requests	Number of queued requests in the task instance dimension	Count	InstanceId Source SubUin	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
EmsTotalProcessedTokens	Total number of tokens processed	Total number of tokens processed in the task instance dimension	Count	InstanceId Source SubUin	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
EmsTotalProcessedTokensInput	Total number of input tokens processed	Total number of input tokens processed in the task instance dimension	Count	InstanceId Source SubUin	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]



					sum]
EmsTotalProcessedTokensOutput	Total number of output tokens processed	Total number of output tokens processed in the task instance dimension	Count	InstanceId Source SubUin	[10s, sum] [60s, sum] [300s, sum] [3600s, sum] [86400s, sum]
EmsAverageLengthInput	Average input length (tokens)	Average input length (tokens) in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
EmsAverageLengthOutput	Average output length (tokens)	Average output length (tokens) in the task instance dimension	Count	InstanceId Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp16EngineActivity	FP16 active time ratio	FP16 active time ratio in the service instance-GPU card dimension	%	Appld InstanceIdGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp32EngineActivity	FP32 active time ratio	FP32 active time ratio in the service instance-GPU card dimension	%	Appld InstanceIdGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
Fp64EngineActivity	FP64 active time ratio	FP64 active time ratio in the service instance-GPU card dimension	%	Appld InstanceIdGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



					avg]
NvlinkBandwidth	NVLink transmission rate	NVLink transmission rate in the service instance-GPU card dimension	Bytes/s	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
PcieBandwidth	PCIe bus transmission rate	PCIe bus transmission rate in the service instance-GPU card dimension	Bytes/s	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
SmActivity	SM active time ratio	SM active time ratio in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
TensorActivity	Tensor active time ratio	Tensor active time ratio in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFiDevFbUsed	GPU memory usage	GPU memory usage in the service instance-GPU card dimension	MBytes	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
DcgmFiDevGpuUtil	GPU utilization	GPU utilization in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



DcgmFiDevMemCopyUtil	GPU memory utilization	GPU memory utilization in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuDecUtil	GPU decoder utilization	GPU decoder utilization in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuEncUtil	GPU encoder utilization	GPU encoder utilization in the service instance-GPU card dimension	%	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuMemoryClock	GPU memory frequency	GPU memory frequency in the service instance-GPU card dimension	S	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkRxMb	NVLink received data volume	NVLink received data volume in the service instance-GPU card dimension	Mbps	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuNvlinkTxMb	NVLink transmitted data volume	NVLink transmitted data volume in the service instance-GPU card dimension	Mbps	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuPcieRxMb	PCIe received	PCIe received	Mbps	Appld InstanceGpuNum	[10s, avg] [60s, avg]



	data volume	data volume in the service instance-GPU card dimension		Source SubUin	[300s, avg] [3600s, avg] [86400s, avg]
GpuPcieTxMb	PCIe transmitted data volume	PCIe transmitted data volume in the service instance-GPU card dimension	Mbps	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GpuSmClock	SM clock frequency	SM clock frequency in the service instance-GPU card dimension	S	Appld InstanceGpuNum Source SubUin	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



TI-ONE Resource Management

Metric English Name	Metric Chinese Name	Metric Description	Unit	Dimension	Statistical Granularity
GroupCpuUsage	CPU utilization	CPU utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupGpuUtil	GPU utilization	GPU utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupLanInTraffic	Inbound private network bandwidth	Inbound private network bandwidth of the resource group	Mbps	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupLanOutTraffic	Outbound private network bandwidth	Outbound private network bandwidth of the resource group	Mbps	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupMemUsage	Memory utilization	Memory utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



					[86400s, avg]
GroupWanInTraffic	Inbound public network bandwidth	Inbound public network bandwidth of the resource group	Mbps	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupWanOutTraffic	Outbound public network bandwidth	Outbound public network bandwidth of the resource group	Mbps	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsCpuUsage	CPU utilization	CPU utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuUtil	GPU utilization	GPU utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsMemUsage	Memory utilization	Memory utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



InsLanInTraffic	Inbound private network bandwidth	Inbound private network bandwidth of the resource (node)	Mbps	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsLanOutTraffic	Outbound private network bandwidth	Outbound private network bandwidth of the resource (node)	Mbps	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsWanInTraffic	Inbound public network bandwidth	Inbound public network bandwidth of the resource (node)	Mbps	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsWanOutTraffic	Outbound public network bandwidth	Outbound public network bandwidth of the resource (node)	Mbps	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupWanOutratio	Public network bandwidth utilization	Public network bandwidth utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GroupFp16EngineActivity	FP16 active time ratio	FP16 active time ratio of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupFp32EngineActivity	FP32 active time ratio	FP32 active time ratio of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupFp64EngineActivity	FP64 active time ratio	FP64 active time ratio of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupGpuDecUtil	GPU decoder utilization	GPU decoder utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
GroupGpuEccPersistent	Persistent ECC errors	Persistent ECC errors of the resource group	Count	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



GroupGpuEccVolatile	Volatile ECC errors	Volatile ECC errors of the resource group	Count	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg]] [3600s, avg] [86400s, avg]
GroupGpuEncUtil	GPU encoder utilization	GPU encoder utilization of the resource group	%	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg]] [3600s, avg] [86400s, avg]
GroupGpuPowerUsage	GPU power consumption	GPU power consumption of the resource group	W	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg]] [3600s, avg] [86400s, avg]
GroupGpuRetiredPages	Disabled memory pages	Disabled memory pages of the resource group	Count	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg]] [3600s, avg] [86400s, avg]
GroupGpuTemperature	GPU temperature	GPU temperature of the resource group	°C	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg]] [3600s, avg] [86400s, avg]



GroupGpuXidErrors	GPU XID count	GPU XID count of the resource group	Count	ResourceGroupId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsWanOutratio	Public network bandwidth utilization	Public network bandwidth utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuDecUtil	GPU decoder utilization	GPU decoder utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuEccPersistent	Persistent ECC errors	Persistent ECC errors of the resource (node)	Count	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuEccVolatile	Volatile ECC errors	Volatile ECC errors of the resource (node)	Count	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



InsGpuEncUtil	GPU encoder utilization	GPU encoder utilization of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuPowerUsage	GPU power consumption	GPU power consumption of the resource (node)	W	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuRetiredPages	Disabled memory pages	Disabled memory pages of the resource (node)	Count	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuTemperature	GPU temperature	GPU temperature of the resource (node)	°C	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsGpuXidErrors	GPU XID count	GPU XID count of the resource (node)	Count	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



InsFp16EngineActivity	FP16 active time ratio	FP16 active time ratio of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsFp32EngineActivity	FP32 active time ratio	FP32 active time ratio of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]
InsFp64EngineActivity	FP64 active time ratio	FP64 active time ratio of the resource (node)	%	ResourceId AppId	[10s, avg] [60s, avg] [300s, avg] [3600s, avg] [86400s, avg]



Querying Monitoring Metrics: Guide for Calling the GetMonitorData

1. API description

API Name	Version	API Feature
GetMonitorData	2017/3/12	Pulls the monitoring data of cloud product metrics.

2. Input parameters

Parameter Name	Required	Type	Description
Namespace	Yes	String	Namespace, such as qce/cvm. For detailed namespaces of each cloud product, see the appendix of this document. Example value: qce/cvm.
MetricName	Yes	String	Metric name, such as cpu_usage. Only single-metric pulling is supported. For detailed metric descriptions of each cloud product, see the appendix of this document. Example value: cpu_usage.
Dimensions	Yes	Array	The dimension group of instance objects, in the form of a collection of key-value pairs. The fields of different instance types are completely different. For example, the field of CVM is [{"unInstanceId": "ins-miltleuc"}]. For the dimensions of each cloud product, see the appendix of this document. A single request supports pulling monitoring data for up to 10 instances in batches. Example value: [{"unInstanceId": "ins-miltleuc"}, {"unInstanceId": "ins-4xny0cbt"}]
Period	Yes	Integer	Monitoring statistical period, such as 60, in seconds. The statistical period supported by each metric may not be the same. For the statistical periods supported by each cloud product, see the appendix of this document. The maximum number of data points of a single request is 1,440. Example value: 300.
StartTime	Yes	Time	Start time, for example, 2018-09-22T19:51:23+08:00. Example value: 2019-03-24T10:51:23+08:00.
EndTime	Yes	Time	End time, such as 2018-09-22T20:51:23+08:00. The current time is used by default. EndTime cannot be earlier than StartTime. Example value: 2019-03-24T20:51:23+08:00.

3. Request domain name

API request domain name: monitor.api3.\${domain_main}, such as monitor.api3.3100light2az.fsphere.cn.

Note:

`${domain_main}` can be obtained by logging into any Pod, opening `/convergecloud/conf/cm/local.json`, and searching for the `domain_main` keyword.

```

"default_host_user": "root",
"domain_cos": "csp.3100light2az.fsphere.cn",
"domain_cospub": "cos.3100light2az.fsphere.cn",
"domain_main": "3100light2az.fsphere.cn",
"domain_main_login": "3100light2az.fsphere.cn",
"domain_main_others": [
  "3100light2az-others.fsphere.cn"
]

```

4. Request region

Since monitoring data is reported and stored by region, it is necessary to explicitly specify the region where the instance to be pulled is located when an API is called. The method to obtain region information is as follows:

Log in to any Pod, open `/convergecloud/conf/cm/local.json`, search for the `region_list` keyword, and the `region_name` indicates available regions.

```

{
  "region_list": [
    {
      "RegionNo": 5367,
      "cloud_id": 4755,
      "main_zone_name": "yf1",
      "real_region_name": " ",
      "region_area": " ",
      "region_area_en-US": "southwest",
      "region_city": "MR",
      "region_id": 50000001,
      "region_name": "city1",
      "region_name_en-US": " ",
      "region_name_long": " ",
      "region_name_upper": " ",
      "region_role": "MR",
      "xgw_bgp_as": "0"
    }
  ]
}

```

5. Calling frequency limit



Default API request frequency limit: 20 times/second.

6. Output parameters

Parameter Name	Type	Description
MetricName	String	Metric name. Example value: cpu_usage.
Period	Integer	Monitoring statistical period. Example value: 60.
DataPoints[].Dimensions	Json	Instance object dimension group. Example value: {"unInstanceId": "ins-miltleuc"}.
DataPoints[].Points	Array	Data point array.
StartTime	Time	Start time. Example value: 2019-03-24T10:50:00+08:00.
EndTime	Time	End time. Example value: 2019-03-24T20:50:00+08:00.
RequestId	String	Unique request ID. It is generated by the server and is returned for each request. (No RequestId is returned if the request is not received by the server due to certain reasons.) RequestId is required for locating an issue.

7. Examples

Pull CPU utilization monitoring data with a 5-minute statistical period for a CVM instance over a period.

Input example

```
POST HTTP/1.1 Host: monitor.api3.3100light2az.fsphere.cn Content-Type: application/json Action:
GetMonitorData { "Namespace": "qce/cvm", "MetricName": "CPUUsage", "Period": 300, "Dimensions": [ {
"unInstanceId": "ins-miltleuc" } ], "StartTime": "2024-03-24T10:51:23+08:00", "EndTime":
"2024-03-24T20:51:23+08:00" }
```

Output example

```
{ "Response": { "StartTime": "2019-03-24 10:50:00", "EndTime": "2019-03-24 20:50:00", "Period": 300, "MetricName":
"cpu_usage", "DataPoints": [ { "Dimensions": { "unInstanceId": "ins-miltleuc" }, "Points": [ 2.566, 2.283, 6.316, 2.816, 2.7,
2.35 ] } ], "RequestId": "d96ec542-6547-4af2-91ac-fee85c1b8b85" } }
```

8. SDK code calling

Pull CPU utilization monitoring data with a 5-minute statistical period for a CVM instance over a period.

i. Golang example
package main

```
import (
    "fmt"
    "github.com/convergecloud/convergecloud-sdk-go/convergecloud/common"
    "github.com/convergecloud/convergecloud-sdk-go/convergecloud/common/errors"
    "github.com/convergecloud/convergecloud-sdk-go/convergecloud/common/profile"
```

```
monitor "github.com/convergecloud/convergecloud-sdk-go/convergecloud/monitor/v20170312"
)

func main() {
    secretId := "AKIDxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx"
    secretKey := "eyzi69sGK3SWFeiblb8NKwD9l2yZpINf"

    credential := common.NewCredential(secretId, secretKey)
    cpf := profile.NewClientProfile()
    cpf.HttpProfile.Scheme = "HTTP"
    cpf.HttpProfile.ReqTimeout = 10
    cpf.HttpProfile.Endpoint = "monitor.api3.3100light2az.fsphere.cn"
    client, _ := monitor.NewClient(credential, "city1", cpf)

    request := monitor.NewGetMonitorDataRequest()

    request.Namespace = common.StringPtr("qce/cvm")
    request.MetricName = common.StringPtr("cpu_usage")
    request.Period = common.Uint64Ptr(60)
    request.StartTime = common.StringPtr("2024-10-17T15:10:42+08:00")
    request.EndTime = common.StringPtr("2024-10-17T16:10:42+08:00")

    // Building the Dimensions field
    dimensions := []string{
        "{\"unInstanceId\": \"ins-miltleuc\"}",
    }
    request.Dimensions = common.StringPtrs(dimensions)
    response, err := client.GetMonitorData(request)

    if _, ok := err.(*errors.CloudSDKError); ok {
        fmt.Printf("An API error has returned: %s", err)
        return
    }
    if err != nil {
        panic(err)
    }
    fmt.Printf("%s", response.ToJsonString())
}
```

Note:

Lines 13 to 14: secretId and secretKey are calling credentials used for calling authentication, which means that through secretId and secretKey, the called AppID and UIN can be identified. secretId and secretKey are created in the following ways:

Line 20: Endpoint is the calling domain name. For how to obtain it, see 3. Request Domain.

Line 21: "city1" is the region where the monitoring data of cloud product instances is located. For how to obtain it, see 4. Request Region.

2. Python example

```
# -*- coding: utf8 -*-
import json
from convergecloud.common import credential
from convergecloud.common.exception.cloud_sdk_exception import CloudSDKException
from convergecloud.monitor.v20170312 import monitor_client, models
from convergecloud.common.profile.client_profile import ClientProfile
from convergecloud.common.profile.http_profile import HttpProfile
import ssl
```

```
ssl._create_default_https_context = ssl._create_unverified_context
```

```
try:
```

```
    secret_id = "AKIDxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx"
```

```
    secret_key = "1qVuzkBH3WgWhX3F7LJyJJyIJ0NP77rM"
```

```
    cred = credential.Credential(secret_id, secret_key)
```

```
    httpProfile = HttpProfile()
```

```
    httpProfile.endpoint = "monitor.api3.3100light2az.fsphere.cn"
```

```
    clientProfile = ClientProfile()
```

```
    clientProfile.httpProfile = httpProfile
```

```
    client = monitor_client.MonitorClient(cred, "city1", clientProfile)
```

```
    req = models.GetMonitorDataRequest()
```

```
    params = {
```

```
        "Namespace": "qce/cvm",
```

```
        "MetricName": "cpu_usage",
```

```
        "Period": 60,
```

```
        "StartTime": "2024-10-17T15:10:42+08:00",
```

```
        "EndTime": "2024-10-17T16:10:42+08:00",
```

```
        "Dimensions": [{"unInstanceId": "ins-miltleuc"}]
```

```
    }
```

```
    req.from_json_string(json.dumps(params))
```

```
    resp = client.GetMonitorData(req)
```

```
    print(resp.to_json_string(indent=2))
```

```
except CloudSDKException as err:
```

```
    print(err)
```

Note:

Lines 14 to 15: secretId and secretKey are calling credentials used for calling authentication, which means that through secretId and secretKey, the called AppID and UIN can be identified. secretId and secretKey are created in the following ways:

Line 19: Endpoint is the calling domain name. For how to obtain it, see 3. Request Domain.



Line 23: "city1" is the region where the monitoring data of cloud product instances is located. For how to obtain it, see 4. Request Region.

9. Appendix

Namespace	Metric Name	Time Granularity	Dimension Group	Dimension Group Example
qce/cvm	cpu_usage	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	cpu_loadavg	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	CPULoadAvg5m	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	CPULoadAvg15m	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	base_cpu_usage	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	gpu_mem_total	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuMemUsage	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	gpu_mem_used	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuPowDraw	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuPowLimit	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuPowUsage	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuTemp	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	GpuUtil	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	lan_outtraffic	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	lan_intraffic	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	lan_outpkg	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	lan_inpkg	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	tcp_curr_estab	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	mem_used	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
	mem_usage	60/300/3600/86400	unInstanceId	"unInstanceId":"ins-096makkh"
qce/ lb_private	outtraffic	60/300/3600/86400	vip	"vip":"111.111.111.11"
	intraffic	60/300/3600/86400	vip	"vip":"111.111.111.11"
	outpkg	60/300/3600/86400	vip	"vip":"111.111.111.11"
	inpkg	60/300/3600/86400	vip	"vip":"111.111.111.11"
	connum	60/300/3600/86400	vip	"vip":"111.111.111.11"



Namespace	Metric Name	Time Granularity	Dimension Group	Dimension Group Example
	new_conn	60/300/3600/86400	vip	"vip":"111.111.111.11"

Shipping Monitoring Metrics to Kafka

I. Feature Description

Cloud Monitor data can be forwarded to a specified Kafka, supporting:

- Full data forwarding, such as forwarding all metric data of CVMs.
- Partial forwarding, such as forwarding metric data of a specific CVM or all CVMs under a specific AppID, and forwarding specified metric data of specified instances.

The above features are configured through forwarding rules.

II. Forwarding Configuration

Due to the lack of a frontend page, forwarding rules are configured via CLI-based operations, that is, by inserting forwarding rules into the database. The steps are as follows:

1. Connect to the forwarding database named dispense.
2. Configure forwarding rules.

-- Create a rule.

```
insert into t_rule (RuleName, Status) values ('forwarding rule name', 1);
```

Description:

RuleName: Rule name.

Status: Rule enabling status, 1: enabled; 0: disabled.

-- Configure the metrics that need to be forwarded.

```
insert into t_metric (RuleId, Metric, Namespace, Measurement, Periods) values (10, 'cpu_usage', 'qce/cvm', 'cvm_device', '60');
```

Note:

RuleId: The ID field after a rule is created via the t_rule above.

Metric: Metric name.

Namespace: The Namespace where metrics are located.

Measurement: The corresponding Cloud Monitor view. To obtain the view, see Note 1.

Periods: The time granularity of metrics. You can configure a type such as 60,300 to specify multiple time granularities. You can also configure "*" to support all granularities.

For how to determine the Namespace and Measurement for metrics and the supported time granularity, see Appendix 1.

-- Configure filter conditions (Optional. Configure this if you only want to forward data of a specific instance. There are 10 tables in total. You can obtain the information about which table \${n} resides on by performing a ruleId % 10 calculation.)

```
insert into t_condition_${n} (RuleId, Filters) values (10, '[{"Key": "vm_uuid", "Values": ["c7fc0b4c-0059-4318-bb0
```



```
c-dc4a31a071da"],"Expression": "="}, {"Key": "__appid__", "Values": ["251005942", "1"], "Expression": "in"}]);
```

Note:

RuleId: The ID field after a rule is created via the t_rule above.

Filters: Forwarding filter rules. It is a JSON array, and the relationship between multiple arrays is AND.

-- Configure the forwarding target Kafka.

```
insert into t_target (RuleId, Target, ProtoType) values (10, '{"brokers":"11.150.215.105:9092","topic":"Nowrite", "user":"","password":""}', 1);
```

Note:

RuleId: The ID field after a rule is created via the t_rule above.

Target: Target Kafka address.

ProtoType: Message type forwarded to Kafka, 1: JSON; 2: Protobuf.

III. Message Protocol

The message protocol forwarded to Kafka is as follows:

```
// json
{
  "Namespace": "qce/cvm",
  "MetricName": "cpu_usage",
  "Statistic": "MAX",
  "Period": 60,
  "Dimensions": [{
    "Name": "appid",
    "Value": "1"
  }, {
    "Name": "projectid",
    "Value": "0"
  }, {
    "Name": "vm_uuid",
    "Value": "4f7639f1-f156-41b4-9072-f7e27af97d3b"
  }],
  "Timestamp": 1737107700000,
  "Value": 22.916666666666668
}
```

IV. Forwarding Table Structure Description

Table Name	Meaning	Description
------------	---------	-------------



t_rule	Forwarding a rule table	Includes rule metadata such as rule ID, rule name, and configuration user. `Id: 38230` `RuleName: 1118-Phase 2-cvm-cpu // Forwarding rule name.` `AppId: 1300260700 // User AppID for configuring rules, can be empty.` `SubUin: 0 // User UIN for configuring rules, can be empty.` `Status: 1 // Rule enabling status, 1: enabled; 0: disabled.` `CreateTime: 2024-11-20 11:14:23` `UpdateTime: 2024-11-20 11:14:23` `IsAllMetric: 0 // Can be empty.`
t_metric	Forwarding a metric table	Includes the metric information associated with the forwarding operation. Note that in a private network, ExtNamespace and ExtMetric are empty. `Id: 3732457` `RuleId: 38230` `ExtMetric: CpuUtil // External metric name, can be empty.` `ExtNamespace: QCE/TI_MODEL // External namespace, can be empty.` `Measurement: model_svc // View name.` `Periods: * // * indicates all granularities. If you only want to forward granularities 60 and 300, configure it as 60,300.` `Metric: cpu_util // Internal metric name.` `Namespace: qce/ti_model // Internal namespace.` `CNMeaning: CPU utilization // Metric Chinese name, which can be empty.` `ENMeaning: cpu_util // Metric English name, which can be empty.` `CName: ` `Unit: % // Metric unit, which can be empty.` `CreateTime: 2024-12-12 18:30:00` `UpdateTime: 2024-12-12 18:30:00`
t_condition_\${n}	Forwarding a condition table	There are 10 tables in total (0 to 9), and you can obtain the information about which table the forwarding condition resides on by performing a ruleId % 10 calculation. Full forwarding can be configured in the private network by setting the condition table to be empty. The Expression in Filters only supports = or in. For =, Values has only one value; for in, Values may have multiple values. `Id: 12` `RuleId: 38230` `Filters: [{"Key":"vm_uuid","Values":["c7fc0b4c-0059-4318-bb0c-dc4a31a071da"],"Expression":"="},{ "Key":"__appid__","Values":["251005942", "1"],"Expression":"in"}]` `CreateTime: 2024-11-19 17:49:19` `UpdateTime: 2024-11-19 17:49:19`



t_target	Forwarding a target table	TargetType currently only supports Kafka, and ProtoType supports two formats: JSON (1) and PB (2). <pre>` Id: 34539` ` RuleId: 38230` `TargetType: Kafka` ` Target: { "brokers": "11.150.215.105:9092", "topic": "Nowrite", "user": "", "password": "" } ` ` ProtoType: 1` `CreateTime: 2024-11-19 16:48:31` `UpdateTime: 2024-11-19 16:48:31`</pre>
----------	---------------------------------	---

V. Appendix 1

How to view metrics, Namespace, Measurement, and Period?

Execute `kubectl get ingress -A | grep isd.barad` on the master node.

```
mateyao@tcs-10-26-0-29 ~]$  
[haleyao@tcs-10-26-0-29 ~]$ kubectl get ingress -A | grep isd.barad  
tce      bypass-tcloud-barad-isd--baradisd-0-oam-1673320956      <none>      isd.barad.base2.fsphere.cn      10.25.230.91  
80      30d  
tce      tcloud-barad-isd--baradisd-0-oam      <none>      isd.barad.baseline-mini-x86ver.fsphere.cn      10.25.230.91  
80      30d
```

Access the domain name through a browser.

Best Practices

Application of Instance Grouping in Alarms

This document introduces how to implement unified settings of alarm policies in batch for cross-instance and cross-region projects of the same product according to workload classification.

1. Overview

As your business grows, the number of cloud resources increases, making efficient daily monitoring a challenge for Ops. With the instance grouping feature in Cloud Monitor, you can classify a large batch of cloud resources by workload. This allows you to apply unified alarm policies to all instances within a group, helping you stay informed about their usage and operational status, and significantly improving Ops efficiency.

- Use cases

Suppose you have five CVMs, three of which (CVM-1, CVM-2, and CVM-3) are used for Game A, while the remaining two are assigned to other workloads.

- CVM-1 is located in Region A and assigned to Project A.
- CVM-2 is located in Region B and assigned to Project B.
- CVM-3 is located in Region C and assigned to Project C.

To promptly learn about the usage and operation status of the three CVMs for Game A, the following configurations are required.

- Create an instance group. Add CVM-1, CVM-2, and CVM-3 to the same instance group.
- Create an alarm policy, which includes metrics such as CPU utilization, memory utilization, disk utilization, and outbound bandwidth of the public network (for monitoring traffic usage). Alarm notifications are sent automatically when metrics of any instance reach a certain threshold.

2. Grouping instances

- Log in to the Cloud Platform console and choose Cloud Monitor > Instance Group.
- Click Create and configure the instance group in the pop-up window as follows.
 - Group name: The name is "Game A".
 - Group type: Choose Cloud Virtual Machine > Basic Monitoring.
 - Add to the group: Select regions City A, City B, and City C respectively, and add CVM-1, CVM-2, and CVM-3 from each region to the instance group.
- After the configuration is completed, click Save.

3. Creating alarms

- Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration >

Alarm Policy.

ii. Click Create, and perform configurations according to the prompts on the page.

- Policy name: Customized by you.
- Policy type: Choose Cloud Virtual Machine > Basic Monitoring.
- Alarm object: Choose Instance Group > Game Business A.
- Alarm trigger conditions.

CPU utilization, statistical period 1 minute, >, 85%, lasts for 1 data point, and alarm once per day.

Memory utilization, statistical period 1 minute, >, 85%, lasts for 1 data point, and alarm once per day.

Disk utilization, statistical period 1 minute, >, 85%, lasts for 1 data point, and alarm once per day.


Outbound bandwidth, statistical period 1 minute, >, 100Mbps, lasts for 1 data point, and alarm once per day.

- Notification template: The system default is set to preset notification template. You can also click Select Template to choose an existing one you've created, or click Create New Template to create one based on your needs.

iii. After the configuration is completed, click Complete.

Best Practices for Monitoring Scenarios

Cloud Monitor provides multiple methods to help users identify resource exceptions and send exception information to users through various channels as quickly as possible.



1. Locating exceptions

i. Detecting exceptions via monitoring and alarms

Monitoring and alarms enable the cloud platform to detect exceptions promptly and send proactive notifications, allowing users to identify exceptions passively. This ensures timely awareness of exceptions under all circumstances. Users can log in to the Cloud Platform console and go to the Cloud Monitor console to configure appropriate alarm policies for the resources they care about. For details, see [Creating an Alarm Policy](#).

Key performance metrics and events configured as alarm rules will trigger multiple notification methods to promptly reach users and their systems in the event of an exception.

Alarm policies configured with designated recipients or recipient groups will notify users promptly via SMS, email, and other channels. Features such as repeated alarms and alarm convergence are supported to help ensure critical alarms are not missed while minimizing unnecessary disturbances.

Users can also configure the callback API feature in alarm notifications to deliver exception alarm information to their systems for further aggregation and processing.

ii. Detecting exceptions via the monitoring dashboard

Locating exceptions via the monitoring dashboard is a user-driven approach that relies on analyzing average performance trends and historical data. It requires users to proactively identify exceptions. For exceptions that are not covered by alarm policies or are difficult to

detect through existing alarm policies, they can still be identified during daily inspections. Compared with alarms, the monitoring dashboard enables users to assess the overall impact scope of resource exceptions. By subscribing key resources to the dashboard and configuring charts appropriately, users can highlight exception information under various scenarios. For details, see [Create New Dashboard](#).

For individual instances, users can subscribe to detailed instance views to easily compare performance trends on the dashboard panel.

For resource clusters, users can subscribe to aggregated data within the same cluster to conveniently view the overall monitoring dashboard on the dashboard panel and compare it with the trend of individual instances within the cluster. For details, see [Monitoring Scenarios for Large Volumes](#).

Exceptions identified through the monitoring dashboard can be further analyzed using the dashboard's sorting and ranking features, enabling users to locate the affected resources and assess the scope of impact for in-depth troubleshooting.

2. Exception troubleshooting

Locating exception objects via the monitoring overview page

During daily inspections or upon receiving alarm notifications, users can log in to the Cloud Platform console and choose [Cloud Monitor > Monitoring Overview](#).

- i. Check the Service Status in Last 24 Hours module to view exception statuses of resources across different regions.
Use the Exception Information Overview feature to get a preliminary view of recent exceptions.
- ii. Click the number of exception objects to be redirected to the specific exception product menu page under Cloud Product Monitoring.
The specific product list page under Cloud Product Monitoring will automatically filter and display the exception resource objects for the user.
- iii. Click the ID of a specific object to be redirected to its monitoring details page, which provides historical status rollback to assist in detailed exception troubleshooting.
 - The exception timeline provides users with access to both current and historical information about the exception object. By reviewing historical alarms and status changes, users can be assisted in troubleshooting the current exception.
 - The monitoring data for resource performance provides users with the most comprehensive resource performance data. It allows for week-over-week and day-over-day comparisons of current and historical data for the same metric and facilitates troubleshooting by comparing data changes in different metrics over the same time period.

3. Locating exception objects via the dashboard

Log in to the Cloud Platform console and choose [Cloud Monitor > Dashboard > Dashboard List](#) to go to the corresponding dashboard page.

- i. When an abnormal trend appears in the monitoring chart, click [Expand the Instance List](#), and then a sorted list of corresponding instances will be displayed below the curved line graph.

- Through the list, the specific objects that are causing the exceptions can be located.
- ii. By clicking the object name in the sorted list, users can be redirected to the monitoring details page of the object, where historical status information is provided to assist users in locating exceptions.
 - The exception timeline provides users with access to both current and historical information of the exception object. By reviewing past alarms and status changes, users can be assisted in troubleshooting the current exception.
 - The monitoring data for resource performance provides users with the most comprehensive resource performance data. It allows for week-over-week and day-over-day comparisons of current and historical data for the same metric and facilitates troubleshooting by comparing data changes in different metrics over the same time period.


Configuring CVM Metric Alarms

Scenarios

The following example illustrates how to configure an alarm: Suppose you want to receive an SMS alarm at the phone number 12345678888 when the CPU utilization of CVM instance ins-12345678 (located in Region A) exceeds 80% for two consecutive five-minute periods.

Operation Steps

1. Log in to the Cloud Platform console and choose Cloud Monitor > Alarm Configuration > Alarm Policy.
2. Click Create and configure the following options.
3. Configure the basic information.
 - Policy name: CPU alarm.
 - Policy type: Choose Cloud Virtual Machine > Basic Monitoring.
4. Configure the alarm object. Under the Alarm Object module, select instance ID, and then choose the CVM instance from the drop-down list on the right.
5. Configure trigger conditions. Under the Trigger Conditions module, configure the following conditions.
 - Select Manual Configuration.
 - In the Metric Alarm module, select CPU utilization, statistical granularity of 5 minutes, >, 80%, for 2 consecutive data points, and trigger an alarm every 15 minutes.



6. Configure the alarm notification template. Click Create New Template, enter a template name, select the recipient with the phone number 12345678888, and choose SMS as the notification channel. After completion, click Confirm.
7. Click Complete to complete the alarm configuration.



8. At this point, when the instance's CPU utilization exceeds 80% for two consecutive 5-minute periods, an SMS alarm will be sent by Cloud Monitor to the phone number 12345678888.

Product White Paper

Product Overview

Cloud Monitor is a platform that can perform real-time monitoring and alarming for cloud product resources. It provides users with the capability to uniformly monitor resources of cloud products, such as Cloud Virtual Machine (CVM) and cloud databases. Users can use Cloud Monitor to comprehensively understand the resource utilization, application performance, and running status of cloud products and perform monitoring, collecting, and analysis on various services and resources on the cloud platform in real time, ensuring the stability, availability, and security of the cloud environment.

Cloud Monitor leverages its powerful visualization and alarm capabilities to provide users with a one-stop monitoring solution based on the monitoring data of metrics, linkages, and events. It improves Ops and troubleshooting efficiency and guarantees the health and stability of workloads.

Introduction to Submodules of Cloud Monitor

Submodule	Introduction	Common Use Case
Dashboard	It provides the alarm feature for monitoring metrics related to cloud product monitoring, cloud automated testing, application performance monitoring, and frontend performance monitoring.	Analyze the causes of metric exceptions through dashboards.
Alarm management	It provides intelligent dashboards with visualization and analysis capabilities for monitoring data of cloud product metrics.	Users can set alarm rules for monitoring metrics that affect system performance to enable the alarm system to automatically check monitoring data and send alarm notifications when an exception occurs.
Cloud product monitoring	It supports viewing and pulling the monitoring data of cloud product metrics.	-

Product Strengths

- Instance-Level Cloud Product Monitoring

Cloud product resource monitoring is implemented at the instance level to accurately display the resource running status.

- Prompt and Personalized Alarms

- Resource alarm policies for different scenarios can be set in different aspects, such as metric and event.
- Alarm levels can be used to distinguish resource exceptions of different severity levels.
- Alarm notifications can be sent through different channels, such as email, SMS message, and WeCom account.

- Multi-Dimensional Monitoring Chart Display

Rich chart styles and metrics can be configured for data display, allowing users to view resource status from dimensions, such as cloud product and cloud resource instance.

Use Cases

Troubleshooting and Locating Exceptions

- Detect exceptions through monitoring and alarming.

Monitoring and alarming is a method that supports the cloud platform in timely detecting and proactively notifying exceptions, as well as passively detecting exceptions by users. It ensures users can promptly detect exceptions under any circumstances. By configuring alarm rules for critical performance metrics and events, users or user-side systems can receive alarm notifications through multiple channels when exceptions related to these metrics and events occur.


- Detect exceptions through monitoring views.

Locating exceptions through monitoring views is a method for users to proactively locate exceptions based on the average trends of performance metrics and historical data. For exceptions with no corresponding alarm configuration or that are hard to be detected by alarm rules, users can detect them through monitoring views during daily inspections. Compared with monitoring and alarming, this method helps users determine the scope of impact on resources from a global perspective.

Monitoring Large-Scale Resources

- Performance view for large-scale resource monitoring.
- Aggregated view for large-scale resources monitoring.
- Detailed view for large-scale resources monitoring.
- Alarm policy configuration for large-scale resources.

Product Architecture



Various cloud services uniformly report monitoring data to Cloud Monitor. After relevant data processing operations, Cloud Monitor can implement product capabilities, including dashboard, alarm management, and cloud product monitoring.

Features

- **Monitoring Cloud Product Resources**

Cloud Monitor provides users with cloud resource monitoring services.

- Cloud Monitor provides the features of collecting basic monitoring metrics automatically, accurately, and almost instantaneously, as well as storing monitoring metric data.
- The cloud product monitoring and dashboard modules support creating diverse charts to display the metric data of cloud products and configuring alarms. In addition, the metric data can be pulled via APIs for further application and analysis.
- The monitoring metrics of most cloud services can be collected automatically for monitoring data display. Users do not need to perform any monitoring-related configuration.
- For certain cloud services, such as CVM and Cloud Bare Metal (CBM), users need to install and run the corresponding monitoring agent to collect monitoring data. Users can choose to automatically install the agent for these cloud Services when purchasing resources.

- **Providing Alarm Services**

Cloud Monitor provides users with prompt and personalized alarm services.

- Based on existing monitoring metric data, users can apply default alarm settings or customize the settings for cloud resources and custom metrics.
- Users can configure different alarm policies, such as event alarms, failure alarms, and threshold alarms, for resources in different Ops scenarios.
- Users can configure alarm frequency and alarm logics to distinguish alarms at different levels.
- Users can receive alarm notifications promptly through different channels by configuring mobile numbers, email addresses, WeCom accounts, and callback URLs.

- **Displaying Data with Multi-Dimensional Charts**

Cloud Monitor allows users to view existing monitoring data in diversified custom charts.

- Users can conveniently view the monitoring data of various cloud resources in the monitoring pop-up window or on the monitoring details page in the console of each cloud product. By default, the latest data is displayed in a curved line graph.
- Users can view the overall monitoring status of cloud services on the Monitoring Overview page and comprehensively monitor the cloud service status from three aspects: health status, timeline, and exception.
- In Dashboard, users can subscribe to key metrics, customize the display forms and calculation rules of different metrics, and sort and compare metric data in lists and charts to assist in troubleshooting and analyzing issues.
- Users can view the monitoring data and corresponding alarm information on all cloud services under their account in Cloud Product Monitoring.

- **Grouping Instances**

Users can group instances of the same cloud product across regions for unified management. When



they create a large number of instances, they can create instance groups as needed. By managing instance groups, they can manage instances more conveniently and set alarm policies to improve Ops efficiency.



API Documentation

Cloud Monitor(monitor)

version(2018-07-24)

API overview

API version

V3

Alarm APIs

Interface name	Interface function
CreateAlarmPolicy	CreateAlarmPolicy
DescribeAlarmEvents	DescribeAlarmEvents
DescribeAlarmMetrics	DescribeAlarmMetrics
DescribeAlarmPolicy	DescribeAlarmPolicy
DescribeMiniDashboardAlarmInfo	DescribeMiniDashboardAlarmInfo
ModifyAlarmPolicyInfo	ModifyAlarmPolicyInfo
ModifyAlarmPolicyStatus	ModifyAlarmPolicyStatus

Cloud Monitor API

Interface name	Interface function
BindingPolicyObject	BindingPolicyObject
CreateAlarmNotice	CreateAlarmNotice
CreateNoticeContentTpl	CreateNoticeContentTpl
CreatePolicyGroup	CreatePolicyGroup



Interface name	Interface function
DeleteAlarmNotices	DeleteAlarmNotices
DeleteNoticeContentTmpIs	DeleteNoticeContentTmpIs
DeletePolicyGroup	DeletePolicyGroup
DescribeAbnormalObjects	DescribeAbnormalObjects
DescribeAccidentEventList	DescribeAccidentEventList
DescribeAgentStatusHistory	DescribeAgentStatusHistory
DescribeAlarmHistories	DescribeAlarmHistories
DescribeAlarmNotice	DescribeAlarmNotice
DescribeAlarmNoticeCallbacks	DescribeAlarmNoticeCallbacks
DescribeAlarmNotices	DescribeAlarmNotices
DescribeAlarmPolicies	DescribeAlarmPolicies
DescribeAllNamespaces	DescribeAllNamespaces
DescribeBaseMetrics	DescribeBaseMetrics
DescribeBasicAlarmList	DescribeBasicAlarmList
DescribeBindingPolicyObjectList	DescribeBindingPolicyObjectList
DescribeMonitorProducts	DescribeMonitorProducts
DescribeNoticeContentTmpI	DescribeNoticeContentTmpI
DescribePolicyConditionList	DescribePolicyConditionList
DescribePolicyGroupInfo	DescribePolicyGroupInfo
DescribePolicyGroupList	DescribePolicyGroupList
DescribeProductEventList	DescribeProductEventList
DescribeProductHealthStatusList	DescribeProductHealthStatusList
DescribeProductList	DescribeProductList
DescribeStatisticData	DescribeStatisticData
DescribeUnifyDashboards	DescribeUnifyDashboards



Interface name	Interface function
GetMonitorData	GetMonitorData
ModifyAlarmNotice	ModifyAlarmNotice
ModifyAlarmPolicyCondition	ModifyAlarmPolicyCondition
ModifyAlarmPolicyNotice	ModifyAlarmPolicyNotice
ModifyAlarmPolicyTasks	ModifyAlarmPolicyTasks
ModifyAlarmReceivers	ModifyAlarmReceivers
ModifyNoticeContentTpl	ModifyNoticeContentTpl
PutMonitorData	PutMonitorData
SetDefaultAlarmPolicy	SetDefaultAlarmPolicy
UnBindingAllPolicyObject	UnBindingAllPolicyObject
UnBindingPolicyObject	UnBindingPolicyObject

Other APIs

Interface name	Interface function
DescribeLogTopics	DescribeLogTopics

CallingMethod signaturev1

Converge Cloud authenticates each access request, i.e. each request needs to include authentication information (Signature) in the common parameters to verify the identity of the requester.

The Signature is generated by the security credentials which include SecretId and SecretKey. If you don't have the security credentials yet, go to the API Key page to apply for them; otherwise, you cannot invoke the API.

1. Applying for Security Credentials

Before using the API for the first time, go to the API Key page to apply for security credentials.

Security credentials consist of SecretId and SecretKey:

- SecretId is used to identify the API requester.
- SecretKey is used to encrypt the signature string and verify it on the server.
- **You must keep your security credentials private and avoid disclosure.**

You can apply for the security credentials through the following steps:

1. Log in to the Converge Cloud Console.
2. Go to the Cloud API Key page.
3. On the API Key Management page, click Create Key to create a SecretId/SecretKey pair.

Note: Each account can have up to two pairs of SecretId/SecretKey.

2. Generating a Signature

With the SecretId and SecretKey, a signature can be generated. The following describes how to generate a signature:

Assume that the SecretId and SecretKey are:

- SecretId: AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE
- SecretKey: Gu5t9xGARNpq86cd98joQYCN3EXAMPLE

Note: This is just an example. For actual operations, please use your own SecretId and SecretKey.

Take the Cloud Virtual Machine's request to view the instance list (DescribeInstances) as an example. When

you invoke this API, the request parameters may be as follows:

Parameter name	Description	Parameter value
Action	Method name	DescribeInstances
SecretId	Key ID	AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE
Timestamp	Current timestamp	1465185768
Nonce	Random positive integer	11886
Region	Region where the instance is located	luzon
InstanceIds.0	ID of the instance to query	ins-09dx96dg
Offset	Offset	0
Limit	Allowed maximum output	20
Version	API version number	2017-03-12

2.1. Sorting Parameters

First, sort all the request parameters in an ascending lexicographical order (ASCII code) by their names.

Notes: (1) Parameters are sorted by their names instead of their values; (2) The parameters are sorted based on ASCII code, not in an alphabetical order or by values. For example, InstanceIds.2 should be arranged after InstanceIds.12. You can complete the sorting process using a sorting function in a programming language, such as the ksort function in PHP. The parameters in the example are sorted as follows:

```
{
  'Action' : 'DescribeInstances',
  'InstanceIds.0' : 'ins-09dx96dg',
  'Limit' : 20,
  'Nonce' : 11886,
  'Offset' : 0,
  'Region' : 'luzon',
  'SecretId' : 'AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE',
  'Timestamp' : 1465185768,
  'Version': '2017-03-12',
}
```

When developing in another programming language, you can sort these sample parameters and it will work as long as you obtain the same results.

2.2. Concatenating a Request String

This step generates a request string.

Format the request parameters sorted in the previous step into the form of "parameter name"="parameter value". For example, for the Action parameter, its parameter name is "Action" and its parameter value is "DescribeInstances", so it will become Action=DescribeInstances after formatted.

Note: The "parameter value" is the original value but not the value after URL encoding.

Then, concatenate the formatted parameters with "&". The resulting request string is as follows:

```
Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Timestamp=1465185768&Version=2017-03-12
```

2.3. Concatenating the Signature Original String

This step generates a signature original string.

The signature original string consists of the following parameters:

1. HTTP method: POST and GET modes are supported, and GET is used here for the request. Please note that the method name should be in all capital letters.
2. Request host: the domain name of the request to view the list of instances (DescribeInstances) is cvm.convergecloud.com. The actual request domain name varies by the module to which the API belongs. For more information, see the instructions of the specific API.
3. Request path: The request path in the current version of Cloud API is fixed to / .
4. Request string: the request string generated in the previous step.

The concatenation rule of the signature original string is: Request method + request host + request path + ? + request string

The concatenation result of the example is:

```
GETcvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Timestamp=1465185768&Version=2017-03-12
```

2.4. Generating a Signature String

This step generates a signature string.

First, use the HMAC-SHA1 algorithm to sign the signature original string obtained in the previous step, and then encode the generated signature using Base64 to obtain the final signature.

The specific code is as follows with the PHP language being used as an example:



```
$secretKey = 'Gu5t9xGARNpq86cd98joQYCN3EXAMPLE';  
$srcStr = 'GETcvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit  
=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPL  
E&Timestamp=1465185768&Version=2017-03-12';  
$signStr = base64_encode(hash_hmac('sha1', $srcStr, $secretKey, true));  
echo $signStr;
```

The final signature is:

EliP9YW3pW28FpsEdkXt/+WcGeI=

When developing in another programming language, you can sign and verify the original in the example above and it works as long as you get the same results.

3. Encoding a Signature String

The generated signature string cannot be directly used as a request parameter and must be URL encoded.

For example, if the signature string generated in the previous step is EliP9YW3pW28FpsEdkXt/+WcGeI= , the final signature string request parameter (Signature) is EliP9YW3pW28FpsEdkXt%2f%2bWcGeI%3d, which will be used to generate the final request URL.

****Note:** If your request method is GET, or the request method is POST and the Content-Type is application/x-www-form-urlencoded, then all the request parameter values need to be URL encoded (except the parameter key and the symbol of =) when sending the request. Non-ASCII characters need to be encoded with UTF-8 before URL encoding. ******

Note: The network libraries of some programming languages automatically URL encode all parameters, in which case there is no need to URL encode the signature string; otherwise, two rounds of URL encoding will cause the signature to fail.

Note: Other parameter values also need to be encoded using RFC 3986. Use %XY in percent-encoding for special characters such as Chinese characters, where "X" and "Y" are hexadecimal characters (0-9 and uppercase A-F), and using lowercase will cause an error.

4. Signature Failure

The following situational error codes for signature failure may occur. Please resolve the errors accordingly.

Error code	Error description
AuthFailure.SignatureExpire	The signature is expired



Error code	Error description
AuthFailure.SecretIdNotFound	The key does not exist
AuthFailure.SignatureFailure	Signature error
AuthFailure.TokenFailure	Token error
AuthFailure.InvalidSecretId	Invalid key (not a Cloud API key type)

5. Signature Demo

When calling API 3.0, you are recommended to use the corresponding Converge Cloud SDK 3.0, which encapsulates the signature process, enabling you to focus on only the specific APIs provided by the product when developing. See SDK Center for more information. Currently, the following programming languages are supported:

- Python
- Java
- PHP
- Go
- Node

To further explain the signing process, we will use a programming language to implement the process described above. The request domain name, API and parameter values in the sample are used here. This goal of this example is only to provide additional clarification for the signature process, please see the SDK for actual usage.

The final output URL might be: `https://cvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Signature=Elip9YW3pW28FpsEdkXt%2F%2BWcGeI%3D&Timestamp=1465185768&Version=2017-03-12`

Note: The key in the example is fictitious, and the timestamp is not the current time of the system, so if this URL is opened in the browser or called using commands such as curl, an authentication error will be returned: Signature expired. In order to get a URL that can work properly, you need to replace the SecretId and SecretKey in the example with your real credentials and use the current time of the system as the Timestamp.

Note: In the example below, even if you use the same programming language, the order of the parameters in the URL may be different for each execution. However, the order does not matter, as long as all the parameters are included in the URL and the signature is calculated correctly.

Note: The following code is only applicable to API 3.0. It cannot be directly used in other signature processes. Even with an older API, signature calculation errors may occur due to the differences in details. Please refer to the corresponding documentation.

Java

```
import java.io.UnsupportedEncodingException;
import java.net.URLEncoder;
import java.util.Random;
import java.util.TreeMap;
import javax.crypto.Mac;
import javax.crypto.spec.SecretKeySpec;
import javax.xml.bind.DatatypeConverter;

public class CloudAPIDemo {
    private final static String CHARSET = "UTF-8";

    public static String sign(String s, String key, String method) throws Exception {
        Mac mac = Mac.getInstance(method);
        SecretKeySpec secretKeySpec = new SecretKeySpec(key.getBytes(CHARSET), mac.getAlgorithm());
        mac.init(secretKeySpec);
        byte[] hash = mac.doFinal(s.getBytes(CHARSET));
        return DatatypeConverter.printBase64Binary(hash);
    }

    public static String getStringToSign(TreeMap<String, Object> params) {
        StringBuilder s2s = new StringBuilder("GETcvm.convergecloud.com/?");
        // When signing, the parameters need to be sorted in lexicographical order. TreeMap is used here
        // to guarantee the correct order.
        for (String k : params.keySet()) {
            s2s.append(k).append("=").append(params.get(k).toString()).append("&");
        }
        return s2s.toString().substring(0, s2s.length() - 1);
    }

    public static String getUrl(TreeMap<String, Object> params) throws UnsupportedEncodingException {
        StringBuilder url = new StringBuilder("https://cvm.convergecloud.com/?");
        // There is no requirement for the order of the parameters in the actual request URL.
        for (String k : params.keySet()) {
            // The request string needs to be URL encoded. As the Key is all in English letters, only the value
            // is URL encoded here.
            url.append(k).append("=").append(URLEncoder.encode(params.get(k).toString(), CHARSET)).append("&");
        }
        return url.toString().substring(0, url.length() - 1);
    }
}
```

```
}

public static void main(String[] args) throws Exception {
    TreeMap<String, Object> params = new TreeMap<String, Object>(); // TreeMap enables automatic sorting
    // A random number should be used when actually calling, for example: params.put("Nonce", new Random().nextInt(java.lang.Integer.MAX_VALUE));
    params.put("Nonce", 11886); // Common parameter
    // The current time of the system should be used when actually calling, for example: params.put("Timestamp", System.currentTimeMillis() / 1000);
    params.put("Timestamp", 1465185768); // Common parameter
    params.put("SecretId", "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"); // Common parameter
    params.put("Action", "DescribeInstances"); // Common parameter
    params.put("Version", "2017-03-12"); // Common parameter
    params.put("Region", "luzon"); // Common parameter
    params.put("Limit", 20); // Business parameter
    params.put("Offset", 0); // Business parameter
    params.put("InstanceIds.0", "ins-09dx96dg"); // Business parameter
    params.put("Signature", sign(getStringToSign(params), "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE", "HmacSHA1")); // Common parameter
    System.out.println(getUrl(params));
}
}
```

Python

Note: If running in a Python 2 environment, the following requests dependency package must be installed first: `pip install requests`.

```
# -*- coding: utf8 -*-
import base64
import hashlib
import hmac
import time

import requests

secret_id = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"
secret_key = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"

def get_string_to_sign(method, endpoint, params):
    s = method + endpoint + "/"
    query_str = "&".join("%s=%s" % (k, params[k]) for k in sorted(params))
    return s + query_str

def sign_str(key, s, method):
```

```
hmac_str = hmac.new(key.encode("utf8"), s.encode("utf8"), method).digest()
return base64.b64encode(hmac_str)

if __name__ == '__main__':
    endpoint = "cvm.convergecloud.com"
    data = {
        'Action': 'DescribeInstances',
        'InstanceIds.0': 'ins-09dx96dg',
        'Limit': 20,
        'Nonce': 11886,
        'Offset': 0,
        'Region': 'luzon',
        'SecretId': secret_id,
        'Timestamp': 1465185768, # int(time.time())
        'Version': '2017-03-12'
    }
    s = get_string_to_sign("GET", endpoint, data)
    data["Signature"] = sign_str(secret_key, s, hashlib.sha1)
    print(data["Signature"])
    # n actual invocation would occur here, which may incur fees after success
    # resp = requests.get("https://" + endpoint, params=data)
    # print(resp.url)
```

signaturev3

Converge Cloud The API will authenticate each access request, meaning that each request must include signature information (Signature) in the public request parameters to verify the requester's identity. The signature information is generated by the security credentials, which include SecretId and SecretKey . If the user does not have security credentials, please apply for them on the Cloud API Key page, otherwise they cannot call the Cloud API interfaces.

1. Apply for security credentials.

Before using the Cloud API for the first time, please go to the Cloud API Key page to apply for a security credential.

Security credentials include SecretId and SecretKey:

- SecretId The security credentials are used to identify the identity of the API caller.
- SecretKey The secret key is used to encrypt and sign the string for server-side verification of the signature.
- **Users must strictly protect their security credentials and avoid disclosure them.**

The specific steps to apply for security credentials are as follows:

1. Log in to Converge Cloud Administration Center Console
2. Go to the console page for cloud API keys
3. On the Cloud API Key page, click New to create a pair of SecretId/SecretKey

Note: Developer accounts can have up to two pairs SecretId / SecretKey.

2. TC3-HMAC-SHA256 signature method

Note: For GET method, only Content-Type: application/x-www-form-urlencoded protocol format is supported. For POST method, Content-Type: application/json and Content-Type: multipart/form-data are currently supported. By default, all business interfaces are supported in json format. Only specific business interfaces are supported in multipart format. In this case, the interface cannot be called in json format. Refer to the specific business interface document description.

The following takes Cloud Virtual Machine querying Region-1 instance list as an example to introduce the signature calculation process step by step. We only use two parameters for the query instance list: Limit and Offset, called using the GET method.

Assume that the SecretId and SecretKey of the user are AKIDz 8krbsJ 5yKBZQpn 74WFkmLPx 3EXAMPLE and Gu 5t9xGARNpq 86cd 98joQYCN3EXAMPLE, respectively.

2.1. splice specification request string

Concatenate CanonicalRequest strings in the following format:

```
CanonicalRequest =  
  HTTPRequestMethod + '\n' +  
  CanonicalURI + '\n' +  
  CanonicalQueryString + '\n' +  
  CanonicalHeaders + '\n' +  
  SignedHeaders + '\n' +  
  HashedRequestPayload
```

- HTTPRequestMethod: HTTP request methods (GET, POST), GET in this example;
- CanonicalURI: URI parameter, API 3.0 fixed to forward slash (/);
- CanonicalQueryString: Query string in the URL that initiates the HTTP request. For POST requests, it is fixed as an empty string. For GET requests, it is the question mark (?) in the URL. The following string content, this example value is: Limit=10&Offset=0. Note: CanonicalQueryString needs to be URL encoded.
- CanonicalHeaders: The header information of participating signature, at least including host and content-type, can also be added with customized header to improve the uniqueness and security of its own request. Splicing rules: 1) head key and value are uniformly converted to lowercase, and the first and last spaces are removed, and spliced according to the format of key:value\n;2) multiple heads are spliced according to the dictionary sorting of head key (lowercase). In this example:
content-type: application/x-www-form-urlencoded\nhost: cvm.convergecloud.com\n
- SignedHeaders: The header information involved in the signature indicates which headers participate in the signature of this request, and the header content contained in CanonicalHeaders is one-to-one corresponding. content-type and host are required headers. constructed as: 1) The head key is uniformly converted to lowercase; 2) Multiple header keys (lowercase) are concatenated according to dictionary sorting and separated by semicolons (;). In this case: content-type;host
- HashedRequestPayload: The hash value of the request body, calculated as Lowercase(HexEncode(Hash.SHA256(RequestPayload))), SHA256 hash the entire payload of the HTTP request body, then hexadecimal encoding, and finally converting the encoding string to lowercase letters. Note: For GET requests, RequestPayload is fixed as an empty string. For POST requests, RequestPayload is the payload of the HTTP request body.

According to the above rules, the resulting canonical request string in the example is as follows (for clarity, \nnewlines are replaced by a new line printed separately):

GET


```
/
Limit=10&Offset=0
content-type:application/x-www-form-urlencoded
host:cvm.convergecloud.com

content-type:host
e3b0c44298fc1c149afb4c8996fb92427ae41e4649b934ca495991b7852b855
```

2.2. Concatenate the string to be signed

Concatenate the string to be signed in the following format:

```
StringToSign =
  Algorithm + \n +
  RequestTimestamp + \n +
  CredentialScope + \n +
  HashedCanonicalRequest
```

- Algorithm: Signature algorithm, currently fixed as TC3-HMAC-SHA256;
- RequestTimestamp: Request timestamp, i.e. the X-TC-Timestamp value of the request header. The request in the example above is 1539084154;
- CredentialScope: Credential range in the format Date/service/tc3_request, containing date, requested service and termination string (tc3_request). **Date is the date of UTC standard time, the value needs to be consistent with UTC standard time converted by common parameter X-TC-Timestamp **;service is the product name, which must be consistent with the product domain name called, such as cvm. The above example request, the value is 2018-10-09/cvm/tc3_request;
- HashedCanonicalRequest: The hash value of the canonical request string obtained by concatenating the above steps is calculated by Lowercase(HexEncode(Hash.SHA256(CanonicalRequest))).

note:

1. Date must be calculated from timestamp X-TC-Timestamp and time zone UTC+0. Adding local time zone information to the system, such as East Zone 8, will cause calls to succeed during the day and night, but calls to fail in the early hours of the morning. Assuming the timestamp is 1551113065, the time in the East Eight District is 2019-02-26 00:44:25, but the calculated Date with UTC+0 should be 2019-02-25 instead of 2019-02-26.
2. Timestamp must be the current system time and ensure that the system time and standard time are synchronized. If the difference exceeds five minutes, it will fail. If it is not synchronized with the standard time for a long time, it may cause the request to fail after running for a period of time (return signature expiration error).

According to the above rules, the string to be signed in the example is as follows (for clarity,\nnewlines are

replaced by new lines printed):

```
TC3-HMAC-SHA256
1539084154
2018-10-09/cvm/tc3_request
91c9c192c14460df6c1ffc69e34e6c5e90708de2a6d282cccf957dbf1aa7f3a7
```

2.3. calculate the signature

1. Compute the derived signature key, pseudocode as follows

```
SecretKey = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"
SecretDate = HMAC_SHA256("TC3" + SecretKey, Date)
SecretService = HMAC_SHA256(SecretDate, Service)
SecretSigning = HMAC_SHA256(SecretService, "tc3_request")
```

- SecretKey: Original SecretKey;
- Date: That is, the Date field information in Credential, as shown in the example above, is 2018-10-09.;
- Service: That is, the Service field information in Credential, as shown in the example above, is cvm;

2. Calculate the signature, pseudocode as follows

```
Signature = HexEncode(HMAC_SHA256(SecretSigning, StringToSign))
```

- SecretSigning: That is, the derivative signature key calculated above;
- StringToSign: That is, the character string to be signed calculated in step 2;

2.4. Splicing Authorization

Splice as follows Authorization:

```
Authorization =
  Algorithm + ' ' +
  'Credential=' + SecretId + '/' + CredentialScope + ', ' +
  'SignedHeaders=' + SignedHeaders + ', ' +
  'Signature=' + Signature
```

- Algorithm: Signature method, fixed as TC3-HMAC-SHA256;
- SecretId: SecretId in key pair;
- CredentialScope: See above, Scope of Voucher;
- SignedHeaders: See above, header information for participating signatures;
- Signature: signature value



According to the above rules, the values obtained in the example are:

TC3-HMAC-SHA256 Credential=AKIDEXAMPLE/Date/service/tc3_request, SignedHeaders=content-type;host, Signature=5da7a33f6993f0614b047e5df4582db9e9bf4672ba50567dba16c6ccf174c474

The final complete invocation information is as follows:

`https://cvm.convergecloud.com/?Limit=10&Offset=0`

Authorization: TC3-HMAC-SHA256 Credential=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE/2018-10-09/cvm/tc3_request, SignedHeaders=content-type;host, Signature=5da7a33f6993f0614b047e5df4582db9e9bf4672ba50567dba16c6ccf174c474
Content-Type: application/x-www-form-urlencoded
Host: cvm.convergecloud.com
X-TC-Action: DescribeInstances
X-TC-Version: 2017-03-12
X-TC-Timestamp: 1539084154
X-TC-Region: luzon

3. signing failed

According to the actual situation, there are the following signature failure error codes, please handle according to the actual situation

error code	error description
AuthFailure.SignatureExpire	signature expiration
AuthFailure.SecretIdNotFound	key is not present
AuthFailure.SignatureFailure	signature error
AuthFailure.TokenFailure	token error
AuthFailure.InvalidSecretId	Illegal key (not cloud API key type)

4. Signature Demo

Java

```
import java.io.BufferedReader;  
import java.io.InputStream;
```

```
import java.io.InputStreamReader;
import java.net.URL;
import java.text.SimpleDateFormat;
import java.util.Date;
import java.util.Map;
import java.util.TimeZone;
import java.util.TreeMap;
import javax.crypto.Mac;
import javax.crypto.spec.SecretKeySpec;
import javax.net.ssl.HttpsURLConnection;
import javax.xml.bind.DatatypeConverter;

import org.apache.commons.codec.digest.DigestUtils;

public class CloudAPITC3Demo {
    private final static String CHARSET = "UTF-8";
    private final static String ENDPOINT = "cvm.convergecloud.com";
    private final static String PATH = "/";
    private final static String SECRET_ID = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE";
    private final static String SECRET_KEY = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE";
    private final static String CT_X_WWW_FORM_URLENCODED = "application/x-www-form-urlencoded";
    private final static String CT_JSON = "application/json";
    private final static String CT_FORM_DATA = "multipart/form-data";

    public static byte[] sign256(byte[] key, String msg) throws Exception {
        Mac mac = Mac.getInstance("HmacSHA256");
        SecretKeySpec secretKeySpec = new SecretKeySpec(key, mac.getAlgorithm());
        mac.init(secretKeySpec);
        return mac.doFinal(msg.getBytes(CHARSET));
    }

    public static void main(String[] args) throws Exception {
        String service = "cvm";
        String host = "cvm.convergecloud.com";
        String region = "luzon";
        String action = "DescribeInstances";
        String version = "2017-03-12";
        String algorithm = "TC3-HMAC-SHA256";
        String timestamp = "1539084154";
        //String timestamp = String.valueOf(System.currentTimeMillis() / 1000);
        SimpleDateFormat sdf = new SimpleDateFormat("yyyy-MM-dd");
        // Pay attention to the time zone, otherwise it is easy to make mistakes.
        sdf.setTimeZone(TimeZone.getTimeZone("UTC"));
        String date = sdf.format(new Date(Long.valueOf(timestamp + "000")));

        // ***** Step 1: Assemble the specification request string *****
    }
}
```

```
String httpRequestMethod = "GET";
String canonicalUri = "/";
String canonicalQueryString = "Limit=10&Offset=0";
String canonicalHeaders = "content-type:application/x-www-form-urlencoded\n" + "host:" + host
+ "\n";
String signedHeaders = "content-type;host";
String hashedRequestPayload = DigestUtils.sha256Hex("");
String canonicalRequest = httpRequestMethod + "\n" + canonicalUri + "\n" + canonicalQueryStri
ng + "\n"
    + canonicalHeaders + "\n" + signedHeaders + "\n" + hashedRequestPayload;
System.out.println(canonicalRequest);

// ***** Step 2: Stitching the string to be signed *****
String credentialScope = date + "/" + service + "/" + "tc3_request";
String hashedCanonicalRequest = DigestUtils.sha256Hex(canonicalRequest.getBytes(CHARSET));
String stringToSign = algorithm + "\n" + timestamp + "\n" + credentialScope + "\n" + hashedCan
onicalRequest;
System.out.println(stringToSign);

// ***** Step 3: Calculate the signature *****
byte[] secretDate = sign256(("TC3" + SECRET_KEY).getBytes(CHARSET), date);
byte[] secretService = sign256(secretDate, service);
byte[] secretSigning = sign256(secretService, "tc3_request");
String signature = DatatypeConverter.printHexBinary(sign256(secretSigning, stringToSign)).toLow
erCase();
System.out.println(signature);

// ***** Step 4: Splicing Authorization *****
String authorization = algorithm + " " + "Credential=" + SECRET_ID + "/" + credentialScope + ", "
    + "SignedHeaders=" + signedHeaders + ", " + "Signature=" + signature;
System.out.println(authorization);

TreeMap<String, String> headers = new TreeMap<String, String>();
headers.put("Authorization", authorization);
headers.put("Host", host);
headers.put("Content-Type", CT_X_WWW_FORM_URL_ENCODED);
headers.put("X-TC-Action", action);
headers.put("X-TC-Timestamp", timestamp);
headers.put("X-TC-Version", version);
headers.put("X-TC-Region", region);
}
}
```

Python

```
# -*- coding: utf-8 -*-
```

```
import hashlib, hmac, json, os, sys, time
from datetime import datetime

# key parameters
secret_id = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"
secret_key = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"

service = "cvm"
host = "cvm.convergecloud.com"
endpoint = "https://" + host
region = "luzon"
action = "DescribeInstances"
version = "2017-03-12"
algorithm = "TC3-HMAC-SHA256"
timestamp = 1539084154
date = datetime.utcfromtimestamp(timestamp).strftime("%Y-%m-%d")
params = {"Limit": 10, "Offset": 0}

# ***** Step 1: Assemble the specification request string *****
http_request_method = "GET"
canonical_uri = "/"
canonical_querystring = "Limit=10&Offset=0"
ct = "x-www-form-urlencoded"
payload = ""
if http_request_method == "POST":
    canonical_querystring = ""
    ct = "json"
    payload = json.dumps(params)
canonical_headers = "content-type:application/%s\nhost:%s\n" % (ct, host)
signed_headers = "content-type;host"
hashed_request_payload = hashlib.sha256(payload.encode("utf-8")).hexdigest()
canonical_request = (http_request_method + "\n" +
                     canonical_uri + "\n" +
                     canonical_querystring + "\n" +
                     canonical_headers + "\n" +
                     signed_headers + "\n" +
                     hashed_request_payload)
print(canonical_request)

# ***** Step 2: Stitching the string to be signed *****
credential_scope = date + "/" + service + "/" + "tc3_request"
hashed_canonical_request = hashlib.sha256(canonical_request.encode("utf-8")).hexdigest()
string_to_sign = (algorithm + "\n" +
                  str(timestamp) + "\n" +
                  credential_scope + "\n" +
                  hashed_canonical_request)
print(string_to_sign)
```

```
# ***** Step 3: Calculate the signature *****
# Compute signature digest function
def sign(key, msg):
    return hmac.new(key, msg.encode("utf-8"), hashlib.sha256).digest()
secret_date = sign(("TC3" + secret_key).encode("utf-8"), date)
secret_service = sign(secret_date, service)
secret_signing = sign(secret_service, "tc3_request")
signature = hmac.new(secret_signing, string_to_sign.encode("utf-8"), hashlib.sha256).hexdigest()
print(signature)

# ***** Step 4: Splicing Authorization *****
authorization = (algorithm + " " +
    "Credential=" + secret_id + "/" + credential_scope + ", " +
    "SignedHeaders=" + signed_headers + ", " +
    "Signature=" + signature)
print(authorization)

# Common parameters added to request header
headers = {
    "Authorization": authorization,
    "Host": host,
    "Content-Type": "application/%s" % ct,
    "X-TC-Action": action,
    "X-TC-Timestamp": str(timestamp),
    "X-TC-Version": version,
    "X-TC-Region": region,
}
```

request

1. Service Address

Region refers to the geographical area of a physical data center. Converge Cloud ensures complete isolation between different regions, providing maximum stability and fault tolerance. To reduce access latency and improve download speed, it is recommended to choose the region closest to your customers.

You can view the complete region list by using the API interface "DescribeRegions".

2. Communications Protocol

All the Converge Cloud APIs communicate via HTTPS, providing highly secure communication tunnels.

3. Request Methods

Supported HTTP request methods:

- POST (recommended)
- GET

The Content-Type types supported by POST requests:

- application/json (recommended). The TC3-HMAC-SHA256 signature algorithm must be used.
- application/x-www-form-urlencoded. The HmacSHA1 or HmacSHA256 signature algorithm must be used.
- multipart/form-data (only supported by certain APIs). You must use TC3-HMAC-SHA256 to calculate the signature.

The size of a GET request packet is up to 32 KB. The size of a POST request is up to 1 MB when the HmacSHA1 or HmacSHA256 signature algorithm is used, and up to 10 MB when TC3-HMAC-SHA256 is used.

4. Character Encoding

Only UTF-8 encoding is used.

result

Response for Successful Requests

For example, when calling CAM API (version: 2017-03-12) to view the status of instances (DescribeInstancesStatus), if the request has succeeded, you may see the response as shown below:

```
{
  "Response": {
    "TotalCount": 0,
    "InstanceStatusSet": [],
    "RequestId": "b5b41468-520d-4192-b42f-595cc34b6c1c"
  }
}
```

- The API will return Response, which contains RequestId, as long as it processes the request. It does not matter if the request is successful or not.
- RequestId is the unique ID of an API request. Contact us with this ID when an exception occurs.
- Except for the fixed fields, all fields are action-specified. For the definitions of action-specified fields, see the corresponding API documentation. In this example, TotalCount and InstanceStatusSet are the fields specified by the API DescribeInstancesStatus. 0 TotalCount means that the requester owns 0 CVM instance so the InstanceStatusSet is empty.

Response for Failed Requests

If the request has failed, you may see the response as shown below:

```
{
  "Response": {
    "Error": {
      "Code": "AuthFailure.SignatureFailure",
      "Message": "The provided credentials could not be validated. Please check your signature is correct."
    },
    "RequestId": "ed93f3cb-f35e-473f-b9f3-0d451b8b79c6"
  }
}
```

- The presence of the Error field indicates that the request has failed. A response for a failed request will include Error, Code and Message fields.

- Code is the code of the error that helps you identify the cause and solution. There are two types of error codes so you may find the code in either common error codes or API-specified error codes.
- Message explains the cause of the error. Note that the returned messages are subject to service updates. The information the messages provide may not be up-to-date and should not be the only source of reference.
- RequestId is the unique ID of an API request. Contact us with this ID when an exception occurs.

Common Error Codes

If there is an Error field in the response, it means that the API call failed. The Code field in Error indicates the error code. The following table lists the common error codes that all actions can return.

Error Code	Description
AuthFailure.InvalidSecretId	Invalid key (not a API key type).
AuthFailure.MFAFailure	MFA failed.
AuthFailure.SecretIdNotFound	The key does not exist.
AuthFailure.SignatureExpire	Signature expired.
AuthFailure.SignatureFailure	Signature error.
AuthFailure.TokenFailure	Token error.
AuthFailure.UnauthorizedOperation	The request does not have CAM authorization.
DryRunOperation	DryRun Operation. It means that the request would have succeeded, but the DryRun parameter was used.
FailedOperation	Operation failed.
InternalError	Internal error.
InvalidAction	The API does not exist.
InvalidParameter	Incorrect parameter.
InvalidParameterValue	Invalid parameter value.
LimitExceeded	Quota limit exceeded.
MissingParameter	A parameter is missing.
NoSuchVersion	The API version does not exist.



Error Code	Description
RequestLimitExceeded	The number of requests exceeds the frequency limit.
ResourceInUse	Resource is in use.
ResourceInsufficient	Insufficient resource.
ResourceNotFound	The resource does not exist.
ResourceUnavailable	Resource is unavailable.
UnauthorizedOperation	Unauthorized operation.
UnknownParameter	Unknown parameter.
UnsupportedOperation	Unsupported operation.
UnsupportedProtocol	hHTTPS request method error. Only GET and POST requests are supported.
UnsupportedRegion	API does not support the requested region.



PublicParameter

Common parameters are parameters used to identify users and interface authentication purposes. If not necessary, these parameters are not described in the separate interface document of each interface, but these parameters need to be carried in each request before the request can be normally initiated.

signature method v3

When using TC3-HMAC-SHA256 signature method, the common parameters need to be uniformly placed in the HTTP Header request header, as follows:

parameter name	type	required	described
X-TC-Action	String	Yes	The name of the operation interface. Refer to the description of the public parameter Action in the input parameters of the interface documentation for the value. For example, the value for the query instance list interface of the cloud server is DescribeInstances.
X-TC-Region	String	Yes	region parameters, Data used to identify which region you wish to operate on. The region value accepted by the interface refers to the description of the input parameter common parameter Region in the interface document. Note: Some interfaces do not need to pass this parameter, which is specifically stated in the interface documentation. In this case, even passing this parameter will not take effect.
X-TC- Timestamp	Integer	Yes	The current UNIX timestamp, which records the time when the API request was initiated. for example 1529223702. Note: If the time difference from the server exceeds 5 minutes, it will cause a signature expiration error.
X-TC-Version	String	Yes	Version of API for operation. Refer to the description of the public parameter Version in the interface document for the value. For example, the version of the cloud server. 2017-03-12.
Authorization	String	Yes	HTTP The standard authentication header field is "Authorization". For example: TC3-HMAC-SHA256 Credential=AKIDEXAMPLE/Date/service/tc3_request, SignedHeaders=content-type;host, Signature=fe5f80f77d5fa3beca038a248ff027d0445342fe2855ddc963176630326f1024 Here, - TC3-HMAC-SHA256: Signature method, currently fixed as this value, - Credential: Credential: Signature credential; AKIDEXAMPLE is the SecretId; Date is a date in UTC time, and this value must match the value of X-TC-Timestamp (a common parameter) in UTC time format; service is the name of the product/service, and is generally a domain name prefix. For example,cvm; - SignedHeaders: The headers that contains the authentication information; content-type and host are the required headers; - Signature: Signature digest.
X-TC-Token	String	No	The token used for temporary certificates needs to be used in conjunction with a temporary key. Temporary keys and tokens need to be obtained by calling the access management service interface. Long-term keys do not require tokens.

signature method v1



When using HmacSHA1 and HmacSHA256 signature methods, common parameters need to be placed uniformly in the request string, as follows

parameter name	type	required	described
Action	String	Yes	The name of the interface to be operated. The value refers to the explanation of the public parameter <code>Action</code> in the interface documentation. For example, for the cloud server's query instance list interface, the value is <code>DescribeInstances</code> .
Region	String	Yes	The region parameter is used to identify which region's data you want to operate on. The region value accepted by the interface is specified in the input parameter of the public parameter <code>Region</code> in the interface documentation. Note: Some interfaces do not require this parameter to be passed, which will be specifically mentioned in the interface documentation. Even if this parameter is passed, it will not take effect in this case.
Timestamp	Integer	Yes	The current UNIX timestamp, which can record the time when the API request is initiated. For example, 1529223702. If the difference between the current time is too large, it will cause a signature expiration error.
Nonce	Integer	Yes	A random positive integer combined with <code>Timestamp</code> is used to prevent replay attacks.
SecretId	String	Yes	The <code>SecretId</code> is an identifier applied for the cloud API key to identify the user's identity. A <code>SecretId</code> corresponds to a unique <code>SecretKey</code> , and the <code>SecretKey</code> is used to generate the request signature <code>Signature</code> .
Signature	String	Yes	Request signature is used to verify the legitimacy of this request. Users need to calculate it based on the actual input parameters. The specific calculation method can be found in the interface authentication documentation.
Version	String	Yes	The version of the API being operated on. The value refers to the description of the public parameter <code>Version</code> in the interface documentation. For example, the version of the cloud server. 2017-03-12.
SignatureMethod	String	No	Signature method, currently supports HmacSHA256 and HmacSHA1. HmacSHA256 algorithm is used to verify signatures only if this parameter is specified as HmacSHA 256, otherwise HmacSHA1 is used to verify signatures.
Token	String	No	Token used for temporary certificate needs to be used together with temporary key. The temporary key and Token need to be obtained from the Access Management service invocation interface. Long-term keys do not require tokens.

zone list

A region (Region) refers to the geographical area of a physical data center. Converge Cloud Translation: To deliver verification that completely isolates different regions, ensuring maximum stability and fault tolerance between regions. In order to reduce access latency and improve download speed, it is recommended that you choose the region closest to your customers.

You can view the complete region list by using the API interface Query Region List.



Alarm APIs

CreateAlarmPolicy

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for creating alarm policies

Default interface request rate limit: 20 times per second.

Interface update time: 2025-07-22 18:11:39.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: CreateAlarmPolicy
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
PolicyName	Yes	No	String	Policy name, which can contain up to 20 characters. Example: CVM alarm policy
Remark	No	No	String	Remarks, which can contain up to100 letters, digits, underscores, and hyphens. Example: Policy demo
MonitorType	Yes	No	String	Monitor type. Valid values: MT_QCE (Cloud Platform service monitoring) Example: MT_QCE
Enable	No	No	Int64	Whether to enable. Valid values: 0 (no), 1 (yes). Default value: 1. This parameter can be left empty. Example: 1
ProjectId	No	No	Int64	Project ID. Valid values: -1 (no project), 0 (default project). Default value: -1. This parameter can be left empty. Example: 0
Namespace	Yes	No	String	Alarm policy type such as cvm_device, which is obtained through the DescribeAllNamespaces API. Example: cvm_device
PolicyExpression	No	No	String	Bare write alarm rules including trigger rules and filter conditions. Example: 29936048 AND 2993604
ConditionTemplateId	No	No	Int64	ID of the trigger condition template. This parameter can be left empty. Example: 123456
Condition	No	No	AlarmPolicyCondition	Metric trigger condition. Example: View
EventCondition	No	No	Array of AlarmPolicyEventCondition	Event trigger condition. Example: View
NoticeIds	No	No	Array of String	List of notification rule IDs, which is obtained through the DescribeAlarmNotices API. Example: ["notice-bv9b4ghqbg","notice-gj2n9wnt29"]
TriggerTasks	No	No	Array of AlarmPolicyTriggerTask	List of trigger tasks. Example: View
AlarmLevel	No	No	String	Alarm Level Example: Remind

3. Output Parameters

Parameter name	Type	Description
PolicyId	String	Alarm policy ID. Example: policy-abc123
OriginId	String	Policy ID for APIs for binding and unbinding instances or instance groups (BindingPolicyObject, UnBindingAllPolicyObject, UnBindingPolicyObject). Example: 1234556



Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalServerError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.
LimitExceeded	The quota limit has been reached.
InvalidParameterValue	Invalid parameter value.



DescribeAlarmEvents

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query the list of alarm events.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-11-22 16:46:49.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmEvents
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. The value is fixed to "monitor". Example: monitor
Namespace	Yes	No	String	Alarm policy type such as cvm_device, which is obtained through the DescribeAllNamespaces API. Example: cvm_device
MonitorType	No	No	String	Monitor type, such as "MT_QCE". If not specified, the default value is "MT_QCE". Example: MT_QCE

3. Output Parameters

Parameter name	Type	Description
Events	Array of AlarmEvent	Alarm event list. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
ResourceNotFound	The resource does not exist.
UnsupportedOperation	Unsupported operation.



DescribeAlarmMetrics

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query the list of alarm metrics.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-11-16 10:17:56.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmMetrics
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
MonitorType	Yes	No	String	Filters by monitor type. "MT_QCE" (Cloud Platform service monitoring). Example: MT_QCE
Namespace	Yes	No	String	Alarm policy type such as cvm_device, which is obtained through the DescribeAllNamespaces API. Example: cvm_device

3. Output Parameters

Parameter name	Type	Description
Metrics	Array of Metric	Alarm metric list. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
ResourceNotFound	The resource does not exist.
UnsupportedOperation	Unsupported operation.



DescribeAlarmPolicy

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get the details of a single alarm policy.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-11-22 16:25:07.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmPolicy
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
PolicyId	Yes	No	String	The ID of the alarm policy. Example: policy-t1pvz47f

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
Policy	AlarmPolicy	Policy details. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.



DescribeMiniDashboardAlarmInfo

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

MiniDashboard: pulls alarm-related information of an instance.

Default interface request rate limit: 20 times per second.

Interface update time: 2023-05-23 19:20:49.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeMiniDashboardAlarmInfo
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
StartTime	Yes	No	Int64	The start time. Example: 1611218128
EndTime	Yes	No	Int64	End time. Example: 1611218200
MonitorType	Yes	No	String	Monitor type. Valid values: MT_QCE (Cloud Platform service monitoring) Example: MT_QCE
Namespace	Yes	No	String	Alarm namespace: Is used to distinguish between cloud products Example: cvm_device
Dimensions	Yes	No	String	Instance Information of Cloud Product, JSON Format Example: {"name":"instanceId","value":"1"}
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
SevenDaysStartTime	No	No	Int64	Start Time of Total Quantity of Alarms Seven Days Ago Example: 1611218200

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
AlarmCountInSevenDays	Int64	Quantity of Alarms within Seven Days Example: 3
AlarmHistory	Array of AlarmHistory	Alarm History in Specified Period Example: View
AlarmMetrics	Array of AlarmHistoryMetric	Alarm Metric Corresponding to Alarm History Example: View
PoliciesInfo	Array of MiniDashboardAlarmInfo	Whether Instance Has Policy Related Information Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
ResourceNotFound	The resource does not exist.
UnsupportedOperation	Unsupported operation.
FailedOperation	Operation failed.



ModifyAlarmPolicyInfo

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to edit the basic information of a v2.0 alarm policy, including policy name and remarks.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-21 19:35:31.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmPolicyInfo
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-298gn92
Key	Yes	No	String	Field to be modified. NAME (policy name), REMARK (policy remarks). Example: NAME
Value	Yes	No	String	Value after modification. Example: New CVM alarm policy

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.



4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.
InvalidParameterValue	Invalid parameter value.



ModifyAlarmPolicyStatus

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to enable/disable an alarm policy.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-21 19:41:55.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmPolicyStatus
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. The value is fixed to "monitor". Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-2g22g82
Enable	Yes	No	Int64	Enabled or disabled status. 1: enabled. 0: disabled. Example: 0

3. Output Parameters



Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
InvalidParameterValue	Invalid parameter value.



Cloud Monitor API

BindingPolicyObject

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to bind an alarm policy to a specific object.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-12 12:00:48.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: BindingPolicyObject
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
GroupId	Yes	No	Int64	Policy group ID. Example: 111111
InstanceGroupId	No	No	Int64	Instance group ID. Example: 0
Dimensions	No	No	Array of BindingPolicyObjectDimension	Dimensions of an object to be bound. Example: View
Module	Yes	No	String	Required. The value is fixed to "monitor". Example: monitor
PolicyId	No	No	String	Alarm policy ID. When this field is used, any value can be passed in for GroupId. Example: policy-abc123

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter	Invalid parameter.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InternalError	Internal error.



Error Code	Description
FailedOperation	Operation failed.



CreateAlarmNotice

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to create a notification template.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-07-25 20:37:38.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: CreateAlarmNotice
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
Name	Yes	No	String	Notification template name, which can contain up to 60 characters. Example: Default notification template
NoticeType	Yes	No	String	Notification type. Valid values: ALARM (for unresolved alarms), OK (for resolved alarms), ALL (for all alarms) Example: ALL
NoticeLanguage	Yes	No	String	Notification language. Example: zh-CN
UserNotices	No	No	Array of UserNotice	Number of user notifications (up to 5). Example: View
URLNotices	No	No	Array of URLNotice	Number of callback notifications (up to 3). Example: View
ExtraChannels	No	No	Array of String	List of other non-public notification channels. Example: ["TSS"]
BigCustomerNotices	No	No	Array of BigCustomerNotice	Number of major client notifications (up to 1). Example: View

3. Output Parameters

Parameter name	Type	Description
NoticeId	String	Alarm notification template ID. Example: notice-abcdef
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.



Error Code	Description
FailedOperation	Operation failed.



CreateNoticeContentTpl

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to create a custom notification content template.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-02-24 15:24:30.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: CreateNoticeContentTpl
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
TmplName	Yes	No	String	Template name Example: tempName
MonitorType	Yes	No	String	Monitoring type Example: MT_QCE
TmplContents	Yes	No	NoticeContentTplItem	Template Content Example: View
TmplLanguage	Yes	No	String	Template language. Valid values: en and zh. Example: zh
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor



3. Output Parameters

Parameter name	Type	Description
TmplID	String	ID of the custom content template. Example: tmpl-1
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



CreatePolicyGroup

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.
This API is used to add a policy group.
Default interface request rate limit: 20 times per second.
Interface update time: 2020-12-01 11:34:23.
The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters. For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: CreatePolicyGroup
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
GroupName	Yes	No	String	Group policy name. Example: test_group
ViewName	No	No	String	Name of the view to which the policy group belongs. If the policy group is created based on a template, this parameter can be left empty. Example: cvm_device
ProjectId	No	No	Int64	ID of the project to which the policy group belongs, which will be used for authentication. Example: 0
ConditionTempGroupId	No	No	Int64	ID of a template-based policy group. This parameter is required only when the policy group is created based on a template. Example: 123
IsShielded	No	No	Int64	Whether the policy group is shielded. The value 0 indicates that the policy group is not shielded. The value 1 indicates that the policy group is shielded. The default value is 0. Example: 1
Remark	No	No	String	Remarks of the policy group. Example: backup_group
InsertTime	No	No	Int64	Insertion time in the format of Unix timestamp. If this parameter is not configured, the backend processing time is used. Example: 106648246
Conditions	No	No	Array of CreatePolicyGroupCondition	Alarm threshold rules in the policy group. Example:View
EventConditions	No	No	Array of CreatePolicyGroupEventCondition	Event alarm rules in the policy group. Example:View
Module	Yes	No	String	The value is fixed to 'monitor'. Example: monitor
BackEndCall	No	No	Int64	Whether it is a backend call. If the value is 1, rules from the policy template will be used to fill in the Conditions and EventConditions fields. Example: 0
IsUnionRule	No	No	Int64	The 'AND' and 'OR' rules for alarm metrics. The value 0 indicates 'OR', which means that an alarm will be triggered when any rule is met. The value 1 indicates 'AND', which means that an alarm will be triggered only when all rules are met. Example: 1

3. Output Parameters

Parameter name	Type	Description
GroupId	Int64	Created policy ID. Example: 1288099
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic. For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
ResourcesSoldOut	The resources have been sold out.



DeleteAlarmNotices

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to delete alarm notification templates.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-31 11:10:40.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DeleteAlarmNotices
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
NoticeIds	Yes	No	Array of String	List of alarm notification template IDs. Example: ["notice-235h325y","notice-h25hj534h"]

3. Output Parameters

Parameter	Type	Description
-----------	------	-------------



name		
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.



DeleteNoticeContentTmpls

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to delete a custom notification content template.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-02-24 15:24:57.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DeleteNoticeContentTmpls
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
TmplIDs	Yes	No	Array of String	Template ID Example: temp-xxx
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter	Type	Description
-----------	------	-------------



name		
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



DeletePolicyGroup

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to delete an alarm policy group.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-11-30 19:34:04.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DeletePolicyGroup
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
GroupId	Yes	No	Array of Int64	Policy group ID. Example: 12322

3. Output Parameters

Parameter	Type	Description
-----------	------	-------------



name		
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.



Error Code	Description
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



DescribeAbnormalObjects

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for pulling business instances with exceptions in the past 24 hours (alarm dimension)

Default interface request rate limit: 20 times per second.

Interface update time: 2022-10-24 15:08:03.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAbnormalObjects
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
ViewName	Yes	No	String	Name of the alarm type. Example: cvm_device
StartTime	No	No	String	Start time. Format: "2019-01-01". Example: 1734950808
ProjectIds	No	No	Array of Int64	List of project IDs. Example: 10
AbnormalStatus	No	No	String	Alarm status, "all" indicates all instances, "abnormal" indicates abnormal instances (alarms have not been recovered), "warning" indicates warning instances (alarms have been recovered). Example: abnormal
GroupBy	No	No	String	Whether to aggregate or not. If this parameter is left empty, it means no aggregation. "instance" means aggregation by instance. Example: instance
Dimensions	No	No	String	JSON strings filtered by dimension. Example: {"unInstanceId":"","ins-111111111"}

3. Output Parameters

Parameter name	Type	Description
ThresholdObjects	Array of DescribeAbnormalObjectsThresholdObject	List of exceptional objects in the metric alarm Example: View
EventObjects	Array of DescribeAbnormalObjectsEventObject	List of exceptional objects in the product event alarm Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.



Error Code	Description
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.
FailedOperation.DruidTableNotFound	The druid table does not exist.
FailedOperation.DivisionByZero	The dividend is zero.



DescribeAccidentEventList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.
This API is used to get the platform event list.
Default interface request rate limit: 20 times per second.
Interface update time: 2020-03-01 17:38:44.
The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAccidentEventList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	API module name. The value of the current API is "monitor". Example: monitor
StartTime	No	No	Int64	Start time. The default value is the timestamp that is 1 day ago from this day. Example: 1734900808
EndTime	No	No	Int64	End time. The default value is the current timestamp. Example: 1734950808
Limit	No	No	Int64	Pagination parameter. Number of returned results per page. Value range: 1-100. Default: 20. Example: 10
Offset	No	No	Int64	Pagination parameter. Page offset. It starts from 0 and the default value is 0. Example: 0
UpdateTimeOrder	No	No	String	Sorting rule by UpdateTime. Valid values: asc or desc. Example: desc
OccurTimeOrder	No	No	String	Sorting rule by OccurTime. Valid values: asc or desc. Sorting by UpdateTimeOrder takes priority. Example: desc
AccidentType	No	No	Array of Int64	Filters by event type. The value 1 indicates service issues. The value 2 indicates other subscriptions. Example: 1
AccidentEvent	No	No	Array of Int64	Filters by event. The value 1 indicates CVM storage issues. The value 2 indicates CVM network connection issues. The value 3 indicates that the CVM has an exception. The value 202 indicates that an ISP network jitter occurs. Example: 1
AccidentStatus	No	No	Array of Int64	Filters by event status. The value 0 indicates that the event has been recovered. The value 1 indicates that the event has not been recovered. Example: 0
AccidentRegion	No	No	Array of String	Filters by event region. Example: gz
AffectResource	No	No	String	Filters by affected resource, such as ins-19a06bka. Example: ins-19a06bka

3. Output Parameters

Parameter name	Type	Description
Alarms	Array of DescribeAccidentEventListAlarms	List of platform events. Example: View
Total	Int64	Total number of platform events. Example: 10
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter	Invalid parameter.
LimitExceeded	The quota limit has been reached.

DescribeAgentStatusHistory

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for obtaining the status history of the CVM

Default interface request rate limit: 20 times per second.

Interface update time: 2022-08-27 21:47:02.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAgentStatusHistory
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
StartTime	Yes	No	Datetime_iso	Start time of the time range to query. Example: 2023-04-02T16:04:00+08:00
UnInstanceIDs	Yes	No	Array of String	The IDs of the instances you want to restart. Example: lhins-eqecz
EndTime	No	No	Datetime_iso	End time of the query. Example: 2023-04-02T15:04:00+08:00

3. Output Parameters

Parameter name	Type	Description
Data	Array of DescribeAgentStatusHistoryData	CVM status information list. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
FailedOperation	Operation failed.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
FailedOperation	Operation failed.



DescribeAlarmHistories

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.
V2.0 Alarm history list API
Default interface request rate limit: 20 times per second.
Interface update time: 2025-07-22 18:10:52.
The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmHistories
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
PageNumber	No	No	Int64	Number of pages. It starts from 1 and the default value is 1. Example: 1
PageSize	No	No	Int64	Number of entries per page. Value range: 1-100. Default: 20. Example: 20
Order	No	No	String	Sorts by the first occurrence time in descending order by default. Valid values: ASC (ascending), DESC (descending). Example: DESC
StartTime	No	No	Int64	Start time. The default value is the timestamp that is 1 day ago from this day. Example: 1611600000
EndTime	No	No	Int64	End time. The default value is the current timestamp. Example: 1611650000
MonitorTypes	No	No	Array of String	Filters by monitor type. Valid values: "MT_QCE" (Cloud Platform service monitoring), "MT_CUSTOM" (custom monitoring), "MT_PROMETHEUS"=prometheus monitoring. If this parameter is left empty, all types will be queried by default. Example: MT_QCE
AlarmObject	No	No	String	Filter by alarm object. Fuzzy search with string is supported. Example: tdsq1shard-h2phzy69
AlarmStatus	No	No	Array of String	Filters by alarm status. Valid values: ALARM (not resolved), OK (resolved), NO_CONF (expired), NO_DATA (insufficient data). If this parameter is left empty, all will be queried by default. Example: ALARM
ProjectIds	No	No	Array of Int64	Filters by project ID. Valid values: -1 (no project), 0 (default project). Example: 10
InstanceGroupIds	No	No	Array of Int64	Filters by instance group ID Example: 10
Namespaces	No	No	MonitorTypeNamespace	Filters by policy type. Example: View
PolicyName	No	No	String	Fuzzy search by policy name. Example: Testing
Content	No	No	String	Fuzzy search by alarm content. Example: abc
ReceiverUids	No	No	Array of Int64	Searches by recipient Example: 1234
ReceiverGroups	No	No	Array of Int64	Searches by recipient group. Example: 1234
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
PolicyIds	No	No	Array of String	Searches by alarm policy ID list. Example: policy-abcdef
MetricNames	No	No	Array of String	Filters by metric name. Example: CpuUsage
UniqueIds	No	No	Array of String	Searches by unique ID of the alarm instance. Example: dadeqe13zcz
Dimensions	No	No	String	Dimension information of an instance. Example: [{"name":"unInstanceId","value":"ins-abcdef"}]]
AlarmLevel	No	No	Array of String	Alarm Level Example: Remind

3. Output Parameters

Parameter name	Type	Description
TotalCount	Int64	Total number. Example: 100
Histories	Array of AlarmHistory	Alarm history list. Example: View
RequestId	String	Unique request id. Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
LimitExceeded	The quota limit has been reached.
InvalidParameterValue	Invalid parameter value.
MissingParameter	Missing parameter.



DescribeAlarmNotice

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query the details of a single notification template.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-16 18:31:33.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmNotice
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
NoticeId	Yes	No	String	Alarm notification template ID. Example: notice-2g892hg8

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
Notice	AlarmNotice	Alarm notification template details. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InvalidParameterValue	Invalid parameter value.

DescribeAlarmNoticeCallbacks

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get all the callback URLs of an alarm notification template.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-01 14:40:46.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmNoticeCallbacks
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor

3. Output Parameters

Parameter name	Type	Description
URLNotices	Array of URLNotice	Alarm callback notification. Example: View



Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.
UnsupportedOperation	Unsupported operation.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.



DescribeAlarmNotices

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query the list of notification templates.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-11-22 16:04:12.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmNotices
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
OwnerId	No	No	Int64	Root account UID, which is used to create preset notifications. Example: 1234567
Name	No	No	String	Alarm notification template name, which is used for fuzzy search. Example: template
ReceiverType	No	No	String	Filter by recipient. The type of notified users should be selected for the alarm notification template. Valid values: USER (user), GROUP (user group). If this parameter is left empty, no filter by recipient will be performed. Example: USER
UserIds	No	No	Array of Int64	Recipient object list. Example: [1234567]
GroupIds	No	No	Array of Int64	Recipient group list. Example: [1234567]
PageNumber	Yes	No	Int64	Page number. Minimum value: 1. Example: 1
PageSize	Yes	No	Int64	Number of entries per page. Value range: 1–200. Example: 20
Order	Yes	No	String	Sorts by update time. Valid values: ASC (ascending), DESC (descending). Example: DESC
AMPConsumerIds	No	No	Array of String	Filters by the background amp consumer ID list. If this parameter is left empty, the filter operation will not be performed. Example: ["Consumer-9gfn2g92hg92"]
NoticeIds	No	No	Array of String	Filters by notification template ID. If an empty array is passed in or if this parameter is left empty, the filter operation will not be performed. Example: ["notice-ah28cv9d"]

3. Output Parameters

Parameter name	Type	Description
TotalCount	Int64	Total number of alarm notification templates. Example: 1
Notices	Array of AlarmNotice	List of alarm notification templates. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic. For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InvalidParameterValue	Invalid parameter value.



DescribeAlarmPolicies

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query the list of alarm policies.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-07-22 18:09:06.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAlarmPolicies
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
PageNumber	No	No	Int64	Number of pages. It starts from 1 and the default value is 1. Example: 1
PageSize	No	No	Int64	Number of entries per page. Value range: 1-100. Default: 20. Example: 20
PolicyName	No	No	String	Fuzzy search by policy name. Example: policy-24sxe890
MonitorTypes	No	No	Array of String	Filters by monitor type. MT_QCE (Cloud Platform service monitoring). If this parameter is left empty, all will be queried by default. Example: ["MT_QCE"]
Namespaces	No	No	Array of String	Filters by namespace. Example: ["cvm_device"]
Measurements	No	No	Array of String	Filters by policy type (viewName) (for Cloud Platform service monitoring). Example: [cvm]
Dimensions	No	No	String	Alarm object list. Example: [{"name": "unInstanceId", "value": "ins-qr888845g"}]]
ReceiverUids	No	No	Array of Int64	Searches by recipient Example: [9989]
ReceiverGroups	No	No	Array of Int64	Searches by recipient group. Example: [1112]
PolicyType	No	No	Array of String	Filters by default policy. Valid values: DEFAULT (display default policy), NOT_DEFAULT (display non-default policies). If this parameter is left empty, all policies will be displayed. Example: ["DEFAULT"]
Field	No	No	String	Sort field. Example: PolicyId
Order	No	No	String	Sort order. Valid values: ASC (ascending), DESC (descending). Example: DESC
ProjectIds	No	No	Array of Int64	Array of project IDs. Example: [1]
AlarmStatus	No	No	Array of Int64	Obsolete field. Enable or disable. 1: enable. 0: disable. Example: [1]
NoticeIds	No	No	Array of String	Alarm notification ID list. Example: [1,2]
RuleTypes	No	No	Array of String	Filters by trigger condition. Valid values: STATIC (display policies with static threshold), DYNAMIC (display policies with dynamic threshold). If this parameter is left empty, all policies will be displayed. Example: [STATIC]
Enable	No	No	Array of Int64	Enable or disable. 1: enable. 0: disable. Example: 1
NotBindingNoticeRule	No	No	Int64	Whether the notification rule is configured, 1: not configured; 0: configured. Example: 1
InstanceGroupId	No	No	Int64	Instance group ID. Example: 1
ConditionTemplateId	No	No	Int64	Condition template ID. Example: 1
Like	No	No	String	Fuzzy match. Example: Abandoned
Limit	No	No	String	limit. Example: 10
Offset	No	No	Int64	Offset. Example: 0
AlarmLevels	No	No	Array of String	Alarm Level Example: Remind

3. Output Parameters

Parameter name	Type	Description
TotalCount	Int64	Total number of policies. Example: 100



Parameter name	Type	Description
Policies	Array of AlarmPolicy	Policy array. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
UnsupportedOperation	Unsupported operation.
InternalError	Internal error.
FailedOperation	Operation failed.



DescribeAllNamespaces

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for pulling all namespaces.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-10-27 19:42:25.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeAllNamespaces
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
SceneType	Yes	No	String	Filter by monitoring types, "ST_DASHBOARD"=Cloud product monitoring, and "ST_ALARM"=Cloud monitoring alarm. Example: ST_ALARM
MonitorTypes	No	No	Array of String	Filters by namespace ID. If this parameter is left empty, all will be queried. Example: ["MT_QCE"]
Ids	No	No	Array of String	Filters by use case. Valid values: "ST_DASHBOARD" (dashboard type), "ST_ALARM"(alarm type). Example: cvm_device
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
QceNamespaces	Array of CommonNamespace	Cloud product namespace. Example: View
CustomNamespaces	Array of CommonNamespace	Custom monitoring namespace. Example: View
CommonNamespaces	Array of String	CommonNamespaces Example: {"Id":"performance_metric","MonitorType":"MT_TAW","Name":"Performance metric","Dimensions":[]}
CustomNamespacesNew	Array of String	CustomNamespacesNew Example: { "Id":"wenlong_sidecar","Name":"wenlong_sidecar","ProductName":"wenlong_sidecar","Value":"wenlong_sidecar","Config":"","AvailableRegions": [], "DashboardId":"wenlong_sidecar","SortId":0}
QceNamespacesNew	Array of DashboardNamespace	QceNamespacesNew Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



DescribeBaseMetrics

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for obtaining the details of basic metrics.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-31 19:56:55.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeBaseMetrics
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Namespace	Yes	No	String	Service namespace. Example: QCE/CVM
MetricName	No	No	String	Metric name. Example: AccOuttraffic

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
MetricSet	Array of MetricSet	List of queried metric descriptions. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



DescribeBasicAlarmList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get the basic alarm list.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-09-25 15:17:37.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeBasicAlarmList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	API module name. The current value is "monitor". Example: monitor
StartTime	No	No	Int64	Start time. The default value is the timestamp that is 1 day ago from this day. Example: 1573660800
EndTime	No	No	Int64	End time. The default value is the current timestamp. Example: 1573919999
Limit	No	No	Int64	Pagination parameter. Number of returned results per page. Value range: 1-100. Default: 20. Example: 20
Offset	No	No	Int64	Pagination parameter. Page offset. It starts from 0 and the default value is 0. Example: 0
OccurTimeOrder	No	No	String	Sorts by the occurrence time. Valid values: ASC, DESC. Example: DESC
ProjectIds	No	No	Array of Int64	Filters by project ID. Example: ["0"]
ViewNames	No	No	Array of String	Filters by policy type. Example: ["cvm_device"]
AlarmStatus	No	No	Array of Int64	Filters by alarm status. Example: ["1"]
ObjLike	No	No	String	Filters by alarm object. Example: 123
InstanceGroupIds	No	No	Array of Int64	Filters by instance group ID Example: [11233]



3. Output Parameters

Parameter name	Type	Description
Alarms	Array of DescribeBasicAlarmListAlarms	List of alarms. Example: View
Total	Int64	Total number. Example: 2
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter	Invalid parameter.
MissingParameter	Missing parameter.
LimitExceeded	The quota limit has been reached.



DescribeBindingPolicyObjectList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get the bound object list.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-11-22 16:13:15.

The interface only verifies the signature but does not authenticate.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeBindingPolicyObjectList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
GroupId	Yes	No	Int64	Policy group ID. Example: 11111
Limit	No	No	Int64	Pagination parameter. Number of returned results per page. Value range: 1-100. Default: 20. Example: 20
Offset	No	No	Int64	Pagination parameter. Page offset. It starts from 0 and the default value is 0. Example: 0
Dimensions	No	No	Array of DescribeBindingPolicyObjectListDimension	Dimension information of the filtered object. Example: View

3. Output Parameters

Parameter name	Type	Description
List	Array of DescribeBindingPolicyObjectListInstance	List of bound object instances. Example: View
Total	Int64	Total number of bound object instances. Example: 3
NoShieldedSum	Int64	Number of unshielded object instances. Example: 3
InstanceGroup	DescribeBindingPolicyObjectListInstanceGroup	Information about bound instance groups. Leave it empty if no instance group is bound. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.



Error Code	Description
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.
FailedOperation.DruidTableNotFound	The druid table does not exist.
FailedOperation.DivisionByZero	The dividend is zero.



DescribeMonitorProducts

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Queries the monitoring product list.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-08-25 14:20:38.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeMonitorProducts
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
ProductList	String	Cloud product list. JSON string. Example: {"availableRegions":[{}], "id":"dcchannel", "isShowInDashboard":true, "meta":{"alarms":[{"dimensions":{"directconnectconnid":"directConnectTunnelId"},"policyViewName":"dcchannel"}], "columns":[{"enName":"Channel ID/Name", "isShowInMonitorList":true, "keys":["directConnectTunnelId", "directConnectTunnelName"], "name":"\u901a\u9053ID/\u540d\u79f0", "required":true}, {"enName":"Status", "isShowInMonitorList":true, "isShowInSelector":false, "name":"\u72b6\u6001", "renderConditions":{"key":"status", "switch":[[0, {"enShow":"Connected", "show":"\u5df2\u8fde\u63a5"}, {"success"}, [1, {"enShow":"Applying", "show":"\u7533\u8bf7\u4e2d"}], [2, {"enShow":"Configuring", "show":"\u914d\u7f6e\u4e2d"}], [20, {"enShow":"Waiting for connection", "show":"\u7b49\u5f85\u8fde\u63a5"}], [21, {"enShow":"Reject", "show":"\u62d2\u7edd", "danger"}]]]}, {"enName":"Physical Dedicated Line", "isShowInMonitorList":false, "key":"directConnectId", "name":"\u7269\u7406\u4e13\u7ebf"}, {"enShow":"Associated dedicated line gateway", "isShowInMonitorList":false, "isShowInSelector":false, "key":"directConnectGatewayId", "name":"\u5173\u8054\u4e13\u7ebf\u7f51\u5173"}, {"enName":"Virtual Private Cloud", "isShowInMonitorList":true, "keys":["vpcId", "vpcName"], "name":"\u79c1\u6709\u7f51\u7edc"}, {"enName":"VPC - Direct Connect tunnel", "enProductName":"VPC - Direct Connect tunnel", "enSearchPlaceHolder":"Direct Connect Channel ID", "id":"dcchannel", "idKey":["directConnectTunnelId", "directConnectConnId"], "instanceLoader":{"cmd":"DescribeDirectConnectTunnels", "fieldsMapping":{"directConnectConnId":"directConnectTunnelId"}, "fieldsToInstances":{"isArray":false, "reqParams":{"directConnectTunnelId":"<%=obj.directconnectconnid
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalServerError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalServerError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.



Error Code	Description
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



DescribeNoticeContentTpl

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query custom notification content templates.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-02-24 15:23:52.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeNoticeContentTpl
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
TmplIDs	No	No	Array of String	Template ID Example: temp-xxx
TmplName	No	No	String	Template name Example: tmplName
TmplLanguage	No	No	String	Template language. Valid values: en and zh. If this parameter is left blank, filtering is not performed. Example: zh
PageNumber	Yes	No	Uint64	Page number. Example: 1
PageSize	Yes	No	Uint64	Page Size Example: 10
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
NoticeContentTmpls	Array of NoticeContentTpl	Custom notification content template. Example: View
NoticeContentTplBindPolicyCounts	Array of NoticeContentTplBindPolicyCount	Number of alarm policies bound to the notification content template. Example: View
PageNumber	Uint64	Page number. Example: 0
PageSize	Uint64	Page Size Example: 0



Parameter name	Type	Description
TotalCount	UInt64	Number of returned results. Example: 0
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



DescribePolicyConditionList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get basic alarm policy conditions.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-10-27 16:28:47.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribePolicyConditionList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
Conditions	Array of DescribePolicyConditionListCondition	Alarm policy condition list. Example: View



Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.



Error Code	Description
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



DescribePolicyGroupInfo

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get details of a basic policy group.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-10-12 11:25:49.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribePolicyGroupInfo
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
GroupId	Yes	No	Int64	Policy group ID. Example: 123456

3. Output Parameters

Parameter name	Type	Description
GroupName	String	Policy group name. Example: Policies
ProjectId	Int64	Project ID to which the policy group belongs. Example: 0



Parameter name	Type	Description
IsDefault	Int64	Whether it is a default policy. 0: non-default policy. 1: default policy. Example: 1
ViewName	String	Policy type Example: cvm_device
Remark	String	Policy description. Example: Testing
ShowName	String	Policy type name. Example: Basic CVM monitoring
LastEditUin	String	UIN of the last editor. Example: 123
UpdateTime	String	Last modification time. Example: 1718159371
Region	Array of String	Regions supported by this policy. Example: bj
DimensionGroup	Array of String	List of dimensions for policy types. Example: uuid
ConditionsConfig	Array of DescribePolicyGroupInfoCondition	Threshold rules list. Example: View
EventConfig	Array of DescribePolicyGroupInfoEventCondition	List of product event rules. Example: View
ReceiverInfos	Array of DescribePolicyGroupInfoReceiverInfo	User recipient list. Example: View
Callback	DescribePolicyGroupInfoCallback	User callback information. Example: View
ConditionsTemp	DescribePolicyGroupInfoConditionTpl	Template-based policy group. Example: View
CanSetDefault	Bool	Whether it can be set as the default policy. Example: false
IsUnionRule	Int64	Whether it is an AND rule. Example: 1
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.



Error Code	Description
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



DescribePolicyGroupList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get the list of basic policy alarm groups.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-10-24 10:18:55.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribePolicyGroupList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
Limit	Yes	No	Int64	Pagination parameter, the number of entries per page. Value range: 1-1000. Example: 10
Offset	Yes	No	Int64	Pagination parameter. Page offset. It starts from 0. Example: 0
Like	No	No	String	Searches by policy name. Example: test
InstanceGroupId	No	No	Int64	Instance group ID. Example: 12345
UpdateTimeOrder	No	No	String	Sorts by update time. Valid values: asc, desc. Example: asc
ProjectIds	No	No	Array of Int64	List of project IDs. Example: [1]
ViewNames	No	No	Array of String	List of alarm policy types. Example: [cvm_device]
FilterUnuseReceiver	No	No	Int64	Whether to filter policy groups that have no recipients. 1: yes. 0: no. Example: 0
Receivers	No	No	Array of String	Filters by recipient group list. Example: [123]
ReceiverUserList	No	No	Array of String	Filters by recipient list. Example: [12345]
Dimensions	No	No	String	Dimension set field (JSON string), for example, [{"name": "unInstanceId", "value": "ins-6e4b2aaa"}]]. Example: {}
ConditionTempGroupId	No	No	String	Template-based policy group ID. Multiple IDs are separated by commas. Example: 123,345
ReceiverType	No	No	String	Filters by recipient or recipient group. The value 'user' indicates by recipient. The value 'group' indicates by recipient group. Example: user

3. Output Parameters

Parameter name	Type	Description
GroupList	Array of DescribePolicyGroupListGroup	Policy group list. Example: View



Parameter name	Type	Description
Total	Int64	Total number of policy groups. Example: 142
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.





DescribeProductEventList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to get the list of product events by page.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-01-02 10:12:28.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeProductEventList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	API module name. The value is set to monitor. Example: monitor
ProductName	No	No	Array of String	Product type as a filter condition. For example, the value cvm filters Cloud Virtual Machine (CVM). Example: cvm
EventName	No	No	Array of String	Event name as a filter condition. For example, the value guest_reboot filters a machine reboot. Example: guest_reboot
InstanceId	No	No	Array of String	Affected object. Sample value: ins-19708ino. Example: ins-19708ino
Dimensions	No	No	Array of DescribeProductEventListDimensions	Dimension as a filter condition. Sample value: 10.0.0.1. The sample value is a public IP address. Example: View
RegionList	No	No	Array of String	Region as a filter condition. Sample value: gz. Example: gz
Type	No	No	Array of String	Event type as a filter condition. Valid values: status_change and abnormal. The value status_change filters state change events. The value abnormal filters exceptional event. Example: abnormal
Status	No	No	Array of String	Event state as a filter condition. Valid values: recover, alarm, and -. recover: filters recovered events. alarm: filters unrecovered events. -: filters events that have no states. Example: recover
Project	No	No	Array of String	Project ID as a filter condition. Example: 0
IsAlarmConfig	No	No	Int64	Specifies whether alarm states are configured as a filter condition. 1: configured. 0: not configured. Example: 1
TimeOrder	No	No	String	Time-based sorting order. ASC: ascending order. DESC: descending order. Default value: DESC. Example: DESC
StartTime	No	No	Int64	Start time. The default value is the timestamp that is 1 day ago from this day. Example: 1572624000
EndTime	No	No	Int64	End time. The default value is the current timestamp. Example: 1573228799
Offset	No	No	Int64	Page offset. Default value: 0. Example: 0
Limit	No	No	Int64	Number of entries to return per page. Default value: 20. Example: 20

3. Output Parameters

Parameter name	Type	Description
Events	Array of DescribeProductEventListEvents	Event list. Example: View
OverView	DescribeProductEventListOverView	Event statistics. Example: View
Total	Int64	Number of events. Example: 6
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
MissingParameter	Missing parameter.
LimitExceeded	The quota limit has been reached.

DescribeProductHealthStatusList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for pulling the health statistics of each service in the past 24 hours

Default interface request rate limit: 20 times per second.

Interface update time: 2022-08-31 15:04:45.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeProductHealthStatusList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
ViewName	No	No	String	Filters by view name, such as "cvm_device". Example: cvm_device
AllRegions	No	No	Int64	1 means to pull all regions, and 0 is the opposite. Example: 1
ProjectIds	No	No	Array of Int64	Filters by project ID. Example: [1234]

3. Output Parameters

Parameter name	Type	Description
List	Array of ProductHealthStatus	List of health status of each product. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnsupportedOperation	Unsupported operation.
LimitExceeded	The quota limit has been reached.
FailedOperation	Operation failed.



DescribeProductList

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for querying the Cloud Monitor product list

Default interface request rate limit: 20 times per second.

Interface update time: 2021-01-25 19:29:02.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeProductList
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Order	No	No	String	Sorting method: DESC/ASC (case sensitive). The default value is DESC. Example: DESC
Offset	No	No	Uint64	Offset of the pagination query. The default value is 0. Example: 0
Limit	No	No	Uint64	Number of data entries per page for pagination query. Default: 20. Example: 5
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
ProductList	Array of ProductSimple	List of product information. Example: View
TotalCount	Uint64	Total number of products. Example: 294
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.
UnsupportedOperation	Unsupported operation.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
InternalError	Internal error.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter.InvalidParameterParam	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
InternalError.ExeTimeout	Execution timed out.



DescribeStatisticData

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to query monitoring data by dimension conditions.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-04-21 15:13:52.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeStatisticData
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module. The value is fixed to "monitor". Example: monitor
Namespace	Yes	No	String	Namespace. Supported value: QCE/TKE. Example: QCE/TKE2
MetricNames	Yes	No	Array of String	List of metric names. Example: ["K8sPodCpuCoreUsed"]
Conditions	No	No	Array of MidQueryCondition	Dimension condition. The = and in operators are supported. Example: View
Period	No	No	UInt64	Statistical period in seconds. Default value: 300. Example: 300
StartTime	No	No	String	Start time, which is the current time by default, such as 2020-12-08T19:51:23+08:00. Example: 2020-11-24T15:15:50+08:00
EndTime	No	No	String	End time, which is the current time by default, such as 2020-12-08T19:51:23+08:00. Example: 2020-11-24T15:25:50+08:00
GroupBy	No	No	Array of String	groupBy by the specified dimension. Example: ["K8sPodCpuCoreUsed"]

3. Output Parameters

Parameter name	Type	Description
Period	UInt64	Statistical period. Example: 300
StartTime	String	Start time. Example: 2020-11-24 15:15:00



Parameter name	Type	Description
EndTime	String	End time. Example: 2020-11-24 15:25:00
Data	Array of MetricData	Monitoring data Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InvalidParameterValue.InvalDashboardNameExists	The dashboard name already exists.
FailedOperation	Operation failed.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
InvalidParameter.InvalidParameter	Invalid parameter.
MissingParameter	Missing parameter.
FailedOperation.DataQueryFailed	Failed to query the data.
InvalidParameter.InvalidParameterParam	Invalid parameter.
UnauthorizedOperation	Unauthorized operation.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
InvalidParameter	Invalid parameter.
FailedOperation.DataTableNotFound	The data table doesn't exist.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
ResourceInsufficient	Insufficient resource.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
ResourceInUse	The resource is in use.
ResourceNotFound	The resource does not exist.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
InternalError	Internal error.
LimitExceeded	The quota limit has been reached.
FailedOperation.DataColumnNotFound	The data table field doesn't exist.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
InvalidParameterValue	Invalid parameter value.
InvalidParameterValue.VersionMismatch	Inconsistent versions.
UnknownParameter	Unknown parameter error.





DescribeUnifyDashboards

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for obtaining a dashboard list

Default interface request rate limit: 20 times per second.

Interface update time: 2022-08-27 21:53:11.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeUnifyDashboards
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
IsStarred	No	No	String	Whether to add to "Favorite". Example: false
Keyword	No	No	String	The keyword for search. Example: dadceqe231cx
IsFolder	No	No	String	Whether it is a folder. Example: false
Caller	No	No	String	Mini program: applet. Example: applet

3. Output Parameters

Parameter name	Type	Description
Dashboards	Array of UnifyDashboardMeta	Dashboard list. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
UnsupportedOperation	Unsupported operation.
InternalError	Internal error.
InvalidParameter.InvalidParameter	Invalid parameter.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
UnknownParameter	Unknown parameter error.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
ResourceInUse	The resource is in use.
MissingParameter	Missing parameter.
UnauthorizedOperation	Unauthorized operation.
InvalidParameter	Invalid parameter.
FailedOperation	Operation failed.
ResourceInsufficient	Insufficient resource.



Error Code	Description
ResourceNotFound	The resource does not exist.



GetMonitorData

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Obtains the monitoring data of a cloud product. After you specify your product namespace, object dimension description, and monitoring metrics, you can obtain the corresponding monitoring data.

Highest frequency of calls that can be made per second/minute: 20/1200.

If you call excessive metrics and objects in a short period of time, the system may fail to pull data because frequency is limited. We recommend that you balance your requests by time.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-11-30 19:22:03.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: GetMonitorData
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Namespace	Yes	No	String	Namespace. Example: QCE/CVM
MetricName	Yes	No	String	Metric name. Example: CpuUsage
Period	No	No	Uint64	cycle, Example: 60
StartTime	No	No	Datetime_iso	Start time. Sample value: 2018-09-22T19:51:23+08:00. Example: 2019-03-24T10:51:23+08:00
EndTime	No	No	Datetime_iso	End time. Sample value: 2018-09-22T20:51:23+08:00. By default, the system uses the current time as the parameter value. The time corresponding to the value of EndTime cannot be earlier than that of StartTime. Example: 2019-03-24T20:51:23+08:00
Instances	Yes	No	Array of Instance	Combination of instance object dimensions, a group of key-value pairs. Example: View

3. Output Parameters

Parameter name	Type	Description
Period	Uint64	Statistical period. Example: 300
MetricName	String	Metric name. Example: cpu_usage
DataPoints	Array of DataPoint	Data point array. Example: View
StartTime	Datetime	Start time. Example: 2019-03-24T10:50:00+08:00
EndTime	Datetime	End time. Example: 2019-03-24T20:50:00+08:00
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.



ModifyAlarmNotice

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to edit an alarm notification template.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-02-24 20:11:26.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmNotice
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
Name	Yes	No	String	Name of the alarm notification rule, which can contain up to 60 characters. Example: Default notification template
NoticeType	Yes	No	String	Notification type. Valid values: ALARM (for unresolved alarms), OK (for resolved alarms), ALL (for all alarms) Example: ALL
NoticeLanguage	Yes	No	String	Notification language. Example: zh-CN
UserNotices	No	No	Array of UserNotice	Number of user notifications (up to 5). Example: View
URLNotices	No	No	Array of URLNotice	Number of callback notifications (up to 3). Example: View
NoticeId	Yes	No	String	ID of the alarm notification template. Example: notice-qwer
ExtraChannels	No	No	Array of String	List of other non-public notification channels. Example: ["TSS"]

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.



Error Code	Description
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.



ModifyAlarmPolicyCondition

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for editing trigger conditions for an alarm policy

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-21 19:47:17.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmPolicyCondition
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. The value is fixed to "monitor". Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-hi498gw3h2
PolicyExpression	No	No	String	Bare write alarm rules including trigger rules and filter conditions. Example: expression
ConditionTemplateId	No	No	Int64	Trigger condition template ID, to be transformed into a string. Example: 123
Condition	No	No	AlarmPolicyCondition	Metric trigger condition. Example: View
EventCondition	No	No	AlarmPolicyEventCondition	Event trigger condition. Example: View

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).



Error Code	Description
InternalServerError	Internal error.
InvalidParameter	Invalid parameter.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.
InvalidParameterValue	Invalid parameter value.



ModifyAlarmPolicyNotice

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to modify the alarm notification template bound to an alarm policy.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-01-21 14:21:06.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmPolicyNotice
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-asgh3gb2
NoticeIds	No	No	Array of String	List of alarm notification template IDs. Example: ["notice-bv9b4ghqbg","notice-gj2n9wnt29"]
NoticeContentTplBindInfos	No	No	Array of NoticeContentTplBindInfo	Notification template ID and content template ID. Example: View

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).



Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.



ModifyAlarmPolicyTasks

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to modify the task triggered by an alarm policy. The `TriggerTasks` field contains the list of triggered tasks. If an empty array is passed in for `TriggerTasks` , it indicates to unbind all the triggered tasks from this policy.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-01 11:43:16.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmPolicyTasks
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. Enter "monitor" here. Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-29ng82fs
TriggerTasks	No	No	Array of AlarmPolicyTriggerTask	List of tasks triggered by an alarm policy. If an empty array is passed in, it indicates to unbind all the triggered tasks from this policy. Example: View

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.



ModifyAlarmReceivers

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to modify alarm recipients.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-12-01 11:15:09.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyAlarmReceivers
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
GroupId	Yes	No	Int64	ID of a policy group whose recipient needs to be modified. Example: 1234
ReceiverInfos	No	No	Array of ReceiverInfo	New recipient information. If this parameter is not configured, all recipients will be deleted. Example: View
Module	Yes	No	String	Required. The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).

ModifyNoticeContentTpl

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to modify a custom notification content template.

Default interface request rate limit: 20 times per second.

Interface update time: 2025-02-24 15:24:12.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).



Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: ModifyNoticeContentTpl
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
TmplName	No	No	String	Template name Example: tempName
TmplID	Yes	No	String	Template ID Example: temp-xxx
TmplContents	No	No	NoticeContentTplItem	Template Content Example: View
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

There is no error code related to business logic for this interface, For other error codes, see [public ErrorCode](#).



PutMonitorData

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Default frequency limit on API requests: 50 requests/second.

Default metric limit for a single tenant: 100 metrics.

A maximum of 30 metric/value pairs are reported at a time. When the request returns an error, all metrics/values in the request will not be saved.

The reported timestamp is the timestamp expected to be saved. It is recommended to create a timestamp with the number of minutes expressed in integers.

The time range of the timestamp must be between the current time and 300 seconds ago.

Data of the same IP metric pair should be reported in chronological order based on minutes.

Default interface request rate limit: 50 times per second.

Interface update time: 2019-12-13 19:17:02.

The interface only verifies the signature but does not authenticate.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: PutMonitorData
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
AnnounceIp	No	No	String	IP specified by yourself when reporting data. Example: 10.0.0.1
AnnounceTimestamp	No	No	UInt64	Timestamp specified by yourself when reporting data. Example: 1569379988
Metrics	Yes	No	Array of MetricDatum	A set of metrics and data. Example: View
AnnounceInstance	No	No	String	IP or product instance ID specified by yourself when reporting data . Example: 10.0.0.1

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when



Parameter name	Type	Description
		locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
FailedOperation	Operation failed.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.



SetDefaultAlarmPolicy

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Sets an alarm policy as the default policy in the current policy type under the current project.
Alarm policies in the same type under the project will be set as non-default.

Default interface request rate limit: 20 times per second.

Interface update time: 2021-03-01 11:52:23.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: SetDefaultAlarmPolicy
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	Module name. The value is fixed to "monitor". Example: monitor
PolicyId	Yes	No	String	Alarm policy ID. Example: policy-jfg9hg2g2

3. Output Parameters

Parameter	Type	Description
-----------	------	-------------



name		
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameter	Invalid parameter.
InvalidParameterValue	Invalid parameter value.
UnsupportedOperation	Unsupported operation.
InternalError	Internal error.
ResourceNotFound	The resource does not exist.
FailedOperation	Operation failed.



UnBindingAllPolicyObject

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to delete all bound objects.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-01-20 09:27:50.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: UnBindingAllPolicyObject
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
GroupId	Yes	No	Int64	Policy group ID. Example: 11111

3. Output Parameters

Parameter name	Type	Description
----------------	------	-------------



Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalError.ExeTimeout	Execution timed out.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.



Error Code	Description
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



UnBindingPolicyObject

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

This API is used to delete an object that is bound to a policy.

Default interface request rate limit: 20 times per second.

Interface update time: 2020-03-02 00:28:36.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: UnBindingPolicyObject
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Module	Yes	No	String	The value is fixed to "monitor". Example: monitor
GroupId	Yes	No	Int64	Policy group ID. Example: 11111
UniqueId	Yes	No	Array of String	List of unique IDs of the object instances to be deleted. Example: ["3dd5113208fd467b2e5d0c1111111111\n"]
InstanceGroupId	No	No	Int64	Instance group ID. The UniqueId parameter is invalid if object instances are deleted by instance group. Example: 0

3. Output Parameters

Parameter name	Type	Description
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InvalidParameterValue	Invalid parameter value.
InternalServerError	Internal error.
InvalidParameter.InvalidParameterParam	Invalid parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
InvalidParameter	Invalid parameter.
InternalServerError.ExeTimeout	Execution timed out.



Error Code	Description
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnknownParameter	Unknown parameter error.
UnauthorizedOperation	Unauthorized operation.
UnsupportedOperation	Unsupported operation.
ResourceNotFound	The resource does not exist.
LimitExceeded	The quota limit has been reached.
ResourceUnavailable	The resource is unavailable.
ResourceInsufficient	Insufficient resource.
FailedOperation	Operation failed.
ResourceInUse	The resource is in use.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.
FailedOperation.DuplicateName	The name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.



DescribeLogTopics

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Pulls CLS log topics.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-08-27 22:31:17.

The interface only verifies the signature but does not authenticate.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeLogTopics
Version	Yes	No	String	Public parameter, The value of this interface: 2018-07-24
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
LogSetId	Yes	No	String	Log set ID. Example: d5f10b84-def8-4e58-bab0-16ef567b1f22

3. Output Parameters

[illegible]

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalServerError	Internal error.
InvalidParameter	Invalid parameter.
FailedOperation	Operation failed.
MissingParameter	Missing parameter.
UnauthorizedOperation	Unauthorized operation.
FailedOperation	Operation failed.
UnsupportedOperation	Unsupported operation.



Data structure

DescribePolicyQuotaV3ResponseDataQuotaList

DescribePolicyQuotaV3ResponseDataQuotaList

Referenced by the following interfaces: DescribePolicyQuota

name	required	NULL allowed	type	description
Used	yes	no	Int64	User. Example: 10
Total	yes	no	Int64	Total number. Example: 10
ProjectID	yes	no	Int64	Project ID. Example: 10

BindingPolicyObjectDimension

Dimensions of instances bound to a policy

Referenced by the following interfaces: BindingPolicyObject, CreateInstanceGroup, DescribeInstanceGroup, ModifyInstanceGroup, ShieldPolicyAlarm

name	required	NULL allowed	type	description
RegionId	no	no	Int64	Region ID. Example: 1
Region	yes	no	String	Region name. Example: gz
Dimensions	no	no	String	Dimension information. Example: ("unInstanceId":"ins-0jvw9mo")
EventDimensions	no	no	String	Event dimension information. Example: ("uid":"c734cd8d-d050-48bd-8d17-66381039b4b6")

CustomAlarmList

CustomAlarmList

Referenced by the following interfaces: DescribeCustomAlarmList

name	required	NULL allowed	type	description
LocalIP	yes	no	String	IP. Example: 127.0.0.1
Msg	yes	no	String	Message. Example: ok
OccurTime	yes	no	String	Event time. Example: 1735041205
Caller	yes	no	String	Caller. Example: remote

MetricTooltip

Rich text prompt for the metric.

Referenced by the following interfaces: DescribeAlarmEvents, DescribeAlarmHistories, DescribeAlarmMetrics, DescribeMiniDashboardAlarmInfo

name	required	NULL allowed	type	description
Message	yes	no	String	Text command. Example: This metric indicates the CPU utilization of this instance.
URL	yes	no	String	Details link. Example: https://convergecloud.com/
UrlName	yes	no	String	Link name. Example: View Details

DescribeAlarmCallbackHistory

Historical callback information.

Referenced by the following interfaces: DescribeAlarmCallbackHistory

name	required	NULL allowed	type	description
Url	yes	no	String	Callback address. Example: http://test.com
ValidFlag	yes	no	Int64	Whether the callback is validated. Example: 1
VerifyCode	yes	no	String	Callback address verification code. Example: 1131ad

DescribePolicyGroupListGroupInstanceGroup

Instance group that is bound to a policy group of the DescribePolicyGroupList API

Referenced by the following interfaces: DescribePolicyGroupList

name	required	NULL allowed	type	description
InstanceGroupId	yes	no	Int64	Instance group name ID. Example: 1234
ViewName	yes	no	String	Policy type view name. Example: cvm_device
LastEditUin	yes	no	String	UIN of the last editor. Example: 123456
GroupName	yes	no	String	Instance group name. Example: testing
InstanceSum	yes	no	Int64	Number of instances. Example: 10
UpdateTime	yes	no	Int64	Update time. Example: 1735095122
InsertTime	yes	no	Int64	Creation time. Example: 1735095122

DescribeAbnormalObjectsThresholdObject

Metric alarm exception object returned by the DescribeAbnormalObjects API.

Referenced by the following interfaces: DescribeAbnormalObjects

name	required	NULL allowed	type	description
Id	yes	no	Int64	Alarm ID. Example: 1
RuleId	yes	no	Int64	Alarm rule ID. Example: 10
GroupId	yes	no	Int64	Policy group ID. Example: 1234
GroupName	yes	no	String	Policy group name. Example: testing
ProjectId	yes	yes	Int64	Project ID. Example: 1
Status	yes	no	Int64	Alarm status. Example: 1
Content	yes	no	String	The alarm content. Example: over
FirstOccurTime	yes	no	String	Time of first occurrence. Example: 1735041205
LastOccurTime	yes	no	String	Time of last occurrence. Example: 1735041205
Dimensions	yes	no	String	Dimension combination. JSON string. Example: ("unInstanceId":"ins-xxx")
Uniqueld	yes	no	String	Dimension combination md5. Example: eqeq-cda
AbnormalStatus	yes	no	String	Alarm status: "abnormal" indicates that the alarm has not been recovered, and "warning" indicates that the alarm has been recovered. Example: abnormal
InstanceId	yes	no	String	Object ID. Example: ins-0jvw9mo

DescribePolicyConditionListConfigManualPeriod

DescribePolicyConditionListConfigManualPeriod

Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
Default	yes	yes	Int64	Default period in seconds.



name	required	NULL allowed	type	description
				Example: 10
Keys	yes	yes	Array of Int64	Custom period in seconds. Example: 10
Need	yes	no	Bool	Whether required. Example: true

DescribeBaseMetricsDataPeriod

DescribeBaseMetricsDataPeriod

Referenced by the following interfaces: DescribeBaseMetricsForConsoleForEnd

name	required	NULL allowed	type	description
Period	yes	no	UInt64	Interval. Example: 60
StatType	yes	yes	Array of String	Statistical method. Example: ["avg"]

AttributeInfoInput

Attribute information.

Referenced by the following interfaces: CreateAttributes

name	required	NULL allowed	type	description
AttributeName	yes	no	String	Attribute name. Example: Testing
AttributeTypeId	no	no	UInt64	The type. Example: 1
Data Type	yes	no	Int64	Attribute data type. Example: 1
AttributeLevel	no	no	Int64	Attribute level. Example: 1
Unit	no	no	Int64	Attribute unit. Example: 1
StatisticalPeriod	no	no	Int64	Statistical period. Example: 60
OwnerId	no	no	Array of UInt64	Owner list ID. The sub_ain of the logged in user is used by default. Example: 1234
Description	no	no	String	Description. Example: Testing
AttributeUniqueName	yes	no	String	Unique name of the attribute. It consists of letters, digits, hyphens or underscores. Example: qwer_123

CgrpModuleNode

Group leaf node data structure.

Referenced by the following interfaces: CreateModule, DeleteModule, DescribeModule, ModifyModule

name	required	NULL allowed	type	description
AppId	no	yes	Int64	AppId Example: 1234
High	no	yes	Int64	Grouping tree height. Example: 1
Id	yes	no	Int64	Leaf group ID. Example: 1
L1Id	no	yes	Int64	Level-1 group ID. Example: 1
L1Name	no	yes	String	Level-1 group name. Example: Testing
L2Id	no	yes	Int64	Level-2 group ID. Example: 1
L2Name	no	yes	String	Level-2 group name. Example: Testing
L3Id	no	yes	Int64	Level-3 group ID. Example: 1
L3Name	no	yes	String	Level-3 group name. Example: Testing
Name	no	yes	String	Leaf group name. Example: Testing
OwnerBack	no	yes	String	Backup owner. Example: qwer123
OwnerMain	no	yes	String	Major owner. Example: qwer123
ParentId	yes	no	Int64	Parent group ID. Example: 1
SubIdIn	no	yes	String	SubIdIn Example: 123456
TypeId	yes	no	String	Type of the instance that is allowed to be added to the leaf group. Example: cvm_device
Uin	no	yes	String	Uin Example: 123456

DimensionsDesc

Dimension information

Referenced by the following interfaces: DescribeBaseMetrics

name	required	NULL allowed	type	description
Dimensions	yes	no	Array of String	Array of dimension names. Example: ["vm_uuid"]

GroupIdTag

1.0 policy ID, tag.

Referenced by the following interfaces: DescribeGroupIDByTags

name	required	NULL allowed	type	description
GroupIDList	yes	no	Array of String	1.0 policy ID. Example: ["123456"]
Key	yes	no	String	Tag key. Example: qwer
Value	yes	no	String	Tag value. Example: qwer

DescribeBindingPolicyObjectListInstance

Object instance information returned by the DescribeBindingPolicyObjectListInstance API.

Referenced by the following interfaces: DescribeBindingPolicyObjectList

name	required	NULL allowed	type	description
UniquelId	yes	no	String	Unique ID of the object. Example: eqeq-cda
Dimensions	yes	no	String	Dimension set of an object instance, which is a jsonObj string. Example: {"unInstanceId":"ins-xxx"}
IsShielded	yes	no	Int64	Whether the object is shielded. The value 0 indicates that the object is not shielded. The value 1 indicates that the object is shielded. Example: 1
Region	yes	no	String	Region where the object resides. Example: gr

Contact

Recipient information returned by the DescribeContactList API.

Referenced by the following interfaces: DescribeContactList

name	required	NULL allowed	type	description
Uid	yes	no	Int64	uid Example: 1
Uin	yes	no	String	uin Example: 123456
Name	yes	no	String	Recipient name. Example: Testing



name	required	NULL allowed	type	description
CanLogin	yes	no	Int64	Whether you can log in. 0: you can't log in. 1: you can log in. Example: 1
PhoneFlag	yes	no	Int64	Whether the mobile phone number is verified. Example: 1
PhoneNum	yes	no	String	The mobile phone. Example: 10
EmailFlag	yes	no	Int64	Whether the email is verified. Example: 1
Email	yes	no	String	Email Example: 123@com
IsReceiverOwner	yes	no	Int64	Whether it is the person in charge of receiving. Example: 123456
OwnerLid	yes	no	Int64	ownerId Example: 123456

CimMetricAnalysisBasicMetric

Basic metric parameters in CLM metric analysis.
Referenced by the following interfaces: DescribeMetricAnalysisData

name	required	NULL allowed	type	description
Operator	yes	no	String	Operator. Example: =
Name	yes	no	String	Metric name. Example: Testing

DescribePolicyConditionListMetric

Metric alarm configuration.
Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
ConfigManual	yes	yes	DescribePolicyConditionListConfigManual	Metric configuration Example: View
MetricId	yes	no	Int64	Metric ID. Example: 10
MetricShowName	yes	no	String	Metric name. Example: cvm_device
MetricUnit	yes	no	String	Metric unit. Example: %

CvmAgentStatus

Agent status returned by the DescribeCvmAgentStatus API.
Referenced by the following interfaces: DescribeCvmAgentStatus

name	required	NULL allowed	type	description
InstanceId	yes	no	String	Instance ID. Example: ins-00jv9mo
AgentInstalled	yes	no	Bool	Whether the agent is installed. Example: false

DescribeBindingPolicyObjectListDimension

Dimensions of the DescribeBindingPolicyObjectList API.
Referenced by the following interfaces: DescribeBindingPolicyObjectList

name	required	NULL allowed	type	description
RegionId	yes	no	Int64	Region ID. Example: 1
Region	yes	no	String	Region name abbreviation. Example: gr
Dimensions	yes	no	String	Combined JSON string of dimensions. Example: ("unInstanceId":"ins-xxx")
EventDimensions	yes	no	String	Combined JSON string of event dimensions. Example: ("unInstanceId":"ins-xxx")

CgrpInstanceGroupNode

Group array in which the instance is located.
Referenced by the following interfaces: CreateInstances, DeleteInstances, DescribeInstance

name	required	NULL allowed	type	description
Id	no	yes	Int64	The group ID. Example: 1
Name	no	yes	String	Group name. Example: test

AttributeUnitInfoOutputData

AttributeUnitInfoOutputData
Referenced by the following interfaces: DescribeAttributeUnits

name	required	NULL allowed	type	description
Data	yes	no	Array of AttributeUnitInfoOutput	Attribute unit data list. Example: View
TotalCount	yes	no	Int64	Number of attribute unit data lists. Example: 10

DescribeMonitorDataByAlarmIDDatapoint

DescribeMonitorDataByAlarmIDDatapoint
Referenced by the following interfaces: DescribeMonitorDataByAlarmID

name	required	NULL allowed	type	description
IsNull	yes	no	Bool	Whether it is empty. Example: true
Value	yes	no	Float	Value. Example: 10

ServerInfoData

ServerInfoData
Referenced by the following interfaces: DescribeServers

name	required	NULL allowed	type	description
Data	yes	no	Array of ServerInfo	Return data. Example: View
TotalCount	yes	no	Int64	Total number. Example: 10

ModifyConditionsTemplateRequestEventCondition

ModifyConditionsTemplateRequestEventCondition
Referenced by the following interfaces: CreateConditionsTemplate, ModifyConditionsTemplate

name	required	NULL allowed	type	description
AlarmNotifyPeriod	yes	no	String	Alarm notification cycle. Example: 5
AlarmNotifyType	yes	no	String	Alarm notification method. Example: sms
EventID	yes	no	String	Event ID. Example: 10
RuleID	no	no	Int64	Rule ID. Example: 10

DescribeAgentStatusHistoryData

DescribeAgentStatusHistoryData
Referenced by the following interfaces: DescribeAgentStatusHistory



name	required	NULL allowed	type	description
InstanceId	yes	no	String	Instance ID. Example: ins-0ijvdm0
Status	yes	no	Int64	CVM status. Example: 1
Histories	yes	no	Array of DescribeAgentStatusHistory	Historical data. Example: View

NoticeContentTplItem

Elements in the notification content template.

Referenced by the following interfaces: [CreateNoticeContentTpl](#), [DescribeNoticeContentTpl](#), [ModifyNoticeContentTpl](#)

name	required	NULL allowed	type	description
CustomCallback	no	no	Array of CustomCallbackTplMatcher	Custom notification channel configuration. Example: View

MetricConfig

Metric configuration.

Referenced by the following interfaces: [DescribeAlarmMetrics](#)

name	required	NULL allowed	type	description
Operator	yes	no	Array of String	Allowed operator. Example: =
Period	yes	no	Array of Int64	Allowed data cycle in seconds. Example: 5
ContinuePeriod	yes	no	Array of Int64	Allowed number of consecutive periods. Example: 5

PCLMDimension

Metric set dimension object for log monitoring.

Referenced by the following interfaces: [CLMDDescribeMetricSets](#)

name	required	NULL allowed	type	description
Field	yes	no	String	Field name. Example: timeField
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: qwer
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: qwer
MetricSetCID	no	no	String	Metric set CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx

TemplateGroup

Template list.

Referenced by the following interfaces: [DescribeConditionsTemplateList](#)

name	required	NULL allowed	type	description
Conditions	yes	yes	Array of Condition	Metric alarm rule. Example: View
EventConditions	yes	yes	Array of EventCondition	Event alarm rule. Example: View
PolicyGroups	yes	yes	Array of PolicyGroup	Associated alarm policy group. Example: View
GroupID	yes	no	Int64	Template-based policy group ID. Example: 1
GroupName	yes	no	String	Template-based policy group name. Example: test
InsertTime	yes	no	Int64	Creation time. Example: 11
LastEditUin	yes	no	Int64	UIN of the last user who modified it. Example: 1
Remark	yes	no	String	Description. Example: test
UpdateTime	yes	no	Int64	Update time. Example: 1
ViewName	yes	no	String	View. Example: cvm_device
IsJoinRule	yes	no	Int64	Whether the AND rule is used. Example: 1

NoticeContentTplBindPolicyCount

Number of alarm policies bound to the notification content template.

Referenced by the following interfaces: [DescribeNoticeContentTpl](#)

name	required	NULL allowed	type	description
NoticeContentTplID	no	no	String	Notification template ID. Example: tpl-xxx
BindCount	no	no	Int64	Number of bound alarm policies. Example: 1

MonitorSelectedDimension

Dimension selected.

Referenced by the following interfaces: [DescribeDashboardDimensionValues](#)

name	required	NULL allowed	type	description
DimensionName	no	no	String	Dimension name. Example: Testing
DimensionValue	no	no	String	The value of the dimension. Example: 100

CimMetricCustomItem

Compound metric configurations for the log monitoring metric set.

Referenced by the following interfaces: [CreateMetricSet](#), [DescribeMetricSet](#), [DescribeMetricSets](#), [ModifyMetricSet](#)

name	required	NULL allowed	type	description
Formula	yes	no	String	Expression. Example: ("cluster_name"=es-dnxxxxs')
Name	yes	no	String	Metric name. Example: Testing
Desc	yes	no	String	Metric description name. Example: Testing
Id	no	no	Int64	Item ID (only for output parameter; leave it empty for input parameter). Example: 1
MetricSetId	no	no	Int64	Metric set ID (only for output parameter; leave it empty for input parameter). Example: 12
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: eqeaddfqc
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: eqeaddfqc

ServiceInfo

Service info.

Referenced by the following interfaces: [CreateService](#), [DescribeService](#)

name	required	NULL allowed	type	description
ServiceId	yes	yes	Int64	Service ID. Example: 1
IsOpen	yes	yes	Int64	Whether to enable the service. Example: 1
ViewId	yes	yes	Int64	Default view ID. Example: 10

ModifyPolicyGroupEventCondition



Modification of the event alarm condition passed in by the alarm policy group.

Referenced by the following interfaces: ModifyPolicyGroup

name	required	NULL allowed	type	description
RuleId	no	no	Int64	Rule ID. No filling means new addition while filling in ruleId means to modify existing rules. Example: 12
EventId	yes	no	Int64	Event ID. Example: 12
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 1
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value u003c0 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime. Example: 5

DescribeProductEventListEvents

Events returned by the DescribeProductEventList API

Referenced by the following interfaces: DescribeProductEventList

name	required	NULL allowed	type	description
EventId	yes	yes	Int64	Event ID. Example: 111
EventCName	yes	yes	String	The name of an event. Example: Unreachable by ping
EventEName	yes	yes	String	English name of an event. Example: ping_unreachable
EventName	yes	yes	String	Abbreviated name of an event. Example: ping_unreachable
ProductCName	yes	yes	String	The name of the product. Example: cvm
ProductEName	yes	yes	String	The product name. Example: cvm
ProductName	yes	yes	String	Product Name Abbreviation Example: cvm
InstanceId	yes	yes	String	Instance ID. Example: ins-3xdt690
InstanceName	yes	yes	String	Instance name. Example: ins-3xdt690
ProjectId	yes	yes	String	Project ID. Example: 123
Region	yes	yes	String	Region. Example: gz
Status	yes	yes	String	State. Example: 1
SupportAlarm	yes	yes	Int64	Specifies whether to support alarm notifications. Example: 1
Type	yes	yes	String	Event type. Example: 21
StartTime	yes	yes	Int64	Start time. Example: 1611560738
UpdateTime	yes	yes	Int64	Update time. Example: 1611560790
Dimensions	yes	yes	Array of DescribeProductEventListEventsDimensions	Information about an instance object. Example: view
AdditionMsg	yes	yes	Array of DescribeProductEventListEventsDimensions	Additional information about an instance object. Example: view
IsAlarmConfig	yes	yes	Int64	Specifies whether to configure alarms. Example: 1
GroupInfo	yes	yes	Array of DescribeProductEventListEventsGroupInfo	Policy information Example: View

StrategyChannelInfo

StrategyChannelInfo

Referenced by the following interfaces: ModifyStrategyChannels

name	required	NULL allowed	type	description
StrategyId	yes	no	UInt64	The ID of the alarm policy. Example: 10
AlarmChannel	no	no	Array of String	Alarm channel list. Example: sms

TransLogItem

Changelog returned by DescribeTransLog

Referenced by the following interfaces: DescribeTransLog

name	required	NULL allowed	type	description
Id	yes	yes	Int64	Changelog ID. Example: 1
ModuleId	yes	yes	Int64	Module ID. Example: 1
LogData	yes	yes	String	Log information. JSON string. Example: qwer
CreateTime	yes	yes	Int64	Creation time. Example: 1735179378
LastEditUin	yes	yes	String	UIN of the last user who modified it. Example: 123456

CimAlertFilterRule

Expired.

Referenced by the following interfaces: CreateAlertPolicy, DescribeAlertPolicies, DescribeAlertPolicy, ModifyAlertPolicy

name	required	NULL allowed	type	description
AlertPolicyId	yes	yes	Int64	Associated alarm policy ID. Example: 1234
Key	yes	yes	String	Filtered keywords. Example: qwer
Operating	yes	yes	String	Operator. Example: =
Value	yes	yes	String	Filter value (multiple values are separated by commas). Example: 1234
Id	no	yes	Int64	Filter condition ID. Example: 1
CreatedAt	no	yes	String	Creation time. Example: eqeafdfgc
UpdatedAt	no	yes	String	Update time. Example: eqeafdfgc

DescribeAccidentConfigAccidentTypeInfo

Event type of the DescribeAccidentConfig API

Referenced by the following interfaces: DescribeAccidentConfig

name	required	NULL allowed	type	description
AccidentId	yes	no	Int64	Platform event ID. Example: 1
AccidentName	yes	no	String	Platform event name. Example: qwer
AccidentEnName	yes	no	String	Platform event name in English. Example: qwer

AttributeValueInfoOutput

AttributeValueInfoOutput

Referenced by the following interfaces: DescribeServerData, DescribeViewData

name	required	NULL allowed	type	description
Values	yes	no	Array of AttributeTimestampValueOutput	Attribute value list. Example: view
StartTime	yes	no	String	Start time. Example: 1734950008



name	required	NULL allowed	type	description
EndTime	yes	no	String	End time. Example: 1734953808
StartPosition	yes	no	Int64	Start position. Example: 1
EndPosition	yes	no	Int64	End position. Example: 1

ReceiverInfo

Recipient information.

Referenced by the following interfaces: ModifyAlarmReceivers

name	required	NULL allowed	type	description
Id	no	no	Int64	The ID. Example: 1234
StartTime	yes	no	Int64	Alarm period start time. Range: [0,86400]. Remove the date after converting the time from UNIX timestamp to UTC+8 time. For example, 7200 means "10:00". Example: 1734953308
EndTime	yes	no	Int64	End time of the alarm period. The meaning is the same as that of StartTime. Example: 1734953308
NotifyWay	yes	no	Array of String	Alarm notification method. Valid values: "SMS", "SITE", "EMAIL", "CALL", and "WECHAT". Example: sms
SendFor	no	no	Array of String	Alarm call notification time. Valid values: OCCUR (indicating that a notice is sent when the alarm is triggered) and RECOVER (indicating that a notice is sent when the alarm is recovered). Example: qwer
UidList	no	no	Array of Int64	UID of the alarm call recipient. Example: 1234
RoundNumber	no	no	Int64	Number of alarm call rounds. Example: 1
PersonInterval	no	no	Int64	Alarm call intervals for individuals in seconds. Example: 1
RoundInterval	no	no	Int64	Intervals of alarm call rounds in seconds. Example: 1
RecoverNotify	no	no	Array of String	Notification method when an alarm is recovered. Valid value: SMS. Example: sms
NeedSendNotice	no	no	Int64	Whether to send an alarm call delivery notice. The value 0 indicates that no notice needs to be sent. The value 1 indicates that a notice needs to be sent. Example: 1
ReceiverType	yes	no	Array of String	Recipient type. Valid values: user, group. Example: group
ReceiverGroupList	no	no	Array of Int64	Recipient group list. The list of recipient group IDs that is queried by API. Example: [1234]
ReceiverUserList	no	no	Array of Int64	Recipient list. The list of recipient IDs that is queried by API. Example: [1234]

URLNotice

Cloud Monitor alarm notification template - callback notification details

Referenced by the following interfaces: CreateAlarmNotice, DescribeAlarmNotice, DescribeAlarmNoticeCallbacks, DescribeAlarmNotifies, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmNotice

name	required	NULL allowed	type	description
URL	yes	yes	String	Callback URL, which can contain up to 256 characters. Example: http://www.123.com
IsValid	no	yes	Int64	Whether verification is passed. Valid values: 0 (no), 1 (yes). Example: 1
ValidationCode	no	yes	String	Verification code. Example: 82h8t

StrategyStatesInfo

StrategyStatesInfo

Referenced by the following interfaces: ModifyStrategyStates

name	required	NULL allowed	type	description
StrategyId	yes	no	Int64	The ID of the alarm policy. Example: 1
IsStart	yes	no	Int64	Enablement status. Default value: 1. 0: stopping. 1: starting. Example: 1

MetricData

DescribeMetricData output parameters

Referenced by the following interfaces: DescribeDataForMiniProgram, DescribeStatisticData

name	required	NULL allowed	type	description
MetricName	yes	no	String	None. Example: CpuUsage
Points	yes	no	String	None. Example: qwer

AlarmPolicyRule

Alarm policy trigger condition (shared by metrics and events and example values are separated by /).

Referenced by the following interfaces: CreateAlarmPolicy, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmPolicyCondition

name	required	NULL allowed	type	description
MetricName	no	no	String	Metric name. Example: CpuUsage/disk_readonly
AggregationDimensions	no	yes	Array of String	Aggregation dimension list (not passed for events). Example: ["sum"]
Period	no	no	Int64	Seconds. Statistical period (not passed for events). Example: 60
AggregateType	no	no	String	Data aggregation type. Multiple metrics may be involved due to compound conditions. Metrics are indicated in JSON format, such as ("report_metric_gauge":"last") (not passed for events). Example: last
Operator	no	no	String	English operators Intelligent = No intelligent detection for the threshold eq = Equal to ge = Greater than or equal to gt = Greater than le = Less than or equal to lt = Less than ne = Not equal to day_increase = Day-on-day growth day_decrease = Day-on-day decline day_wave = Day-on-day fluctuation week_increase = Week-on-week growth week_decrease = Week-on-week decline week_wave = Week-on-week fluctuation cycle_increase = Month-on-month growth cycle_decrease = Month-on-month decline cycle_wave = Month-on-month fluctuation re = Regular expression matching (not passed for events) Example: gt
Value	no	no	String	Threshold (not passed for events). Example: 100
ContinuePeriod	no	no	Int64	Number of cycles. Continuous notification cycle. 1 = last for 1 cycle; 2 = last for 2 cycles... (not passed for events). Example: 1
NoticeFrequency	no	no	Int64	Seconds. Alarm interval: 0 = non-repeating; 300 = every 5 minutes; 600 = every 10 minutes; 900 = every 15 minutes; 1800 = every 30 minutes; 3600 = every 1 hour; 7200 = every 2 hours; 10800 = every 3 hours; 21600 = every 6 hours; 43200 = every 12 hours; 86400 = every day (not passed for events). Example: 300
IsPowerNotice	no	no	Int64	Whether the alarm frequency increases exponentially. 0 = no; 1 = yes (not passed for events). Example: 0
Filter	no	yes	AlarmPolicyFilter	Filter condition for a single trigger rule (not passed for events). Example: view
Description	no	no	String	Metric display name, which is used in the output parameter. Example: CPU utilization/read-only disks
Unit	no	no	String	Unit, which is used for output parameters (not passed for events). Example: %
RuleType	no	no	String	Trigger condition type. STATIC = static threshold; DYNAMIC = dynamic threshold (not passed for events). Example: STATIC
ValueMax	no	yes	String	ValueMax (not passed for events). Example: 0
ValueMin	no	yes	String	ValueMin (not passed for events). Example: 0

MonitorTypeInfo

Detailed information of Monitoring Type

Referenced by the following interfaces: DescribeMonitorTypes



name	required	NULL allowed	type	description
Id	yes	no	String	Monitoring Type ID Example: 19023
Name	yes	no	String	Monitoring type. Example: MT_QCE
SortId	yes	no	Int64	Arrangement Order Example: 1

DescribePolicySituationAlarmSituation

DescribePolicySituationAlarmSituation

Referenced by the following interfaces: DescribePolicySituation

name	required	NULL allowed	type	description
AlarmRuleCount	yes	no	Int64	Number of alarm rules. Example: 10
AlarmTouchCount	yes	no	Int64	Number of alarm deliveries. Example: 10

CCMInstanceAttributeDataOutput

CCMInstanceAttributeDataOutput

Referenced by the following interfaces: DescribeCCMInstanceDatas

name	required	NULL allowed	type	description
AttributeId	yes	no	UInt64	Metric ID. Example: 1
ServerId	yes	no	UInt64	Server ID. Example: 1
Values	yes	no	Array of AttributeTimestampValueOutput	Metric report data. Example: View
InstanceName	yes	no	String	Instance name. Example: ins-qwer

PCLMLogProfileItem

Log monitoring metric set - log data structure description.

Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
MetricSetCID	no	no	String	Associated metric set CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx
Field	yes	no	String	Field name. Example: timeField
Type	yes	no	String	Field type. Valid values: string, long, double. Example: string
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: qwer
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: qwer

PCLMMetricSet

Log monitoring metric set.

Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
LogsetId	yes	yes	String	CLS logset ID. Example: d5f10b84-dcf8-4e58-bab0-16ef56761d22
LogsetName	yes	yes	String	CLS log set name. Example: Testing
LogtopicId	yes	yes	String	CLS log topic ID. Example: d4253323-7dfc-4b1b-8889-d83cef77375a
LogtopicName	yes	yes	String	CLS log topic name. Example: Testing
Name	yes	yes	String	Metric set name. Example: Testing
StatisticCycle	yes	yes	Int64	Statistical period. Valid values: 60, 300. Example: 1
TimeField	yes	yes	String	Time field. Example: 1314141
LogFilterRules	yes	yes	Array of PCLMLogFilterRule	Log filtering rule. Example: View
MetricBasicItems	yes	yes	Array of PCLMMetricBasicItem	Basic metric rule. Example: View
MetricCustomItems	yes	yes	Array of PCLMMetricCustomItem	Compound metric rule. Example: View
Dimensions	yes	yes	Array of PCLMDimension	Dimension rule. Example: View
CID	no	yes	String	CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx
CreatedAt	no	yes	String	Creation time (only for output parameter; leave it empty for input parameter) Example: qwer
UpdatedAt	no	yes	String	Update time (only for output parameter; leave it empty for input parameter) Example: qwer
AppId	no	yes	Int64	App ID (only for output parameter; leave it empty for input parameter). Example: 1234
Uin	no	yes	String	UIN (only for output parameter; leave it empty for input parameter). Example: 123456
Region	no	yes	String	Region (only for output parameter; leave it empty for input parameter). Example: gz
LogProfileItems	yes	yes	Array of PCLMLogProfileItem	Log data structure description. Example: View
SubAccountUin	no	yes	String	SubAccountUin (only for output parameter; leave it empty for input parameter). Example: 123456

CgrpInstance

Creates a new instance ID.

Referenced by the following interfaces: CreateInstances, DeleteInstances

name	required	NULL allowed	type	description
InstanceId	yes	no	String	Instance ID. Example: ins-0Qjvrlmo
InstanceName	no	no	String	Instance name. Example: test
TypeId	no	no	String	Type Example: cvm_device
Region	no	no	String	Region. Example: gz
ModuleId	yes	no	Int64	Leaf group node. Example: 1

CommonNamespace

Unified namespace information

Referenced by the following interfaces: DescribeAllNamespaces

name	required	NULL allowed	type	description
Id	yes	no	String	Namespace identifier. Example: performance_metric
Name	yes	no	String	The name of the namespace. Example: Performance metrics
Value	yes	no	String	Namespace value. Example: qwer
ProductName	yes	no	String	Product name. Example: cvm_device
Config	yes	no	String	Configuration information. Example: qwer
AvailableRegions	yes	no	Array of String	List of supported regions. Example: ["bj","bjr"]



name	required	NULL allowed	type	description
SortId	yes	no	Int64	Sort ID Example: 251
DashboardId	yes	no	String	Unique identifier in Dashboard Example: elpv6

DescribeProductEventListDimensions

Input parameter Dimensions of the DescribeProductEventList API

Referenced by the following interfaces: DescribeProductEventList

name	required	NULL allowed	type	description
Name	yes	no	String	Dimension name. Example: Testing
Value	yes	no	String	The value of the dimension. Example: XXXX

PCLMStatisticFilterRule

Metric filter condition in log monitoring metric set configurations.

Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
MetricItemId	no	yes	Int64	Associated metric item ID (only for output parameter; leave it empty for input parameter). Example: 1
CreatedAt	no	yes	String	Creation time (only for output parameter; leave it empty for input parameter). Example: qwer
UpdatedAt	no	yes	String	Update time (only for output parameter; leave it empty for input parameter). Example: qwer
Relation	yes	no	Int64	Relationship: 1: AND; 2: OR. Example: 1
Field	yes	no	String	Field name. Example: timeField
Operator	yes	no	String	Filter operator: Numeric fields support: gt lt ge le eq ne in. Character fields support: eq ne in contains. Example: =
Value	yes	no	String	Filter operation value. Example: 10

CimStatisticFilterRule

Metric filter condition in log monitoring metric set configurations.

Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
Id	no	no	Int64	Item ID (only for output parameter; leave it empty for input parameter). Example: 1
MetricItemId	no	no	Int64	Associated metric item ID (only for output parameter; leave it empty for input parameter). Example: 1
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: eqeadtfg
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: eqeadtfg
Relation	yes	no	Int64	Relationship: 1: AND; 2: OR. Example: 12
Field	yes	no	String	Field name. Example: timeField
Operator	yes	no	String	Filter operator: Numeric fields support: gt lt ge le eq ne in. Character fields support: eq ne in contains. Example: =
Value	no	no	String	Filter operation value. Example: 50

AlarmPolicyTriggerTask

Task triggered by alarm policy

Referenced by the following interfaces: CreateAlarmPolicy, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmPolicyTasks

name	required	NULL allowed	type	description
Type	yes	no	String	Triggered task type. Valid value: AS (auto scaling). Example: AS
TaskConfig	yes	no	String	Configuration information in JSON format, such as { "Key1":"Value1","Key2":"Value2"}. Example: { "Key1":"Value1","Key2":"Value2"}

DescribeAppFlowConverterResponseDataPoint

DescribeAppFlowConverterResponseDataPoint

Referenced by the following interfaces: DescribeAppFlow

name	required	NULL allowed	type	description
Value	yes	yes	Float	Value. Example: 100

UserNotice

Cloud Monitor alarm notification template - user notification details

Referenced by the following interfaces: CreateAlarmNotice, DescribeAlarmNotice, DescribeAlarmNotices, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmNotice

name	required	NULL allowed	type	description
ReceiverType	yes	no	String	Recipient type. Valid values: USER (user), GROUP (user group). Example: USER
UserIds	no	yes	Array of Int64	User uid list. Example: [100001,100002]
GroupIds	no	yes	Array of Int64	User group ID list. Example: [10001,10002]
StartTime	yes	no	Int64	Number of seconds since notification start time 00:00:00 (Value range: 0-86399). Example: 0
EndTime	yes	no	Int64	Number of seconds since notification end time 00:00:00 (Value range: 0-86399). Example: 86399
NoticeWay	yes	no	Array of String	Notification channel list. Valid values: EMAIL (email), SMS (SMS), CALL (phone), WECHAT (WeChat). Example: ["SMS", "CALL"]
PhoneOrder	no	yes	Array of Int64	Phone polling list. Example: [100001,100002]
PhoneCircleTimes	no	no	Int64	Number of phone pollings. Value range: 1-5. Example: 1
PhoneInOneInterval	no	no	Int64	Call interval in seconds within one polling. Value range: 60-900. Example: 60
PhoneCircleInterval	no	no	Int64	Polling interval in seconds. Value range: 60-900. Example: 60
NeedPhoneArriveNotice	no	no	Int64	Whether receipt notification is required. Valid values: 0 (no), 1 (yes). Example: 1

DescribePolicyGroupInfoCallback

User callback information output by the policy query

Referenced by the following interfaces: DescribePolicyGroupInfo

name	required	NULL allowed	type	description
CallbackUrl	yes	no	String	URL of the user callback API. Example: http://test.com
ValidFlag	yes	no	Int64	Status of the user callback API. The value 0 indicates that the API is not verified. The value 1 indicates that the API is verified. The value 2 indicates that a URL exists but the API fails to be verified. Example: 1
VerifyCode	yes	no	String	Verification code of the user callback API. Example: 12345

PCLMMetricBasicItem

Basic metric configurations for the log monitoring metric set.

Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
Field	yes	yes	String	Field name. Example: timeField



name	required	NULL allowed	type	description
Operator	yes	yes	String	Metric statistics method: sum, count, min, max. Example: +
Name	yes	yes	String	Metric name. Example: Testing
Desc	yes	yes	String	Metric description name. Example: Testing
StatisticFilterRules	no	yes	Array of PCLMStatisticFilterRule	Metric filtering rule. Example: View
MetricSetCID	no	yes	String	Metric set CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx
CreatedAt	no	yes	String	Creation time (only for output parameter; leave it empty for input parameter) Example: qwer
UpdatedAt	no	yes	String	Update time (only for output parameter; leave it empty for input parameter) Example: qwer

DescribePolicyQuotaV3ResponseDataQuota

DescribePolicyQuotaV3ResponseDataQuota

Referenced by the following interfaces: DescribePolicyQuota

name	required	NULL allowed	type	description
Used	yes	no	Int64	User. Example: 10
Total	yes	no	Int64	Total number. Example: 10

AttributeIdOutput

AttributeIdOutput

Referenced by the following interfaces: ModifyAttribute

name	required	NULL allowed	type	description
AttributeId	yes	yes	UInt64	Attribute ID. Example: 10

DescribeBaseMetricsDataMeaning

DescribeBaseMetricsDataMeaning

Referenced by the following interfaces: DescribeBaseMetricsForConsoleFontEnd

name	required	NULL allowed	type	description
Language	yes	no	String	Language. Example: zh
Meaning	yes	no	String	Meaning. Example: qwer

CimMetricAnalysisCustomMetric

Compound metric parameters in CLM metric analysis.

Referenced by the following interfaces: DescribeMetricAnalysisData

name	required	NULL allowed	type	description
Name	no	no	String	Compound metric name. Example: Testing
Formula	yes	no	String	Operation expression. Example: ("cluster_name"="es-dnsssss")

AttributeValueInfoOutputData

AttributeValueInfoOutputData

Referenced by the following interfaces: DescribeServerData, DescribeViewData

name	required	NULL allowed	type	description
Data	yes	no	Array of AttributeValueInfoOutput	Attribute report data list. Example: View
TotalCount	yes	no	Int64	Number of attribute data lists. Example: 10

CimDescribeAlertPoliciesData

CLM alarm policy list return structure.

Referenced by the following interfaces: DescribeAlertPolicies

name	required	NULL allowed	type	description
TotalCount	yes	yes	Int64	Total number. Example: 10
AlertPolicies	yes	yes	Array of CimAlertPolicy	List element. Example: View

Dimension

Combination of instance object dimensions

Referenced by the following interfaces: DescribeDashboardMetricData, DescribePolicyGroupCount, GetMonitorData, GetTheData

name	required	NULL allowed	type	description
Name	yes	no	String	Instance dimension name. Example: InstanceId
Value	yes	no	String	Instance dimension value. Example: ins-c282wnl0

Condition

Alarm condition

Referenced by the following interfaces: DescribeConditionsTemplateList, DescribePolicyInfoByInstance, DescribeRecommendedTemplate

name	required	NULL allowed	type	description
AlarmNotifyPeriod	yes	no	Int64	Alarm notification frequency. Example: 7200
AlarmNotifyType	yes	no	Int64	Predefined repeated notification policy. 0: One-time alarm; 1: exponential alarm; 2: consecutive alarm. Example: 0
CalcType	yes	yes	String	Test method. Example: "1"
CalcValue	yes	yes	String	Test value. Example: "95"
ContinueTime	yes	yes	String	Duration. Example: "1800"
MetricID	yes	no	Int64	Metric ID. Example: 33
MetricDisplayName	yes	no	String	Displayed metric name. Example: "CPU utilization"
Period	yes	no	Int64	Interval. Example: 60
RuleID	yes	no	Int64	Rule ID. Example: 623123
Unit	yes	no	String	Metric unit. Example: "%"

CreatePolicyGroupCondition

Alarm threshold condition passed in when a policy is created.

Referenced by the following interfaces: CreatePolicyGroup

name	required	NULL allowed	type	description
MetricId	yes	no	Int64	Metric ID. Example: 1234
CalcType	no	no	Int64	Comparative type. The value 1 indicates greater than. The value 2 indicates greater than or equal to. The value 3 indicates smaller than. The value 4 indicates smaller than or equal to. The value 5 indicates equal to. The value 6 indicates not equal to. This parameter is optional if a default comparative type is configured for the metric. Example: 1
CalcValue	no	no	Float	Comparative value. This parameter is optional if the metric has no requirement. Example: 1.13
CalcPeriod	no	no	Int64	Data aggregation period in seconds. This parameter is optional if the metric has a default value. Example: 1



name	required	NULL allowed	type	description
ContinuePeriod	no	no	Int64	Number of consecutive periods after which an alarm will be triggered. Example: 5
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 0
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value u003c0 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime.
RuleId	no	no	Int64	If a metric is created based on a template, the RuleId of the metric in the template must be passed in. Example: 1

DescribeMsgPolicyListVoiceConfig

DescribeMsgPolicyListVoiceConfig
Referenced by the following interfaces: DescribeMsgPolicyInfo, DescribeMsgPolicyList

name	required	NULL allowed	type	description
RoundNumber	yes	no	Int64	Number of calls. Example: 10
UIDList	yes	yes	Array of Int64	URN list. Example: 10
RoundInterval	yes	no	Int64	Interval between each round. Example: 10
PersonInterval	yes	no	Int64	Interval. Example: 10
NeedSendNotice	yes	no	Int64	Whether to send a reminder. Example: 10

CimAnalysisFilter

Filter condition in CLM multidimensional analysis.
Referenced by the following interfaces: DescribeDimensionAnalysisData, DescribeMetricAnalysisData

name	required	NULL allowed	type	description
Field	yes	no	String	Field name. Example: timeField
Operator	yes	no	String	Operator. Only = is supported (when the value array contains multiple values, it is an "in" relationship). Example: =
Value	yes	no	Array of String	Value. Example: 50

TemplateTag

Output parameter of DescribeTemplateTags: list of tags for template variables.
Referenced by the following interfaces: DescribeTemplateTags

name	required	NULL allowed	type	description
Tag	yes	no	String	Tag name. Example: qwer
TagType	yes	no	String	Tag type. Example: qwer
ProductId	yes	no	String	Associated product ID (basic monitoring). Example: qwer

AttributeTimestampValueOutput

AttributeTimestampValueOutput
Referenced by the following interfaces: DescribeAttributeAggregateData, DescribeCMIInstanceData, DescribeServerData, DescribeServerData, DescribeViewData

name	required	NULL allowed	type	description
Timestamp	yes	no	Int64	Timestamp. Example: 1735041205
Value	yes	yes	Int64	Attribute value. Example: 10

DashboardDataSource

Dashboard2.0 data source information.
Referenced by the following interfaces: DescribeDashboardDataSources

name	required	NULL allowed	type	description
UUID	yes	no	String	Data source unique identifier. Example: u78haeoysq8w8wr
Name	yes	no	String	Data source name. Example: Testing
Type	yes	no	String	Data source type, such as MySQL, Prometheus. Example: MySQL
TypeLogoUrl	yes	yes	String	Data source icon. Example: http://test.com
Access	yes	yes	String	Access mode. Example: mode
Url	yes	yes	String	Data source access address. Example: http://test.com
Password	yes	no	String	Password. It can be an empty string. Example: 123456
User	yes	no	String	Username. It can be an empty string. Example: qwer
Database	yes	no	String	Database. Example: mysql
BasicAuth	yes	no	Bool	It is "false" by default. Example: false
IsDefault	yes	no	Bool	Whether it is the default data source. Example: false
JsonData	yes	yes	String	Additional information of the storage data source, such as ES link information {"eversion": 5, "logLevelField": "", "logMessageField": "", "maxConcurrentShardRequests": 256, "timeField": "@timestamp"}.
ReadOnly	yes	no	Bool	Whether the data source data is read-only. Example: false

ModifyNotifyBatchNotifyInfo

Alarm notification method of the ModifyNotifyBatch API.
Referenced by the following interfaces: ModifyNotifyBatch

name	required	NULL allowed	type	description
GroupId	yes	no	Int64	Policy group ID. Example: 1234
NotifyWay	yes	no	Array of String	List of alarm methods. Example: sms

NoticeContentTplBindInfo

Information on binding of the notification template and content template.
Referenced by the following interfaces: DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmPolicyNotice

name	required	NULL allowed	type	description
ContentTplID	no	no	String	Content template ID. Example: tmpl-xxx
NoticeID	no	no	String	Notification template ID. Example: notice-xxx

AttributeInfoOutput

Attribute information.
Referenced by the following interfaces: DescribeAttributes, DescribeCMGroupViewAttribute

name	required	NULL allowed	type	description
AttributeId	yes	no	UInt64	Attribute ID. Example: 1
AttributeName	yes	no	String	Attribute name. Example: Testing
AttributeLevel	yes	no	Int64	Attribute level. Example: 1



name	required	NULL allowed	type	description
Description	yes	no	String	Description. Example: test
AttributeType	yes	yes	String	The type. Example: cpu_usage
DataType	yes	no	Int64	Attribute data type. Example: 1
CreateTime	yes	no	String	Creation time. Example: 1735041205
OwnerName	yes	no	String	Attribute owner. Example: test
UnitId	yes	no	Int64	Unit ID. Example: 1
UnitName	yes	no	String	The unit. Example: test
StatisticalPeriod	yes	no	Int64	Statistical period. Example: 60
AttributeUniqueName	yes	no	String	Unique string of the attribute. It consists of letters, digits, hyphens or underscores. Example: qwer_123

IdcInfoData

IdcInfoData

Referenced by the following interfaces: DescribeIdcServerCount

name	required	NULL allowed	type	description
Data	yes	no	Array of IdcInfo	Return data. Example: View
TotalCount	yes	no	Int64	Total number. Example: 10

DescribePolicyGroupListGroup

DescribePolicyGroupListGroup

Referenced by the following interfaces: DescribePolicyGroupList

name	required	NULL allowed	type	description
GroupId	yes	no	Int64	Policy group ID. Example: 1234
GroupName	yes	no	String	Policy group name. Example: test
IsOpen	yes	no	Bool	Indicates whether self-healing notifications are enabled. Example: true
ViewName	yes	no	String	Policy view name. Example: cvm_device
LastEditLin	yes	no	String	URL of the last editor. Example: 123456
UpdateTime	yes	no	Int64	Last modification time. Example: 12314155251
InsertTime	yes	no	Int64	Creation time. Example: 12314155251
UseSum	yes	no	Int64	Number of instances bound to the policy group. Example: 10
NotShieldedSum	yes	no	Int64	Number of unshielded instances that are bound to the policy group. Example: 10
IsDefault	yes	no	Int64	Whether it is a default policy: 0: non-default policy; 1: default policy. Example: 1
CanSetDefault	yes	no	Bool	Whether it can be set as the default policy. Example: true
ParentGroupId	yes	no	Int64	Parent policy group ID. Example: 1234
Remark	yes	no	String	Remarks of the policy group. Example: test
ProjectId	yes	no	Int64	ID of the project to which the policy group belongs. Example: 0
Conditions	yes	yes	Array of DescribePolicyGroupInfoCondition	Threshold rules list. Example: View
EventConditions	yes	yes	Array of DescribePolicyGroupInfoEventCondition	List of product event rules. Example: View
ReceiverInfos	yes	yes	Array of DescribePolicyGroupInfoReceiverInfo	User recipient list. Example: View
ConditionsTemp	yes	yes	DescribePolicyGroupInfoConditionTpl	Template-based policy group. Example: View
InstanceGroup	yes	yes	DescribePolicyGroupListGroupInstanceGroup	Instance group that is bound to the policy group. Example: View
IsUnionRule	yes	yes	Int64	The 'AND' or 'OR' rule. The value 0 indicates the 'OR' rule (indicating that an alarm will be triggered if any rule meets the threshold condition). The value 1 indicates the 'AND' rule (indicating that an alarm will be triggered when all rules meet the threshold conditions). Example: 1

PolicyGroup

Policy group information

Referenced by the following interfaces: DescribeConditionsTemplateList

name	required	NULL allowed	type	description
CanSetDefault	yes	no	Bool	Whether the policy can be set as the default policy. Example: false
GroupId	yes	no	Int64	Alarm policy group ID. Example: 1234
GroupName	yes	no	String	Alarm policy group name. Example: testing
InsertTime	yes	no	Int64	Creation time. Example: 1735179378
IsDefault	yes	no	Int64	Whether it is a default alarm policy. Example: 1
Enable	yes	no	Bool	Enablement status of the alarm policy. Example: false
LastEditLin	yes	no	Int64	URL of the last user who modified it. Example: 123456
NotShieldedInstanceCount	yes	no	Int64	Number of unshielded instances. Example: 10
ParentGroupID	yes	no	Int64	Parent policy group ID. Example: 1234
ProjectID	yes	no	Int64	Project ID. Example: 1
ReceiverInfos	yes	yes	Array of PolicyGroupReceiverInfo	Information about the alarm recipient. Example: View
Remark	yes	no	String	Remarks. Example: testing
UpdateTime	yes	no	Int64	Modification time. Example: 1735179378
TotalInstanceCount	yes	no	Int64	Total number of bound instances. Example: 10
ViewName	yes	no	String	View. Example: cvm_device
IsUnionRule	yes	no	Int64	Whether the AND rule is used. Example: 1

CimMetricSet

Log monitoring metric set.

Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
LogsetId	yes	no	String	CLS logset ID. Example: d3f2fb84-dcf8-4c58-bab0-16ef567cd122
LogsetName	yes	no	String	CLS log set name. Example: testing
LogtopicId	yes	no	String	CLS log topic ID. Example: d4253323-7dfc-4b1b-8889-d82cef77375a
LogtopicName	yes	no	String	CLS log topic name. Example: Testing



name	required	NULL allowed	type	description
Name	yes	no	String	Metric set name. Example: Testing
StatisticCycle	yes	no	Int64	Statistical period. Valid values: 60, 300. Example: 1
TimeField	yes	no	String	Time field. Example: 3131411
LogFilterRules	yes	yes	Array of CmLogFilterRule	Log filtering rule. Example: View
MetricBasicItems	yes	yes	Array of CmMetricBasicItem	Basic metric rule. Example: View
MetricCustomItems	yes	yes	Array of CmMetricCustomItem	Compound metric rule. Example: View
Dimensions	yes	yes	Array of CmDimension	Dimension rule. Example: View
Id	no	no	Int64	Item ID (only for output parameter; leave it empty for input parameter) Example: 1
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter) Example: eqeadiqe
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter) Example: eqeadiqe
AppId	no	no	Int64	App ID (only for output parameter; leave it empty for input parameter). Example: 1234
Uin	no	no	String	UIN (only for output parameter; leave it empty for input parameter). Example: 123456
Region	no	no	String	Region (only for output parameter; leave it empty for input parameter). Example: gz
LogProfileItems	yes	yes	Array of CmLogProfileItem	Log data structure description. Example: View

DashboardMetricData

Reported data returned by Dashboard2.0 query metrics.

Referenced by the following interfaces: DescribeDashboardMetricData

name	required	NULL allowed	type	description
MetricName	yes	no	String	Metric name. Example: CpuUsage
Aggregate	yes	no	String	The aggregation method. Example: avg
GroupBy	yes	no	Array of Dimension	Query condition array. Example: View
Timestamps	yes	no	Array of UInt64	Returns the Timestamp array. Example: [1604303550]
Value	yes	no	String	Metric report data. JSON serialized strings are returned in array form. Example: [1.0,8]
StartTime	yes	no	Datetime_iso	Returns the start time of the query period in ISO format, such as: 2018-04-10T10:15:58.858Z. Example: 2018-11-29T12:30:11+08:00
EndTime	yes	no	Datetime_iso	Returns the start time of the query period in ISO format, such as: 2018-04-10T10:15:58.858Z. Example: 2019-03-24T20:50:00+08:00
Period	yes	no	Int64	Statistical period in seconds. Example: 60
Conditions	yes	no	Array of DashboardMetricCondition	Filter condition. Example: View
Namespace	yes	no	String	Namespace. Example: QCE/CVM
Error	yes	no	String	Error message. Example: error
Code	yes	no	String	Error code. Example: 11001
Serialized	yes	no	String	Query flag Example: 1a6deff1-7991-4d82-ab1c-44b66e1c1386
ConfigId	yes	yes	String	Product configuration ID. Example: qwer
Dimensions	yes	no	Array of Dimension	Dimension combination of an instance. Example: View
OrderTag	yes	yes	float	Field for sorting. Example: 1234
Type	no	yes	String	Type Example: qwer

MetricObjectMeaning

Meaning of metric data

Referenced by the following interfaces: DescribeBaseMetrics

name	required	NULL allowed	type	description
En	yes	no	String	Meaning of metric data (English). Example: qwer
Zh	yes	no	String	Meaning of metric data. Example: qwer

PCLMMetricAnalysisData

CLM metric analysis data structure.

Referenced by the following interfaces: DescribeMetricAnalysisData

name	required	NULL allowed	type	description
Compare	yes	yes	Array of PCLMMetricAnalysisPoint	Comparison data. Example: View
Current	yes	yes	Array of PCLMMetricAnalysisPoint	Current data. Example: View
Granularity	yes	yes	Int64	Time granularity (seconds). Example: 1

AlarmHistory

Alarm record data

Referenced by the following interfaces: DescribeAlarmHistories, DescribeMiniDashboardAlarmInfo

name	required	NULL allowed	type	description
AlarmId	yes	no	String	Alarm history ID. Example: 01e193f3b4ec-43db-8f60-6f7e163eca5
MonitorType	yes	no	String	Monitoring type. Example: MT_QCE
Namespace	yes	no	String	Policy type Example: cvm_device
AlarmObject	yes	no	String	Alarm object. Example: its-abcdef
Content	yes	no	String	The alarm content. Example: CPU utilisation > 80%
FirstOccurTime	yes	no	Int64	Timestamp of the first occurrence time. Example: 1611700000
LastOccurTime	yes	no	Int64	Timestamp of the final occurrence time. Example: 1611794567
AlarmStatus	yes	no	String	Alarm status. ALARM=not recovered. OK=recovered. NO_CONF=expired. NO_DATA=insufficient data. Example: ALARM
PolicyId	yes	no	String	Alarm policy ID. Example: policy-abcdef
PolicyName	yes	no	String	Policy name. Example: CVM alarm policy
VPC	yes	no	String	VPC of the alarm object for the basic product alarm. Example: 0
ProjectId	yes	no	Int64	Project ID. Example: 0
ProjectName	yes	no	String	Project name. Example: Default project
InstanceGroup	yes	yes	Array of InstanceGroups	Instance group of alarm object Example: View
ReceiverUids	yes	no	Array of Int64	Recipient list. Example: [1234]



name	required	NULL allowed	type	description
ReceiverGroups	yes	no	Array of Int64	Recipient group list. Example: [1234]
NoticeWays	yes	no	Array of String	Alarm channel list. Valid values: SMS (SMS), EMAIL (email), CALL (phone), WECHAT (WeChat). Example: ["SMS"]
OriginId	yes	no	String	Compatibility alarm v1.0 policy group ID. Example: 12345
AlarmType	yes	no	String	Alarm type. Example: METRIC
EventId	yes	no	Int64	Event ID. Example: 0
Region	yes	no	String	Region. Example: region1
PolicyExists	yes	no	Int64	Whether the policy exists. 0: no. 1: yes. Example: 1
ExtraTags	yes	yes	String	Extra information. JSON string. Example: {"cluster_name": "es-dnsssss"}
MetricsInfo	yes	yes	Array of AlarmHistoryMetric	Metric information. Example: view
Dimensions	no	yes	String	Dimensions. Example: {"cluster_name": "es-dnsssss"}
AlarmLevel	no	no	String	Alarm Level. Example: Remind

AlarmPolicyCondition

Metric trigger condition of alarm policy

Referenced by the following interfaces: [CreateAlarmPolicy](#), [DescribeAlarmPolicies](#), [DescribeAlarmPolicy](#), [ModifyAlarmPolicyCondition](#)

name	required	NULL allowed	type	description
IsJoinRule	yes	no	String	The 'AND' or 'OR' rule of the metric. The value 0 indicates the 'OR' rule. The value 1 indicates the 'AND' rule. Example: 1
Rules	yes	no	Array of AlarmPolicyRule	Alarm trigger condition list. Example: view

DescribePolicyGroupInfoCondition

Alarm threshold conditions output by the policy query.

Referenced by the following interfaces: [DescribePolicyGroupInfo](#), [DescribePolicyGroupList](#)

name	required	NULL allowed	type	description
MetricShowName	yes	no	String	Metric name. Example: CpuUsage
Period	yes	no	Int64	Data aggregation period in seconds. Example: 60
MetricId	yes	no	Int64	Metric ID. Example: 10
RuleId	yes	no	Int64	Threshold rule ID. Example: 10
Unit	yes	no	String	Metric unit. Example: %
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 10
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value u003c0 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime.
CalcType	yes	no	Int64	Comparative type. The value 1 indicates greater than. The value 2 indicates greater than or equal to. The value 3 indicates smaller than. The value 4 indicates smaller than or equal to. The value 5 indicates equal to. The value 6 indicates not equal to. The value 7 indicates day-on-day increase. The value 8 indicates day-on-day decrease. The value 9 indicates week-on-week increase. The value 10 indicates week-on-week decrease. The value 11 indicates periodical increase. The value 12 indicates periodical decrease. Example: 10
CalcValue	yes	no	String	Detection threshold. Example: 100
ContinueTime	yes	no	Int64	Duration at which an alarm will be triggered in seconds. Example: 50

PolicyGroupReceiverInfo

Information on recipients in the policy template list (API v2018)

Referenced by the following interfaces: [DescribeConditionsTemplateList](#)

name	required	NULL allowed	type	description
EndTime	yes	no	Int64	End time of a valid time period. Example: 1734957911
NeedSendNotice	yes	no	Int64	Whether it is required to send notifications. Example: 1
NotifyWay	yes	yes	Array of String	The channel for sending alarms. Example: sms
PersonInterval	yes	no	Int64	Alarm call intervals for individuals in seconds. Example: 1
ReceiverGroupList	yes	yes	Array of Int64	Message recipient group list. Example: 10
ReceiverType	yes	no	String	Recipient type. Example: sms
ReceiverUserList	yes	yes	Array of Int64	Recipient list. The list of recipient IDs that is queried by API. Example: [1234]
RecoverNotify	yes	yes	Array of String	Notification method when an alarm is recovered. Example: sms
RoundInterval	yes	no	Int64	Intervals of alarm call rounds in seconds. Example: 1
RoundNumber	yes	no	Int64	Number of alarm call rounds. Example: 1
SendFor	yes	yes	Array of String	Alarm call notification time. Valid values: OCCUR (indicating that a notice is sent when the alarm is triggered) and RECOVER (indicating that a notice is sent when the alarm is recovered). Example: qwer
StartTime	yes	no	Int64	Start time of a valid time period. Example: 1734953808
UIDList	yes	yes	Array of Int64	UID of the alarm call recipient. Example: 1234

AlarmEvent

Alarm event

Referenced by the following interfaces: [DescribeAlarmEvents](#)

name	required	NULL allowed	type	description
EventName	yes	no	String	Event name. Example: Testing
Description	yes	no	String	Displayed event name. Example: Testing
Namespace	yes	no	String	Alarm policy type. Example: cvm_device
Tooltip	yes	yes	MetricTooltip	Prompt information that can be displayed. Example: View

UnifyDashboardMeta

Dashboard list element information.

Referenced by the following interfaces: [DescribeUnifyDashboards](#)

name	required	NULL allowed	type	description
UUID	yes	no	String	dashboard uuid Example: 1234
IsStarred	yes	no	Bool	Whether to add to 'Favorite'. Example: false
Title	yes	no	String	Dashboard name. Example: 1735179378
IsDefault	yes	no	Bool	Default. Example: false
Type	yes	no	String	Dashboard type. Example: qwer
LastVisitTime	yes	no	String	Last access time. Example: 1735179378
CreatedAt	yes	no	String	Creation time. Example: qwer



name	required	NULL allowed	type	description
UpdatedAt	yes	no	String	Update time. Example: qwer
FolderUUID	no	no	String	The folder UUID. Example: f-4on2b4aggrdjo
IsFolder	no	no	Bool	Whether it is a folder. Example: false
Order	no	no	String	Order. Example: desc

RegionPolicyObjectCount

Region statistics returned by the DescribePolicyObjectCount API.
Referenced by the following interfaces: DescribePolicyObjectCount

name	required	NULL allowed	type	description
Region	yes	no	String	Region. Example: gc
Count	yes	no	Int64	Number of instances bound. Example: 10

CimDimension

Metric set dimension object for log monitoring.
Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
Field	yes	no	String	Field name. Example: timeField
Id	no	no	Int64	Item ID (only for output parameter; leave it empty for input parameter). Example: 1
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: eqeafdfg
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: eqeafdfg
MetricSetId	no	no	Int64	Metric set ID (only for output parameter; leave it empty for input parameter). Example: 1

ServerAttributeDataOutput

ServerAttributeDataOutput
Referenced by the following interfaces: DescribeServerDatas

name	required	NULL allowed	type	description
AttributeId	yes	no	UInt64	Metric ID. Example: 1
ServerId	yes	no	UInt64	Server ID. Example: 1
Values	yes	no	Array of AttributeTimestampValueOutput	Reported value of the metric. Example: View

MetricDatum

Metric names and values
Referenced by the following interfaces: PutMonitorData

name	required	NULL allowed	type	description
MetricName	yes	no	String	Metric name. Example: CpuUsage
Value	yes	no	UInt64	Metric value. Example: 10

DescribePolicyConditionListConfigManual

DescribePolicyConditionListConfigManual
Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
CalcType	yes	yes	DescribePolicyConditionListConfigManualCalcType	Test method. Example: View
CalcValue	yes	yes	DescribePolicyConditionListConfigManualCalcValue	Detection threshold. Example: View
ContinueTime	yes	yes	DescribePolicyConditionListConfigManualContinueTime	Duration. Example: View
Period	yes	yes	DescribePolicyConditionListConfigManualPeriod	Data cycle. Example: View
PeriodNum	yes	yes	DescribePolicyConditionListConfigManualPeriodNum	Number of consecutive periods. Example: View
StatType	yes	yes	DescribePolicyConditionListConfigManualStatType	The aggregation method. Example: View

AttributeAggrValueInfoOutputData

AttributeAggrValueInfoOutputData
Referenced by the following interfaces: DescribeAttributeAggregateData

name	required	NULL allowed	type	description
Data	yes	no	Array of AttributeTimestampValueOutput	Returns a list of aggregation data. Example: View
TotalCount	yes	no	Int64	Returns the number of aggregation data lists. Example: 10

DescribePolicyConditionListConfigManualContinueTime

DescribePolicyConditionListConfigManualContinueTime
Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
Default	yes	yes	Int64	Default duration in seconds. Example: 10
Keys	yes	yes	Array of Int64	Custom duration in seconds. Example: 10
Need	yes	no	Bool	Whether required. Example: true

DescribePolicyConditionListConfigManualCalcValue

DescribePolicyConditionListConfigManualCalcValue
Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
Default	yes	yes	String	Default value. Example: test
Fixed	yes	yes	String	Fixed value. Example: qwer
Max	yes	yes	String	Maximum value. Example: 100
Min	yes	yes	String	Minimum value. Example: 10
Need	yes	no	Bool	Whether required. Example: true

MessagePolicy

MessagePolicy
Referenced by the following interfaces: DescribeMsgPolicyList

name	required	NULL allowed	type	description
PolicyID	yes	no	String	Policy ID. Example: policy-abc123
PolicyName	yes	no	String	Policy name. Example: Testing



name	required	NULL allowed	type	description
ReceiverGroupIds	yes	yes	Array of Int64	Recipient group list. Example: [1234]
NotifyWay	yes	yes	Array of String	Notification method. Example: sms
VoiceConfig	yes	yes	DescribeMsgPolicyListVoiceConfig	Voice configurations. Example: view
IsDefault	yes	no	Bool	Whether it is a default policy. Example: true
AlarmCount	yes	no	Int64	Number of alarms. Example: 1

HistoryAlarmInfo

Return parameters of the DescribeAlarmHistoryByAlarmId API.
Referenced by the following interfaces: DescribeAlarmHistoryByAlarmId

name	required	NULL allowed	type	description
Id	yes	no	Int64	Alarm ID. Example: 1
GroupId	yes	no	Int64	Policy group ID. Example: 1234
AlarmStatus	yes	yes	String	Alarm status. Example: 1
AlarmType	yes	yes	Int64	Alarm type. 0 (metric alarm), 2 (product event alarm), 3 (platform event alarm). Example: 1
Content	yes	no	String	The alarm content. Example: qwer
CurrentValue	yes	yes	String	Current value. Example: 10
FirstOccurTime	yes	yes	String	Initial triggered time. Example: 1735129241
LastOccurTime	yes	yes	String	Final triggered time. Example: 1735129241
Duration	yes	yes	Int64	Duration. Example: 10
ObjId	yes	yes	String	Object ID. Example: (a523bfb-d009-47e2-a85c-b23455b0949)
ObjName	yes	yes	String	Object name. Example: 172.16.0.15#75904
ProjectId	yes	yes	Int64	Project ID. Example: 10
ProjectName	yes	yes	String	Project name. Example: Default
Region	yes	yes	String	Region. Example: gp
Status	yes	yes	Int64	Status. Valid values: 0, 1, 2, 3, 4, 5. 0: not recovered, 1: recovered, 4: expired, 2/3/5: insufficient data.
ViewName	yes	yes	String	View name. Example: cvm_device

ModifyConditionsTemplateRequestCondition

ModifyConditionsTemplateRequestCondition
Referenced by the following interfaces: CreateConditionsTemplate, ModifyConditionsTemplate

name	required	NULL allowed	type	description
AlarmNotifyPeriod	no	no	String	Alarm notification cycle. Example: 60/60
AlarmNotifyType	no	no	Int64	Alarm notification method. Example: 0
CalcPeriod	yes	no	String	Statistical period. Example: 60
CalcType	yes	no	String	Statistical method. Example: 1
CalcValue	yes	no	String	Statistics value. Example: 0
ContinuePeriod	yes	no	String	Consecutive period. Example: 1
MetricId	yes	no	Int64	Metric ID. Example: 10
RuleId	no	no	Int64	Rule ID. Example: 1

PCLMDescribeMetricSetsData

CLMDescribeMetricSets return data.
Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
MetricSets	yes	yes	Array of PCLMMetricSet	Metric set list data. Example: view
TotalCount	yes	yes	Int64	Total number. Example: 10

CgrpGroupNode

CgrpGroupNode
Referenced by the following interfaces: CreateGroup, DeleteGroup, DescribeGroup, InitGroup, ModifyGroup

name	required	NULL allowed	type	description
AppId	no	yes	Int64	Group ID. Example: 1234
High	no	no	Int64	Group depth. Example: 1
Id	yes	no	Int64	Group ID. Example: 1
IsLeaf	no	no	Bool	Whether it is a leaf node. Example: true
Level	no	no	Int64	Current level in the tree. Example: 1
Name	no	no	String	Tree node. Example: Testing
ParentId	no	no	Int64	Parent node ID. Example: 1
SubIdIn	no	yes	String	SubIdIn Example: 1234
TypeId	no	no	String	Type of the instance that is allowed to be stored in the leaf node. Example: cvm_device
Un	no	yes	String	Un Example: 123456

CimAlertPolicy

Expired.
Referenced by the following interfaces: CreateAlertPolicy, DescribeAlertPolicies, DescribeAlertPolicy, ModifyAlertPolicy

name	required	NULL allowed	type	description
Name	yes	yes	String	Policy name. Example: test
MetricSetId	yes	yes	Int64	Metric set ID (invalid parameter). Example: 1
Status	yes	yes	Int64	Status. 1: enabled, 2: not enabled. Example: 1
AlertGroupId	yes	yes	String	Alarm recipient group ID. Multiple IDs are separated by commas. Example: 1234
AlertChannel	yes	yes	String	Channels for receiving alarms: "SMS", "EMAIL", "WECHAT", "CALL". Multiple values are separated by commas. Example: sms
NoticePeriodBegin	yes	yes	Int64	Start time of the time range to send notifications (number of seconds since 00:00:00). Example: 100
NoticePeriodEnd	yes	yes	Int64	End time of the time range to send notifications (number of seconds since 00:00:00). Example: 200



name	required	NULL allowed	type	description
UriScheme	no	yes	String	Scheme of the callback URL. Example: http
CallbackUri	no	yes	String	Callback URL, excluding the scheme part. Example: http://test.com
AlertFilterRules	no	yes	Array of CinAlertFilterRule	List of alarm filter conditions. Example: view
AlertTriggerRules	yes	yes	Array of CinAlertTriggerRule	Alarm trigger condition list. Example: view
Id	no	yes	Int64	Alarm policy ID (output parameter). Example: 1
CreatedAt	no	yes	String	Creation time (output parameter). Example: eqeaddrq:
UpdatedAt	no	yes	String	Update time (output parameter). Example: eqeaddrq:
AlertUserId	no	yes	String	Alarm recipient ID. Multiple IDs are separated by commas. Example: 1234
LatestAlertTime	no	yes	String	Last alarm time (output parameter). Example: 1735041205
FilterRelation	no	yes	Int64	Relationship between filter conditions. 1: AND. 2: OR. Example: 1
TriggerRelation	yes	yes	Int64	Relationship between trigger conditions. 1: AND. 2: OR. Example: 1
MetricSetCID	no	no	Float	Metric set CID. Example: 123455

Metric

Metric, which can be used to set alarms and query data

Referenced by the following interfaces: DescribeAlarmMetrics

name	required	NULL allowed	type	description
Namespace	yes	no	String	Alarm policy type. Example: cvm.device
QceNamespace	yes	no	String	It is only valid for cloud product monitoring and is used by certain APIs to query data. Example: QCE/CVM
MetricName	yes	no	String	Metric name. Example: CpuUsage
Description	yes	no	String	Displayed metric name. Example: CPU Utilization
Aggregations	yes	no	Array of MetricAggregation	The aggregation method. Example: view
Min	yes	no	Float	Minimum value. Example: 0
Max	yes	no	Float	Maximum value. Example: 100
Dimensions	yes	no	Array of String	The dimensions. Example: vm_id
Unit	yes	no	String	Unit. Example: %
Tooltip	yes	yes	MetricTooltip	Rich text prompt. Example: view
MetricConfig	yes	yes	MetricConfig	Metric configuration Example: view
Operators	no	no	Array of String	Operators Example: {"Id":"eq","Name":"+"}
Periods	no	no	Array of Int64	Periods Example: 5

CustomCallbackNoticeImpl

Elements in the custom notification content template.

Referenced by the following interfaces: CreateNoticeContentImpl, DescribeNoticeContentImpl, ModifyNoticeContentImpl

name	required	NULL allowed	type	description
ContentImpl	yes	no	String	Alarm notification content template. Example: Alarm notification template
TitleImpl	no	no	String	Alarm notification topic template. Example: Title

AlarmPolicyBasic

Basic information of a v2.0 alarm policy.

Referenced by the following interfaces: DescribeAlarmPoliciesBasic

name	required	NULL allowed	type	description
MonitorType	yes	yes	String	Monitoring type. Example: MT_QCE
OriginId	yes	yes	String	V1.0 alarm policy ID. Example: 1234
PolicyId	no	yes	String	V2.0 alarm policy ID. Example: policy-abc123
PolicyName	no	yes	String	The name of the alarm policy. Example: Testing

StrategyIdInfo

StrategyIdInfo

Referenced by the following interfaces: CreateStrategy

name	required	NULL allowed	type	description
StrategyId	yes	no	Int64	The ID of the alarm policy. Example: 1

ModifyMsgPolicyVoiceConfig

Custom message voice alarm configuration.

Referenced by the following interfaces: CreateMsgPolicy, ModifyMsgPolicy

name	required	NULL allowed	type	description
UidList	no	no	Array of Int64	List of UIDs. Example: [1234]
RoundNumber	no	no	Int64	Number of alarm rounds. Valid values: 1-5. Example: 10
RoundInterval	no	no	Int64	Intervals of alarm rounds in seconds. Example: 10
PersonInterval	no	no	Int64	Alarm intervals for individuals in seconds. Example: 10
NeedSendNotice	no	no	Int64	Whether notification is required. 1: yes. 0: no. Example: 10

ProjectInfo

Output parameter of the DescribeProjectList API

Referenced by the following interfaces: DescribeProjectList

name	required	NULL allowed	type	description
AppId	yes	no	Int64	AppId Example: 1234
CreatorUin	yes	no	Int64	The UIN of the creator. Example: 123456
Name	yes	no	String	Project name. Example: Testing
Info	yes	no	String	Project information. Example: over
IsDefault	yes	no	Int64	Indicates whether to use your default value. Example: 1
ProjectId	yes	no	Int64	Project ID. Example: 1
OwnerUin	yes	no	Int64	The UIN of the root account. Example: 123456



name	required	NULL allowed	type	description
SrcAppId	yes	no	Int64	Source App ID. Example: 1234
SrcPlatform	yes	no	String	Source platform. Example: qwer
Status	yes	no	Int64	State. Example: 1
CreateTime	yes	no	String	Creation time. Example: 1735179378

ConditionsTemp

Alarm condition template

Referenced by the following interfaces: DescribeAlarmPolicies, DescribeAlarmPolicy

name	required	NULL allowed	type	description
ConditionId	yes	yes	Int64	Alarm condition ID. Example: 1234
TemplateName	yes	yes	String	Template name. Example: test
Condition	yes	yes	AlarmPolicyCondition	Metric trigger condition. Example: view
EventCondition	yes	yes	AlarmPolicyEventCondition	Event trigger condition. Example: view

PeriodsStat

Statistical method during the period

Referenced by the following interfaces: DescribeBaseMetrics

name	required	NULL allowed	type	description
Period	yes	no	String	Interval. Example: 60
StatType	yes	no	Array of String	Statistical method. Example: avg

WebStorageInfos

Dashboard pop-up information management.

Referenced by the following interfaces: DescribeWebStorage

name	required	NULL allowed	type	description
CreatedAt	yes	no	String	Creation time. Example: qwer
SubId	yes	no	String	Sub-id. Example: 123456
Url	yes	no	String	Primary url. Example: 123456
UpdatedAt	yes	no	String	Update time. Example: qwer
WebStorageInfo	yes	no	String	Pop-up information. Example: qwer

DescribeAccidentEventListAlarms

Output parameter type of the DescribeAccidentEventList API

Referenced by the following interfaces: DescribeAccidentEventList

name	required	NULL allowed	type	description
BusinessTypeDesc	yes	yes	String	Event category. Example: qwer
AccidentTypeDesc	yes	yes	String	Event type. Example: qwer
BusinessId	yes	yes	Int64	ID of the event category. The value 1 indicates service issues. The value 2 indicates other subscriptions. Example: 1
EventStatus	yes	yes	Int64	Event status ID. The value 0 indicates that the event has been recovered. The value 1 indicates that the event has not been recovered. Example: 1
AffectResource	yes	yes	String	Affected object. Example: qwer
Region	yes	yes	String	Region where the event occurs. Example: gc
OccurTime	yes	yes	String	Time when the event occurs. Example: 1735041205
UpdateTime	yes	yes	String	Update time. Example: 1735041205

PolicyTag

Policy tag.

Referenced by the following interfaces: BindingPolicyTag, DescribeGroupDbTags, UnbindingPolicyTag

name	required	NULL allowed	type	description
Key	yes	no	String	Tag key. Example: qwer
Value	yes	no	String	Tag value. Example: qwer

MetricSet

Description of the unit and supported statistical period of the business metric

Referenced by the following interfaces: DescribeBaseMetrics

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace. Each cloud product has a namespace. Example: QCS/CVM
MetricName	yes	no	String	Metric name. Example: AccOuttraffic
Unit	yes	no	String	Unit used by the metric. Example: MB
UnitName	yes	no	String	Unit used by the metric. Example: ""
Period	yes	no	Array of Int64	Statistical period in seconds supported by the metric, such as 60 and 300. Example: [10,60]
Periods	yes	no	Array of PeriodsStat	Metric in a statistical period. Example: view
Meaning	yes	no	MetricObjectMeaning	The meaning of the statistical metric. Example: view
Dimensions	yes	no	Array of DimensionsDesc	The description of the dimension. Example: view

ModifyPolicyGroupCondition

Modification of the metric threshold condition passed in by the alarm policy group.

Referenced by the following interfaces: ModifyPolicyGroup

name	required	NULL allowed	type	description
RuleId	no	no	Int64	Rule ID. No filling means new addition while filling in ruleId means to modify existing rules. Example: 1
MetricId	yes	no	Int64	Metric ID. Example: 10
CalcType	yes	no	Int64	Comparative type. The value 1 indicates greater than. The value 2 indicates greater than or equal to. The value 3 indicates smaller than. The value 4 indicates smaller than or equal to. The value 5 indicates equal to. The value 6 indicates not equal to. Example: 10
CalcValue	yes	no	String	Detection threshold. Example: 10
CalcPeriod	yes	no	Int64	Data period of the detected metric. Example: 5
ContinuePeriod	yes	no	Int64	Number of consecutive periods. Example: 5
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 1
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value <0 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime. Example: 5



MonitorProductInfo

Product information returned by the DescribeMonitorProductByIds API.
Referenced by the following interfaces: DescribeMonitorProductByIds

name	required	NULL allowed	type	description
Id	yes	yes	String	The product code. Example: 10
ProductName	yes	yes	String	Product name. Example: cvm_device
PolicyViewName	yes	yes	String	Product view name. Example: cvm_device
AvailableRegions	yes	yes	Array of String	Region supported. Example: ["gz"]
IsShownDashboard	yes	yes	Bool	Whether the Dashboard is visible. Example: false
Meta	yes	yes	String	Product details. JSON string. Example: qwer
Namespace	yes	yes	String	Namespace of the product. Example: QCE/CVM

ProductHealthStatus

HealthStatus returned by the DescribeProductHealthStatusList API.
Referenced by the following interfaces: DescribeProductHealthStatusList

name	required	NULL allowed	type	description
ViewName	yes	yes	String	View name. Example: cvm_device
HealthStatus	yes	yes	Int64	Health status. 1: not recovered. Example: 1
WarningCount	yes	yes	Int64	Number of reminders. Example: 1
AbnormalCount	yes	yes	Int64	Number of exceptions. Example: 1
AlarmRegions	yes	yes	Array of String	List of regions that receive alarms. Example: ["gz"]

DescribePolicyUseList

Object returned by the DescribePolicyUseList API.
Referenced by the following interfaces: DescribePolicyUseList

name	required	NULL allowed	type	description
UniqueId	yes	no	String	Unique ID of the alarm object. Example: eqeq-csda
Dimensions	yes	no	String	Dimension string. Example: ("unInstanceId":"ins-xxx")

DescribeEventPolicyConfigDimension

DescribeEventPolicyConfigDimension
Referenced by the following interfaces: DescribeEventPolicyConfig

name	required	NULL allowed	type	description
Name	yes	no	String	The name of the dimension. Example: Testing
Key	yes	no	String	Dimension key value. Example: qwer

AlarmBindingInstance

AlarmBindingInstance
Referenced by the following interfaces: DescribeAlarmBindingInstanceList

name	required	NULL allowed	type	description
UUID	yes	no	String	Instance UUID. Example: u78haoyaq8w6wbr
Information	yes	no	String	Information about instance dimension combinations. Example: {"appid":"1251000011","projectId":"10","vm_uuid":"9566d415-fb0a-4515-9b87-09ad16d87884"}

AttributeUnitInfoOutput

AttributeUnitInfoOutput
Referenced by the following interfaces: DescribeAttributeUnits

name	required	NULL allowed	type	description
UnitId	yes	no	UInt64	Metric unit ID. Example: 1
UnitName	yes	no	String	Metric unit name. Example: test

DescribeBindingPolicyObjectListInstanceGroup

Instance group information returned by the DescribeBindingPolicyObjectList API.
Referenced by the following interfaces: DescribeBindingPolicyObjectList

name	required	NULL allowed	type	description
InstanceGroupId	yes	no	Int64	Instance group ID. Example: 1234
ViewName	yes	no	String	Name of the alarm policy type. Example: cvm_device
LastEditUin	yes	no	String	Uin that was last edited. Example: 123456
GroupName	yes	no	String	Instance group name. Example: Testing
InstanceSum	yes	no	Int64	Number of instances. Example: 10
UpdateTime	yes	no	Int64	Update time. Example: 1735095122
InsertTime	yes	no	Int64	Creation time. Example: 1735095122
Regions	yes	yes	Array of String	Regions where the instances reside. Example: ["gz"]

AlarmPolicyEventCondition

Event trigger condition of alarm policy
Referenced by the following interfaces: CreateAlarmPolicy, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmPolicyCondition

name	required	NULL allowed	type	description
Rules	yes	yes	Array of AlarmPolicyRule	Alarm trigger condition list. Example: View

CCMChartData

CCMChartData
Referenced by the following interfaces: DescribeCCMCharts

name	required	NULL allowed	type	description
Data	yes	no	Array of CCMChartEntry	Returns the data list. Example: View
TotalCount	yes	no	Int64	Queries the total amount of data. Example: 10

CreatePolicyGroupEventCondition

Event alarm condition passed in when a policy is created.
Referenced by the following interfaces: CreatePolicyGroup

name	required	NULL allowed	type	description
RuleId	no	no	Int64	If a metric is created based on a template, the RuleId of the metric in the template must be passed in. Example: 1



name	required	NULL allowed	type	description
EventId	yes	no	Int64	Alarm event ID. Example: 1
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 1
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value 0/03600 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime.

DescribePolicyConditionListConfigManualStatType

DescribePolicyConditionListConfigManualStatType

Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
P5	yes	yes	String	Data aggregation method in a period of 5 seconds. Example: 5
P10	yes	yes	String	Data aggregation method in a period of 10 seconds. Example: 10
P60	yes	yes	String	Data aggregation method in a period of 1 minute. Example: 60
P300	yes	yes	String	Data aggregation method in a period of 5 minute. Example: 300
P600	yes	yes	String	Data aggregation method in a period of 10 minute. Example: 600
P1800	yes	yes	String	Data aggregation method in a period of 30 minute. Example: 1800
P3600	yes	yes	String	Data aggregation method in a period of 1 hour. Example: 3600
P86400	yes	yes	String	Data aggregation method in a period of 1 day. Example: 86400

MetricAggregation

Metric aggregation method.

Referenced by the following interfaces: DescribeAlarmMetrics

name	required	NULL allowed	type	description
NameCn	yes	no	String	Name. Example: test
NameEn	yes	no	String	The name. Example: Testing
Id	no	yes	String	The ID. Example: 1
Name	no	yes	String	Name Example: Testing

DescribeAccidentConfigAccident

Platform event of the DescribeAccidentConfig API

Referenced by the following interfaces: DescribeAccidentConfig

name	required	NULL allowed	type	description
BusinessId	yes	no	Int64	Business ID Example: 10
BusinessName	yes	no	String	Business name. Example: qwer
BusinessEnName	yes	no	String	Business name. Example: qwer
PolicyShowName	yes	no	String	Displayed strategy name. Example: qwer
PolicyShowEnName	yes	no	String	Displayed strategy name in English. Example: qwer
PolicyViewName	yes	no	String	Policy type name. Example: cvm_device
AccidentTypeInfo	yes	no	Array of DescribeAccidentConfigAccidentTypeInfo	List of platform event types. Example: View

IdcInfo

IdcInfo

Referenced by the following interfaces: DescribeIdcServerCount

name	required	NULL allowed	type	description
IdcId	yes	no	Int64	Region ID Example: 12345
ServerCount	yes	no	Int64	Number of instances. Example: 10
IdcName	yes	no	String	The region name. Example: Testing

DashboardMetricQuery

Dashboard 2.0 metric query input parameter structure.

Referenced by the following interfaces: DescribeDashboardMetricData

name	required	NULL allowed	type	description
StartTime	yes	no	Datetime_iso	Start time of the query period in ISO format, such as: 2018-04-10T10:15:58.858Z Example: 2019-11-29T12:30:13+08:00
EndTime	yes	no	Datetime_iso	End time of the query period in ISO format, such as: 2018-04-10T10:15:58.858Z Example: 2019-03-24T20:50:00+08:00
DataSource	yes	no	String	Data source. Example: DS_QCBMetric
Namespace	yes	no	String	The name of the namespace. Example: QCB/CVM
MetricName	yes	no	String	Name of the query metric. Example: LanOutTraffic
Period	no	no	Int64	Statistical period in seconds. The default value is 60 seconds. Example: 60
GroupBy	yes	no	Array of String	Group. Fill in the metric dimension. Example: LanOutTraffic
Aggregate	no	no	String	Aggregation method. Fill in the aggregation method according to the metric type. Example: min
Conditions	yes	no	Array of DashboardMetricCondition	Filter condition. Example: View
SeriesId	no	no	String	Query flag. Example: 1a6def11-7991-4d82-ab1c-44b6a6e1c336
DataSourceRegion	no	no	String	Name of the data source region. Example: gz
ConfigId	no	no	String	Product configuration ID. Example: cvm
QueryVersion	no	no	String	Queries the version number. Leave it empty for the old version. For the new version, pass in '2020-10-21'. Example: 2020-10-21
OrderBy	no	no	String	Calculation method of sort value. Valid values: avg, sum, min, max. Example: desc
AscDesc	no	no	String	Sort order. Valid values: asc, desc. Example: desc
Limit	no	no	UInt64	Number of items to be sorted. Example: 10

CimMetricBasicItem

Basic metric configurations for the log monitoring metric set.

Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
Field	yes	yes	String	Field name. Example: timeField
Operator	yes	yes	String	Metric statistics method: sum, count, min, max. Example: +
Name	yes	yes	String	Metric name. Example: Testing



name	required	NULL allowed	type	description
Desc	yes	yes	String	Metric description name. Example: Testing
StatisticFilterRules	no	yes	Array of CimStatisticFilterRule	Metric filtering rule. Example: view
Id	no	yes	Int64	Item ID (only for output parameter; leave it empty for input parameter) Example: 1
MetricSetId	no	yes	Int64	Metric set ID (only for output parameter; leave it empty for input parameter) Example: 1
CreatedAt	no	yes	String	Creation time (only for output parameter; leave it empty for input parameter) Example: eqeadiq
UpdatedAt	no	yes	String	Update time (only for output parameter; leave it empty for input parameter) Example: eqeadiq

AttributeInfoOutputData

Attribute data list.
Referenced by the following interfaces: DescribeAttributes

name	required	NULL allowed	type	description
Data	yes	no	Array of AttributeInfoOutput	Attribute data list. Example: view
TotalCount	yes	no	Int64	Number of attribute data lists. Example: 10

DashboardDimensionSource

Dashboard2.0 dimension list.
Referenced by the following interfaces: DescribeDashboardDimensionKeys

name	required	NULL allowed	type	description
DataSource	yes	no	String	Data source. Example: DS_QCEMetric
Namespace	yes	no	String	Namespace. Example: cvm_device
DimensionName	yes	no	String	Dimension name. Example: Testing
MetricName	yes	no	String	Metric name. Example: cpu_usage

DescribePolicyInfoByInstanceInstanceGroup

DescribePolicyInfoByInstanceInstanceGroup
Referenced by the following interfaces: DescribePolicyInfoByInstance

name	required	NULL allowed	type	description
InstanceGroupId	yes	yes	Int64	Instance group ID. Example: 1234
ViewName	yes	no	String	View. Example: cvm_device
LastEditUin	yes	yes	Int64	UIN of the last editor. Example: 123456
GroupName	yes	no	String	Instance group name. Example: Testing
InstanceSum	yes	yes	Int64	Number of instances. Example: 10
UpdateTime	yes	yes	Int64	Update time. Example: 1735095122
InsertTime	yes	yes	Int64	Creation time. Example: 1735095122

CimLogFilterRule

Metric set filtering rule for log monitoring.
Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
Relation	yes	no	Int64	Relationship: 1: AND; 2: OR. Example: 1
Field	yes	no	String	Field name. Example: timeField
Operator	yes	no	String	Filter operator: Numeric fields support: gt lt ge le eq ne in. Character fields support: eq ne in contains. Example: =
Value	yes	no	String	Filter operation value. Example: 50
Id	no	no	Int64	Item ID (only for output parameter; leave it empty for input parameter) Example: 1
MetricSetId	no	no	Int64	Metric set ID (only for output parameter; leave it empty for input parameter) Example: 12
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter) Example: eqeadiq
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter) Example: eqeadiq

IdcData

IdcData
Referenced by the following interfaces: DescribeIdcTree

name	required	NULL allowed	type	description
Id	yes	no	Int64	idc id, which represents zoneid on the cloud platform. Example: 1
Name	yes	no	String	idc id, which represents zone name on the cloud platform. Example: Testing

SubscribeInfoReceiver

Output parameter of DescribeSubscribeInfo.
Referenced by the following interfaces: DescribeSubscribeInfo

name	required	NULL allowed	type	description
Username	yes	yes	String	User name. Example: test
Uin	yes	yes	String	User UIN. Example: 123456
Uid	yes	yes	String	User UID. Example: 1234

AlarmPolicyQuota

Specific v2.0 alarm policy quota.
Referenced by the following interfaces: DescribeAlarmObjectQuota, DescribeAlarmPolicyQuota

name	required	NULL allowed	type	description
AppId	yes	no	Int64	The account ID. Example: 1234
Namespace	yes	no	String	Policy type. "": no policy type. Example: cvm_device
ProjectId	yes	no	Int64	Project ID. -1: no project. Example: 1
Total	yes	no	Int64	Total amount of quotas. Example: 10
Used	yes	no	Int64	Number of used resources. Example: 10

DescribeAlarmSmsQuotaQuota

Quota information of the DescribeAlarmSmsQuota API.
Referenced by the following interfaces: DescribeAlarmSmsQuota

name	required	NULL allowed	type	description
Type	yes	no	String	The quota type.



name	required	NULL allowed	type	description
Name	yes	no	String	Example: cloud_test Quota name. Example: Cloud Automated Testing alarm
FreeLeft	yes	no	Int64	Remaining free quota. Example: 100
PurchaseLeft	yes	no	Int64	Remaining paid quota. Example: 200
Used	yes	no	Int64	Number of used resources. Example: 100

DescribePolicyConditionListEventMetric

DescribePolicyConditionListEventMetric

Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
EventId	yes	no	Int64	Event ID. Example: 10
EventShowName	yes	no	String	Event name. Example: ReadOnly
NeedRecovered	yes	no	Bool	Whether to recover. Example: true
Type	yes	no	Int64	Event type, which is a reserved field. Currently, it is fixed to 2. Example: 1

DashboardMetricEntry

Dashboard2.0 metric information.

Referenced by the following interfaces: DescribeDashboardMetrics

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace value. Example: QCE/CVM
MetricName	yes	no	String	Metric name. Example: WardInTraffic
MetricType	yes	no	String	The metric type. Example: QCEMetric
Aggregations	yes	no	Array of String	Aggregation method of the metric. Example: Max
Description	yes	no	String	Displayed metric name. Example: Public Network Inbound Bandwidth
Unit	yes	no	String	Metric data unit. Example: Mbps
Min	yes	no	Float	Minimum value. Example: 0
Max	yes	no	Float	Maximum value. Example: 0
Dimensions	yes	no	Array of String	The dimensions. Example: ("InstanceId":"ins-xxx")

NoticeContentTpl

Information on the queried custom content templates.

Referenced by the following interfaces: DescribeNoticeContentTpl

name	required	NULL allowed	type	description
TmplID	no	no	String	Template ID Example: tmpl-xxx
TmplName	no	no	String	Template name. Example: tmplName
MonitorType	no	no	String	Monitoring type. Example: MT_QCE
TmplContents	no	no	NoticeContentTplItem	Content template details. Example: view
TmplLanguage	no	no	String	Template language. Valid values: en and zh. Example: zh
CreateTime	no	no	Int64	Creation time. It is a Unix timestamp in second. Example: 1729655205
UpdateTime	no	no	Int64	Modification time. It is a Unix timestamp in second. Example: 1729655205
LastModifier	no	no	String	Last Modified By Example: tester-b
Creator	no	no	String	Creator. Example: tester-a
IsPreset	no	no	Int64	Whether the template content is the default content. 0: no; 1: yes. Example: 0

DashboardNamespace

Namespace information under Dashboard2.0 data source.

Referenced by the following interfaces: DescribeAllNamespaces, DescribeDashboardNamespaces

name	required	NULL allowed	type	description
Id	yes	no	String	Namespace identifier. Example: dcchannel
Name	yes	no	String	The name of the namespace. Example: Direct Connect—Dedicated tunnel
Value	yes	no	String	Namespace value. Example: QCE/OCK
ProductName	yes	yes	String	Product name. Example: Direct Connect—Dedicated tunnel
Config	yes	yes	String	Configuration information. Example: {}
AvailableRegions	yes	yes	Array of String	List of supported regions. Example: ["gc"]
SortId	yes	yes	Int64	Sort ID. Example: 301
Type	no	yes	String	Namespace type. Example: BUSINESS
DashboardId	no	no	String	DashboardId Example: epv6

CimLogProfileItem

Log monitoring metric set - log data structure description.

Referenced by the following interfaces: CreateMetricSet, DescribeMetricSet, DescribeMetricSets, ModifyMetricSet

name	required	NULL allowed	type	description
Id	no	no	Int64	ID (only for output parameter; leave it empty for input parameter) Example: 1
MetricSetId	no	no	Int64	Associated metric set ID (only for output parameter; leave it empty for input parameter) Example: 12
Field	yes	no	String	Field name. Example: timeField
Type	yes	no	String	Field type. Valid values: string, long, double. Example: string
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter). Example: eqeadiqc
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter). Example: eqeadiqc

DescribeBasicAlarmListAlarms

Alarms returned by DescribeBasicAlarmList

Referenced by the following interfaces: DescribeBasicAlarmList

name	required	NULL allowed	type	description
Id	yes	no	UInt64	ID of the alarm. Example: 1
ProjectId	yes	yes	Int64	Project ID. Example: 1



name	required	NULL allowed	type	description
ProjectName	yes	yes	String	Project Name Example: Testing
Status	yes	yes	Int64	Alarm status ID. Example: 1
AlarmStatus	yes	yes	String	Alarm status. Example: ALARM
GroupId	yes	yes	Int64	Policy group ID. Example: 1234
GroupName	yes	yes	String	Policy group name. Example: Testing
FirstOccurTime	yes	yes	String	Event time. Example: 1735095122
Duration	yes	yes	Int64	Duration in seconds. Example: 10
LastOccurTime	yes	yes	String	End time. Example: 1735095122
Content	yes	yes	String	The alarm content. Example: qwer
ObjName	yes	yes	String	Alarm object. Example: 172.16.0.154/7504
ObjId	yes	yes	String	Alarm object ID. Example: 0a5238fb-d809-47a2-a85c-0b23455b0949
ViewName	yes	yes	String	Policy type Example: cvm_device
Vpc	yes	yes	String	VPC, which is unique to CVM. Example: qwer
MetricId	yes	yes	Int64	Metric ID. Example: 10
MetricName	yes	yes	String	Metric name. Example: CpuUsage
AlarmType	yes	yes	Int64	Alarm type. The value 0 indicates metric alarms. The value 2 indicates product event alarms. The value 3 indicates platform event alarms. Example: 1
Region	yes	yes	String	Region. Example: gp
Dimensions	yes	yes	String	Dimension information of an alarm object. Example: ("unInstanceId":"ins-xxx")
NotifyWay	yes	yes	Array of String	Notification method. Example: sms
InstanceGroup	yes	yes	Array of InstanceGroup	Instance group information. Example: View

MoveFailReason

Reasons why the dashboard failed to be moved.

Referenced by the following interfaces: MoveUnifyDashboards

name	required	NULL allowed	type	description
UUID	yes	no	String	UUID of the dashboard. Example: daaeqe
Mug	yes	no	String	Reasons why the movement failed. Example: ok

DashboardMetricCondition

Query condition for the Dashboard2.0 metric query.

Referenced by the following interfaces: DescribeDashboardMetricData

name	required	NULL allowed	type	description
Dimension	yes	no	Array of String	Array elements are JSON serialized strings. Example: ("unInstanceId":"ins-0bjv8me")
Region	yes	no	String	Domain name Example: gp

MonitorDimensionSource

Dimensio Key Sources.

Referenced by the following interfaces: DescribeDashboardDimensionKeys

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace. Example: QCE/CVM
Metric	yes	no	String	List of metrics. Example: CpuUsage
SearchValue	yes	no	String	The values. Example: qwer

Instance

Array of instance dimension combinations

Referenced by the following interfaces: DescribePolicyGroupCount, GetMonitorData

name	required	NULL allowed	type	description
Dimensions	yes	no	Array of Dimension	Dimension combination of an instance. Example: ins

AlarmPolicyFilter

Filter condition of alarm policy

Referenced by the following interfaces: CreateAlarmPolicy, DescribeAlarmPolicies, DescribeAlarmPolicy, ModifyAlarmPolicyCondition

name	required	NULL allowed	type	description
Type	yes	no	String	Filter condition type. Valid values: DIMENSION (uses dimensions for filtering). Example: =
Expression	no	no	String	Bare write filter expression. Example: test
Dimensions	no	no	String	JSON string generated by serializing the AlarmPolicyDimension two-dimensional array. The one-dimensional arrays are in OR relationship, and the elements in a one-dimensional array are in AND relationship. Example: test

DashboardPanel

Dashboard panel.

Referenced by the following interfaces: AddDashboardPanels, TopDashboardPanel

name	required	NULL allowed	type	description
Type	no	no	String	copy
DashboardUUID	no	no	String	UUID of the dashboard. Example: u78haecyagfw8wbr
PanelID	no	no	Int64	Panel ID. Example: 1234
Panel	no	no	String	Panel data. Example: qwer

DescribeDashboardViewList

DescribeDashboardViewList

Referenced by the following interfaces: DescribeDashboardViews

name	required	NULL allowed	type	description
ViewID	yes	no	Int64	View ID. Example: 1
DescName	yes	no	String	Description name. Example: Testing
Namespace	yes	no	String	Namespace. Example: QCE/CVM
MetricName	yes	yes	Array of String	List of metric names. Example: CpuUsage
Meta	yes	no	String	Metadata JSON. Example: {"aggregateType":"detail","aggregations":{"Avg","Min"},"chartTypes":{"column"},"configId":"cvm","layout":{"h":"S","h2":"","w":"4","x":"","y":"","timeAggregate":"last"}}
Instances	yes	yes	Array of String	Instance list. Example: ("ins-xxx")



AlarmPolicy

Alarm policy details

Referenced by the following interfaces: DescribeAlarmPolicies, DescribeAlarmPolicy

name	required	NULL allowed	type	description
PolicyId	yes	yes	String	Alarm policy ID. Example: policy-abc123
PolicyName	yes	yes	String	The name of the alarm policy. Example: testing
Remark	yes	yes	String	Remarks. Example: Testing
MonitorType	yes	yes	String	Monitor type. Valid values: MT_QCE (Cloud Platform service monitoring) Example: MT_QCE
Enable	yes	yes	Int64	Enabled or disabled status. 1: enabled. 0: disabled. Example: 1
UseSum	yes	yes	Int64	Number of instances bound to the policy group. Example: 10
ProjectId	yes	yes	Int64	Project ID. -1: no project. 0: default project. Example: 1
ProjectName	yes	yes	String	Project name. Example: Testing
Namespace	yes	yes	String	Alarm policy type. Example: cvm_device
Measurement	yes	yes	String	That is, viewName / View. Cloud Platform service monitoring: cvm_device, etc. Custom monitoring: Measurement under Namespace. Example: test
PolicyExpression	yes	yes	String	Writes alarm rules including trigger rules, filter conditions, etc. It is suitable for prometheus monitoring. Example: Testing
ConditionTemplateId	yes	yes	String	Trigger condition template ID. Example: 1234
Condition	yes	yes	AlarmPolicyCondition	Metric trigger condition. Example: View
EventCondition	yes	yes	AlarmPolicyEventCondition	Event trigger condition. Example: View
NoticeIds	yes	yes	Array of String	List of notification rule IDs. Example: ["1234"]
Notices	yes	yes	Array of AlarmNotice	Notification rule list. Example: View
TriggerTasks	yes	yes	Array of AlarmPolicyTriggerTask	List of trigger tasks. Example: View
OriginId	no	yes	String	Obsolete field. Policy ID for APIs for binding and unbinding instances or instance groups (BindingPolicyObject , UnBindingAllPolicyObject , UnBindingPolicyObject). Example: 1234
ConditionsTemp	yes	yes	ConditionsTemp	Template-based policy group. Note: This field may return null, indicating that no valid value was found. Example: View
LastEditUin	yes	yes	String	UIN of the last user who modified it. Example: 5678
UpdateTime	yes	yes	Int64	Update time. Note: This field may return null, indicating that no valid value was found. Example: 1795022702
InsertTime	yes	yes	Int64	Creation time. Note: This field may return null, indicating that no valid value was found. Example: 1795002702
Region	yes	yes	Array of String	Region. Example: gz
NamespaceShowName	yes	no	String	Namespace display name. Example: cvm_device
IsDefault	yes	no	Int64	Whether it is the default policy. Valid values: 1 (yes), 0 (no). Example: 1
CanSetDefault	yes	no	Int64	Whether the default policy can be set. Valid values: 1 (yes), 0 (no). Example: 1
InstanceGroupId	yes	no	Int64	Instance group ID. Example: 1234
InstanceSum	yes	no	Int64	Total number of instances in instance group. Example: 10
InstanceGroupName	yes	no	String	Instance group name. Example: test
JsConfig	yes	no	String	JsConfig foreground configuration. Example: {"cluster_name": "es-dnssvc"}
RuleType	yes	no	String	Trigger condition type. Valid values: STATIC (static threshold), DYNAMIC (dynamic). Example: STATIC
OriginId	yes	no	String	Policy ID for APIs for binding and unbinding instances or instance groups (BindingPolicyObject , UnBindingAllPolicyObject , UnBindingPolicyObject). Example: 1234
TagInstances	yes	yes	Array of tagInstance	Tag Example: View
Filter	no	yes	String	Filter Example: ("Dimensions":"","Expression":"","Type":"")
GroupBy	no	yes	String	GroupBy Example: ("Id":"","Name":"","")
NoticeContentTplBindInfos	no	no	NoticeContentTplBindInfo	Information on the notification template and content template. Example: View
AlarmLevel	no	no	String	Alarm Level Example: Remind

DescribeProductEventListEventsDimensions

Dimensions of events returned by the DescribeProductEventList API

Referenced by the following interfaces: DescribeProductEventList

name	required	NULL allowed	type	description
Key	yes	yes	String	Dimension name (English). Example: readOnly
Name	yes	yes	String	Dimension name. Example: Disk read-only
Value	yes	yes	String	The value of the dimension. Example: qwer

DescribeDashboardsList

DescribeDashboardsList

Referenced by the following interfaces: DescribeDashboards

name	required	NULL allowed	type	description
DashboardID	yes	no	String	DashboardID Example: eipv6
DescName	yes	no	String	Description name. Example: test
Meta	yes	no	String	Metadata. Example: {"aggregateType":"detail","aggregations":{"Avg":"Max","Min"},"chartTypes":{"column"},"configId":"cvm","layout":{"h":5,"h2":"0","w":4,"w2":"0","y":"0"},"timeAggregate":"last"}

CimAlertTriggerRule

Deprecated parameter.

Referenced by the following interfaces: CreateAlertPolicy, DescribeAlertPolicies, DescribeAlertPolicy, ModifyAlertPolicy

name	required	NULL allowed	type	description
Id		no	yes	Int64 Trigger condition ID (output parameter). Example: 1
CreatedAt		no	yes	String Creation time (output parameter). Example: eqeadiqg
UpdatedAt		no	yes	String Update time (output parameter). Example: eqeadiqg
AlertPolicyId		yes	yes	Int64 Primary key ID of the associated alarm policy. Example: 1234
MetricName		yes	yes	String Metric name (English). Example: cpu_usage
MetricType		yes	yes	Int64 Metric type. 1: common metric. 2: compound metric. Example: 1
Operating		yes	yes	String Operator. Example: =
Value		yes	yes	Float Metric threshold. Example: 50



name	required	NULL allowed	type	description
ContinuousCycleCount	yes	yes	Int64	Number of consecutive periods. Example: 10
NoticeFrequencySec	yes	yes	Int64	Notification frequency (interval between notifications in seconds). Example: 10
MetricFormula	no	yes	String	Compound index expression (leave it empty for basic indexes). Example: ("cluster_name" <= <threshold>)

DescribeGraphDataPartition

DescribeGraphDataPartition

Referenced by the following interfaces: DescribeGraphData

name	required	NULL allowed	type	description
Name	yes	no	Array of String	Partition name. Example: Testing
Usage	yes	no	Float	Usage. Example: 1234
Total	yes	no	Float	Total. Example: 10

ProductSimple

Brief information on products supported by Cloud Monitor.

Referenced by the following interfaces: DescribeProductList

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace. Example: QCL/CVM
ProductName	yes	no	String	The name of the product. Example: cvm_device
ProductEnName	yes	no	String	English name of the product. Example: test

DescribePolicyConditionListConfigManualPeriodNum

DescribePolicyConditionListConfigManualPeriodNum

Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
Default	yes	yes	Int64	Number of default periods. Example: 10
Keys	yes	yes	Array of Int64	Number of custom periods. Example: 10
Need	yes	no	Bool	Whether required. Example: true

DescribeInstanceGroupListInstanceGroup

Instance group information returned by the DescribeInstanceGroupList API.

Referenced by the following interfaces: DescribeInstanceGroupList

name	required	NULL allowed	type	description
InstanceGroupId	yes	no	Int64	Instance group ID. Example: 1234
ViewName	yes	no	String	Instance group policy type name. Example: cvm_device
LastEditLin	yes	no	String	URL of the latest update. Example: 123456
GroupName	yes	no	String	Instance group name. Example: Testing
InstanceSum	yes	no	Int64	Number of instances in the group. Example: 10
UpdateTime	yes	no	Int64	Update time in the format of Unix timestamp. Example: 1735095122
InsertTime	yes	no	Int64	Creation time in the format of Unix timestamp. Example: 1735095122
PolicyGroups	yes	yes	Array of DescribeInstanceGroupListPolicyGroup	List of bound alarm policy groups. Example: View

ModifyRecoverNotifyBatchNotifyInfo

ModifyRecoverNotifyBatch recovery method information.

Referenced by the following interfaces: ModifyRecoverNotifyBatch

name	required	NULL allowed	type	description
GroupId	yes	no	Int64	Policy group ID. Example: 1234
RecoverNotify	yes	no	Array of String	List of alarm recovery notification methods. Example: sms

StrategyEntryAlarm

StrategyEntryAlarm

Referenced by the following interfaces: CreateStrategy, DescribeCCMGroupViewStrategy, DescribeStrategys, ModifyStrategy

name	required	NULL allowed	type	description
AlarmType	yes	no	UInt64	Alarm rule type for the policy. 100: Maximum value (i.e. >), 101: Maximum value (i.e. >=), 102: Minimum value alarm (i.e. <), 103: Minimum value alarm (i.e. <=), 104: Fluctuation value alarm. Example: 1
AttributeId	yes	no	UInt64	Alarm rule attribute ID of the policy. Example: 1
Threshold	yes	no	Int64	Alarm rule threshold of the policy. Example: 1
DetectCount	yes	no	Int64	Policy's alarm rule: the number of alarms in DetectPeriod minutes. Example: 1
DetectPeriod	yes	no	Int64	Alarm period of the policy. Example: 1
TriggerPeriod	yes	no	Int64	Policy's alarm rule: alarm interval period. Example: 1
Description	yes	no	String	Description. Example: Testing
AttributeName	no	yes	String	Metric description. Example: Testing
AttributeUniqueName	no	yes	String	Metric description in English. Unique name. Example: qwer_123

SubscribeInfo

Output parameter of DescribeSubscribeInfo.

Referenced by the following interfaces: DescribeSubscribeInfo

name	required	NULL allowed	type	description
BusinessId	yes	yes	Int64	Event type ID. Example: 1
BusinessName	yes	yes	String	Event name. Example: qwer
AccidentId	yes	yes	Int64	Question type ID. Example: 1
AccidentName	yes	yes	String	Question name. Example: XXXX
NotifyWay	yes	yes	Array of Int64	Notification method. Example: 1
Receivers	yes	yes	Array of SubscribeInfoReceiver	Recipient list. Example: View
Tips	yes	yes	String	Prompt. Example: qwer
UserConfig	yes	yes	String	User configuration, JSON string. Example: {"qwer":"1234"}

DescribeInstanceGroupListPolicyGroup

Policy group information returned by the DescribeInstanceGroupList API.



Referenced by the following interfaces: DescribeInstanceGroupList

name	required	NULL allowed	type	description
GroupId	yes	no	Int64	Policy group ID. Example: 1234
GroupName	yes	no	String	Policy group name. Example: Testing

GroupTemplateList

GetRecommendedTemplateResponse.GroupTemplateList

Referenced by the following interfaces: DescribeRecommendedTemplate

name	required	NULL allowed	type	description
GroupID	yes	no	Int64	Template policy group ID. Example: 1234
GroupName	yes	no	String	Template-based policy group name. Example: Testing
IsDefault	yes	no	Int64	Whether it is a default policy. Example: 1
Enable	yes	no	Bool	Enablement status of the alarm policy. Example: true
LastEditUin	yes	no	Int64	UIN of the last user who modified it. Example: 123456
NoShieldedInstanceCount	yes	no	Int64	Number of unshielded instances. Example: 10
TotalInstanceCount	yes	no	Int64	Total number of bound instances. Example: 10
ParentGroupID	yes	no	Int64	Parent policy group ID. Example: 1234
Remark	yes	no	String	Remarks. Example: Marker
ViewName	yes	no	String	View. Example: cvm_device
Conditions	yes	no	Array of Condition	Metric alarm trigger condition. Example: view
EventConditions	yes	no	Array of EventCondition	Event alarm trigger condition. Example: view
CanSetDefault	yes	no	Bool	Whether the policy can be set as the default policy. Example: true
InsertTime	yes	no	Int64	Creation time. Example: 1735129241
UpdateTime	yes	no	Int64	Modification time. Example: 1735129241

CimDescribeMetricSetsData

DescribeMetricSets return data.

Referenced by the following interfaces: DescribeMetricSets

name	required	NULL allowed	type	description
MetricSets	yes	yes	Array of CimMetricSet	Metric set list data. Example: View
TotalCount	yes	no	Int64	Total number. Example: 10

AttributeServerInfoOutputData

AttributeServerInfoOutputData

Referenced by the following interfaces: DescribeAttributeAllServer, DescribeIdcServer

name	required	NULL allowed	type	description
Data	yes	no	Array of AttributeServerInfoOutput	Returns a list of servers reporting this attribute. Example: View
TotalCount	yes	no	Int64	Returns the number of server lists reporting this attribute. Example: 10

DescribePolicyGroupInfoConditionTpl

Template-based policy group information output by the policy query

Referenced by the following interfaces: DescribePolicyGroupInfo, DescribePolicyGroupList

name	required	NULL allowed	type	description
GroupId	yes	no	Int64	Policy group ID. Example: 1234
GroupName	yes	no	String	Policy group name. Example: Testing
ViewName	yes	no	String	Policy type Example: cvm_device
Remark	yes	no	String	Policy group remarks. Example: test
LastEditUin	yes	no	String	UIN of the last user who modified it. Example: 123456
UpdateTime	yes	yes	Int64	Update time. Example: 1735095122
InsertTime	yes	yes	Int64	Creation time. Example: 1735095122
IsUnionRule	yes	yes	Int64	Whether it is an AND rule. Example: 1

StrategyData

StrategyData

Referenced by the following interfaces: DescribeCCMGroupViewStrategy, DescribeStrategy

name	required	NULL allowed	type	description
Data	yes	no	Array of StrategyEntry	Return data. Example: View
TotalCount	yes	no	Int64	Queries the total number of data lists. Example: 10

PCLMMetricAnalysisPoint

CLM metric analysis data point.

Referenced by the following interfaces: DescribeMetricAnalysisData

name	required	NULL allowed	type	description
Timestamp	yes	no	Int64	Timestamp (seconds). Example: 1735129241
Value	yes	yes	Float	Value. Example: 10
Name	yes	no	String	Metric name. Example: Testing

DescribePolicyConditionListConfigManualCalcType

DescribePolicyConditionList.ConfigManualCalcType

Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
Keys	yes	yes	Array of Int64	Value of CalcType. Example: 1
Need	yes	no	Bool	Whether required. Example: true

DescribePolicyInfoByInstanceGroupList

DescribePolicyInfoByInstanceGroupList

Referenced by the following interfaces: DescribePolicyInfoByInstance

name	required	NULL allowed	type	description
GroupID	yes	no	Int64	Policy group ID. Example: 1234



name	required	NULL allowed	type	description
GroupName	yes	no	String	Policy name. Example: testing
IsOpen	yes	no	Bool	Indicates whether self-healing notifications are enabled. Example: true
ViewName	yes	no	String	View name. Example: cmv,device
LastEditLin	yes	no	Int64	LIN of the last editor. Example: 123456
IsDefault	yes	no	Int64	Whether it is a default policy. Example: 1
CanSetDefault	yes	no	Bool	Whether it can be set as the default policy. Example: true
ParentGroupID	yes	no	Int64	Parent policy group ID. Example: 1234
Remark	yes	no	String	Description. Example: testing
IsUnionRule	yes	no	Int64	Whether it is an AND relationship policy. Example: 1
ProjectID	yes	no	Int64	Project ID. Example: 1
Conditions	yes	yes	Array of Condition	Alarm rule. Example: View
ConditionsTemp	yes	yes	DescribePolicyInfoByInstanceConditionsTemp	Rule template information. Example: View
InstanceGroup	yes	yes	DescribePolicyInfoByInstanceInstanceGroup	Instance group. Example: View
NoShieldedSum	yes	no	Int64	Number of unshielded instances. Example: 10
UseSum	yes	no	Int64	The total number of instances. Example: 10
UpdateTime	yes	no	Int64	Update time. Example: 1735095122
InsertTime	yes	no	Int64	Creation time. Example: 1735095122

CCMChartEntry

CCMChartEntry
Referenced by the following interfaces: [DescribeCCMCharts](#)

name	required	NULL allowed	type	description
ChartId	yes	no	Int64	Monitoring chart ID. Example: 1
ViewId	yes	no	Int64	Group view ID. Example: 1
ChartName	yes	no	String	Name of the monitoring chart. Example: test
ChartType	yes	no	Int64	Type of the monitoring chart. 1 Detail view. 2 Aggregate view. Example: 1
ProductType	yes	no	Int64	Product type. 1 Basic monitoring. 2 Custom monitoring. Example: cmv
AttributId	yes	no	Int64	Metric ID. Example: 1
Aggregation	yes	no	Int64	Aggregation method. 0 SUM. 1 AVG. 2 MAX. 3 MIN. Example: 1
Description	yes	no	String	Description. Example: test
CreatorId	yes	no	UInt64	Creator ID. Example: 1
CreateTime	yes	no	String	Creation time. Example: 1735041205
UpdaterId	yes	no	UInt64	Updater ID. Example: 1
UpdateTime	yes	no	String	Update time. Example: 1735041205
AttributeName	yes	yes	String	Metric name. Example: Testing
AttributeUniqueName	yes	yes	String	Unique English name of the metric. Example: qwer_123
UnitName	yes	yes	String	Metric unit name. Example: test

MidQueryCondition

[DescribeMidDimensionValueList](#) query conditions
Referenced by the following interfaces: [DescribeMidDimensionValueList](#), [DescribeStatisticData](#)

name	required	NULL allowed	type	description
Key	yes	no	String	Dimension. Example: qwer
Operator	yes	no	String	Operator. Valid values: eq (equal to), ne (not equal to), in. Example: =
Value	yes	no	Array of String	Dimension value. If Operator is eq or ne, only the first element will be used. Example: 10

MiniDashboardAlarmInfo

MiniDashboard AlarmInfo
Referenced by the following interfaces: [DescribeMiniDashboardAlarmInfo](#)

name	required	NULL allowed	type	description
Dimension	no	no	String	Dimension information. Example: {"name":"instanceId","value":"1"}
NoPolicy	no	no	Bool	No Alarm Policy. Example: true
DefaultPolicyWithoutNotice	no	no	String	Default Policy without Notification Rule. Example: policy-abcdef

MonitorTypeNamespace

Policy type
Referenced by the following interfaces: [DescribeAlarmHistories](#)

name	required	NULL allowed	type	description
MonitorType	yes	no	String	Monitoring type. Example: MT_QCE
Namespace	yes	no	String	Policy type value. Example: cmv,device

AlarmHistoryMetric

Metric information of alarm records
Referenced by the following interfaces: [DescribeAlarmHistories](#), [DescribeMiniDashboardAlarmInfo](#)

name	required	NULL allowed	type	description
QceNamespace	yes	no	String	Queries the namespace used by the data. Example: qce/cvm
MetricName	yes	no	String	Metric name. Example: CpuUsage
Period	yes	no	Int64	Statistical period. Example: 60
Value	yes	no	String	Value that triggers the alarm. Example: 10
Tooltip	yes	yes	MetricTooltip	Explanation of the metric. Example: View
Description	yes	no	String	Display name of the metric. Example: CPU Utilization

StrategyEntry

StrategyEntry



Referenced by the following interfaces: DescribeCCMGroupViewStrategy, DescribeStrategies

name	required	NULL allowed	type	description
StrategyId	yes	no	Int64	The ID of the alarm policy. Example: 10
StrategyName	yes	no	String	The name of the alarm policy. Example: qwer
ReceiverType	yes	no	Int64	Alarm reception type. Example: 1
ReceiverId	yes	no	Array of UInt64	List of IDs of alarm recipient users or user groups. Example: 1234
EffectiveStartTime	yes	no	String	The start time of the validity period. Example: 1734953008
EffectiveEndTime	yes	no	String	The end time of the validity period. Example: 1734953808
AlarmChannel	yes	no	Array of String	Alarm channel list. Valid values: "SMS", "SITE", "EMAIL", "CALL", and "WECHAT". Example: sms
CallbackUrl	yes	no	String	Alarm callback address. Example: http://test.com
Description	yes	no	String	Description. Example: Testing
CreatorId	yes	no	UInt64	Creator ID. Example: 1
CreateTime	yes	no	String	Creation time. Example: 1735179378
UpdaterId	yes	no	UInt64	ID of the user who updated it. Example: 10
UpdateTime	yes	no	String	Update time. Example: 1735179378
IsStart	yes	no	Int64	Whether to start it. 0: stopping. 1: starting. Example: 1
MixType	yes	no	UInt64	Type of alarm objects. 1: server. 2: view. Example: 1
MixSubType	yes	no	Int64	Alarm object subtype. When MixType is 2, then Midd is a list of view IDs. When Midd is an empty array [], then the background will automatically query the default view ID. When MixType is 1 (server), if MixSubType is 1, Midd can be left empty. If MixSubType is 2, then Midd is a list of server IDs, which can contain more than one server ID.
Alarm	yes	no	Array of StrategyEntryAlarm	Alarm rule list. Example: view
Midd	yes	no	Array of Int64	List of alarm object type IDs. Example: 1
Ip	yes	no	Array of String	If MixType is the server type and the subtype is the specified server ID, then the Ip list exists. Example: 127.0.0.1

DescribeEventPolicyConfig

DescribeEventPolicyConfig

Referenced by the following interfaces: DescribeEventPolicyConfig

name	required	NULL allowed	type	description
EventID	yes	no	String	Event ID. Example: 1234
ProductName	yes	no	String	Product name. Example: cvm
ProductCName	yes	no	String	The product name. Example: cvm
ProductCNName	yes	no	String	The name of the product. Example: CVM instance
EventName	yes	no	String	Event name. Example: ReadOnly
EventENName	yes	no	String	English name of an event. Example: ReadOnly
EventCNName	yes	no	String	The name of an event. Example: Disk read-only
Dimensions	yes	yes	Array of DescribeEventPolicyConfigDimension	Dimension. Example: View

CCMGroupViewEntry

CCMGroupViewEntry

Referenced by the following interfaces: DescribeCCMGroupView

name	required	NULL allowed	type	description
ViewId	yes	yes	Int64	Group view ID. Example: 1
ViewName	yes	yes	String	Group view name. Example: cvm_device
IsAuto	yes	yes	Int64	Whether the group view automatically binds the metric. 0: no. 1: yes. Example: 1

DescribePolicyInfoByInstanceConditionsTemp

DescribePolicyInfoByInstanceConditionsTemp

Referenced by the following interfaces: DescribePolicyInfoByInstance

name	required	NULL allowed	type	description
GroupID	yes	yes	Int64	Group ID. Example: 1234
GroupName	yes	no	String	Group name. Example: Testing
ViewName	yes	no	String	View name. Example: cvm_device
Remark	yes	no	String	Description. Example: Testing
LastEditUin	yes	yes	Int64	UIN of the last editor. Example: 123456
IsJoinRule	yes	yes	Int64	Whether the AND rule is used. Example: 1
InsertTime	yes	yes	Int64	Creation time. Example: 1735095122
UpdateTime	yes	yes	Int64	Update time. Example: 1735095122

CustomCallbackTplMatcher

Matcher for custom notification content templates.

Referenced by the following interfaces: CreateNoticeContentTpl, DescribeNoticeContentTpl, ModifyNoticeContentTpl

name	required	NULL allowed	type	description
MatchingStatus	yes	no	Array of String	Matching status. Valid values: Invalid, Trigger, and Recovery. Example: Trigger
Template	yes	no	CustomCallbackNoticeTpl	Template configuration Example: view

TransLogInstance

List of instances returned by DescribeTransLog

Referenced by the following interfaces: DescribeInstanceGroup

name	required	NULL allowed	type	description
Dimensions	yes	yes	String	Dimension of the instance. Example: qwer
UniquedId	yes	yes	String	Unique ID of the instance. Example: eqeq-czda
IsShielded	yes	yes	Int64	Shielding status. 1: shielding enabled. 0: no shielding. Example: 1
Region	yes	yes	String	Region. Example: gz

DescribeSortObjectListDimension

Dimension of the DescribeSortObjectList API. It refers to a dimension, including the dimension name and dimension value.

Referenced by the following interfaces: DescribeSortObjectList



name	required	NULL allowed	type	description
Name	yes	no	String	Dimension name. Example: appid
Value	yes	no	String	The value of the dimension. Example: 1

AttributeldDeleteOutput

AttributeldDeleteOutput
Referenced by the following interfaces: DeleteAttribute, DeleteAttributes

name	required	NULL allowed	type	description
DeleteCount	yes	no	Int64	Number of deletions. Example: 1
Attributeld	yes	no	Array of UInt64	Attribute ID. Example: 10

DescribePolicyConditionListCondition

Policy conditions returned by the DescribePolicyConditionList API
Referenced by the following interfaces: DescribePolicyConditionList

name	required	NULL allowed	type	description
PolicyViewName	yes	no	String	Policy view name. Example: cvm.device
EventMetrics	yes	yes	Array of DescribePolicyConditionListEventMetric	Event alarm conditions Example: View
IsSupportMultiRegion	yes	no	Bool	Whether multiple regions are supported. Example: true
Metrics	yes	yes	Array of DescribePolicyConditionListMetric	Metric alarm conditions. Example: View
Name	yes	no	String	Policy type name. Example: test
SortId	yes	no	Int64	Sorting ID. Example: 1
SupportDefault	yes	no	Bool	Whether the default policy is supported. Example: true
SupportRegions	yes	yes	Array of String	List of regions that support this policy type. Example: ["gz"]
DeprecatingInfo	no	yes	String	Expiration Information Example: qwer

DescribeProductEventListEventsGroupInfo

GroupInfo in Events returned by the DescribeProductEventList API
Referenced by the following interfaces: DescribeProductEventList

name	required	NULL allowed	type	description
GroupId	yes	yes	Int64	Policy ID. Example: 1234
GroupName	yes	yes	String	Policy name. Example: Testing

TagInstance

Instance tag information of the alarm policy
Referenced by the following interfaces: DescribeAlarmPolicies, DescribeAlarmPolicy

name	required	NULL allowed	type	description
Key	yes	yes	String	Tag key. Example: tag
Value	yes	yes	String	Tag value. Example: value
InstanceSum	yes	yes	Int64	Number of instances. Example: 1
ServiceType	yes	yes	String	Product type. For example, cvm. Example: cvm
RegionId	yes	yes	String	Region ID. Example: 1
BindingStatus	yes	yes	Int64	Binding status. 2: bound; 1: binding. Example: 2
TagStatus	yes	yes	Int64	Tag status. 2: existent; 1: nonexistent. Example: 2

DescribePolicyGroupInfoEventCondition

Event alarm conditions output by the policy query
Referenced by the following interfaces: DescribePolicyGroupInfo, DescribePolicyGroupList

name	required	NULL allowed	type	description
EventId	yes	no	Int64	Event ID. Example: 10
RuleId	yes	no	Int64	Event alarm rule ID. Example: 10
EventShowName	yes	no	String	Event name. Example: ReadOnly
AlarmNotifyPeriod	yes	no	Int64	Alarm sending period in seconds. The value u003c0 indicates that no alarm will be triggered. The value 0 indicates that an alarm is triggered only once. The value >0 indicates that an alarm is triggered at the interval of triggerTime. Example: 5
AlarmNotifyType	yes	no	Int64	Alarm sending and converging type. The value 0 indicates that alarms are sent consecutively. The value 1 indicates that alarms are sent exponentially. Example: 1

PCLMDimensionAnalysisResultData

Dimension analysis results data.
Referenced by the following interfaces: DescribeDimensionAnalysisData

name	required	NULL allowed	type	description
Current	yes	no	String	Dimension data. Example: qwer
Granularity	yes	no	Int64	Granularity. Example: 1

PCLMMetricCustomItem

Compound metric configurations for the log monitoring metric set.
Referenced by the following interfaces: CLMDDescribeMetricSets

name	required	NULL allowed	type	description
Formula	yes	no	String	Expression. Example: ("cluster_name" <= dxhsssss')
Name	yes	no	String	Metric name. Example: Testing
Desc	yes	no	String	Metric description name. Example: Testing
MetricSetCID	no	no	String	Metric set CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter) Example: qwer
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter) Example: qwer

DescribeAgentStatusHistory

DescribeAgentStatusHistory
Referenced by the following interfaces: DescribeAgentStatusHistory

name	required	NULL allowed	type	description
Timestamp	yes	no	Datetime_iso	Timestamp. Example: 2019-11-29T12:30:13+08:00
Status	yes	no	Int64	State. Example: 1



ServerInfo

ServerInfo
Referenced by the following interfaces: DescribeServers

name	required	NULL allowed	type	description
ServerId	yes	no	UInt64	Server ID. Example: 1
ServerName	yes	no	String	Server name. Example: qwer
Ip	yes	no	String	Server private IP address. Example: 127.0.0.1
IdcId	yes	no	Int64	Region ID. Example: 10
IdcName	yes	no	String	The region name. Example: qwer

DescribeBaseMetricsForConsoleFontEndData

DescribeBaseMetricsForConsoleFontEndData
Referenced by the following interfaces: DescribeBaseMetricsForConsoleFontEnd

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace. Example: QCE/CVM
MetricName	yes	no	String	Metric name. Example: CpuUsage
MetricCNName	yes	no	String	Metric name. Example: CPU Usage
MetricENName	yes	no	String	English name of metrics. Example: CpuUsage
Dimensions	yes	no	String	Dimension. Example: ("unInstanceId":"ins-xxx")
Unit	yes	no	String	Unit. Example: %
UnitCNName	yes	no	String	Unit name. Example: Percentage
PeriodAndStartTypes	yes	yes	Array of DescribeBaseMetricsDataPeriod	Period and statistical method. Example: view
Meaning	yes	yes	Array of DescribeBaseMetricsDataMeaning	Metric description. Example: view

AttributeServerInfoOutput

AttributeServerInfoOutput
Referenced by the following interfaces: DescribeAttributeAllServer, DescribeIdcServer

name	required	NULL allowed	type	description
ServerId	yes	yes	UInt64	Server ID. Example: 1
ServerName	yes	yes	String	Server name. Example: test
Ip	yes	yes	String	Server IP address. Example: 127.0.0.1
IdcId	yes	yes	Int64	Region ID. Example: 1
IdcName	yes	yes	String	The region name. Example: test

PolicyGroupItem

PolicyGroups returned by the DescribeInstanceGroup API.
Referenced by the following interfaces: DescribeInstanceGroup

name	required	NULL allowed	type	description
GroupId	yes	yes	Int64	Policy ID. Example: 1234
GroupName	yes	yes	String	Policy name. Example: Testing

PCLMLogFilterRule

Metric set filtering rule for log monitoring.
Referenced by the following interfaces: CLMDescribeMetricSets

name	required	NULL allowed	type	description
Relation	yes	no	Int64	Relationship: 1: AND 2: OR. Example: 10
Field	yes	no	String	Field name. Example: timeField
Operator	yes	no	String	Filter operator: Numeric fields support: gt lt ge le eq ne in. Character fields support: eq ne in contains. Example: =
Value	yes	no	String	Filter operation value. Example: 10
MetricSetCID	no	no	String	Metric set CID (only for output parameter; leave it empty for input parameter). Example: cid-xxx
CreatedAt	no	no	String	Creation time (only for output parameter; leave it empty for input parameter) Example: qwer
UpdatedAt	no	no	String	Update time (only for output parameter; leave it empty for input parameter) Example: qwer

DescribeProductEventListOverView

OverView object returned by the DescribeProductEventList API
Referenced by the following interfaces: DescribeProductEventList

name	required	NULL allowed	type	description
StatusChangeAmount	yes	yes	Int64	Number of state change events. Example: 1
UnConfigAlarmAmount	yes	yes	Int64	Number of events corresponding to which alarm states are not configured. Example: 1
UnNormalEventAmount	yes	yes	Int64	Number of abnormal events. Example: 1
UnRecoverAmount	yes	yes	Int64	Number of unrecovered events. Example: 1

AlarmNotice

Alarm notification template details
Referenced by the following interfaces: DescribeAlarmNotice, DescribeAlarmNotices, DescribeAlarmPolicies, DescribeAlarmPolicy

name	required	NULL allowed	type	description
Id	yes	yes	String	ID of the alarm notification template. Example: 12345
Name	yes	yes	String	Name of the alarm notification template. Example: Default notification
UpdatedAt	yes	yes	String	Last modification time. Example: 2020-11-16 13:56:56
UpdatedBy	yes	yes	String	Last editor. Example: 1500000688
NoticeType	yes	yes	String	Alarm notification type. ALARM=Notification not recovered. OK=Notification recovered. ALL=All notifications. Example: ALL
UserNotices	yes	yes	Array of UserNotice	User notification list. Example: view
URLNotices	yes	yes	Array of URLNotice	Callback notification list. Example: view
IsPreset	yes	yes	Int64	Whether it is the system default notification template. 0: no. 1: Yes. Example: 1
NoticeLanguage	yes	yes	String	Notification language Example: zh-CN
PolicyIds	no	yes	Array of String	List of alarm policy IDs bound to the alarm notification template. Example: ["policy-abc123"]



name	required	NULL allowed	type	description
AMPConsumerId	no	yes	String	Background amp consumer ID. Example: Consumer-asafast
ExtraChannels	yes	yes	Array of String	Other non-public notification channels. Example: ["TSS"]
BigCustomerNotices	no	yes	Array of BigCustomerNotice	BigCustomerNotices Example: View

CgrpInstanceNode

Group Instance details.
Referenced by the following interfaces: [CreateInstances](#), [DeleteInstances](#), [DescribeInstance](#)

name	required	NULL allowed	type	description
Id	no	yes	String	Auto increment ID. Example: 1234
InstanceId	yes	no	String	Instance ID. Example: ins-0Gjv9mo
InstanceName	yes	no	String	Instance name. Example: test
TypeId	yes	no	String	The instance type. Example: cvm_device
Region	yes	no	String	Region. Example: gz
ModuleId	yes	no	Int64	Leaf group ID. Example: 1
ModuleName	yes	no	String	Leaf group name. Example: qwer
L1Id	no	yes	Int64	Level-1 group ID. Example: 1
L2Id	no	yes	Int64	Level-2 group ID. Example: 1
L3Id	no	yes	Int64	Level-3 group ID. Example: 1
AppId	no	yes	Int64	appId Example: 1234
Uin	no	yes	String	Uin Example: 123456
SubUin	no	yes	String	SubUin Example: 123456
Group	no	yes	Array of CgrpInstanceGroupNode	Group array. Example: View

DescribeStorageDurationData

DescribeStorageDurationData
Referenced by the following interfaces: [DescribeStorageDuration](#)

name	required	NULL allowed	type	description
Period	yes	no	Int64	Interval. Example: 5
Duration	yes	no	Int64	Duration. Example: 10

InstanceGroupInfo

InstanceGroupInfo API returned by the [DescribeInstanceGroup](#) API.
Referenced by the following interfaces: [DescribeInstanceGroup](#)

name	required	NULL allowed	type	description
GroupName	yes	yes	String	Instance group name. Example: Testing
InstanceGroupId	yes	yes	Int64	Instance group ID. Example: 1234
InstanceSum	yes	yes	Int64	Number of instances. Example: 10
ViewName	yes	yes	String	View name/strategy type. Example: cvm_device
InsertTime	yes	yes	Int64	Creation time. Example: 1735129241
UpdateTime	yes	yes	Int64	Update time. Example: 1735129241
LastEditUin	yes	yes	String	UIN of the last user who updated it. Example: 123456

DescribePolicyQuotaV3ResponseData

DescribePolicyQuotaV3ResponseData
Referenced by the following interfaces: [DescribePolicyQuota](#)

name	required	NULL allowed	type	description
ViewName	yes	no	String	View. Example: cvm_device
IsQuotaByProject	yes	no	Bool	Whether it is a project quota. Example: true
QuotaList	yes	yes	Array of DescribePolicyQuotaV3ResponseDataQuotaList	List of quotas. Example: View
Quota	yes	yes	DescribePolicyQuotaV3ResponseDataQuota	The quota. Example: View

InstanceGroup

InstanceGroup In Alarms returned by the [DescribeBasicAlarmList](#) API
Referenced by the following interfaces: [DescribeBasicAlarmList](#)

name	required	NULL allowed	type	description
InstanceGroupId	yes	yes	Int64	Instance group ID. Example: 1234
InstanceGroupName	yes	yes	String	Instance group name. Example: Testing

EventCondition

Event alarm conditions
Referenced by the following interfaces: [DescribeConditionsTemplateList](#), [DescribeRecommendedTemplate](#)

name	required	NULL allowed	type	description
AlarmNotifyPeriod	yes	no	String	Alarm notification frequency. Example: 5
AlarmNotifyType	yes	no	String	Preddefined repeated notification policy. 0: One-time alarm; 1: exponential alarm; 2: consecutive alarm.
EventID	yes	no	String	Event ID. Example: qwer
EventDisplayName	yes	no	String	Displayed event name. Example: test
RuleID	yes	no	String	Rule ID. Example: qwer

DescribePolicyGroupInfoReceiverInfo

Alarm recipient information output by the policy query
Referenced by the following interfaces: [DescribePolicyGroupInfo](#), [DescribePolicyGroupList](#)

name	required	NULL allowed	type	description
ReceiverGroupList	yes	no	Array of Int64	List of alarm recipient group IDs. Example: [1234]
ReceiverUserList	yes	no	Array of Int64	List of alarm recipient IDs. Example: [1234]
StartTime	yes	no	Int64	Alarm period start time. Range: (0,86400), Remove the date after converting the time from UNIX timestamp to UTC+8 time. For example, 7200 means "10:00". Example: 1734953008
EndTime	yes	no	Int64	End time of the alarm period. The meaning is the same as that of StartTime. Example: 1734953808



name	required	NULL allowed	type	description
ReceiverType	yes	no	String	Recipient type. Valid values: group (recipient group) and user (recipient). Example: group
NotifyWay	yes	no	Array of String	Alarm notification method. Valid values: "SMS", "SITE", "EMAIL", "CALL", and "WECHAT". Example: sms
UidList	yes	yes	Array of Int64	UID of the alarm call recipient. Example: [1234]
RoundNumber	yes	no	Int64	Number of alarm call rounds. Example: [1234]
RoundInterval	yes	no	Int64	Intervals of alarm call rounds in seconds. Example: 60
PersonInterval	yes	no	Int64	Alarm call intervals for individuals in seconds. Example: 60
NeedSendNotice	yes	no	Int64	Whether to send an alarm call delivery notice. The value 0 indicates that no notice needs to be sent. The value 1 indicates that a notice needs to be sent. Example: 0
SendFor	yes	no	Array of String	Alarm call notification time. Valid values: OCCUR (indicating that a notice is sent when the alarm is triggered) and RECOVER (indicating that a notice is sent when the alarm is recovered). Example: OCCUR
RecoverNotify	yes	no	Array of String	Notification method when an alarm is recovered. Valid value: SMS. Example: SMS

DataPoint

Monitoring data point

Referenced by the following interfaces: GetMonitorData

name	required	NULL allowed	type	description
Dimensions	yes	no	Array of Dimension	Combination of instance object dimensions. Example: View
Timestamps	yes	no	Array of Float	Timestamp array that indicates the points in time that have data. A missing timestamp has no data points. Example: 31415513
Values	yes	no	Array of Float	Metric value array, which corresponds to the values returned for Timestamps. Example: 31314

BigCustomerNotice

Major client notification.

Referenced by the following interfaces: CreateAlarmNotice, DescribeAlarmNotice, DescribeAlarmNotices, DescribeAlarmPolicies, DescribeAlarmPolicy

name	required	NULL allowed	type	description
NeedPushChatGroup	yes	no	Int64	Whether to push to the after-sales group of major clients. 0: no. 1: yes. Example: 1
StartTime	yes	no	Int64	Number of seconds since notification start time 00:00:00 (Value range: 0-86399). Example: 0
EndTime	yes	no	String	Number of seconds since notification end time 00:00:00 (Value range: 0-86399). Example: 3600

DescribeAbnormalObjectsEventObject

Product event alarm exception object returned by the DescribeAbnormalObjects API.

Referenced by the following interfaces: DescribeAbnormalObjects

name	required	NULL allowed	type	description
Status	yes	no	Int64	Alarm status. Example: 1
Content	yes	no	String	The alarm content. Example: qewriq
InstanceId	yes	no	String	Instance ID. Example: ins-00jv9lmo
Dimensions	yes	no	String	Dimension combination. JSON string. Example: ("InstanceId":"ins-xxx")
AbnormalStatus	yes	no	String	Alarm status: "abnormal" indicates that the alarm has not been recovered, and "warning" indicates that the alarm has been recovered. Example: abnormal
FirstOccurTime	yes	no	String	Time of first occurrence. Example: 1735041205
LastOccurTime	yes	no	String	Time of last occurrence. Example: 1735041205
UniqueId	yes	no	String	Dimension combination md5. Example: 1314edae411314
GroupId	yes	yes	Int64	Policy group ID. Example: 1234
GroupName	yes	yes	String	Policy group name. Example: Testing
ProjectId	yes	yes	Int64	Project ID. Example: 1
ProductCName	yes	no	String	The name of the product. Example: Cloud Virtual Machine
ProductENName	yes	no	String	English name of the product. Example: cvm
EventENName	yes	no	String	Event name. Example: ReadOnly
EventCName	yes	no	String	The name of the event. Example: Disk read-only
EventId	yes	no	Int64	Product event ID. Example: 1
Region	yes	no	String	Region. Example: gz
EventUniqueId	yes	no	String	Product dimension combination md5. Example: eqeq-caba

InstanceGroups

Instance group of alarm object

Referenced by the following interfaces: DescribeAlarmHistories, DescribeMiniDashboardAlarmInfo

name	required	NULL allowed	type	description
Id	yes	no	Int64	Instance group ID. Example: 1
Name	yes	no	String	Instance group name. Example: Testing



ErrorCode

Feature Description

If there is an Error field in the response, it means that the API call failed. For example:

```
{
  "Response": {
    "Error": {
      "Code": "AuthFailure.SignatureFailure",
      "Message": "The provided credentials could not be validated. Please check your signature is correct."
    },
    "RequestId": "ed93f3cb-f35e-473f-b9f3-0d451b8b79c6"
  }
}
```

Code in Error indicates the error code, and Message indicates the specific information of the error.

Error Code List

Common Error Codes

Error codes	Description
AuthFailure.InvalidSecretId	Invalid key (not a Cloud API key type).
AuthFailure.MFAFailure	MFA failed.
AuthFailure.SecretIdNotFound	Key does not exist. Check if the key has been deleted or disabled in the console, and if not, check if the key is correctly entered. Note that whitespaces should not exist before or after the key.
AuthFailure.SignatureExpire	Signature expired. Timestamp and server time cannot differ by more than five minutes. Please ensure your current local time matches the standard time.
AuthFailure.SignatureFailure	Invalid signature. Signature calculation error. Please ensure you've followed the signature calculation process described in the Signature API documentation.
AuthFailure.TokenFailure	Token error.



Error codes	Description
AuthFailure.UnauthorizedOperation	The request does not have CAM authorization.
DryRunOperation	DryRun Operation. It means that the request would have succeeded, but the DryRun parameter was used.
FailedOperation	Operation failed.
InternalError	Internal error.
InvalidAction	The API does not exist.
InvalidParameter	Incorrect parameter.
InvalidParameterValue	Invalid parameter value.
LimitExceeded	Quota limit exceeded.
MissingParameter	A parameter is missing.
NoSuchVersion	The API version does not exist.
RequestLimitExceeded	The number of requests exceeds the frequency limit.
ResourceInUse	Resource is in use.
ResourceInsufficient	Insufficient resource.
ResourceNotFound	The resource does not exist.
ResourceUnavailable	Resource is unavailable.
UnauthorizedOperation	Unauthorized operation.
UnknownParameter	Unknown parameter.
UnsupportedOperation	Unsupported operation.
UnsupportedProtocol	HTTPS request method error. Only GET and POST requests are supported.
UnsupportedRegion	API does not support the requested region.

Service Error Codes

Error codes	Description
FailedOperation.DbRecordUpdateFailed	Failed to update the database record.



Error codes	Description
InvalidParameterValue	Invalid parameter value.
FailedOperation.DataQueryFailed	Failed to query the data.
FailedOperation.AlertTriggerRuleDeleteFailed	Failed to delete the trigger condition.
FailedOperation.DuplicateName	The name already exists.
InvalidParameter.InvalidParameterParam	Invalid parameter.
ResourceUnavailable	The resource is unavailable.
FailedOperation.DivisionByZero	The dividend is zero.
InvalidParameterValue.VersionMismatch	Inconsistent versions.
InternalError.ExeTimeout	Execution timed out.
FailedOperation.AlertPolicyDeleteFailed	Failed to delete the alarm policy.
ResourcesSoldOut	The resources have been sold out.
LimitExceeded.MetricQuotaExceeded	Quota limit on metrics is reached. Requests containing unregistered metrics are prohibited.
FailedOperation.DruidColumnNotFound	The druid table field does not exist.
FailedOperation.DbTransactionCommitFailed	Failed to submit the database transaction.
FailedOperation.DruidTableNotFound	The druid table does not exist.
UnsupportedOperation	Unsupported operation.
FailedOperation.DimQueryRequestFailed	Failed to query the service in the request dimension.
UnauthorizedOperation	Unauthorized operation.
FailedOperation.AlertFilterRuleDeleteFailed	Failed to delete the filter rule.
InvalidParameterValue.InvalDashboardNameExists	The dashboard name already exists.
FailedOperation.DruidQueryFailed	Failed to query analysis data.
FailedOperation.DbRecordCreateFailed	Failed to create the database record.
FailedOperation.AlertPolicyCreateFailed	Failed to create the alarm policy.
ResourceInUse	The resource is in use.



Error codes	Description
InternalError	Internal error.
FailedOperation.DataTableNotFound	The data table doesn't exist.
FailedOperation	Operation failed.
InvalidParameter	Invalid parameter.
FailedOperation.DbRecordDeleteFailed	Failed to delete the database record.
LimitExceeded	The quota limit has been reached.
ResourceInsufficient	Insufficient resource.
FailedOperation.DbTransactionBeginFailed	Failed to start the database transaction.
FailedOperation.AlertPolicyModifyFailed	Failed to modify the alarm policy.
DryRunOperation	DryRun operation, which means the DryRun parameter is passed in yet the request will still be successful.
FailedOperation.AlertPolicyDescribeFailed	Failed to query the alarm policy.
FailedOperation.ServiceNotEnabled	The service is not enabled and can be used only after being enabled.
UnknownParameter	Unknown parameter error.
MissingParameter	Missing parameter.
InvalidParameter.InvalidParameter	Invalid parameter.
FailedOperation.DbQueryFailed	Failed to query the database.
FailedOperation.DataColumnNotFound	The data table field doesn't exist.
ResourceNotFound	The resource does not exist.
AuthFailure.UnauthorizedOperation	The request is not authorized. Please refer to the CAM documentation for the description of authentication.



version(2017-03-12)

API overview

API version

V3

Cloud Monitor API

Interface name	Interface function
DescribeBaseMetrics	DescribeBaseMetrics
GetMonitorData	GetMonitorData

CallingMethod signaturev1

Converge Cloud authenticates each access request, i.e. each request needs to include authentication information (Signature) in the common parameters to verify the identity of the requester.

The Signature is generated by the security credentials which include SecretId and SecretKey. If you don't have the security credentials yet, go to the API Key page to apply for them; otherwise, you cannot invoke the API.

1. Applying for Security Credentials

Before using the API for the first time, go to the API Key page to apply for security credentials.

Security credentials consist of SecretId and SecretKey:

- SecretId is used to identify the API requester.
- SecretKey is used to encrypt the signature string and verify it on the server.
- **You must keep your security credentials private and avoid disclosure.**

You can apply for the security credentials through the following steps:

1. Log in to the Converge Cloud Console.
2. Go to the Cloud API Key page.
3. On the API Key Management page, click Create Key to create a SecretId/SecretKey pair.

Note: Each account can have up to two pairs of SecretId/SecretKey.

2. Generating a Signature

With the SecretId and SecretKey, a signature can be generated. The following describes how to generate a signature:

Assume that the SecretId and SecretKey are:

- SecretId: AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE
- SecretKey: Gu5t9xGARNpq86cd98joQYCN3EXAMPLE

Note: This is just an example. For actual operations, please use your own SecretId and SecretKey.

Take the Cloud Virtual Machine's request to view the instance list (DescribeInstances) as an example. When

you invoke this API, the request parameters may be as follows:

Parameter name	Description	Parameter value
Action	Method name	DescribeInstances
SecretId	Key ID	AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE
Timestamp	Current timestamp	1465185768
Nonce	Random positive integer	11886
Region	Region where the instance is located	luzon
InstanceIds.0	ID of the instance to query	ins-09dx96dg
Offset	Offset	0
Limit	Allowed maximum output	20
Version	API version number	2017-03-12

2.1. Sorting Parameters

First, sort all the request parameters in an ascending lexicographical order (ASCII code) by their names.

Notes: (1) Parameters are sorted by their names instead of their values; (2) The parameters are sorted based on ASCII code, not in an alphabetical order or by values. For example, InstanceIds.2 should be arranged after InstanceIds.12. You can complete the sorting process using a sorting function in a programming language, such as the ksort function in PHP. The parameters in the example are sorted as follows:

```
{
  'Action' : 'DescribeInstances',
  'InstanceIds.0' : 'ins-09dx96dg',
  'Limit' : 20,
  'Nonce' : 11886,
  'Offset' : 0,
  'Region' : 'luzon',
  'SecretId' : 'AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE',
  'Timestamp' : 1465185768,
  'Version': '2017-03-12',
}
```

When developing in another programming language, you can sort these sample parameters and it will work as long as you obtain the same results.

2.2. Concatenating a Request String

This step generates a request string.

Format the request parameters sorted in the previous step into the form of "parameter name"="parameter value". For example, for the Action parameter, its parameter name is "Action" and its parameter value is "DescribeInstances", so it will become Action=DescribeInstances after formatted.

Note: The "parameter value" is the original value but not the value after URL encoding.

Then, concatenate the formatted parameters with "&". The resulting request string is as follows:

```
Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Timestamp=1465185768&Version=2017-03-12
```

2.3. Concatenating the Signature Original String

This step generates a signature original string.

The signature original string consists of the following parameters:

1. HTTP method: POST and GET modes are supported, and GET is used here for the request. Please note that the method name should be in all capital letters.
2. Request host: the domain name of the request to view the list of instances (DescribeInstances) is cvm.convergecloud.com. The actual request domain name varies by the module to which the API belongs. For more information, see the instructions of the specific API.
3. Request path: The request path in the current version of Cloud API is fixed to / .
4. Request string: the request string generated in the previous step.

The concatenation rule of the signature original string is: Request method + request host + request path + ? + request string

The concatenation result of the example is:

```
GETcvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Timestamp=1465185768&Version=2017-03-12
```

2.4. Generating a Signature String

This step generates a signature string.

First, use the HMAC-SHA1 algorithm to sign the signature original string obtained in the previous step, and then encode the generated signature using Base64 to obtain the final signature.

The specific code is as follows with the PHP language being used as an example:



```
$secretKey = 'Gu5t9xGARNpq86cd98joQYCN3EXAMPLE';  
$srcStr = 'GETcvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit  
=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPL  
E&Timestamp=1465185768&Version=2017-03-12';  
$signStr = base64_encode(hash_hmac('sha1', $srcStr, $secretKey, true));  
echo $signStr;
```

The final signature is:

```
EliP9YW3pW28FpsEdkXt/+WcGeI=
```

When developing in another programming language, you can sign and verify the original in the example above and it works as long as you get the same results.

3. Encoding a Signature String

The generated signature string cannot be directly used as a request parameter and must be URL encoded.

For example, if the signature string generated in the previous step is EliP9YW3pW28FpsEdkXt/+WcGeI= , the final signature string request parameter (Signature) is EliP9YW3pW28FpsEdkXt%2f%2bWcGeI%3d, which will be used to generate the final request URL.

****Note:** If your request method is GET, or the request method is POST and the Content-Type is application/x-www-form-urlencoded, then all the request parameter values need to be URL encoded (except the parameter key and the symbol of =) when sending the request. Non-ASCII characters need to be encoded with UTF-8 before URL encoding. ******

Note: The network libraries of some programming languages automatically URL encode all parameters, in which case there is no need to URL encode the signature string; otherwise, two rounds of URL encoding will cause the signature to fail.

Note: Other parameter values also need to be encoded using RFC 3986. Use %XY in percent-encoding for special characters such as Chinese characters, where "X" and "Y" are hexadecimal characters (0-9 and uppercase A-F), and using lowercase will cause an error.

4. Signature Failure

The following situational error codes for signature failure may occur. Please resolve the errors accordingly.

Error code	Error description
AuthFailure.SignatureExpire	The signature is expired



Error code	Error description
AuthFailure.SecretIdNotFound	The key does not exist
AuthFailure.SignatureFailure	Signature error
AuthFailure.TokenFailure	Token error
AuthFailure.InvalidSecretId	Invalid key (not a Cloud API key type)

5. Signature Demo

When calling API 3.0, you are recommended to use the corresponding Converge Cloud SDK 3.0, which encapsulates the signature process, enabling you to focus on only the specific APIs provided by the product when developing. See SDK Center for more information. Currently, the following programming languages are supported:

- Python
- Java
- PHP
- Go
- Node

To further explain the signing process, we will use a programming language to implement the process described above. The request domain name, API and parameter values in the sample are used here. This goal of this example is only to provide additional clarification for the signature process, please see the SDK for actual usage.

The final output URL might be: `https://cvm.convergecloud.com/?Action=DescribeInstances&InstanceIds.0=ins-09dx96dg&Limit=20&Nonce=11886&Offset=0&Region=luzon&SecretId=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE&Signature=Elip9YW3pW28FpsEdkXt%2F%2BWcGeI%3D&Timestamp=1465185768&Version=2017-03-12`

Note: The key in the example is fictitious, and the timestamp is not the current time of the system, so if this URL is opened in the browser or called using commands such as curl, an authentication error will be returned: Signature expired. In order to get a URL that can work properly, you need to replace the SecretId and SecretKey in the example with your real credentials and use the current time of the system as the Timestamp.

Note: In the example below, even if you use the same programming language, the order of the parameters in the URL may be different for each execution. However, the order does not matter, as long as all the parameters are included in the URL and the signature is calculated correctly.

Note: The following code is only applicable to API 3.0. It cannot be directly used in other signature processes. Even with an older API, signature calculation errors may occur due to the differences in details. Please refer to the corresponding documentation.

Java

```
import java.io.UnsupportedEncodingException;
import java.net.URLEncoder;
import java.util.Random;
import java.util.TreeMap;
import javax.crypto.Mac;
import javax.crypto.spec.SecretKeySpec;
import javax.xml.bind.DatatypeConverter;

public class CloudAPIDemo {
    private final static String CHARSET = "UTF-8";

    public static String sign(String s, String key, String method) throws Exception {
        Mac mac = Mac.getInstance(method);
        SecretKeySpec secretKeySpec = new SecretKeySpec(key.getBytes(CHARSET), mac.getAlgorithm());
        mac.init(secretKeySpec);
        byte[] hash = mac.doFinal(s.getBytes(CHARSET));
        return DatatypeConverter.printBase64Binary(hash);
    }

    public static String getStringToSign(TreeMap<String, Object> params) {
        StringBuilder s2s = new StringBuilder("GETcvm.convergecloud.com/?");
        // When signing, the parameters need to be sorted in lexicographical order. TreeMap is used here
        // to guarantee the correct order.
        for (String k : params.keySet()) {
            s2s.append(k).append("=").append(params.get(k).toString()).append("&");
        }
        return s2s.toString().substring(0, s2s.length() - 1);
    }

    public static String getUrl(TreeMap<String, Object> params) throws UnsupportedEncodingException {
        StringBuilder url = new StringBuilder("https://cvm.convergecloud.com/?");
        // There is no requirement for the order of the parameters in the actual request URL.
        for (String k : params.keySet()) {
            // The request string needs to be URL encoded. As the Key is all in English letters, only the value
            // is URL encoded here.
            url.append(k).append("=").append(URLEncoder.encode(params.get(k).toString(), CHARSET)).append("&");
        }
        return url.toString().substring(0, url.length() - 1);
    }
}
```

```
}

public static void main(String[] args) throws Exception {
    TreeMap<String, Object> params = new TreeMap<String, Object>(); // TreeMap enables automatic sorting
    // A random number should be used when actually calling, for example: params.put("Nonce", new Random().nextInt(java.lang.Integer.MAX_VALUE));
    params.put("Nonce", 11886); // Common parameter
    // The current time of the system should be used when actually calling, for example: params.put("Timestamp", System.currentTimeMillis() / 1000);
    params.put("Timestamp", 1465185768); // Common parameter
    params.put("SecretId", "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"); // Common parameter
    params.put("Action", "DescribeInstances"); // Common parameter
    params.put("Version", "2017-03-12"); // Common parameter
    params.put("Region", "luzon"); // Common parameter
    params.put("Limit", 20); // Business parameter
    params.put("Offset", 0); // Business parameter
    params.put("InstanceIds.0", "ins-09dx96dg"); // Business parameter
    params.put("Signature", sign(getStringToSign(params), "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE", "HmacSHA1")); // Common parameter
    System.out.println(getUrl(params));
}
}
```

Python

Note: If running in a Python 2 environment, the following requests dependency package must be installed first: `pip install requests`.

```
# -*- coding: utf8 -*-
import base64
import hashlib
import hmac
import time

import requests

secret_id = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"
secret_key = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"

def get_string_to_sign(method, endpoint, params):
    s = method + endpoint + "/"
    query_str = "&".join("%s=%s" % (k, params[k]) for k in sorted(params))
    return s + query_str

def sign_str(key, s, method):
```

```
hmac_str = hmac.new(key.encode("utf8"), s.encode("utf8"), method).digest()
return base64.b64encode(hmac_str)

if __name__ == '__main__':
    endpoint = "cvm.convergecloud.com"
    data = {
        'Action': 'DescribeInstances',
        'InstanceIds.0': 'ins-09dx96dg',
        'Limit': 20,
        'Nonce': 11886,
        'Offset': 0,
        'Region': 'luzon',
        'SecretId': secret_id,
        'Timestamp': 1465185768, # int(time.time())
        'Version': '2017-03-12'
    }
    s = get_string_to_sign("GET", endpoint, data)
    data["Signature"] = sign_str(secret_key, s, hashlib.sha1)
    print(data["Signature"])
    # n actual invocation would occur here, which may incur fees after success
    # resp = requests.get("https://" + endpoint, params=data)
    # print(resp.url)
```

signaturev3

Converge Cloud The API will authenticate each access request, meaning that each request must include signature information (Signature) in the public request parameters to verify the requester's identity. The signature information is generated by the security credentials, which include SecretId and SecretKey . If the user does not have security credentials, please apply for them on the Cloud API Key page, otherwise they cannot call the Cloud API interfaces.

1. Apply for security credentials.

Before using the Cloud API for the first time, please go to the Cloud API Key page to apply for a security credential.

Security credentials include SecretId and SecretKey:

- SecretId The security credentials are used to identify the identity of the API caller.
- SecretKey The secret key is used to encrypt and sign the string for server-side verification of the signature.
- **Users must strictly protect their security credentials and avoid disclosure them.**

The specific steps to apply for security credentials are as follows:

1. Log in to Converge Cloud Administration Center Console
2. Go to the console page for cloud API keys
3. On the Cloud API Key page, click New to create a pair of SecretId/SecretKey

Note: Developer accounts can have up to two pairs SecretId / SecretKey.

2. TC3-HMAC-SHA256 signature method

Note: For GET method, only Content-Type: application/x-www-form-urlencoded protocol format is supported. For POST method, Content-Type: application/json and Content-Type: multipart/form-data are currently supported. By default, all business interfaces are supported in json format. Only specific business interfaces are supported in multipart format. In this case, the interface cannot be called in json format. Refer to the specific business interface document description.

The following takes Cloud Virtual Machine querying Region-1 instance list as an example to introduce the signature calculation process step by step. We only use two parameters for the query instance list: Limit and Offset, called using the GET method.

Assume that the SecretId and SecretKey of the user are AKIDz 8krbsJ 5yKBZQpn 74WFkmLPx 3EXAMPLE and Gu 5t9xGARNpq 86cd 98joQYCN3EXAMPLE, respectively.

2.1. splice specification request string

Concatenate CanonicalRequest strings in the following format:

```
CanonicalRequest =  
  HTTPRequestMethod + '\n' +  
  CanonicalURI + '\n' +  
  CanonicalQueryString + '\n' +  
  CanonicalHeaders + '\n' +  
  SignedHeaders + '\n' +  
  HashedRequestPayload
```

- HTTPRequestMethod: HTTP request methods (GET, POST), GET in this example;
- CanonicalURI: URI parameter, API 3.0 fixed to forward slash (/);
- CanonicalQueryString: Query string in the URL that initiates the HTTP request. For POST requests, it is fixed as an empty string. For GET requests, it is the question mark (?) in the URL. The following string content, this example value is: Limit=10&Offset=0. Note: CanonicalQueryString needs to be URL encoded.
- CanonicalHeaders: The header information of participating signature, at least including host and content-type, can also be added with customized header to improve the uniqueness and security of its own request. Splicing rules: 1) head key and value are uniformly converted to lowercase, and the first and last spaces are removed, and spliced according to the format of key:value\n;2) multiple heads are spliced according to the dictionary sorting of head key (lowercase). In this example:
content-type: application/x-www-form-urlencoded\nhost: cvm.convergecloud.com\n
- SignedHeaders: The header information involved in the signature indicates which headers participate in the signature of this request, and the header content contained in CanonicalHeaders is one-to-one corresponding. content-type and host are required headers. constructed as: 1) The head key is uniformly converted to lowercase; 2) Multiple header keys (lowercase) are concatenated according to dictionary sorting and separated by semicolons (;). In this case: content-type;host
- HashedRequestPayload: The hash value of the request body, calculated as Lowercase(HexEncode(Hash.SHA256(RequestPayload))), SHA256 hash the entire payload of the HTTP request body, then hexadecimal encoding, and finally converting the encoding string to lowercase letters. Note: For GET requests, RequestPayload is fixed as an empty string. For POST requests, RequestPayload is the payload of the HTTP request body.

According to the above rules, the resulting canonical request string in the example is as follows (for clarity, \nnewlines are replaced by a new line printed separately):

GET

```
/
Limit=10&Offset=0
content-type:application/x-www-form-urlencoded
host:cvm.convergecloud.com

content-type:host
e3b0c44298fc1c149afb4c8996fb92427ae41e4649b934ca495991b7852b855
```

2.2. Concatenate the string to be signed

Concatenate the string to be signed in the following format:

```
StringToSign =
  Algorithm + \n +
  RequestTimestamp + \n +
  CredentialScope + \n +
  HashedCanonicalRequest
```

- Algorithm: Signature algorithm, currently fixed as TC3-HMAC-SHA256;
- RequestTimestamp: Request timestamp, i.e. the X-TC-Timestamp value of the request header. The request in the example above is 1539084154;
- CredentialScope: Credential range in the format Date/service/tc3_request, containing date, requested service and termination string (tc3_request). **Date is the date of UTC standard time, the value needs to be consistent with UTC standard time converted by common parameter X-TC-Timestamp **;service is the product name, which must be consistent with the product domain name called, such as cvm. The above example request, the value is 2018-10-09/cvm/tc3_request;
- HashedCanonicalRequest: The hash value of the canonical request string obtained by concatenating the above steps is calculated by Lowercase(HexEncode(Hash.SHA256(CanonicalRequest))).

note:

1. Date must be calculated from timestamp X-TC-Timestamp and time zone UTC+0. Adding local time zone information to the system, such as East Zone 8, will cause calls to succeed during the day and night, but calls to fail in the early hours of the morning. Assuming the timestamp is 1551113065, the time in the East Eight District is 2019-02-26 00:44:25, but the calculated Date with UTC+0 should be 2019-02-25 instead of 2019-02-26.
2. Timestamp must be the current system time and ensure that the system time and standard time are synchronized. If the difference exceeds five minutes, it will fail. If it is not synchronized with the standard time for a long time, it may cause the request to fail after running for a period of time (return signature expiration error).

According to the above rules, the string to be signed in the example is as follows (for clarity,\nnewlines are

replaced by new lines printed):

```
TC3-HMAC-SHA256
1539084154
2018-10-09/cvm/tc3_request
91c9c192c14460df6c1ffc69e34e6c5e90708de2a6d282cccf957dbf1aa7f3a7
```

2.3. calculate the signature

1. Compute the derived signature key, pseudocode as follows

```
SecretKey = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"
SecretDate = HMAC_SHA256("TC3" + SecretKey, Date)
SecretService = HMAC_SHA256(SecretDate, Service)
SecretSigning = HMAC_SHA256(SecretService, "tc3_request")
```

- SecretKey: Original SecretKey;
- Date: That is, the Date field information in Credential, as shown in the example above, is 2018-10-09.;
- Service: That is, the Service field information in Credential, as shown in the example above, is cvm;

2. Calculate the signature, pseudocode as follows

```
Signature = HexEncode(HMAC_SHA256(SecretSigning, StringToSign))
```

- SecretSigning: That is, the derivative signature key calculated above;
- StringToSign: That is, the character string to be signed calculated in step 2;

2.4. Splicing Authorization

Splice as follows Authorization:

```
Authorization =
  Algorithm + ' ' +
  'Credential=' + SecretId + '/' + CredentialScope + ', ' +
  'SignedHeaders=' + SignedHeaders + ', ' +
  'Signature=' + Signature
```

- Algorithm: Signature method, fixed as TC3-HMAC-SHA256;
- SecretId: SecretId in key pair;
- CredentialScope: See above, Scope of Voucher;
- SignedHeaders: See above, header information for participating signatures;
- Signature: signature value



According to the above rules, the values obtained in the example are:

TC3-HMAC-SHA256 Credential=AKIDEXAMPLE/Date/service/tc3_request, SignedHeaders=content-type;host, Signature=5da7a33f6993f0614b047e5df4582db9e9bf4672ba50567dba16c6ccf174c474

The final complete invocation information is as follows:

`https://cvm.convergecloud.com/?Limit=10&Offset=0`

Authorization: TC3-HMAC-SHA256 Credential=AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE/2018-10-09/cvm/tc3_request, SignedHeaders=content-type;host, Signature=5da7a33f6993f0614b047e5df4582db9e9bf4672ba50567dba16c6ccf174c474

Content-Type: application/x-www-form-urlencoded

Host: cvm.convergecloud.com

X-TC-Action: DescribeInstances

X-TC-Version: 2017-03-12

X-TC-Timestamp: 1539084154

X-TC-Region: luzon

3. signing failed

According to the actual situation, there are the following signature failure error codes, please handle according to the actual situation

error code	error description
AuthFailure.SignatureExpire	signature expiration
AuthFailure.SecretIdNotFound	key is not present
AuthFailure.SignatureFailure	signature error
AuthFailure.TokenFailure	token error
AuthFailure.InvalidSecretId	Illegal key (not cloud API key type)

4. Signature Demo

Java

```
import java.io.BufferedReader;  
import java.io.InputStream;
```

```
import java.io.InputStreamReader;
import java.net.URL;
import java.text.SimpleDateFormat;
import java.util.Date;
import java.util.Map;
import java.util.TimeZone;
import java.util.TreeMap;
import javax.crypto.Mac;
import javax.crypto.spec.SecretKeySpec;
import javax.net.ssl.HttpURLConnection;
import javax.xml.bind.DatatypeConverter;

import org.apache.commons.codec.digest.DigestUtils;

public class CloudAPITC3Demo {
    private final static String CHARSET = "UTF-8";
    private final static String ENDPOINT = "cvm.convergecloud.com";
    private final static String PATH = "/";
    private final static String SECRET_ID = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE";
    private final static String SECRET_KEY = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE";
    private final static String CT_X_WWW_FORM_URLENCODED = "application/x-www-form-urlencoded";
    private final static String CT_JSON = "application/json";
    private final static String CT_FORM_DATA = "multipart/form-data";

    public static byte[] sign256(byte[] key, String msg) throws Exception {
        Mac mac = Mac.getInstance("HmacSHA256");
        SecretKeySpec secretKeySpec = new SecretKeySpec(key, mac.getAlgorithm());
        mac.init(secretKeySpec);
        return mac.doFinal(msg.getBytes(CHARSET));
    }

    public static void main(String[] args) throws Exception {
        String service = "cvm";
        String host = "cvm.convergecloud.com";
        String region = "luzon";
        String action = "DescribeInstances";
        String version = "2017-03-12";
        String algorithm = "TC3-HMAC-SHA256";
        String timestamp = "1539084154";
        //String timestamp = String.valueOf(System.currentTimeMillis() / 1000);
        SimpleDateFormat sdf = new SimpleDateFormat("yyyy-MM-dd");
        // Pay attention to the time zone, otherwise it is easy to make mistakes.
        sdf.setTimeZone(TimeZone.getTimeZone("UTC"));
        String date = sdf.format(new Date(Long.valueOf(timestamp + "000")));

        // ***** Step 1: Assemble the specification request string *****
    }
}
```

```
String httpRequestMethod = "GET";
String canonicalUri = "/";
String canonicalQueryString = "Limit=10&Offset=0";
String canonicalHeaders = "content-type:application/x-www-form-urlencoded\n" + "host:" + host
+ "\n";
String signedHeaders = "content-type;host";
String hashedRequestPayload = DigestUtils.sha256Hex("");
String canonicalRequest = httpRequestMethod + "\n" + canonicalUri + "\n" + canonicalQueryStri
ng + "\n"
    + canonicalHeaders + "\n" + signedHeaders + "\n" + hashedRequestPayload;
System.out.println(canonicalRequest);

// ***** Step 2: Stitching the string to be signed *****
String credentialScope = date + "/" + service + "/" + "tc3_request";
String hashedCanonicalRequest = DigestUtils.sha256Hex(canonicalRequest.getBytes(CHARSET));
String stringToSign = algorithm + "\n" + timestamp + "\n" + credentialScope + "\n" + hashedCan
onicalRequest;
System.out.println(stringToSign);

// ***** Step 3: Calculate the signature *****
byte[] secretDate = sign256(("TC3" + SECRET_KEY).getBytes(CHARSET), date);
byte[] secretService = sign256(secretDate, service);
byte[] secretSigning = sign256(secretService, "tc3_request");
String signature = DatatypeConverter.printHexBinary(sign256(secretSigning, stringToSign)).toLow
erCase();
System.out.println(signature);

// ***** Step 4: Splicing Authorization *****
String authorization = algorithm + " " + "Credential=" + SECRET_ID + "/" + credentialScope + ", "
    + "SignedHeaders=" + signedHeaders + ", " + "Signature=" + signature;
System.out.println(authorization);

TreeMap<String, String> headers = new TreeMap<String, String>();
headers.put("Authorization", authorization);
headers.put("Host", host);
headers.put("Content-Type", CT_X_WWW_FORM_URLENCODED);
headers.put("X-TC-Action", action);
headers.put("X-TC-Timestamp", timestamp);
headers.put("X-TC-Version", version);
headers.put("X-TC-Region", region);
}
}
```

Python

```
# -*- coding: utf-8 -*-
```

```
import hashlib, hmac, json, os, sys, time
from datetime import datetime

# key parameters
secret_id = "AKIDz8krbsJ5yKBZQpn74WFkmLPx3EXAMPLE"
secret_key = "Gu5t9xGARNpq86cd98joQYCN3EXAMPLE"

service = "cvm"
host = "cvm.convergecloud.com"
endpoint = "https://" + host
region = "luzon"
action = "DescribeInstances"
version = "2017-03-12"
algorithm = "TC3-HMAC-SHA256"
timestamp = 1539084154
date = datetime.utcfromtimestamp(timestamp).strftime("%Y-%m-%d")
params = {"Limit": 10, "Offset": 0}

# ***** Step 1: Assemble the specification request string *****
http_request_method = "GET"
canonical_uri = "/"
canonical_querystring = "Limit=10&Offset=0"
ct = "x-www-form-urlencoded"
payload = ""
if http_request_method == "POST":
    canonical_querystring = ""
    ct = "json"
    payload = json.dumps(params)
canonical_headers = "content-type:application/%s\nhost:%s\n" % (ct, host)
signed_headers = "content-type;host"
hashed_request_payload = hashlib.sha256(payload.encode("utf-8")).hexdigest()
canonical_request = (http_request_method + "\n" +
                     canonical_uri + "\n" +
                     canonical_querystring + "\n" +
                     canonical_headers + "\n" +
                     signed_headers + "\n" +
                     hashed_request_payload)
print(canonical_request)

# ***** Step 2: Stitching the string to be signed *****
credential_scope = date + "/" + service + "/" + "tc3_request"
hashed_canonical_request = hashlib.sha256(canonical_request.encode("utf-8")).hexdigest()
string_to_sign = (algorithm + "\n" +
                  str(timestamp) + "\n" +
                  credential_scope + "\n" +
                  hashed_canonical_request)
print(string_to_sign)
```

```
# ***** Step 3: Calculate the signature *****
# Compute signature digest function
def sign(key, msg):
    return hmac.new(key, msg.encode("utf-8"), hashlib.sha256).digest()
secret_date = sign(("TC3" + secret_key).encode("utf-8"), date)
secret_service = sign(secret_date, service)
secret_signing = sign(secret_service, "tc3_request")
signature = hmac.new(secret_signing, string_to_sign.encode("utf-8"), hashlib.sha256).hexdigest()
print(signature)

# ***** Step 4: Splicing Authorization *****
authorization = (algorithm + " " +
                "Credential=" + secret_id + "/" + credential_scope + ", " +
                "SignedHeaders=" + signed_headers + ", " +
                "Signature=" + signature)
print(authorization)

# Common parameters added to request header
headers = {
    "Authorization": authorization,
    "Host": host,
    "Content-Type": "application/%s" % ct,
    "X-TC-Action": action,
    "X-TC-Timestamp": str(timestamp),
    "X-TC-Version": version,
    "X-TC-Region": region,
}
```

request

1. Service Address

Region refers to the geographical area of a physical data center. Converge Cloud ensures complete isolation between different regions, providing maximum stability and fault tolerance. To reduce access latency and improve download speed, it is recommended to choose the region closest to your customers.

You can view the complete region list by using the API interface "DescribeRegions".

2. Communications Protocol

All the Converge Cloud APIs communicate via HTTPS, providing highly secure communication tunnels.

3. Request Methods

Supported HTTP request methods:

- POST (recommended)
- GET

The Content-Type types supported by POST requests:

- application/json (recommended). The TC3-HMAC-SHA256 signature algorithm must be used.
- application/x-www-form-urlencoded. The HmacSHA1 or HmacSHA256 signature algorithm must be used.
- multipart/form-data (only supported by certain APIs). You must use TC3-HMAC-SHA256 to calculate the signature.

The size of a GET request packet is up to 32 KB. The size of a POST request is up to 1 MB when the HmacSHA1 or HmacSHA256 signature algorithm is used, and up to 10 MB when TC3-HMAC-SHA256 is used.

4. Character Encoding

Only UTF-8 encoding is used.

result

Response for Successful Requests

For example, when calling CAM API (version: 2017-03-12) to view the status of instances (DescribeInstancesStatus), if the request has succeeded, you may see the response as shown below:

```
{
  "Response": {
    "TotalCount": 0,
    "InstanceStatusSet": [],
    "RequestId": "b5b41468-520d-4192-b42f-595cc34b6c1c"
  }
}
```

- The API will return Response, which contains RequestId, as long as it processes the request. It does not matter if the request is successful or not.
- RequestId is the unique ID of an API request. Contact us with this ID when an exception occurs.
- Except for the fixed fields, all fields are action-specified. For the definitions of action-specified fields, see the corresponding API documentation. In this example, TotalCount and InstanceStatusSet are the fields specified by the API DescribeInstancesStatus. 0 TotalCount means that the requester owns 0 CVM instance so the InstanceStatusSet is empty.

Response for Failed Requests

If the request has failed, you may see the response as shown below:

```
{
  "Response": {
    "Error": {
      "Code": "AuthFailure.SignatureFailure",
      "Message": "The provided credentials could not be validated. Please check your signature is correct."
    },
    "RequestId": "ed93f3cb-f35e-473f-b9f3-0d451b8b79c6"
  }
}
```

- The presence of the Error field indicates that the request has failed. A response for a failed request will include Error, Code and Message fields.

- Code is the code of the error that helps you identify the cause and solution. There are two types of error codes so you may find the code in either common error codes or API-specified error codes.
- Message explains the cause of the error. Note that the returned messages are subject to service updates. The information the messages provide may not be up-to-date and should not be the only source of reference.
- RequestId is the unique ID of an API request. Contact us with this ID when an exception occurs.

Common Error Codes

If there is an Error field in the response, it means that the API call failed. The Code field in Error indicates the error code. The following table lists the common error codes that all actions can return.

Error Code	Description
AuthFailure.InvalidSecretId	Invalid key (not a API key type).
AuthFailure.MFAFailure	MFA failed.
AuthFailure.SecretIdNotFound	The key does not exist.
AuthFailure.SignatureExpire	Signature expired.
AuthFailure.SignatureFailure	Signature error.
AuthFailure.TokenFailure	Token error.
AuthFailure.UnauthorizedOperation	The request does not have CAM authorization.
DryRunOperation	DryRun Operation. It means that the request would have succeeded, but the DryRun parameter was used.
FailedOperation	Operation failed.
InternalError	Internal error.
InvalidAction	The API does not exist.
InvalidParameter	Incorrect parameter.
InvalidParameterValue	Invalid parameter value.
LimitExceeded	Quota limit exceeded.
MissingParameter	A parameter is missing.
NoSuchVersion	The API version does not exist.



Error Code	Description
RequestLimitExceeded	The number of requests exceeds the frequency limit.
ResourceInUse	Resource is in use.
ResourceInsufficient	Insufficient resource.
ResourceNotFound	The resource does not exist.
ResourceUnavailable	Resource is unavailable.
UnauthorizedOperation	Unauthorized operation.
UnknownParameter	Unknown parameter.
UnsupportedOperation	Unsupported operation.
UnsupportedProtocol	hHTTPS request method error. Only GET and POST requests are supported.
UnsupportedRegion	API does not support the requested region.



PublicParameter

Common parameters are parameters used to identify users and interface authentication purposes. If not necessary, these parameters are not described in the separate interface document of each interface, but these parameters need to be carried in each request before the request can be normally initiated.

signature method v3

When using TC3-HMAC-SHA256 signature method, the common parameters need to be uniformly placed in the HTTP Header request header, as follows:

parameter name	type	required	described
X-TC-Action	String	Yes	The name of the operation interface. Refer to the description of the public parameter Action in the input parameters of the interface documentation for the value. For example, the value for the query instance list interface of the cloud server is DescribeInstances.
X-TC-Region	String	Yes	region parameters, Data used to identify which region you wish to operate on. The region value accepted by the interface refers to the description of the input parameter common parameter Region in the interface document. Note: Some interfaces do not need to pass this parameter, which is specifically stated in the interface documentation. In this case, even passing this parameter will not take effect.
X-TC-Timestamp	Integer	Yes	The current UNIX timestamp, which records the time when the API request was initiated. for example 1529223702. Note: If the time difference from the server exceeds 5 minutes, it will cause a signature expiration error.
X-TC-Version	String	Yes	Version of API for operation. Refer to the description of the public parameter Version in the interface document for the value. For example, the version of the cloud server. 2017-03-12.
Authorization	String	Yes	HTTP The standard authentication header field is "Authorization". For example: TC3-HMAC-SHA256 Credential=AKIDEXAMPLE/Date/service/tc3_request, SignedHeaders=content-type;host, Signature=fe5f80f77d5fa3beca038a248ff027d0445342fe2855ddc963176630326f1024 Here, - TC3-HMAC-SHA256: Signature method, currently fixed as this value, - Credential: Credential: Signature credential; AKIDEXAMPLE is the SecretId; Date is a date in UTC time, and this value must match the value of X-TC-Timestamp (a common parameter) in UTC time format; service is the name of the product/service, and is generally a domain name prefix. For example,cvm; - SignedHeaders: The headers that contains the authentication information; content-type and host are the required headers; - Signature: Signature digest.
X-TC-Token	String	No	The token used for temporary certificates needs to be used in conjunction with a temporary key. Temporary keys and tokens need to be obtained by calling the access management service interface. Long-term keys do not require tokens.

signature method v1



When using HmacSHA1 and HmacSHA256 signature methods, common parameters need to be placed uniformly in the request string, as follows

parameter name	type	required	described
Action	String	Yes	The name of the interface to be operated. The value refers to the explanation of the public parameter <code>Action</code> in the interface documentation. For example, for the cloud server's query instance list interface, the value is <code>DescribeInstances</code> .
Region	String	Yes	The region parameter is used to identify which region's data you want to operate on. The region value accepted by the interface is specified in the input parameter of the public parameter <code>Region</code> in the interface documentation. Note: Some interfaces do not require this parameter to be passed, which will be specifically mentioned in the interface documentation. Even if this parameter is passed, it will not take effect in this case.
Timestamp	Integer	Yes	The current UNIX timestamp, which can record the time when the API request is initiated. For example, 1529223702. If the difference between the current time is too large, it will cause a signature expiration error.
Nonce	Integer	Yes	A random positive integer combined with <code>Timestamp</code> is used to prevent replay attacks.
SecretId	String	Yes	The <code>SecretId</code> is an identifier applied for the cloud API key to identify the user's identity. A <code>SecretId</code> corresponds to a unique <code>SecretKey</code> , and the <code>SecretKey</code> is used to generate the request signature <code>Signature</code> .
Signature	String	Yes	Request signature is used to verify the legitimacy of this request. Users need to calculate it based on the actual input parameters. The specific calculation method can be found in the interface authentication documentation.
Version	String	Yes	The version of the API being operated on. The value refers to the description of the public parameter <code>Version</code> in the interface documentation. For example, the version of the cloud server. 2017-03-12.
SignatureMethod	String	No	Signature method, currently supports HmacSHA256 and HmacSHA1. HmacSHA256 algorithm is used to verify signatures only if this parameter is specified as HmacSHA 256, otherwise HmacSHA1 is used to verify signatures.
Token	String	No	Token used for temporary certificate needs to be used together with temporary key. The temporary key and Token need to be obtained from the Access Management service invocation interface. Long-term keys do not require tokens.

zone list

A region (Region) refers to the geographical area of a physical data center. Converge Cloud Translation: To deliver verification that completely isolates different regions, ensuring maximum stability and fault tolerance between regions. In order to reduce access latency and improve download speed, it is recommended that you choose the region closest to your customers.

You can view the complete region list by using the API interface Query Region List.



Cloud Monitor API

DescribeBaseMetrics

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

API for obtaining the details of basic metrics.

Default interface request rate limit: 20 times per second.

Interface update time: 2022-10-24 18:12:59.

The interface only verifies the signature but does not authenticate.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: DescribeBaseMetrics
Version	Yes	No	String	Public parameter, The value of this interface: 2017-03-12
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Namespace	Yes	No	String	Service namespace. Example: QCE/CVM
MetricName	No	No	String	Metric name. Example: AccOuttraffic

3. Output Parameters



Parameter name	Type	Description
MetricSet	Array of MetricObject	List of queried metric descriptions. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.



GetMonitorData

1. Interface Description

Interface request domain name: monitor.api3.convergecloud.com.

Obtains the monitoring data of a cloud product. After you specify your product namespace, object dimension description, and monitoring metrics, you can obtain the corresponding monitoring data.

The API call frequency is limited to: 50 times/second, 500 times/minute.

If you call excessive metrics and objects in a short period of time, the system may fail to pull data because frequency is limited. We recommend that you balance your requests by time.

Default interface request rate limit: 300 times per second.

Interface update time: 2022-11-22 16:40:20.

The interface is both signature verification and authentication.

2. Input Parameters

The following list of request parameters only lists interface request parameters and some public parameters, For a complete list of public parameters see [public request parameters](#).

Parameter name	Required	Allow NULL	Type	Description
Action	Yes	No	String	Public parameter, The value of this interface: GetMonitorData
Version	Yes	No	String	Public parameter, The value of this interface: 2017-03-12
Region	No	No	String	Public parameter,Regional information A list of supported geographies is available through the DescribeRegions interface
Namespace	Yes	No	String	Namespace. Each cloud product has a namespace. Example: qce/cvm
MetricName	Yes	No	String	Metric name. Example: cpu_usage
Period	No	No	UInt64	Statistical period of monitoring data. The default value is 300. Unit: seconds. Example: 300
StartTime	No	No	Datetime_iso	Start time. Example: 2018-01-01 00:00:00. Example: 2019-03-24T10:51:23+08:00
EndTime	No	No	Datetime_iso	End time. The default value is the current time. endTime cannot be earlier than startTime. Example: 2019-03-24T20:51:23+08:00
Dimensions	Yes	No	Array of String	Combination of instance object dimensions Example: [{"unInstanceId":"ins-c282wnl0"}]
Statistics	No	No	String	Statistical method. Example: qwer

3. Output Parameters

Parameter name	Type	Description
MetricName	String	Monitoring metrics. Example: cpu_usage



Parameter name	Type	Description
StartTime	Datetime_iso	Start time of data point. Example: 2019-03-24T10:50:00+08:00
EndTime	Datetime_iso	End time of data point. Example: 2019-03-24T20:50:00+08:00
Period	UInt64	Statistical period. Example: 300
DataPoints	Array of PointsObject	List of monitoring data. Example: View
RequestId	String	Unique request id, Each request will return. The RequestId of the request needs to be provided when locating the problem.

4. Error Code

The following lists only the error codes related to the interface business logic, For other error codes, see [public ErrorCode](#).

Error Code	Description
InternalError	Internal error.
InvalidParameterValue	Invalid parameter value.



Data structure

MetricObject

Description of the unit and supported statistical period of the business metric

Referenced by the following interfaces: DescribeBaseMetrics

name	required	NULL allowed	type	description
Namespace	yes	no	String	Namespace. Each cloud product has a namespace. Example: QCE/CVM
MetricName	yes	no	String	Metric name. Example: CpuUsage
Unit	yes	no	String	Unit used by the metric. Example: %
Period	yes	no	Array of Int64	Statistical period in seconds supported by the metric, such as 60 and 300. Example: 5

PointsObject

List of the monitoring data of an instance.

Referenced by the following interfaces: GetMonitorData

name	required	NULL allowed	type	description
Dimensions	yes	no	Array of String	Dimension combination of the monitored instance. Example: qwer
Points	yes	no	Array of Float	Array of monitoring data points. The time span of each point is a Period value. Example: 10



ErrorCode

Feature Description

If there is an Error field in the response, it means that the API call failed. For example:

```
{
  "Response": {
    "Error": {
      "Code": "AuthFailure.SignatureFailure",
      "Message": "The provided credentials could not be validated. Please check your signature is correct."
    },
    "RequestId": "ed93f3cb-f35e-473f-b9f3-0d451b8b79c6"
  }
}
```

Code in Error indicates the error code, and Message indicates the specific information of the error.

Error Code List

Common Error Codes

Error codes	Description
AuthFailure.InvalidSecretId	Invalid key (not a Cloud API key type).
AuthFailure.MFAFailure	MFA failed.
AuthFailure.SecretIdNotFound	Key does not exist. Check if the key has been deleted or disabled in the console, and if not, check if the key is correctly entered. Note that whitespaces should not exist before or after the key.
AuthFailure.SignatureExpire	Signature expired. Timestamp and server time cannot differ by more than five minutes. Please ensure your current local time matches the standard time.
AuthFailure.SignatureFailure	Invalid signature. Signature calculation error. Please ensure you've followed the signature calculation process described in the Signature API documentation.
AuthFailure.TokenFailure	Token error.



Error codes	Description
AuthFailure.UnauthorizedOperation	The request does not have CAM authorization.
DryRunOperation	DryRun Operation. It means that the request would have succeeded, but the DryRun parameter was used.
FailedOperation	Operation failed.
InternalError	Internal error.
InvalidAction	The API does not exist.
InvalidParameter	Incorrect parameter.
InvalidParameterValue	Invalid parameter value.
LimitExceeded	Quota limit exceeded.
MissingParameter	A parameter is missing.
NoSuchVersion	The API version does not exist.
RequestLimitExceeded	The number of requests exceeds the frequency limit.
ResourceInUse	Resource is in use.
ResourceInsufficient	Insufficient resource.
ResourceNotFound	The resource does not exist.
ResourceUnavailable	Resource is unavailable.
UnauthorizedOperation	Unauthorized operation.
UnknownParameter	Unknown parameter.
UnsupportedOperation	Unsupported operation.
UnsupportedProtocol	HTTPS request method error. Only GET and POST requests are supported.
UnsupportedRegion	API does not support the requested region.

Service Error Codes

Error codes	Description
InvalidParameterValue	Invalid parameter value.



Error codes	Description
ResourceUnavailable	The resource is unavailable.
ResourcesSoldOut	The resources have been sold out.
UnsupportedOperation	Unsupported operation.
UnauthorizedOperation	Unauthorized operation.
ResourceInUse	The resource is in use.
InternalError	Internal error.
FailedOperation	Operation failed.
InvalidParameter	Invalid parameter.
LimitExceeded	The quota limit has been reached.
ResourceInsufficient	Insufficient resource.
UnknownParameter	Unknown parameter error.
MissingParameter	Missing parameter.
ResourceNotFound	The resource does not exist.